

Table 12. STM32C542xx pin/ball definition

Pin number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
TSSOP20	UFQFPN20	UFQFPN24	UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64						
-	-	-	-	-	1	1	1	PE2	I/O	FT	-	TRACECLK, LPTIM1_IN2, EVENTOUT	-
-	-	-	-	-	2	2	2	PC13	I/O	FT_t	(1)(2)	FDCAN1_TX, EVENTOUT	TAMP_IN1, RTC_OUT1/ RTC_TS, WKUP4
-	-	-	2	2	3	3	3	PC14-OSC32_IN (OSC32_IN)	I/O	FT	(1)	TIM12_CH1, FDCAN1_RX, EVENTOUT	OSC32_IN
-	-	-	-	-	4	4	4	PC15- OSC32_OUT (OSC32_OUT)	I/O	FT	(1)	TIM12_CH2, EVENTOUT	OSC32_OUT
4	2	1	2	2	5	5	5	PH0-OSC_IN (PH0)	I/O	FT_f	-	I2C1_SDA, EVENTOUT	OSC_IN
3	1	2	3	3	6	6	6	PH1-OSC_OUT (PH1)	I/O	FT_f	-	I2C1_SCL, EVENTOUT	OSC_OUT
2	20	3	4	4	7	7	7	NRST	I/O	RST	-	-	-
-	-	-	-	-	-	-	8	PC0	I/O	FT_a	-	SPI2_RDY, EVENTOUT	ADC1_IN8, COMP2_INP
-	-	-	-	-	-	-	9	PC1	I/O	FT_a	-	TRACED0, SPI2_MOSI/ I2S2_SDO, EVENTOUT	ADC1_IN9, COMP2_INM, TAMP_IN2
-	-	-	-	-	-	-	10	PC2	I/O	FT_a	-	PWR_CSLEEP, SPI2_MISO/ I2S2_SDI, EVENTOUT	ADC1_IN10
-	-	-	-	-	-	-	11	PC3	I/O	FT_a	-	PWR_CSTOP, LPUART1_TX, SPI2_MOSI/I2S2_SDO, EVENTOUT	ADC1_IN11
5	3	-	-	-	8	8	12	VREF-	S	-	-	-	-
6	4	4	5	5	9	9	13	VREF+	S	-	-	-	-
-	-	5	6	6	10	10	14	PA0	I/O	FT_a	-	TIM2_CH1, TIM8_ETR, TIM15_BKIN, SPI2_RDY, SPI1_RDY, USART2_CTS/ USART2_NSS, UART4_TX, SPI2_NSS/I2S2_WS, TIM2_ETR, EVENTOUT	ADC1_IN0, COMP1_INP, TAMP_IN2, WKUP1

