

Pin number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
TSSOP20	UFQFPN20	UFQFPN24	UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64						
7	5	6	7	7	11	11	15	PA1	I/O	TT_a	-	TIM2_CH2, TIM8_BKIN, TIM15_CH1N, LPTIM1_IN1, USART2_RTS, UART4_RX, EVENTOUT	ADC1_IN1, OPAMP1_VINP0, TAMP_IN3
7	5	7	8	8	12	12	16	PA2	I/O	TT_a	-	TIM2_CH3, LPUART1_RX, TIM15_CH1, LPTIM1_IN2, USART2_TX, COMP2_OUT, EVENTOUT	ADC1_IN2, COMP2_INM, OPAMP1_VINM0, TAMP_IN3, WKUP2
7	5	7	9	9	13	13	17	PA3	I/O	FT_a	-	TIM2_CH4, LPUART1_TX, TIM15_CH2, SPI2_NSS/ I2S2_WS, SPI2_MOSI/ I2S2_SDO, USART2_RX, COMP1_OUT, EVENTOUT	ADC1_IN3, COMP2_INP
-	-	-	-	-	-	-	18	VSS	S	-	-	-	-
-	-	-	-	-	-	-	19	VDD	S	-	-	-	-
8	6	8	10	10	14	14	20	PA4	I/O	TT_a	-	TIM1_BKIN2, SPI1_MOSI/ I2S1_SDO, SPI1_NSS/ I2S1_WS, SPI2_NSS/I2S2_WS, USART2_CK, EVENTOUT	ADC1_IN4, DAC1_OUT1
8	6	8	11	11	15	15	21	PA5	I/O	TT_a	-	TIM2_CH1, TIM1_CH3, TIM8_CH1N, SPI1_SCK/ I2S1_CK, SPI2_SCK/I2S2_CK, USART1_CTS/USART1_NSS, TIM2_ETR, EVENTOUT	ADC1_IN5, DAC2_OUT1, COMP1_INM
9	7	9	12	12	16	16	22	PA6	I/O	TT_a	-	TIM1_BKIN, TIM8_BKIN, SPI1_MISO/I2S1_SDI, USART1_TX, LPUART1_RTS, EVENTOUT	ADC1_IN6, OPAMP1_VOUT
9	7	9	13	13	17	17	23	PA7	I/O	FT_a	-	TIM1_CH1N, TIM8_CH1N, TIM15_CH1, SPI1_MOSI/ I2S1_SDO, SPI2_MISO/ I2S2_SDI, USART1_RX, LPUART1_CTS, COMP2_OUT, EVENTOUT	ADC1_IN7
9	7	9	-	-	-	-	24	PC4	I/O	FT_a	-	TIM2_CH4, TIM8_BKIN, I2S1_MCK, USART2_RX, EVENTOUT	ADC1_IN2, COMP1_INM
-	-	-	-	-	-	-	25	PC5	I/O	FT_a	-	TIM1_CH4N, TIM8_BKIN2, COMP1_OUT, EVENTOUT	ADC1_IN5, COMP2_INM

