

Pin number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
TSSOP20	UFQFPN20	UFQFPN24	UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64						
10	8	10	14	14	18	18	26	PB0	I/O	TT_a	-	TIM1_CH2N, TIM8_CH2N, SPI1_MISO/I2S1_SDI, USART2_TX, UART4_CTS, EVENTOUT	ADC1_IN6, COMP1_INP, OPAMP1_VINP1
10	8	11	15	-	19	19	27	PB1	I/O	TT_a	-	TIM1_CH3N, TIM8_CH3N, SPI2_NSS/I2S2_WS, USART2_RX, COMP1_OUT, EVENTOUT	ADC1_IN7, COMP1_INM, OPAMP1_VINM1
10	8	11	-	-	20	20	28	PB2	I/O	FT_a	-	RTC_OUT2, TIM8_CH4N, SPI1_RDY, LPTIM1_CH1, SPI2_SCK/I2S2_CK, SPI2_MOSI/I2S2_SDO, EVENTOUT	COMP1_INP, LSCO
-	-	-	-	-	21	21	29	PB10	I/O	FT_f	-	TIM2_CH3, TIM8_CH1, LPTIM1_IN1, I2C1_SCL, SPI2_SCK/I2S2_CK, USART2_TX, EVENTOUT	-
11	9	12	16	15	22	22	30	VCAP	S	-	-	-	-
12	10	-	-	16	23	23	31	VSS	S	-	-	-	-
13	11	13	17	17	24	24	32	VDD	S	-	-	-	-
-	-	-	-	-	25	25	33	PB12	I/O	FT_f	-	TIM1_BKIN, TIM8_CH3, I2C1_SDA, SPI2_NSS/ I2S2_WS, USART2_CK, FDCAN2_RX, UART5_RX, EVENTOUT	-
-	-	-	-	-	26	26	34	PB13	I/O	FT	-	TIM1_CH1N, TIM8_CH2, LPTIM1_CH1, I2C1_SMBA, SPI2_SCK/I2S2_CK, USART2_CTS/USART2_NSS, LPUART1_RX, FDCAN2_TX, UART5_TX, EVENTOUT	-
-	-	-	-	-	27	27	35	PB14	I/O	FT	-	TIM1_CH2N, TIM12_CH1, TIM8_CH2N, USART1_TX, SPI2_MISO/I2S2_SDI, USART2_RTS, UART4_RTS, EVENTOUT	-

