

Pin number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
TSSOP20	UFQFPN20	UFQFPN24	UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64						
19	17	20	26	26	39	39	55	PB3 (JTDO/ TRACESWO)	I/O	FT_f	-	JTDO/TRACESWO, TIM2_CH2, I3C1_SDA, I2C1_SDA, SPI1_SCK/I2S1_CK, FDCAN2_RX, USART1_CK, LPUART1_TX, I2C1_SCL, CRS_SYNC, USART1_TX, TIM8_CH1, UART5_RTS, EVENTOUT	-
20	18	21	27	27	40	40	56	PB4 (NJTRST)	I/O	FT_f	-	NJTRST, TIM15_CH1, I3C1_SCL, LPTIM1_CH2, SPI1_MISO/I2S1_SDI, FDCAN2_TX, SPI2_NSS/ I2S2_WS, LPUART1_CTS, I2C1_SDA, USART1_RX, TIM8_CH2, UART5_CTS, EVENTOUT	-
-	-	22	28	28	41	41	57	PB5	I/O	FT	-	I3C1_SDA, I2C1_SMBA, SPI1_MOSI/I2S1_SDO, LPUART1_RTS, FDCAN2_RX, USART1_CK, TIM8_CH3, UART5_RX, EVENTOUT	-
-	-	-	29	29	42	42	58	PB6	I/O	FT_f	-	I3C1_SCL, I2C1_SCL, SPI1_MISO/I2S1_SDI, USART1_TX, LPUART1_TX, FDCAN2_TX, USART1_CTS/ USART1_NSS, TIM8_CH4, UART5_TX, EVENTOUT	-
-	-	23	30	30	43	43	59	PB7	I/O	FT_f	-	I3C1_SDA, I2C1_SDA, SPI1_SCK/I2S1_CK, USART1_RX, LPUART1_RX, FDCAN1_TX, USART1_RTS, EVENTOUT	WKUP5
-	-	-	31	-	44	44	60	PH2-BOOT0	I/O	FT	-	MCO1, LPTIM1_IN2, FDCAN1_RX, EVENTOUT	-
1	19	24	-	31	-	-	-	PB8-BOOT0	I/O	FT_f	-	TIM1_CH1, I3C1_SCL, I2C1_SCL, SPI1_NSS/ I2S1_WS, UART4_RX, FDCAN1_RX, EVENTOUT	-

