

Pin number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
TSSOP20	UFQFPN20	UFQFPN24	UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64						
-	-	-	32	-	45	45	61	PB8	I/O	FT_f	-	TIM1_CH1, I3C1_SCL, I2C1_SCL, SPI1_NSS/ I2S1_WS, UART4_RX, FDCAN1_RX, EVENTOUT	-
-	-	-	-	-	46	46	62	PB9	I/O	FT_f	-	I3C1_SDA, I2C1_SDA, SPI2_NSS/I2S2_WS, SPI1_SCK/I2S1_CK, UART4_TX, FDCAN1_TX, EVENTOUT	-
-	-	-	-	32	47	47	63	VSS	S	-	-	-	-
-	-	-	1	1	48	48	64	VDD	S	-	-	-	-

1. After a RTC domain reset, PC13, PC14, and PC15 operate as GPIOs. Their function depends on the content of the RTC registers that are not reset by the system reset. For details on how to manage these GPIOs, refer to the backup domain and RTC register descriptions in the product reference manual.
2. Toggling the PC13 port can disturb the low-speed crystal connected to the LSE on PC14 and PC15. Refer to product errata sheet for more details.
3. After reset, this pin is configured for JTAG or SWD alternate function. The internal pull-up on the PA15, PA13, and PB4 pins, and the internal pull-down on the PA14 pin, are activated.

