

Pin number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
LQFP32	UFQFPN32	LQFP48	UFQFPN48	LQFP64	LQFP64 alternative pinout ⁽¹⁾	LQFP80	LQFP100						
-	-	-	-	8	8	11	15	PC0	I/O	FT_a	-	SPI2_RDY, TIM16_BKIN, EVENTOUT	ADC1_IN8
-	-	-	-	9	9	12	16	PC1	I/O	FT_ta	-	TRACED0, SPI2_MOSI/ I2S2_SDO, EVENTOUT	ADC1_IN9, ADC2_IN9, TAMP_IN2, WKUP6
-	-	-	-	10	10	13	17	PC2	I/O	FT_a	-	PWR_CSLEEP, TIM17_CH1, SPI2_MISO/I2S2_SDI, EVENTOUT	ADC1_IN10, ADC2_IN10
-	-	-	-	11	11	14	18	PC3	I/O	FT_a	-	PWR_CSTOP, LPUART1_TX, SPI2_MOSI/I2S2_SDO, EVENTOUT	ADC1_IN11, ADC2_IN11
-	-	-	-	-	-	-	19	PH4	I/O	FT_a	-	EVENTOUT	ADC2_IN12
-	-	8	8	12	12	15	20	VREF-	S	-	-	-	-
5	5	9	9	13	13	16	21	VREF+	S	-	-	-	-
-	-	-	-	-	-	17	22	PH5	I/O	FT_a	-	EVENTOUT	ADC2_IN13
6	6	10	10	14	14	18	23	PA0	I/O	FT_ta	-	TIM2_CH1, TIM5_CH1, TIM8_ETR, TIM15_BKIN, SPI2_RDY, SPI3_RDY, USART2_CTS/USART2_NSS, UART4_TX, SPI2_NSS/I2S2_WS, TIM2_ETR, EVENTOUT	ADC1_IN0, ADC2_IN0, COMP1_INP1, TAMP_IN2, WKUP1
7	7	11	11	15	15	19	24	PA1	I/O	FT_ta	-	TIM2_CH2, TIM5_CH2, TIM8_BKIN, TIM15_CH1N, LPTIM1_IN1, USART2_RTS, UART4_RX, EVENTOUT	ADC1_IN1, ADC2_IN1, TAMP_IN3
8	8	12	12	16	16	20	25	PA2	I/O	FT_ta	-	TIM2_CH3, TIM5_CH3, LPUART1_RX, TIM15_CH1, LPTIM1_IN2, USART2_TX, EVENTOUT	ADC1_IN2, ADC2_IN2, TAMP_IN3, WKUP2
9	9	13	13	17	17	21	26	PA3	I/O	FT_a	-	TIM2_CH4, TIM5_CH4, LPUART1_TX, TIM15_CH2, SPI2_NSS/I2S2_WS, SPI3_MOSI/ I2S3_SDO, USART2_RX, COMP1_OUT, EVENTOUT	ADC1_IN3, ADC2_IN3

