

Pin number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
LQFP32	UFQFPN32	LQFP48	UFQFPN48	LQFP64	LQFP64 alternative pinout ⁽¹⁾	LQFP80	LQFP100						
-	-	-	-	18	18	22	27	VSS	S	-	-	-	-
-	-	-	-	19	19	23	28	VDD	S	-	-	-	-
10	10	14	14	20	20	24	29	PA4	I/O	TT_a	-	TIM5_ETR, SPI3_MOSI/ I2S3_SDO, SPI1_NSS/I2S1_WS, SPI3_NSS/I2S3_WS, USART2_CK, EVENTOUT	ADC1_IN4, DAC1_OUT1
11	11	15	15	21	21	25	30	PA5	I/O	FT_a	-	TIM2_CH1, TIM1_CH3, TIM8_CH1N, SPI1_SCK/ I2S1_CK, SPI2_SCK/I2S2_CK, USART1_CTS/USART1_NSS, TIM2_ETR, EVENTOUT	ADC1_IN5, COMP1_INM3
12	12	16	16	22	22	26	31	PA6	I/O	FT_a	-	TIM1_BKIN, TIM5_CH1, TIM8_BKIN, SPI1_MISO/ I2S1_SDI, USART1_TX, LPUART1_RTS, EVENTOUT	ADC1_IN6
13	13	17	17	23	23	27	32	PA7	I/O	FT_a	-	TIM1_CH1N, TIM5_CH2, TIM8_CH1N, TIM15_CH1, SPI1_MOSI/I2S1_SDO, SPI2_MISO/I2S2_SDI, USART1_RX, LPUART1_CTS, EVENTOUT	ADC1_IN7
-	-	-	-	24	24	28	33	PC4	I/O	FT_a	-	TIM2_CH4, TIM8_BKIN, I2S1_MCK, USART3_RX, TIM16_CH1, EVENTOUT	ADC2_IN4, COMP1_INM1
-	-	-	-	25	25	29	34	PC5	I/O	FT_a	-	TIM1_CH4N, TIM8_BKIN2, TIM16_CH1N, COMP1_OUT, EVENTOUT	ADC2_IN5
14	14	18	18	26	26	30	35	PB0	I/O	FT_a	-	TIM1_CH2N, TIM5_CH3, TIM8_CH2N, SPI3_MISO/ I2S3_SDI, USART2_TX, UART4_CTS, EVENTOUT	ADC2_IN6, COMP1_INP2
-	15	19	19	27	27	31	36	PB1	I/O	FT_a	-	TIM1_CH3N, TIM5_CH4, TIM8_CH3N, SPI3_SCK/ I2S3_CK, SPI2_NSS/I2S2_WS, USART3_RX, COMP1_OUT, EVENTOUT	ADC2_IN7, COMP1_INM2

