

| Pin number |          |        |          |        |                                             |        |         | Pin name<br>(function after<br>reset) | Pin type | I/O<br>structure | Notes | Alternate functions                                                                                                                              | Additional<br>functions |
|------------|----------|--------|----------|--------|---------------------------------------------|--------|---------|---------------------------------------|----------|------------------|-------|--------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------|
| LQFP32     | UFQFPN32 | LQFP48 | UFQFPN48 | LQFP64 | LQFP64<br>alternative pinout <sup>(1)</sup> | LQFP80 | LQFP100 |                                       |          |                  |       |                                                                                                                                                  |                         |
| -          | -        | -      | -        | 38     | 38                                          | 50     | 64      | PC7                                   | I/O      | FT               | -     | TIM5_CH2, TIM8_CH2,<br>I2S3_MCK, EVENTOUT                                                                                                        | -                       |
| -          | -        | -      | -        | 39     | 39                                          | 51     | 65      | PC8                                   | I/O      | FT               | -     | TRACED1, TIM5_CH3,<br>TIM8_CH3, UART5_RTS,<br>EVENTOUT                                                                                           | -                       |
| -          | -        | -      | -        | 40     | 40                                          | 52     | 66      | PC9                                   | I/O      | FT_f             | -     | MCO2, TIM5_CH4, TIM8_CH4,<br>AUDIOCLK, UART5_CTS,<br>I2C1_SDA, EVENTOUT                                                                          | -                       |
| 19         | 19       | 29     | 29       | 41     | 41                                          | 53     | 67      | PA8                                   | I/O      | FT_f             | -     | MCO1, TIM1_CH1, I3C1_SDA,<br>TIM8_BKIN2, TIM15_CH2,<br>SPI1_RDY, SPI2_MOSI/<br>I2S2_SDO, USART1_CK,<br>TIM5_CH4, I2C1_SCL,<br>TIM2_CH4, EVENTOUT | -                       |
| 20         | 20       | 30     | 30       | 42     | 42                                          | 54     | 68      | PA9                                   | I/O      | FT               | -     | MCO2, TIM1_CH2, I3C1_SCL,<br>LPUART1_TX, TIM15_CH1N,<br>SPI2_SCK/I2S2_CK,<br>USART1_TX, TIM5_ETR,<br>I2C1_SMBA, TIM8_CH2N,<br>EVENTOUT           | -                       |
| -          | -        | 31     | 31       | 43     | 43                                          | 55     | 69      | PA10                                  | I/O      | FT               | -     | TIM1_CH3, LPUART1_RX,<br>USART1_RX, EVENTOUT                                                                                                     | -                       |
| 21         | 21       | 32     | 32       | 44     | 44                                          | 56     | 70      | PA11                                  | I/O      | FT_fu            | (4)   | TIM1_CH4, LPUART1_CTS,<br>USART2_TX, SPI2_NSS/<br>I2S2_WS, UART4_RX,<br>USART1_CTS/USART1_NSS,<br>I2C2_SCL, FDCAN1_RX,<br>EVENTOUT               | USB_DM                  |
| 22         | 22       | 33     | 33       | 45     | 45                                          | 57     | 71      | PA12                                  | I/O      | FT_fu            | (4)   | TIM1_ETR, LPUART1_RTS,<br>USART2_RX, SPI2_SCK/<br>I2S2_CK, UART4_TX,<br>USART1_RTS, I2C2_SDA,<br>FDCAN1_TX, EVENTOUT                             | USB_DP                  |
| 23         | 23       | 34     | 34       | 46     | 46                                          | 58     | 72      | PA13 (JTMS/<br>SWDIO)                 | I/O      | FT               | (5)   | JTMS/SWDIO, COMP1_OUT,<br>EVENTOUT                                                                                                               | -                       |
| -          | -        | -      | -        | -      | -                                           | -      | 73      | PH3                                   | I/O      | FT               | -     | EVENTOUT                                                                                                                                         | -                       |

