

Pin number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
LQFP32	UFQFPN32	LQFP48	UFQFPN48	LQFP64	LQFP64 alternative pinout ⁽¹⁾	LQFP80	LQFP100						
-	-	-	-	-	-	-	86	PD5	I/O	FT	(4)	TIM1_CH4N, SPI2_RDY, USART2_TX, FDCAN1_TX, EVENTOUT	-
-	-	-	-	-	-	-	87	PD6	I/O	FT	-	SPI3_MOSI/I2S3_SDO, USART2_RX, EVENTOUT	-
-	-	-	-	-	-	-	88	PD7	I/O	FT	-	SPI1_MOSI/I2S1_SDO, SPI3_MISO/I2S3_SDI, USART2_CK, EVENTOUT	-
26	26	39	39	55	55	69	89	PB3 (JTDO/ TRACESWO)	I/O	FT_f	(4)	JTDO/TRACESWO, TIM2_CH2, TIM5_CH3, I2C2_SDA, SPI1_SCK/I2S1_CK, SPI3_SCK/ I2S3_CK, LPUART1_TX, I2C2_SCL, CRS_SYNC, USART3_TX, TIM8_CH1, UART5_RTS, EVENTOUT	-
27	27	40	40	56	56	70	90	PB4 (NJTRST)	I/O	FT_f	(5)	NJTRST, TIM5_CH1, I3C1_SCL, LPTIM1_CH2, SPI1_MISO/ I2S1_SDI, SPI3_MISO/I2S3_SDI, SPI2_NSS/I2S2_WS, LPUART1_CTS, I2C2_SDA, TIM16_BKIN, USART3_RX, TIM8_CH2, UART5_CTS, EVENTOUT	-
28	28	41	41	57	57	71	91	PB5	I/O	FT	(4)	TIM17_BKIN, TIM5_CH2, I3C1_SDA, I2C1_SMBA, SPI1_MOSI/I2S1_SDO, SPI3_MOSI/I2S3_SDO, LPUART1_RTS, FDCAN1_RX, USART3_CK, TIM8_CH3, UART5_RX, EVENTOUT	-
29	29	42	42	58	58	72	92	PB6	I/O	FT_f	(4)	I3C1_SCL, I2C1_SCL, SPI3_MISO/I2S3_SDI, USART1_TX, LPUART1_TX, FDCAN1_TX, TIM16_CH1N, USART3_CTS/USART3_NSS, TIM8_CH4, UART5_TX, EVENTOUT	-

