

Pin number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
LQFP32	UFQFPN32	LQFP48	UFQFPN48	LQFP64	LQFP64 alternative pinout ⁽¹⁾	LQFP80	LQFP100						
-	-	26	26	34	34	42	52	PB13	I/O	FT	-	TIM1_CH1N, TIM8_CH2, LPTIM1_CH1, I2C2_SMBA, SPI2_SCK/I2S2_CK, USART3_CTS/USART3_NSS, LPUART1_RX, FDCAN1_TX, UART5_TX, EVENTOUT	-
-	-	27	27	35	35	43	53	PB14	I/O	FT	-	TIM1_CH2N, TIM12_CH1, TIM8_CH2N, USART1_TX, SPI2_MISO/I2S2_SDI, USART3_RTS, UART4_RTS, EVENTOUT	-
18	18	28	28	36	36	44	54	PB15	I/O	FT	-	RTC_REFIN, TIM1_CH3N, TIM12_CH2, TIM8_CH3N, USART1_RX, SPI2_MOSI/ I2S2_SDO, SPI1_MOSI/ I2S1_SDO, SPI3_MOSI/ I2S3_SDO, UART4_CTS, UART5_RX, EVENTOUT	-
-	-	-	-	-	-	-	55	PD8	I/O	FT	-	USART3_TX, EVENTOUT	-
-	-	-	-	-	-	-	56	PD9	I/O	FT	-	USART3_RX, EVENTOUT	-
-	-	-	-	-	-	-	57	PD10	I/O	FT	-	MCO2, LPTIM1_CH2, USART3_CK, EVENTOUT	-
-	-	-	-	-	-	-	58	PD11	I/O	FT	-	LPTIM1_IN2, USART3_CTS/ USART3_NSS, UART4_RX, EVENTOUT	-
-	-	-	-	-	-	45	59	PD12	I/O	FT	-	LPTIM1_IN1, TIM8_CH1N, I3C1_SCL, USART3_RTS, UART4_TX, EVENTOUT	-
-	-	-	-	-	-	46	60	PD13	I/O	FT	-	LPTIM1_CH1, TIM8_CH2N, I3C1_SDA, EVENTOUT	-
-	-	-	-	-	-	47	61	PD14	I/O	FT	-	TIM8_CH3N, EVENTOUT	-
-	-	-	-	-	-	48	62	PD15	I/O	FT	-	TIM8_CH4N, EVENTOUT	-
-	-	-	-	37	37	49	63	PC6	I/O	FT	-	TIM5_CH1, TIM8_CH1, I2S2_MCK, EVENTOUT	-

