

Pin number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
LQFP32	UFQFPN32	LQFP48	UFQFPN48	LQFP64	LQFP64 alternative pinout ⁽¹⁾	LQFP80	LQFP100						
-	-	35	35	47	47	59	74	VSS	S	-	-	-	-
-	-	36	36	48	48	60	75	VDD	S	-	-	-	-
24	24	37	37	49	49	61	76	PA14 (JTCK/ SWCLK)	I/O	FT	(4)	JTCK/SWCLK, EVENTOUT	-
25	25	38	38	50	50	62	77	PA15(JTDI)	I/O	FT	(4)	JTDI, TIM2_CH1, TIM1_CH2N, LPTIM1_ETR, I2C2_SMBA, SPI1_NSS/I2S1_WS, SPI3_NSS/ I2S3_WS, USART2_CK, UART4_RTS, USART1_TX, TIM8_CH4N, TIM2_ETR, EVENTOUT	-
-	-	-	-	51	51	63	78	PC10	I/O	FT	-	TIM8_CH1N, I3C1_SCL, SPI3_SCK/I2S3_CK, USART3_TX, UART4_TX, EVENTOUT	-
-	-	-	-	52	52	64	79	PC11	I/O	FT	-	TIM8_CH2N, I3C1_SDA, SPI3_MISO/I2S3_SDI, USART3_RX, UART4_RX, EVENTOUT	-
-	-	-	-	53	53	65	80	PC12	I/O	FT	-	TRACED3, TIM15_CH1, TIM8_CH3N, SPI3_MOSI/ I2S3_SDO, USART3_CK, UART5_TX, EVENTOUT	-
-	-	-	-	-	-	66	81	PD0	I/O	FT	-	TIM8_CH4N, UART4_RX, FDCAN1_RX, EVENTOUT	-
-	-	-	-	-	-	67	82	PD1	I/O	FT	-	UART4_TX, FDCAN1_TX, EVENTOUT	-
-	-	-	-	54	54	68	83	PD2	I/O	FT	-	TRACED2, TIM15_BKIN, UART5_RX, EVENTOUT	WKUP7
-	-	-	-	-	-	-	84	PD3	I/O	FT	-	SPI2_SCK/I2S2_CK, USART2_CTS/USART2_NSS, EVENTOUT	-
-	-	-	-	-	-	-	85	PD4	I/O	FT	-	USART2_RTS, EVENTOUT	-

