

Table 11. STM32C59xxx pin/ball definition

Pin Number									Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64	VFQFPN68	LQFP80	LQFP100	LQFP144						
-	-	1	1	1	1	1	1	1	PE2	I/O	FT	-	TRACECLK, LPTIM1_IN2, SPI3_SCK/I2S3_CK, XSPI1_IO2, ETH1_MII_TXD3, EVENTOUT	
-	-	-	-	-	-	2	2	2	PE3	I/O	FT	-	TRACED0, TIM15_BKIN, USART1_RX, EVENTOUT	
-	-	-	-	-	-	-	3	3	PE4	I/O	FT	-	TRACED1, TIM15_CH1N, SPI3_NSS/I2S3_WS, USART1_TX, ETH1_MII_RXD0/ETH1_RMII_RXD0, EVENTOUT	
-	-	-	-	-	-	-	4	4	PE5	I/O	FT	-	TRACED2, TIM15_CH1, SPI3_MISO/I2S3_SDI, USART1_CK, ETH1_MII_RXD1/ETH1_RMII_RXD1, EVENTOUT	
-	-	-	-	-	-	-	5	5	PE6	I/O	FT	-	TRACED3, TIM1_BKIN2, TIM15_CH2, SPI3_MOSI/I2S3_SDO, USART1_CTS/USART1_NSS, EVENTOUT	WKUP3
-	-	-	-	-	-	-	6	6	PH15	I/O	FT	-	USART1_RTS, EVENTOUT	
-	-	2	2	2	2	3	7	7	PC13	I/O	FT_t	(1)(2)	FDCAN1_TX, EVENTOUT	TAMP_IN1, RTC_OUT1/RTC_TS, WKUP4
2	2	3	3	3	3	4	8	8	PC14-OSC32_IN(OSC32_IN)	I/O	FT	(1)	TIM12_CH1, FDCAN1_RX, EVENTOUT	OSC32_IN
-	-	4	4	4	4	5	9	9	PC15-OSC32_OUT(OSC32_OUT)	I/O	FT	(1)	TIM12_CH2, EVENTOUT	OSC32_OUT
-	-	-	-	-	-	-	-	10	PF0	I/O	FT_f	-	I2C2_SDA, EVENTOUT	-
-	-	-	-	-	-	-	-	11	PF1	I/O	FT_f	-	I2C2_SCL, EVENTOUT	-
-	-	-	-	-	-	-	-	12	PF2	I/O	FT	-	I2C2_SMBA, EVENTOUT	-
-	-	-	-	-	-	-	-	13	PF3	I/O	FT	-	EVENTOUT	-
-	-	-	-	-	-	-	-	14	PF4	I/O	FT	-	EVENTOUT	-
-	-	-	-	-	-	-	-	15	PF5	I/O	FT_f	-	I3C1_SCL, EVENTOUT	-
-	-	-	-	-	-	6	10	16	VSS	S		-		-

