

Pin Number									Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64	VFQFPN68	LQFP80	LQFP100	LQFP144						
11	11	15	15	21	21	25	30	41	PA5	I/O	FT_a	-	TIM2_CH1, TIM1_CH3, TIM8_CH1N, SPI1_SCK/I2S1_CK, SPI2_SCK/I2S2_CK, USART1_CTS/USART1_NSS, XSPI1_IO1, ETH1_MII_TX_EN/ETH1_RMII_TX_EN, XSPI1_NCS1, TIM2_ETR, EVENTOUT	ADC1_IN5, COMP1_INM3
12	12	16	16	22	22	26	31	42	PA6	I/O	FT_a	-	TIM1_BKIN, TIM3_CH1, TIM8_BKIN, SPI1_MISO/I2S1_SDI, USART1_TX, LPUART1_RTS, XSPI1_IO3, EVENTOUT	ADC1_IN6
13	13	17	17	23	23	27	32	43	PA7	I/O	FT_a	-	TIM1_CH1N, TIM3_CH2, TIM8_CH1N, TIM15_CH1, SPI1_MOSI/I2S1_SDO, SPI2_MISO/I2S2_SDI, USART1_RX, LPUART1_CTS, ETH1_MII_RX_DV/ETH1_RMII_CRS_DV, XSPI1_IO2, EVENTOUT	ADC1_IN7
-	-	-	-	24	24	28	33	44	PC4	I/O	FT_a	-	TIM2_CH4, TIM8_BKIN, I2S1_MCK, USART3_RX, TIM16_CH1, ETH1_MII_RXD0/ETH1_RMII_RXD0, EVENTOUT	ADC2_IN4, COMP1_INM1
-	-	-	-	25	25	29	34	45	PC5	I/O	FT_a	-	TIM1_CH4N, TIM8_BKIN2, TIM16_CH1N, XSPI1_DQS, ETH1_MII_RXD1/ETH1_RMII_RXD1, COMP1_OUT, EVENTOUT	ADC2_IN5
14	14	18	18	26	26	30	35	46	PB0	I/O	FT_a	-	TIM1_CH2N, TIM3_CH3, TIM8_CH2N, SPI3_MISO/I2S3_SDI, USART2_TX, UART4_CTS, ETH1_MII_RXD2, XSPI1_IO1, EVENTOUT	ADC2_IN6, ADC3_IN0, COMP1_INP2
15	-	19	19	27	27	31	36	47	PB1	I/O	FT_a	-	TIM1_CH3N, TIM3_CH4, TIM8_CH3N, SPI3_SCK/I2S3_CK, SPI2_NSS/I2S2_WS, USART3_RX, ETH1_MII_RXD3, XSPI1_IO0, COMP1_OUT, EVENTOUT	ADC2_IN7, ADC3_IN1, COMP1_INM2

