

| Pin Number |        |        |          |        |          |        |         |         | Pin name (function after reset) | Pin type | I/O structure | Notes | Alternate functions                                                                                                                                                       | Additional functions |
|------------|--------|--------|----------|--------|----------|--------|---------|---------|---------------------------------|----------|---------------|-------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------|
| UFQFPN32   | LQFP32 | LQFP48 | UFQFPN48 | LQFP64 | VFQFPN68 | LQFP80 | LQFP100 | LQFP144 |                                 |          |               |       |                                                                                                                                                                           |                      |
| -          | -      | -      | -        | -      | -        | -      | 45      | 67      | PE14                            | I/O      | FT_a          | -     | TIM1_CH4, EVENTOUT                                                                                                                                                        | ADC3_IN10            |
| -          | -      | -      | -        | -      | -        | -      | 46      | 68      | PE15                            | I/O      | FT_a          | -     | TIM1_BKIN, TIM1_CH4N, EVENTOUT                                                                                                                                            | ADC3_IN11            |
| -          | -      | 21     | 21       | 29     | 30       | 37     | 47      | 69      | PB10                            | I/O      | FT_f          | -     | TIM2_CH3, TIM8_CH1, LPTIM1_IN1, I2C2_SCL, SPI2_SCK/I2S2_CK, USART3_TX, XSPI1_NCS1, ETH1_MII_RX_ER, EVENTOUT                                                               | -                    |
| 16         | 15     | 22     | 22       | 30     | 31       | 38     | 48      | 70      | VCAP                            | S        |               | -     | -                                                                                                                                                                         | -                    |
| -          | 16     | 23     | 23       | 31     | 32       | 39     | 49      | 71      | VSS                             | S        |               | -     | -                                                                                                                                                                         | -                    |
| 17         | 17     | 24     | 24       | 32     | 33       | 40     | 50      | 72      | VDD                             | S        |               | -     | -                                                                                                                                                                         | -                    |
| -          | -      | 25     | 25       | 33     | 34       | 41     | 51      | 73      | PB12                            | I/O      | FT_f          | -     | TIM1_BKIN, TIM8_CH3, I2C2_SDA, SPI2_NSS/I2S2_WS, USART3_CK, FDCAN2_RX, ETH1_MII_TXD0/ETH1_RMII_TXD0, XSPI1_NCLK, UART5_RX, EVENTOUT                                       | -                    |
| -          | -      | 26     | 26       | 34     | 35       | 42     | 52      | 74      | PB13                            | I/O      | FT            | -     | TIM1_CH1N, TIM8_CH2, LPTIM1_CH1, I2C2_SMBA, SPI2_SCK/I2S2_CK, USART3_CTS/USART3_NSS, LPUART1_RX, FDCAN2_TX, ETH1_MII_TX_EN/ETH1_RMII_TX_EN, XSPI1_DQS, UART5_TX, EVENTOUT | -                    |
| -          | -      | 27     | 27       | 35     | 36       | 43     | 53      | 75      | PB14                            | I/O      | FT            | -     | TIM1_CH2N, TIM12_CH1, TIM8_CH2N, USART1_TX, SPI2_MISO/I2S2_SDI, USART3_RTS, UART4_RTS, EVENTOUT                                                                           | -                    |

