

Pin Number									Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64	VFQFPN68	LQFP80	LQFP100	LQFP144						
19	19	29	29	41	44	53	67	100	PA8	I/O	FT_f	-	MCO1, TIM1_CH1, I3C1_SDA, TIM8_BKIN2, TIM15_CH2, SPI1_RDY, SPI2_MOSI/ I2S2_SDO, USART1_CK, TIM5_CH4, I2C1_SCL, UART7_RX, XSPI1_IO6, USB_SOF, TIM2_CH4, EVENTOUT	-
20	20	30	30	42	45	54	68	101	PA9	I/O	FT_f	-	MCO2, TIM1_CH2, I3C1_SCL, LPUART1_TX, TIM15_CH1N, SPI2_SCK/I2S2_CK, USART1_TX, TIM5_ETR, I2C1_SMBA, ETH1_MII_TX_ER, XSPI1_IO7, TIM8_CH2N, EVENTOUT	-
-	-	31	31	43	46	55	69	102	PA10	I/O	FT	-	TIM1_CH3, LPUART1_RX, USART1_RX, FDCAN2_TX, UART7_TX, XSPI1_CLK, ETH1_CLK, EVENTOUT	-
21	21	32	32	44	47	56	70	103	PA11	I/O	FT_f	-	TIM1_CH4, LPUART1_CTS, USART2_TX, SPI2_NSS/ I2S2_WS, UART4_RX, USART1_CTS/USART1_NSS, I2C2_SCL, FDCAN1_RX, XSPI1_NCS2, EVENTOUT	USB_DM
22	22	33	33	45	48	57	71	104	PA12	I/O	FT_f	-	TIM1_ETR, LPUART1_RTS, USART2_RX, SPI2_SCK/ I2S2_CK, UART4_TX, USART1_RTS, I2C2_SDA, FDCAN1_TX, EVENTOUT	USB_DP
23	23	34	34	46	49	58	72	105	PA13(JTMS/SWDIO)	I/O	FT	(3)	JTMS/SWDIO, COMP1_OUT, EVENTOUT	-
-	-	-	-	-	-	-	73	106	PH3	I/O	FT	-	EVENTOUT	-
-	-	35	35	47	50	59	74	107	VSS	S		-	-	-
-	-	36	36	48	51	60	75	108	VDD	S		-	-	-
24	24	37	37	49	52	61	76	109	PA14(JTCK/SWCLK)	I/O	FT	(3)	JTCK/SWCLK, EVENTOUT	-

