

Pin Number									Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64	VFQFPN68	LQFP80	LQFP100	LQFP144						
25	25	38	38	50	53	62	77	110	PA15(JTDI)	I/O	FT	(3)	JTDI, TIM2_CH1, TIM1_CH2N, LPTIM1_ETR, I2C2_SMBA, SPI1_NSS/I2S1_WS, SPI3_NSS/I2S3_WS, USART2_CK, UART4_RTS, ETH1_PHY_INTN, USART1_TX, TIM8_CH4N, TIM2_ETR, EVENTOUT	-
-	-	-	-	51	54	63	78	111	PC10	I/O	FT_f	-	TIM8_CH1N, I3C1_SCL, SPI3_SCK/I2S3_CK, USART3_TX, UART4_TX, XSPI1_IO1, ETH1_MII_TXD0/ETH1_RMII_TXD0, EVENTOUT	-
-	-	-	-	52	55	64	79	112	PC11	I/O	FT_f	-	TIM8_CH2N, I3C1_SDA, SPI3_MISO/I2S3_SDI, USART3_RX, UART4_RX, XSPI1_NCS1, EVENTOUT	-
-	-	-	-	53	56	65	80	113	PC12	I/O	FT	-	TRACED3, TIM15_CH1, TIM8_CH3N, SPI3_MOSI/I2S3_SDO, USART3_CK, UART5_TX, ETH1_PPS_OUT, EVENTOUT	-
-	-	-	-	-	-	66	81	114	PD0	I/O	FT	-	TIM8_CH4N, UART4_RX, FDCAN1_RX, XSPI1_NCS2, EVENTOUT	-
-	-	-	-	-	-	67	82	115	PD1	I/O	FT	-	UART4_TX, FDCAN1_TX, ETH1_MII_RX_DV/ETH1_RMII_CRS_DV, EVENTOUT	-
-	-	-	-	54	-	68	83	116	PD2	I/O	FT	-	TRACED2, TIM3_ETR, TIM15_BKIN, UART5_RX, XSPI1_NCS2, EVENTOUT	WKUP7
-	-	-	-	-	-	-	84	117	PD3	I/O	FT	-	SPI2_SCK/I2S2_CK, USART2_CTS/USART2_NSS, EVENTOUT	-
-	-	-	-	-	-	-	85	118	PD4	I/O	FT	-	USART2_RTS, ETH1_CLK, XSPI1_IO4, EVENTOUT	-

