

Pin Number									Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64	VFQFPN68	LQFP80	LQFP100	LQFP144						
-	-	-	-	-	-	-	86	119	PD5	I/O	FT	-	TIM1_CH4N, SPI2_RDY, USART2_TX, FDCAN1_TX, ETH1_MII_CRSS, XSPI1_IO5, EVENTOUT	-
-	-	-	-	-	-	-	-	120	VSS	S		-	-	-
-	-	-	-	-	-	-	-	121	VDD	S		-	-	-
-	-	-	-	-	-	-	87	122	PD6	I/O	FT	-	SPI3_MOSI/I2S3_SDO, USART2_RX, XSPI1_IO6, EVENTOUT	-
-	-	-	-	-	-	-	88	123	PD7	I/O	FT	-	SPI1_MOSI/I2S1_SDO, SPI3_MISO/I2S3_SDI, USART2_CK, XSPI1_IO7, EVENTOUT	-
-	-	-	-	-	-	-	-	124	PG9	I/O	FT	-	SPI1_MISO/I2S1_SDI, USART6_RX, XSPI1_IO6, EVENTOUT	-
-	-	-	-	-	-	-	-	125	PG10	I/O	FT	-	SPI1_NSS/I2S1_WS, USART6_CK, EVENTOUT	-
-	-	-	-	-	-	-	-	126	PG11	I/O	FT	-	LPTIM1_IN2, SPI1_SCK/I2S1_CK, ETH1_MII_TX_EN/ETH1_RMII_TX_EN, EVENTOUT	-
-	-	-	-	-	-	-	-	127	PG12	I/O	FT	-	LPTIM1_IN1, USART6_RTS, ETH1_MII_TXD1/ETH1_RMII_TXD1, EVENTOUT	-
-	-	-	-	-	-	-	-	128	PG13	I/O	FT	-	TRACED0, LPTIM1_CH1, USART6_CTS/USART6_NSS, ETH1_MII_TXD0/ETH1_RMII_TXD0, EVENTOUT	-
-	-	-	-	-	-	-	-	129	PG14	I/O	FT	-	TRACED1, LPTIM1_ETR, LPTIM1_CH2, USART6_TX, XSPI1_IO7, ETH1_MII_TXD1/ETH1_RMII_TXD1, EVENTOUT	-
-	-	-	-	-	-	-	-	130	VSS	S		-	-	-
-	-	-	-	-	-	-	-	131	VDD	S		-	-	-
-	-	-	-	-	-	-	-	132	PG15	I/O	FT	-	USART6_CTS/USART6_NSS, EVENTOUT	-

