

Pin Number									Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64	VFQFPN68	LQFP80	LQFP100	LQFP144						
26	26	39	39	55	57	69	89	133	PB3(JTDO/TRACESWO)	I/O	FT_f	(3)	JTDO/TRACESWO, TIM2_CH2, TIM5_CH3, I2C2_SDA, SPI1_SCK/I2S1_CK, SPI3_SCK/I2S3_CK, LPUART1_TX, I2C2_SCL, CRS_SYNC, USART3_TX, ETH1_MDC, TIM8_CH1, UART5_RTS, EVENTOUT	(3)
27	27	40	40	56	58	70	90	134	PB4(NJTRST)	I/O	FT_f	(3)	NJTRST, TIM3_CH1, I3C1_SCL, LPTIM1_CH2, SPI1_MISO/I2S1_SDI, SPI3_MISO/I2S3_SDI, SPI2_NSS/I2S2_WS, LPUART1_CTS, I2C2_SDA, TIM16_BKIN, USART3_RX, ETH1_MDIO, TIM8_CH2, UART5_CTS, EVENTOUT	(3)
28	28	41	41	57	59	71	91	135	PB5	I/O	FT_f	-	TIM17_BKIN, TIM3_CH2, I3C1_SDA, I2C1_SMBA, SPI1_MOSI/I2S1_SDO, SPI3_MOSI/I2S3_SDO, LPUART1_RTS, FDCAN2_RX, ETH1_PPS_OUT, USART3_CK, TIM8_CH3, UART5_RX, EVENTOUT	-
29	29	42	42	58	60	72	92	136	PB6	I/O	FT_f	-	TIM4_CH1, I3C1_SCL, I2C1_SCL, SPI3_MISO/I2S3_SDI, USART1_TX, LPUART1_TX, FDCAN2_TX, TIM16_CH1N, USART3_CTS/USART3_NSS, ETH1_MII_TX_ER, TIM8_CH4, UART5_TX, EVENTOUT	-
30	30	43	43	59	61	73	93	137	PB7	I/O	FT_f	-	TIM17_CH1N, TIM4_CH2, I3C1_SDA, I2C1_SDA, SPI3_SCK/I2S3_CK, USART1_RX, LPUART1_RX, FDCAN1_TX, TIM16_CH1, USART3_RTS, EVENTOUT	WKUP5
31	-	44	44	60	62	74	94	138	PH2-BOOT0	I/O	FT	-	MCO1, TIM17_CH1N, LPTIM1_IN2, FDCAN1_RX, EVENTOUT	-

