

Pin Number									Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64	VFQFPN68	LQFP80	LQFP100	LQFP144						
32	31	45	45	61	63	75	95	139	PB8	I/O	FT_f	-	TIM17_CH1, TIM4_CH3, I3C1_SCL, I2C1_SCL, SPI3_NSS/I2S3_WS, UART4_RX, FDCAN1_RX, ETH1_MII_TXD3, XSPI1_NCS1, EVENTOUT	-
-	-	46	46	62	64	76	96	140	PB9	I/O	FT_f	-	TIM4_CH4, I3C1_SDA, I2C1_SDA, SPI2_NSS/I2S2_WS, SPI3_SCK/I2S3_CK, UART4_TX, FDCAN1_TX, EVENTOUT	-
-	-	-	-	-	65	77	97	141	PE0	I/O	FT	-	LPTIM1_ETR, TIM4_ETR, SPI3_RDY, FDCAN1_RX, XSPI1_NCS2, EVENTOUT	-
-	-	-	-	-	66	78	98	142	PE1	I/O	FT	-	LPTIM1_IN2, FDCAN1_TX, EVENTOUT	-
-	32	47	47	63	67	79	99	143	VSS	S		-	-	-
1	1	48	48	64	68	80	100	144	VDD	S		-	-	-

1. After a RTC domain reset, PC13, PC14, and PC15 operate as GPIOs. Their function depends on the content of the RTC registers that are not reset by the system reset. For details on how to manage these GPIOs, refer to the backup domain and RTC register descriptions in the product reference manual.
2. Toggling the PC13 port can disturb the low-speed crystal connected to the LSE on PC14 and PC15. Refer to product errata sheet for more details.
3. After reset, this pin is configured for JTAG or SWD alternate function. The internal pull-up on the PA15, PA13, and PB4 pins, and the internal pull-down on the PA14 pin, are activated.

