



Port		AF0	AF1	AF2	AF3	AF4	AF5	AF6	AF7	AF8	AF9	AF10	AF11	AF12	AF13	AF14	AF15
		SYS	LPTIM1/ TIM1/2/17	I3C1/ TIM1/3/4/5/8/12/15	I3C1/LPTIM1/ LPUART1/ TIM1/5/8	I2C1/2/I3C1/ LPTIM1/ SPI1/I2S1/ SPI2/I2S2/ SPI3/I2S3/ TIM15/ USART1/2	I3C1/ LPTIM1/ SPI1/I2S1/ SPI2/I2S2/ SPI3/I2S3/ SPI1/ I2S3/SYS	SPI1/I2S1/ SPI2/I2S2/ SPI3/I2S3/ UART4	SPI2/I2S2/ SPI3/I2S3/ UART7/ USART1/2/3/6/ XSP1	I2C2/ LPUART1/ TIM5/UART4/5	FDCAN1/2/ I2C1/2/SPI2/ I2S2/XSP1	CRS/ETH1_ TIM16/ UART7	USART1/3/ XSP1	ETH1_ 	ETH1_ TIM8/ USB_ 	COMP/TIM2/ UART5	SYS
Port F	PF8	-	-	-	-	-	-	-	UART7_RTS	-	-	TIM16_CH1N	XSP11_IO1	-	ETH1_MII_TX_ER	-	EVENTOUT
	PF9	-	TIM17_CH1N	-	-	-	-	-	UART7_CTS	-	-	ETH1_MDC	XSP11_IO0	-	-	-	EVENTOUT
	PF10	-	-	-	-	-	-	-	-	-	XSP11_CLK	TIM16_BKIN	-	-	-	-	EVENTOUT
	PF11	-	-	-	-	-	-	-	-	-	XSP11_NCLK	-	-	-	-	-	EVENTOUT
	PF12	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	EVENTOUT
	PF13	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	EVENTOUT
	PF14	-	-	TIM3_ETR	-	-	-	-	-	-	-	-	-	-	-	-	EVENTOUT
	PF15	-	-	TIM4_ETR	-	-	I3C1_SDA	-	-	-	-	ETH1_CLK	-	-	-	-	EVENTOUT
Port G	PG0	-	-	TIM4_CH1	-	-	-	-	-	-	-	-	-	-	-	-	EVENTOUT
	PG1	-	-	TIM4_CH2	-	-	-	-	SPI2_MOSI/ I2S2_SDO	-	-	-	-	-	-	-	EVENTOUT
	PG2	-	-	TIM4_CH3	TIM8_BKIN	-	-	-	-	-	-	-	-	-	-	-	EVENTOUT
	PG3	-	-	TIM4_CH4	TIM8_BKIN2	-	-	-	-	-	-	UART7_RX	-	-	ETH1_MII_RX_ER	-	EVENTOUT
	PG4	-	TIM1_BKIN2	TIM5_CH1	-	-	-	-	-	-	-	-	-	-	-	-	EVENTOUT
	PG5	-	TIM1_ETR	TIM5_CH2	-	-	-	-	-	-	-	-	-	-	-	-	EVENTOUT
	PG6	-	TIM17_BKIN	TIM5_CH3	I3C1_SDA	-	SPI1_RDY	-	-	-	-	-	XSP11_NCS1	-	-	-	EVENTOUT
	PG7	-	-	TIM5_CH4	I3C1_SCL	-	-	-	USART6_CK	-	-	-	-	-	-	-	EVENTOUT
	PG8	-	-	TIM5_ETR	TIM8_ETR	-	SPI3_MOSI/ I2S3_SDO	-	USART6_RTS	-	-	ETH1_PPS_OUT	-	-	-	-	EVENTOUT
	PG9	-	-	-	-	-	SPI1_MISO/ I2S1_SDI	-	USART6_RX	-	XSP11_IO6	-	-	-	-	-	EVENTOUT
	PG10	-	-	-	-	-	SPI1_NSS/ I2S1_WS	-	USART6_CK	-	-	-	-	-	-	-	EVENTOUT
	PG11	-	LPTIM1_IN2	-	-	-	SPI1_SCK/ I2S1_CK	-	-	-	-	ETH1_MII_TX_EN/ ETH1_RMII_TX_EN	-	-	-	-	EVENTOUT
	PG12	-	LPTIM1_IN1	-	-	-	-	-	USART6_RTS	-	-	ETH1_MII_TXD1/ ETH1_RMII_TXD1	-	-	-	-	EVENTOUT
	PG13	TRACED0	LPTIM1_CH1	-	-	-	-	-	USART6_CTS/ USART6_NSS	-	-	ETH1_MII_TXD0/ ETH1_RMII_TXD0	-	-	-	-	EVENTOUT
	PG14	TRACED1	LPTIM1_ETR	-	-	LPTIM1_CH2	-	-	USART6_TX	-	XSP11_IO7	ETH1_MII_TXD1/ ETH1_RMII_TXD1	-	-	-	-	EVENTOUT
	PG15	-	-	-	-	-	-	-	USART6_CTS/ USART6_NSS	-	-	-	-	-	-	-	EVENTOUT
Port H	PH0	-	-	-	-	I2C1_SDA	-	-	-	-	-	-	-	-	-	-	EVENTOUT
	PH1	-	-	-	-	I2C1_SCL	-	-	-	-	-	-	-	-	-	-	EVENTOUT
	PH2	MCO1	TIM17_CH1N	-	LPTIM1_IN2	-	-	-	-	-	FDCAN1_RX	-	-	-	-	-	EVENTOUT
	PH3	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	EVENTOUT
	PH4	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	EVENTOUT
	PH5	-	-	-	-	-	-	-	-	-	-	-	-	-	-	-	EVENTOUT
	PH15	-	-	-	-	-	-	-	USART1_RTS	-	-	-	-	-	-	-	EVENTOUT