

| Pin Number |        |        |          |        |        |         |         | Pin name (function after reset) | Pin type | I/O structure | Notes | Alternate functions                                                                                                                                                                                  | Additional functions |
|------------|--------|--------|----------|--------|--------|---------|---------|---------------------------------|----------|---------------|-------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------|
| UFQFPN32   | LQFP32 | LQFP48 | UFQFPN48 | LQFP64 | LQFP80 | LQFP100 | LQFP144 |                                 |          |               |       |                                                                                                                                                                                                      |                      |
| -          | -      | -      | -        | -      | -      | 46      | 68      | PE15                            | I/O      | FT_a          | -     | TIM1_BKIN, TIM1_CH4N, EVENTOUT                                                                                                                                                                       | ADC3_IN11            |
| -          | -      | 21     | 21       | 29     | 37     | 47      | 69      | PB10                            | I/O      | FT_f          | -     | TIM2_CH3, TIM8_CH1, LPTIM1_IN1, I2C2_SCL, SPI2_SCK/I2S2_CK, USART3_TX, XSPI1_NCS1, ETH1_MII_RX_ER, EVENTOUT                                                                                          | -                    |
| 16         | 15     | 22     | 22       | 30     | 38     | 48      | 70      | VCAP                            | S        |               | -     | -                                                                                                                                                                                                    | -                    |
| -          | 16     | 23     | 23       | 31     | 39     | 49      | 71      | VSS                             | S        |               | -     | -                                                                                                                                                                                                    | -                    |
| 17         | 17     | 24     | 24       | 32     | 40     | 50      | 72      | VDD                             | S        |               | -     | -                                                                                                                                                                                                    | -                    |
| -          | -      | 25     | 25       | 33     | 41     | 51      | 73      | PB12                            | I/O      | FT_f          | -     | TIM1_BKIN, TIM8_CH3, I2C2_SDA, SPI2_NSS/I2S2_WS, USART3_CK, FDCAN2_RX, ETH1_MII_TXD0/ETH1_RMII_TXD0, XSPI1_NCLK, UART5_RX, EVENTOUT                                                                  | -                    |
| -          | -      | 26     | 26       | 34     | 42     | 52      | 74      | PB13                            | I/O      | FT            | -     | TIM1_CH1N, TIM8_CH2, LPTIM1_CH1, I2C2_SMB, SPI2_SCK/I2S2_CK, USART3_CTS/USART3_NSS, LPUART1_RX, FDCAN2_TX, ETH1_MII_TX_EN/ETH1_RMII_TX_EN, XSPI1_DQS, UART5_TX, EVENTOUT                             | -                    |
| -          | -      | 27     | 27       | 35     | 43     | 53      | 75      | PB14                            | I/O      | FT            | -     | TIM1_CH2N, TIM12_CH1, TIM8_CH2N, USART1_TX, SPI2_MISO/I2S2_SDI, USART3_RTS, UART4_RTS, EVENTOUT                                                                                                      | -                    |
| 18         | 18     | 28     | 28       | 36     | 44     | 54      | 76      | PB15                            | I/O      | FT            | -     | RTC_REFIN, TIM1_CH3N, TIM12_CH2, TIM8_CH3N, USART1_RX, SPI2_MOSI/I2S2_SDO, SPI1_MOSI/I2S1_SDO, SPI3_MOSI/I2S3_SDO, UART4_CTS, XSPI1_IO0, ETH1_MII_TXD1/ETH1_RMII_TXD1, XSPI1_CLK, UART5_RX, EVENTOUT | -                    |

