

Pin Number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64	LQFP80	LQFP100	LQFP144						
-	-	-	-	-	-	55	77	PD8	I/O	FT	-	USART3_TX, ETH1_MII_RXD0/ ETH1_RMII_RXD0, EVENTOUT	-
-	-	-	-	-	-	56	78	PD9	I/O	FT	-	USART3_RX, FDCAN2_RX, EVENTOUT	-
-	-	-	-	-	-	57	79	PD10	I/O	FT	-	MCO2, LPTIM1_CH2, USART3_CK, ETH1_MII_CRS, EVENTOUT	-
-	-	-	-	-	-	58	80	PD11	I/O	FT	-	LPTIM1_IN2, USART3_CTS/ USART3_NSS, UART4_RX, XSPI1_IO0, ETH1_PTP_AUX_TS, EVENTOUT	-
-	-	-	-	-	45	59	81	PD12	I/O	FT_f	-	LPTIM1_IN1, TIM4_CH1, TIM8_CH1N, I3C1_SCL, USART3_RTS, UART4_TX, XSPI1_IO1, EVENTOUT	-
-	-	-	-	-	46	60	82	PD13	I/O	FT_f	-	LPTIM1_CH1, TIM4_CH2, TIM8_CH2N, I3C1_SDA, XSPI1_IO3, XSPI1_IO2, EVENTOUT	-
-	-	-	-	-	-	-	84	VDD	S		-	-	-
-	-	-	-	-	-	-	83	VSS	S		-	-	-
-	-	-	-	-	47	61	85	PD14	I/O	FT	-	TIM4_CH3, TIM8_CH3N, EVENTOUT	-
-	-	-	-	-	48	62	86	PD15	I/O	FT	-	TIM4_CH4, TIM8_CH4N, EVENTOUT	-
-	-	-	-	-	-	-	87	PG2	I/O	FT	-	TIM4_CH3, TIM8_BKIN, EVENTOUT	-
-	-	-	-	-	-	-	88	PG3	I/O	FT	-	TIM4_CH4, TIM8_BKIN2, UART7_RX, ETH1_MII_RX_ER, EVENTOUT	-
-	-	-	-	-	-	-	89	PG4	I/O	FT	-	TIM1_BKIN2, TIM5_CH1, EVENTOUT	-
-	-	-	-	-	-	-	90	PG5	I/O	FT	-	TIM1_ETR, TIM5_CH2, EVENTOUT	-

