

Pin Number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64	LQFP80	LQFP100	LQFP144						
-	-	-	-	-	-	-	124	PG9	I/O	FT	-	SPI1_MISO/I2S1_SDI, USART6_RX, XSPI1_IO6, EVENTOUT	-
-	-	-	-	-	-	-	125	PG10	I/O	FT	-	SPI1_NSS/I2S1_WS, USART6_CK, EVENTOUT	-
-	-	-	-	-	-	-	126	PG11	I/O	FT	-	LPTIM1_IN2, SPI1_SCK/I2S1_CK, ETH1_MII_TX_EN/ ETH1_RMII_TX_EN, EVENTOUT	-
-	-	-	-	-	-	-	127	PG12	I/O	FT	-	LPTIM1_IN1, USART6_RTS, ETH1_MII_TXD1/ ETH1_RMII_TXD1, EVENTOUT	-
-	-	-	-	-	-	-	128	PG13	I/O	FT	-	TRACED0, LPTIM1_CH1, USART6_CTS/USART6_NSS, ETH1_MII_TXD0/ ETH1_RMII_TXD0, EVENTOUT	-
-	-	-	-	-	-	-	129	PG14	I/O	FT	-	TRACED1, LPTIM1_ETR, LPTIM1_CH2, USART6_TX, XSPI1_IO7, ETH1_MII_TXD1/ ETH1_RMII_TXD1, EVENTOUT	-
-	-	-	-	-	-	-	130	VSS	S		-	-	-
-	-	-	-	-	-	-	131	VDD	S		-	-	-
-	-	-	-	-	-	-	132	PG15	I/O	FT	-	USART6_CTS/USART6_NSS, EVENTOUT	-
26	26	39	39	55	69	89	133	PB3(JTDO/TRACESWO)	I/O	FT_f	(3)	JTDO/TRACESWO, TIM2_CH2, TIM5_CH3, I2C2_SDA, SPI1_SCK/ I2S1_CK, SPI3_SCK/I2S3_CK, LPUART1_TX, I2C2_SCL, CRS_SYNC, USART3_TX, ETH1_MDC, TIM8_CH1, UART5_RTS, EVENTOUT	(3)
27	27	40	40	56	70	90	134	PB4(NJTRST)	I/O	FT_f	(3)	NJTRST, TIM3_CH1, I3C1_SCL, LPTIM1_CH2, SPI1_MISO/ I2S1_SDI, SPI3_MISO/I2S3_SDI, SPI2_NSS/I2S2_WS, LPUART1_CTS, I2C2_SDA, TIM16_BKIN, USART3_RX, ETH1_MDIO, TIM8_CH2, UART5_CTS, EVENTOUT	(3)

