

5.3.20 Temperature sensor characteristics

Table 60. Temperature sensor characteristics

Symbol	Parameter	Min	Typ	Max	Unit
$T_L^{(1)}$	V_{SENSE} linearity with temperature (from V_{sensor} voltage)	-	-	3	°C
Avg_Slope ⁽²⁾	Average slope (from V_{sense} voltage)	-	2.14	-	mV/°C
$V_{30}^{(3)}$	Voltage at 30° C (± 1 ° C)	-	0.65	-	V
$t_{start_run}^{(1)}$	Startup time in Run mode (buffer startup)	-	-	25.2	μ s
$t_{S_temp}^{(1)}$	ADC sampling time when reading the temperature	13	-	-	
$I_{sens}^{(1)}$	Sensor consumption	-	0.18	0.29	μ A
$I_{sensbuf}^{(1)}$	Sensor buffer consumption	-	3.8	6.5	

1. Specified by design - Not tested in production.
2. Evaluated by characterization - Not tested in production.
3. Measured at $V_{DDA} = 3.3\text{ V} \pm 10\text{ mV}$. The V_{30} ADC conversion result is stored in the TS_CAL1.

Table 61. Temperature sensor calibration values

Symbol	Parameter	Memory address
TS_CAL1	Temperature sensor raw data acquired value at 30 °C, $V_{DDA} = 3.3\text{ V}$	0x08FF F814 - 0x08FF F815
TS_CAL2	Temperature sensor raw data acquired value at 140 °C, $V_{DDA} = 3.3\text{ V}$	0x08FF F818 - 0x08FF F819

5.3.21 Digital-to-analog converter characteristics (DAC)

Table 62. DAC characteristics

Specified by design and not tested in production.

specified by design and not tested in production.

Symbol	Parameter	Conditions		Min	Typ	Max	Unit
V _{DDA}	Analog supply voltage	-		2.7	-		V
V _{REF+}	Positive reference voltage	-		2.5	-	V _{DDA}	
V _{REF-}	Negative reference voltage	-		-	V _{SSA}	-	
R _L	Resistive Load	DAC output buffer ON	connected to V _{SSA}	5	-	-	KΩ
			connected to V _{DDA}	25	-	-	
R _O	Output Impedance	DAC output buffer OFF		10.3	13.00	16	
R _{BON}	Output impedance sample and hold mode, output buffer ON	DAC output buffer ON	V _{DD} = 2.7 V	-	-	1.6	KΩ
R _{BOFF}	Output impedance sample and hold mode, output buffer OFF	DAC output buffer OFF	V _{DD} = 2.7 V	-	-	17.8	KΩ
C _L	Capacitive Load	DAC output buffer OFF		-	-	50	pF
C _{SH}		Sample and Hold mode			0.10	1	μF
V _{DAC_OUT}	Voltage on DAC_OUT output	DAC output buffer ON		0.2	-	V _{DDA} - 0.2	V
		DAC output buffer OFF		0	-	V _{REF+}	