FMX-108DP AC Operation

With built-in MP3 Recorder & Digital Effects



8 CHANNEL

- Compact and reliable professional PA Mixer which is aesthetically superior and easily portable.
- Provided with two balanced XLR microphone inputs, with switchable +48V Phantom supply.
- Additionally, four low impedance microphones can be connected in either balanced or unbalanced configuration, through a 6.3 mm (1/4") stereo jack socket.
- Upto six line level signal sources can be connected in either balanced or unbalanced configuration, through a 6.3 mm (1/4") stereo jack socket.
- Each channel has a GAIN control for optimum adjustment of the MIC & LINE input sensitivities.
- Two band equalizer with active BASS & TREBLE controls in each channel for desired equalisation of the input signal.
- Separate FX (effects) level control for each input channel.
- MP3 digital player with recording and playback through USB. Bluetooth facility also available.
- One independent stereo input channel is provided with a GAIN control, 2 band EQ, FX & LEVEL Controls.
- Each channel has a PEAK LED which glows when the level of input signal is excessive.
- A push switch is provided for selection between Ch 7/8 and USB channel.
- Built-in digital effects processor with DELAY, REPEAT and LEVEL controls.
- Effects ON/OFF switch with FX ON & PEAK LEDs.
- Line level LEFT & RIGHT outputs through 6.3 mm (1/4") stereo jack sockets.
- Headphone output, with independent volume control, is available through a 6.3 mm (1/4") stereo jack socket.
- Individual SIGNAL & CLIP LEDs for optimum setting of Left & Right output levels.
- Individual MASTER volume controls for Left & Right line outputs.
- Operates on 240V, 50Hz AC Mains.

SPECIFICATIONS	FMX-108DP
MIC INPUT (IMPEDANCE/GAIN)	2kΩ Balanced/65dB, 1kΩ Unbalanced/65dB
LINE INPUT (IMPEDANCE/GAIN)	20kΩ Balanced/45dB, 10kΩ Unbalanced/45dB
DISTORTION	< 0.1%
FREQUENCY RESPONSE	25-20,000Hz (-1dB)
TONE CONTROLS	Bass: ±15dB at 80Hz, Treble: ±15dB at 12kHz
LINE OUTPUT	0dBu/+21dBu (775mV/9V)
DELAY SYSTEM	Digital Signal Processing
DELAY RANGE SETTINGS	Variable from 20 to 300ms
DIGITAL PLAYER	MP3 Player/Recorder with USB Reader, Bluetooth
SIGNAL TO NOISE RATIO	> 68dB
POWER SUPPLY	AC: 220-240V 50/60Hz
DIMENSIONS	W345 × H75 × D210mm
WEIGHT	1.85kg