AWM-495®VL

PA VHF Wireless Microphone



- Compact, Lightweight, Single Channel VHF Wireless Microphone available in different frequencies.
- Operates on Quartz Crystal Locked VHF High Band frequency.
- Internal antenna in the transmitter and a telescopic Antenna on the receiver for clear and distortion free reception.
- Receiver operates on 12V DC through an AC Adaptor supplied alongwith. Transmitter operates on 2 × 1.5V AA pencil cells.
- Transmitter has 2-position slide switch for 'ON' & 'OFF' positions.
- Audio output from receiver available through 6.3 mm (1/4") jack socket.
- Ideal for: PA Applications... Stage & Auditoriums... Seminar Halls... Places of Worship... Recreation Centres...

SPECIFICATIONS	TRANSMITTER
RF OUTPUT POWER	15mW (Max.)
MODULATION MODE	FM (F3E)
MICROPHONE ELEMENT	Condenser, Omnidirectional
DYNAMIC RANGE	80dB
FREQUENCY RESPONSE	80-15,000Hz
CURRENT CONSUMPTION	≤130mA
POWER REQUIREMENT	3V (2 × 1.5V AA Pencil Cells)
CONTROLS	Transmitter ON/OFF Switch, Volume Control
INDICATION	Red LED for indicating transmitter ON
DIMENSIONS	W67 × H32 × D95 mm
WEIGHT	60g (w/o battery)

SPECIFICATIONS	RECEIVER
FREQUENCY STABILITY	± 0.005% Quartz Crystal Controlled
RECEIVING METHOD	Non-diversity
AUDIO OUTPUT	0-55mV/1kΩ
SIGNAL TO NOISE RATIO	> 80dB
DISTORTION	< 0.5%
FREQUENCY RESPONSE	50-15,000Hz
ANTENNA	Telescopic
POWER REQUIREMENT	240V AC 50Hz from AC adaptor (supplied alongwith)
CONTROLS	Power On / Off Switch, Output Volume Control
INDICATIONS	Red LED for Power ON, Green LED for RF reception
DIMENSIONS	W230 × H42 × D150 mm
WEIGHT	305g

CWM-404U

PA UHF Wireless Microphone



- Compact and elegant high band UHF Wireless Microphone system with four gooseneck microphones.
- Available in different frequencies (3 sets of 4 each).
- Desktop Transmitters are unidirectional condenser types, fitted with gooseneck, ON/OFF switch and display for indicating channel, frequencies, AF led array and battery bar.
- Sleek elegant receiver which can receive signals from upto 4 Desktop Transmitters.
- Individual output volume control, RF LED and AF LED for each channel provided on the front panel of the receiver.
- Separate 6.3 mm phone jack for audio output from each channel and mix out also available on the rear panel.
- Desktop transmitter operates with 3.7V Lithium-Ion Rechargeable cell.
- Receiver operates on12V DC through an AC adaptor, supplied along with.

SPECIFICATIONS	TRANSMITTER
RF OUTPUT POWER	10mW (Max.)
MODULATION MODE	FM
MICROPHONE ELEMENT	Condenser, Cardioid
FREQUENCY RESPONSE	80-15,000Hz
POWER REQUIREMENT	3.7V (LI-ION BATTERY)
CURRENT CONSUMPTION	≤140mA
CONTROLS	ON/OFF slide switch and push Switch for mic ON/OFF
INDICATION	Display, red ring LED in the gooseneck & red round LED in the base
DIMENSIONS	W108 × H70 × D150 mm
WEIGHT	490g (without battery)

SPECIFICATIONS	RECEIVER
AUDIO OUTPUT	0-50mV adjustable (each channel)
S/N RATIO	>80dB
DISTORTION	<0.5%
ANTENNA TYPE	Telescopic
POWER REQUIREMENT	220V-240V AC 50Hz for AC adaptor (supplied along with)
CONTROLS	Power Switch, Output Volume Control for each channel
INDICATION	Display for Power ON, red LED for RF indication of each Channel, Geen LED for AF indication of each channel
DIMENSIONS	W483 × H52 × D210 mm
WEIGHT	1.80kg