ABA-5000

400 WATTS

Bi AMP | 2 WAY | 1×15"



Rear Panel



ABA-5000 has a built-in Bi-Amplifier for woofer and HF driver separately, for use in a wide variety of Professional and PA Programmes. Feature packed ABA-5000 is an ideal equipment for applications such as in Professional Music and Vocal Performances, Touring PA, Mini-Theatres, Pubs and Bars, Religious Gatherings, Stage Monitors etc.

- 1 × Balanced Mic/Line Input selectable through a push switch.
- 1 × Line Input can be used for connecting balanced MONO signal through jack or unbalanced STEREO signal source through dual RCA.
- Switchable balanced output either as a Loop through output of Input-1 or a mix output of Input-1 and 2.
- Balanced output to link another ABA-5000 or for recording on a computer, record player.
- 2-Way Speaker System: 38.1 cm (15") LF Woofer Ø7.6 cm (3.0") voice coil + Dynamic Horn Ø4.4 cm (1.75") voice coil.
- Moulded Cabinet Bi-Amp PA Active Loudspeaker.

SPECIFICATIONS	ABA-5000
POWER OUTPUT (Bi-AMP)	LF: 350W RMS at 1% THD Class H, HF: 50W RMS at 1% THD Class AB
OUTPUT REGULATION	≤ 0.5dB, no load to full load at 1kHz
INPUT CHANNELS	INPUT-1: MIC 20mV/3kΩ balanced, LINE: 775mV/10kΩ balanced, INPUT-2: LINE (Jack) 250mV/20kΩ balanced, RCA: 250mV (L&R)/10kΩ
FREQUENCY RESPONSE	50-20,000Hz ±3dB
CROSSOVER FREQUENCY	2.5kHz , Filter Slope 24dB per octave
SIGNAL TO NOISE RATIO	60dB
TONE CONTROLS	Bass: ±5dB at 100Hz, Treble: ±5dB at 10kHz
OUTPUT	(a) Loop through (INPUT-1): 20mV or 775mV (b) Mixed Output (1+2): 775mV/1kΩ
PROTECTIONS	AC: Fuse 1 × 5A (T 5A L) DC: Fuse 2 × 8A (T 8A L)
POWER SUPPLY	AC: 220-240V 50/60Hz
AC POWER CONSUMPTION	500VA
DIMENSIONS	W450 × H690 × D360 mm
WEIGHT	28.10kg



