



AXI FORZA

AXI FORZA H6/H8/H10/H12/H15/H20LV-3P

THREE PHASE & LV BATTERY HYBRID INVERTER

Excellent Performance

- 3 MPPTs with Max. PV Input power of 30kW
- Support high power module with 20A PV input current
- Up to 380A max. charging/discharging current
- Max. Grid Passthrough Current of 45A

Highly Flexible

- Support 40-60V Lithium or Lead-acid battery
- 3-Phase unbalanced output: Increase the self-use rate of solar energy
- Support smart load/generator/AC Coupling
- Max. 9 units parallel for on-gird and off-gird operation

Safe & Reliable

- IP65: Indoor or outdoor installation
- MC4 PV connectors, convenient for installation
- Multiple built-in protections, with optional AFCI 2.0/RSD/Battery breaker
- Seamless transition to backup mode, for protection against power outages

Intelligent Maintenance

- 4.3“ LCD color touchscreen, easy to operate
- 6 time periods for battery charging/discharging
- Intelligent Management, local & remote monitoring

AXI FORZA

AXI FORZA H6/H8/H10/H12/H15/H20LV-3P

	AXI FORZA H6 LV-3P	AXI FORZA H8 LV-3P	AXI FORZA H10LV-3P	AXI FORZA H12LV-3P	AXI FORZA H15LV-3P	AXI FORZA H15LV-3P
Efficiency						
Max. Efficiency	97.60%					
Input (PV)						
Max. PV Usable Power	25,000W	25,000W	40,000W	40,000W	40,000W	40,000W
Max. PV Input Voltage	1,000V					
Start-up Voltage	120V					
MPPT Voltage Range	160V-980V					
Max. Input Current per MPPT	20A/20A	20A/20A	20A/20A/20A	20A/20A/20A 25A/25A	20A/20A/20A	20A/20A/20A
Max. Short Circuit Current per	25A/25A					
No. of MPP Trackers	2	2	3	3	3	3
	1/1	1/1	1/1/1	1/1/1	1/1/1	1/1/1
Input/Output (BAT)						
2 Battery Input. Battery Type	Lithium-ion/Lead-acid					
Nominal Battery Voltage	48V					
Battery Voltage Range	40V-60V					
Max. Charge/Discharge Current	380A/150A	380A/200A	380A/250A	380A/300A	380A/350A	380A/380A
Max. Charge/Discharge Power	20,000W/7,200	20,000W/9,600	20,000W/12,000	20,000W/14,500	20,000W/18,000	20,000W/20,000
Input/Output (Grid)						
Nominal AC Output Power	6,000W	8,000W	10,000W	12,000W	15,000W	20,000W
Max. AC Output Apparent Power	6,600VA	8,800VA	11,000VA	13,200VA	16,500VA	22,000VA
Nominal AC Output Current	3*9.1A/3*8.7A/3*8.3A	3*12.1A/3*11.6A/3*11.1A	3*15.2A/3*14.5A/3*13.9A	3*18.2A/3*17.4A/3*16.7A	3*22.7A/3*21.7A/3*20.8A	3*30.3A/3*29A/3*27.8A
Max. Grid Passthrough Current	45A					
Nominal Voltage	220V/380V; 230V/400V, 240V/415V 3W+N+PE					
Nominal Frequency	50Hz/60Hz					
Power Factor	> 0.99 @rated power (Adjustable 0.8 LD - 0.8 LG)					
THDI	< 3% @ R Load					
Output (Back up)						
Nominal AC Output Power	6,000W	8,000W	10,000W	12,000W	15,000W	20,000W
Max. AC Output Apparent Power	6,600VA	8,800VA	11,000VA	13,200VA	16,500VA	22,000VA
Nominal AC Output Current	3*9.1A/3*8.7A/3*8.3A	3*12.1A/3*11.6A/3*11.1A	3*15.2A/3*14.5A/3*13.9A	3*18.2A/3*17.4A/3*16.7A	3*22.7A/3*21.7A/3*20.8A	3*30.3A/3*29A/3*27.8A
Peak Output Apparent Power	200% @10s					
Nominal Voltage	220V/380V; 230V/400V, 240V/415V 3W+N+PE					
Nominal Frequency	50Hz/60Hz					
Transfer Time	< 10ms (Typical)					
THDV	< 3% @ 100% R Load					
Protection						
Protection Category	Class I					
PV Switchl	Yes					
Anti-islanding Protection	Yes					
Overcurrent Protection	Yes					
Overvoltage Protection	Yes					
AC Short Circuit Protection	Yes					
PV Reverse Polarity Protection	Yes					
Surge Protection	Type II AC/DC					
General						
Max. Operation Altitude	4,000m (>2,000m derating)					
Operating Temperature Range	-25°C~60°C					
Relative Humidity	0~100%					
Ingress Protection Degree	IP65					
Cooling Method	Smart Cooling					
Mounting	Wall Bracket					
Dimensions (W*H*D)	460mm*742mm*266mm					
Weight	46.5kg					
HMI & COM						
Display	LED+LCD					
Communication Interfaces	RS485/CAN (for BMS), RS485 (for Meter), DRMs, CAN (for parallel), 2*DO, 2*DI, USB (for Wi-Fi/LAN,Optional)					
Certification						
Safety	IEC/EN 62109-1/2					
EMC	IEC/EN 61000-6-1/2/3/4, IEC/EN 62920					
Grid IEC	IEC 61727/62116, IEC 61683					
Warranty	5 Years					

- The range of output voltage and frequency may vary depending on different grid codes.
- Specifications are subject to change without advanced notice.

*: if only one set of terminals is used, the max battery charge/discharge current will be limited to 250A

© 2026 AXISolar All rights reserved.

Note: Please read the safety and installation manual before using the product.

axisolar.com info@axisolar.com