

BOARD_CH		
JST PH 4-pin (PHR-4)	female	4-pin
A2	1	
A1	2	
B1	3	
B2	4	
basically board v1.3 J39		

CH		
4x	24 AWG	40.0 in
BOARD_CH:1:A2	1:BK	CH_LEADS:1:A2
BOARD_CH:2:A1	2:GN	CH_LEADS:2:A1
BOARD_CH:3:B1	3:RD	CH_LEADS:3:B1
BOARD_CH:4:B2	4:BU	CH_LEADS:4:B2
qty 1. Gauge = GUESS. Length = GUESS (copied from channel cables). Straight-through.		

CH_LEADS	
Bare tinned leads, labeled 1-4	4-pin
1	A2
2	A1
3	B1
4	B2
splice to chute stepper flying leads - find coil pairs with a multimeter first	

BOARD_S		
JST PH 4-pin (PHR-4)	female	4-pin
A2	1	
A1	2	
B1	3	
B2	4	
basically board v1.3 J23/J27/J31/J35 - one cable per jack, x4 identical		

S		
4x	24 AWG	40.0 in
BOARD_S:1:A2	1:BK	MOTOR_LEAD:1:A2
BOARD_S:2:A1	2:RD	MOTOR_LEAD:3:A1
BOARD_S:3:B1	3:GN	MOTOR_LEAD:2:B1
BOARD_S:4:B2	4:BU	MOTOR_LEAD:4:B2
S1-S4, qty 4. Gauge = GUESS (JST-PH contact limit). NOT straight-through, see crossover.		

MOTOR_LEAD		
XH2.54 4-pin inline male (clone)	male	4-pin
1	A2	
2	B1	
3	A1	
4	B2	
mates the StepperOnline shipped motor lead, which interleaves the coils		