

SL No	Description	Qty
01	<p><u>315 KVA OIL IMMERSED TRANSFORMER</u></p> <p>Three phase transformers, step down type with normal accessories. Indoor on ONAN type natural; cooling, oil immersed. In accordance with IEC726, IEC & NFC52100 (normal test) standards and tolerance according to IEC 76 standards.</p> <p><u>Terminations:</u> HV= Connection from top into the connecting bars. LV= Connection from top into flat bus terminals.</p> <p>Rated power in KVA : 315 Frequency : 50Hz High Voltage : 11KV HV tapping by links (Off- circuit) in + -1.5%/ +-2.5% LV in Volts : 415V HV insulation Level in KV : 12 Rated Voltage: Primary : 11,000V Secondary : 415V Rated Current: Primary : 11.87A Secondary : 437.85A Power frequency KV rms : 28 Vector group : DYN 11 Max. Ambient temp. In Deg. C. : 40 Altitude Lower than in meter : 1000 Temp. Rise in Winding /oil in Deg.K : 40/55 No load loss : 800W Load loss at 75 deg.c : 2800W Impedance voltage : 4%</p> <p>Accessories: 4 No LT Bushing & 3 Nos. HT Bushing Silica Gel, Breather Dial Type Thermometer Horn Gap Arrestor Conservator Lifting Lugs Earthing Terminals Name plate</p> <p>Silicon core - : Nippon steel- Kawasaki-Japan. Transformer oil : Savita, India. Super Enamel wire : BRB/SQ/Gazi wire Bangladesh Copper strip : Oriental Copper Co- Singapore, BRB.</p> <p>ASSEMBLED BY: Uniko Power Ltd.</p>	01 no

SL No	Description	Qty
02	<p data-bbox="459 315 1158 353">(4) <u>11KV HT SWITCH-GEAR WITH LBS:</u></p> <p data-bbox="336 383 1211 461">Floor mounting indoor switch-gear with 630A hard drawn electrolytic copper bus-bars equipped with:</p> <p data-bbox="336 539 1246 618">1 - No. 630A, 11 KV, 20KA, 350 MVA rated short time current, 50 Hz</p> <p data-bbox="336 663 1243 752">Spring charged" stored energy mechanism triple pole LBS having automatic tripping mechanism whenever any of the fuse's blow.</p> <p data-bbox="336 790 692 828">Origin: ABB- ITALY.</p> <p data-bbox="336 891 1150 992">2 - Nos. Cast resin insulated, double pole, Potential Transformer, ratio: 11/11 kV Class, 0.5, 50 VA, (in open delta connection)</p> <p data-bbox="336 1128 746 1167">Origin: Micro, Malaysia .</p> <p data-bbox="336 1193 1118 1294">1 - No MCB of adequate rating for PT secondary protection</p> <p data-bbox="336 1323 1275 1402">3 - Nos. Cast resin insulated, 11 KV dry type CT with ratio: 30/5/5A, for meter with suitable accuracy class & burden.</p> <p data-bbox="336 1435 647 1473">Origin: ABB- Italy.</p> <p data-bbox="336 1503 676 1541">3 - Nos. Ammeter, 0-30A</p> <p data-bbox="336 1559 999 1597">1 - No. Voltmeter, 0-15 KV, with selector switch.</p> <p data-bbox="336 1615 676 1653">3 - Nos. 63A HRC Fuses.</p> <p data-bbox="336 1671 863 1709">2- Nos. On and Off/TRIP Push Button</p> <p data-bbox="336 1727 943 1765">3 - Nos. Indicating Lamps ON & OFF/TRIP</p> <p data-bbox="336 1783 608 1821">1- No.Panel Heater.</p> <p data-bbox="336 1839 1187 1917">ORIGIN: Assembled by Uniko Power Engineering Company Limited.</p>	01 no

SL No	Description	Qty
03	<p><u>500A LT SWITCH GEAR:</u></p> <p>a) 18 SWG Steel Sheet, floor mounting, free standing, 500V, 50HZ, indoor type Low Tension Switch Gear with hard drawn Copper bus bars, TPN & E Equipped with.</p> <p><u>Technical Specification:</u></p> <p><u>Incoming:</u> The panel comprising of: Incoming: 1 x 500A 36KA TP MCCB.</p> <p>4- Current transformer ratio:400/5A with suitable accuracy and burden.</p> <p>1-Ammeter scaled (Digital) (0-500A) with selector switch.</p> <p>1-Voltmmeter scaled (Digital) (0-500V) with selector switch.</p> <p>3- Indicating lamp R/Y/B.</p> <p><u>Out Going</u></p> <p>01x250A, 25KA, TP MCCB with adjustable thermal overload and magnetic Short- circuit releases (PFI)</p> <p>01x125A, 25KA, TP MCCB with adjustable thermal overload and magnetic Short- circuit releases (Generator)</p> <p>All MCCB and MCB-A.B.B. Italy/ Hyundai, Korea. ASSEMBLED BY: Uniko Power Engineering Company Limited.</p>	01 no

SL No	Description	Qty
04)	<p><u>190 KVAR PFI PLANT:</u></p> <p>Sheet steel clad, dust and vermin proof, free standing floor mounting, cubical made of 18 SWG sheet steel having front hinged type door with door locked. 190 KVAR, 415V, 3 phase, power factor improvement plant with the following components.</p> <p>1 Nos. 50 KVAR- power capacitor bank, 3-phase rated 415V, 50HZ with in-built discharge resistor.</p> <p>2 Nos. 25 KVAR-power capacitor bank, 3-phase rated 415V, 50HZ with in-built discharge.</p> <p>1 Nos. 20 KVAR- power capacitor bank, 3-phase rated 415V, 50HZ with in-built discharge.</p> <p>2 Nos. 15 KVAR- power capacitor bank, 3-phase rated 415V, 50HZ with in-built discharge.</p> <p>2 Nos. 10 KVAR- power capacitor bank, 3-phase rated 415V, 50HZ with in-built discharge.</p> <p>2 Nos. 7.5 KVAR- power capacitor bank, 3-phase rated 415V, 50HZ with in-built Fixt.</p> <p>1 Nos. 5 KVAR- power capacitor bank, 3-phase rated 415V, 50HZ with in-built Fixt.</p> <p>9 Nos. triple pole magnetic contactor, of adequate rating</p> <p>18 Nos. 415V, HRC fuses with base of adequate rating</p> <p>9 Nos. Indicating Lamps.</p> <p>3 set of Control fuse with base.</p> <p> *All Capacitor Origin: Epcos/ Havel's/ India.</p> <p>*Magnetic Contactor Origin: ABB, Italy/ Hyundai, Korea.</p> <p>* PFC relay Origin: Micro-Malaysia/Suzuki- Japan Tech.</p> <p> Assembled by: Uniko Power Engineering Company Limited.</p>	01 no

Sl No	Description	Qty
05.	<p><u>Lighting Arrester:</u></p> <p>Rated Voltage : 11 KV Rated System Voltage : 12 KV Frequency : 50Hz Minimum Spark Over- (rms) : 14 KV Maximum Spark Over (rms) : 40 KV Maximum Impulse Spark : 45KV Bill (Peak) : 75 KV</p> <p>Withstand Voltage : Wet 10 sec: : 24 KV Dry 1 Min: : 28 KV Discharge Current : 5 KA Impulse current Withstand : 55KA</p>	1 Set
06.	<p><u>Drop Out Fuse :</u></p> <p>Rated Voltage (Nominal) : 11 KV Rated Maximum Voltage : 15 KV Rated Frequency : 50Hz Bill : 75 KV Rated current : 50A Interrupting Current(rms) : 35 KA</p> <p>Withstand Test Voltage: Wet 10 sec : 30KV Dry 1 Min: : 35 KV</p> <p>Brand: Gem Co/ Brazil.</p>	1 Set

07. EARTHING OF SUB-STATION:

Supply and Installation of Sub-station earthing as per Specification with the followings:-

- (a)** Earthing of Sub-station and equipment with 1" dia G.I pipe 10' each Top and bottom up to a depth of 100 ft. in four pits using Copper Conductor of 4 SWG HDBC excluding making of inspection pits.
- (b)** Earthing of using 4 SWG Copper conductors (04 Nos*100').
- (c)** Supply Installation testing and Commissioning of 2 Nos Copper earthing block with required Nos of 1/4" hole for Elec Connection Size- 25*4*300mm for transformer neutral and another for all Sub-station equipment's ECC Connection.
- (d)** The earth electrode shall be Driven into the ground by tube well sinking method. The Top/head of the GI pipe after Completing all Connection shall be covered with Hessian cloth soaked in bitumen

WARRANTY CERTIFICATE

We stand warranty for trouble free operation of our supplied equipment and we undertake warranty for free replacement of any parts failing due to manufacturing defects, which shall Not Normal operational wear and tear, for a period of Transformer 36 months, LT switchgear and PFI plant 12 months from the date of delivery.

Thanking you,
Yours faithfully

For,
Uniko Power Engineering Company Limited.