



PagePulse Ollama Cheatsheet

Daily startup, setup, model commands, and troubleshooting for the local Chrome RAG extension.

Backend	<code>http://127.0.0.1:8001</code>
Ollama	<code>http://127.0.0.1:11434</code>
Chat model	<code>llama3.2:3b</code>
Embedding model	<code>nomic-embed-text</code>

Project folder:

```
C:\Users\Abhisekh\Music\webpage-rag-extension-ollama
```

Backend URL:

```
http://127.0.0.1:8001
```

Ollama URL:

```
http://127.0.0.1:11434
```

Chrome extension folder:

```
C:\Users\Abhisekh\Music\webpage-rag-extension-ollama\extension
```

Daily Start After Laptop Restart

- Check installed Ollama models:

```
ollama list
```

Expected models:

```
llama3.2:3b  
nomic-embed-text
```

- Check if Ollama server is running:

```
curl.exe http://127.0.0.1:11434/api/tags
```

If it returns JSON, Ollama is running.

- If Ollama is not running, start it:

```
ollama serve
```

Keep this PowerShell window open. If it says the port is already in use, Ollama is already running.

- Start the PagePulse backend in another PowerShell window:

```
cd "C:\Users\Abhisekh\Music\webpage-rag-extension-ollama"  
.\venv\Scripts\python.exe -m uvicorn app.main:app --app-dir .\backend --reload  
--host 127.0.0.1 --port 8001
```

- Check backend health:

```
curl.exe http://127.0.0.1:8001/health
```

Expected:

```
{"status": "ok"}
```

- Open Chrome and use the PagePulse extension.

First-Time Setup

Install Ollama:

```
irm https://ollama.com/install.ps1 | iex
```

Pull the required models:

```
ollama pull llama3.2:3b  
ollama pull nomic-embed-text
```

Create/install backend environment:

```
cd "C:\Users\Abhisekh\Music\webpage-rag-extension-ollama"  
py -m venv .venv  
.\venv\Scripts\python.exe -m pip install -U pip  
.\venv\Scripts\python.exe -m pip install -r .\backend\requirements.txt
```

Load the Chrome extension:

- Go to `chrome://extensions`
- Enable Developer mode
- Click Load unpacked
- Select:

```
C:\Users\Abhisekh\Music\webpage-rag-extension-ollama\extension
```

Reload After Code/UI Changes

Reload extension:

- Open `chrome://extensions`
- Find PagePulse
- Click the reload icon
- Reopen the popup

Restart backend:

```
CTRL+C  
cd "C:\Users\Abhisekh\Music\webpage-rag-extension-ollama"  
.\.venv\Scripts\python.exe -m uvicorn app.main:app --app-dir .\backend --reload  
--host 127.0.0.1 --port 8001
```

Current Model Settings

File:

```
C:\Users\Abhisekh\Music\webpage-rag-extension-ollama\backend\.env
```

Current values:

```
OLLAMA_BASE_URL=http://127.0.0.1:11434  
OLLAMA_CHAT_MODEL=llama3.2:3b  
OLLAMA_EMBED_MODEL=nomic-embed-text  
NO_PROXY=localhost,127.0.0.1,::1  
no_proxy=localhost,127.0.0.1,::1  
MAX_PAGE_CHARS=120000
```

Change Chat Model

Pull a stronger model:

```
ollama pull llama3.1:8b
```

Then edit backend\.env:

```
OLLAMA_CHAT_MODEL=llama3.1:8b
```

Restart backend after changing .env.

Common Troubleshooting

ollama command not found:

```
irm https://ollama.com/install.ps1 | iex
```

Then close and reopen PowerShell.

Model missing:

```
ollama pull llama3.2:3b
ollama pull nomic-embed-text
```

Backend cannot connect to Ollama:

```
curl.exe http://127.0.0.1:11434/api/tags
```

If this fails, start Ollama:

```
ollama serve
```

McAfee/proxy HTML error:

Make sure backend\.env has:

```
NO_PROXY=localhost,127.0.0.1,::1
no_proxy=localhost,127.0.0.1,::1
```

Then restart the backend.

Extension cannot reach backend:

```
curl.exe http://127.0.0.1:8001/health
```

If this fails, start the backend again.

Port already in use:

Something is already running on that port. For Ollama, this is often fine. For backend, stop the old backend with CTRL+C in its PowerShell window.

Chrome internal pages do not work:

Do not test on chrome:// pages. Use a normal webpage.

Important Files

```
extension\manifest.json Chrome extension config and icon paths
extension\popup.html Popup layout
extension\popup.css Popup styling
extension\popup.js Popup logic and API calls
extension\contentScript.js Extracts visible page text
backend\app\main.py FastAPI routes
backend\app\rag.py LangChain + Ollama RAG logic
backend\.env Ollama model config
```

What PagePulse Remembers

It remembers in backend RAM:

- Current page index
- Page chunks
- Page embeddings
- Cached summary for the page

It does not persist after backend restart.

It does not currently keep conversation memory across questions.