

EOS Radar Sensor - LPWAN Binary Payload

Payload Overview

Property	Value
Payload type	LPWAN binary telemetry payload
Total size	24 bytes
Byte order	Big-endian for multi-byte values
Compile condition	Encoder is used when CONFIG_SENTOS_HAS_NRF_CLOUD_SERVICE is disabled
Structure	3-byte Sentigram telemetry header followed by EOS telemetry fields

LPWAN Binary Payload - 24 bytes

Byte offset	Size	Field	Type	Encoding / scaling	Description
0	1	variant_msb	uint8	High byte of EOS_VARIANT_CODE()	Module base and major version bits
1	1	variant_lsb	uint8	Low byte of EOS_VARIANT_CODE()	Minor version and subtype bits
2	1	uplink_counter	uint8	Increments per encoded LPWAN telemetry message	Uplink counter
3	1	alarm	uint8	Raw is_alarm bitfield	Alarm flags
4	1	internal_temperature	uint8	Raw value = degC + 128; decoded value = raw - 128	Internal temperature
5	1	battery	uint8	Percent	Battery capacity
6..7	2	battery_voltage	uint16	Millivolts; decoded value = raw / 1000	Battery voltage
8	1	radar_status	uint8	0 or 1	Radar acquisition status
9	1	radar_peaks	uint8	Count	Radar peaks found
10..11	2	radar_rd_1	uint16	Millimeters; decoded value = raw / 1000	Radar peak 1 distance
12..13	2	radar_ra_1	int16	Two's complement	Radar peak 1 RCS/amplitude
14..15	2	radar_rd_2	uint16	Millimeters; decoded value = raw / 1000	Radar peak 2 distance
16..17	2	radar_ra_2	int16	Two's complement	Radar peak 2 RCS/amplitude
18..19	2	radar_rd_3	uint16	Millimeters; decoded value = raw / 1000	Radar peak 3 distance
20..21	2	radar_ra_3	int16	Two's complement	Radar peak 3 RCS/amplitude
22	1	orientation	uint8	Enum	Orientation
23	1	tilt_angle	uint8	Degrees	Tilt angle