

HP Insight Remote Support

Release Notes



Software Version: 7.1

Contents

- Legal notices 4
- Document Revision History 4
- About this document 5
- What is new with HP Insight Remote Support 7.1 5
 - New functionality 5
 - New Hosting Device support 5
 - New product support 5
- Overview 6
- Product architecture 6
- Product support 6
 - Supported HP Insight Remote Support versions 7
- Installation process and prerequisites 7
 - Installation management and software updates 7
 - Content Level Updates..... 7
 - Application Patch 7
 - Manual Software Updates..... 7
 - Installation directory 8
 - Connectivity prerequisites..... 8
- Hosting Device prerequisites 8
 - Supported Hosting Device hardware 9
 - Minimum and recommended Hosting Device specifications..... 9
 - Number of Monitored Devices supported 10
 - Configuration Collection capabilities 10
 - Supported Hosting Device operating systems 12
 - Supported Microsoft Windows operating systems 12
 - Virtualization operating system support 13
- Software prerequisite 14
 - .NET Framework requirements..... 14
 - Access requirements..... 14
 - Compatibility with other applications 14
 - Supported Web browsers 14

HP server requirements and recommendations	14
HP ProLiant servers	15
Microsoft Windows support	16
Linux support	17
Virtualization support	17
HP ProLiant Gen8 servers	18
HP Integrity servers	20
Operating system support	21
HP-UX operating system prerequisites	23
HP-UX machine check abort automatic analysis capabilities for HP-UX 11i v3	24
HP BladeSystem Enclosures	25
HP 9000 servers	25
HP NonStop systems	26
HP AlphaServer systems	26
Selected non-HP servers	26
HP Storage	27
HP P6000 Enterprise Virtual Array Systems	27
HP StoreVirtual Storage (formerly P4000 SAN Solutions/LeftHand Storage)	27
Supported hardware platforms	27
Software requirements	28
HP P2000/Modular Smart Array Systems	28
HP StoreAll Storage (formerly HP IBRIX Storage)	29
HP StoreEasy Storage (formerly Commercial NAS)	30
HP Storage Blades	30
HP Virtual Library Systems	30
HP StoreEver Tape Libraries	31
HP Tape Blades	31
HP StoreOnce Backup (D2D)	32
HP P9000/XP Disk Arrays	32
HP 3PAR StoreServ Storage	32
HP Secure Key Manager	32
HP Enterprise Secure Key Manager	32
HP StoreFabric (formerly SAN Fibre Channel Switches)	33
HP Networking Switches	33
HP ProVision-based Switches (formerly E-Series/ProCurve)	33
HP ComWare-based Switches (formerly A-Series or H3C/3Com)	37
HP Solutions	40
Rack and Power	40
HP Modular Cooling System	40
HP Rack-mountable and Tower Uninterruptable Power Systems	41

Management Platform Integration	42
HP Systems Insight Manager	42
HP SNMP Service Event Adapter	42
HP Operations Manager	43
HP SAP Solution Manager	43
HP Insight Online integration	43
Issues and suggested actions	43
Microsoft Internet Explorer window may hang or display black screen	43
HP ProLiant Gen8 servers are displayed by their serial number	43
HP Authorized Channel Partner default settings may not be retained.....	44
How to unregister a Gen8 server from Insight RS	44
Service events display an incorrect timestamp in the Insight RS Console	44
A device appears without a discovery taking place	44
Duplicate records created in Insight Online when the same device is discovered twice	44
Unexpected device discovery	44
Multiple location ID and partner configured.....	44
Unhealthy Monitoring & Collections even when protocols are setup correctly	45
Cannot log on to the Insight RS Console as an Administrator	45
Sign up to receive Insight Remote Support communications	45
We appreciate your feedback	45
Appendix A – Updating existing Insight RS installations.....	46
Upgrading from version 5.x	46
Port adjustments needed	47
Upgrading from previous versions of 7.x	47
Appendix B – Required Protocols and Components	48
Appendix C – Event Log Monitoring Collector	54
Documentation	54
HP Insight Remote Support	54
Related Information	55

Legal notices

The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein. The information contained herein is subject to change without notice.

Warranty

The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein.

The information contained herein is subject to change without notice.

Restricted Right legends

Confidential computer software. Valid license from HP required for possession, use or copying. Consistent with FAR 12.211 and 12.212, Commercial Computer Software, Computer Software Documentation, and Technical Data for Commercial Items are licensed to the U.S. Government under vendor's standard commercial license.

Copyright Notice

© Copyright 2014 Hewlett-Packard Development Company, L.P. All rights reserved. Reproduction, adaptation, or translation of this document without prior written permission is prohibited, except as allowed under copyright laws.

Trademark Notices

Microsoft® and Windows® are U.S. registered trademarks of Microsoft Corporation.

UNIX® is a registered trademark of The Open Group.

Document Revision History

Table 1. Document Revision History

Edition	Software version	Publication date	Change Summary
1.1	7.1	July, 2014	Moved Product support section earlier in the document and clarified support statement
1.0	7.1	July, 2014	Initial release for HP Insight Remote Support 7.1

About this document

This document lists the **minimum** hardware, software prerequisites and supported products for installing and running the HP Insight Remote Support 7.1 software.

Only products running the supported operating system versions with the specified prerequisites are eligible for support from Hewlett-Packard. By default, any unspecified products or operating system versions not listed in this document are considered to be unsupported.

If unspecified combinations of products and operating systems are configured to operate with the HP Insight Remote Support 7.1 solution, HP will not support them or guarantee that they will work correctly or that they do not negatively affect its operation.

See www.hp.com/go/insightremotesupport for more details.

What is new with HP Insight Remote Support 7.1

New functionality

- Localized Online Help packages can now be downloaded from the Software Updates screen
- Ability to delete a software package on the Software Updates screen
- Addition of device relationship chart that shows a device's relationship to other devices, such as for HP Solutions and P6000 Enterprise Virtual Array systems
- Usability enhancements to device health indicators
- Ability to hide closed service events on the service events screens

New Hosting Device support

The following operating systems, hardware devices, and application support has been added to HP Insight Remote Support with this release:

Table 2. New Hosting Device support introduced with HP Insight Remote Support 7.1

Operating System version support	• Microsoft Hyper-V Server 2012 R2 • Microsoft Hyper-V Server 2012 • VMware vSphere ESXi 5.5 Update 1
Web Browser support	• Microsoft Internet Explorer, version 11.x • Mozilla Firefox, version 29.x • Google Chrome, version 33.x

New product support

The HP Insight Remote Support 7.1 release supports the following new products for monitored devices in addition to all of those added in previous versions of Insight RS including all of the Content Level Updates.

Table 3. New product support introduced with HP Insight Remote Support 7.1

HP ProLiant Servers	• HP ProLiant Superdome
HP Storage	• HP MSA 1040 Storage
HP Networking Switches	• Intelligent Resilient Framework (IRF) support for ComWare-based switches
HP Solutions	• HP ConvergedSystems support, including: – CS300 for Vertica – CS500 for SAP HANA Single Node (or Scale Up) – CS500 for SAP HANA Scale Out

Overview

This document is the Release Notes for the HP Insight Remote Support 7.1 software, which is a remote support solution that is scalable to meet your needs and all of the capabilities and product coverage found in HP Insight Remote Support Standard. See [Appendix A](#) for more details.

HP Insight Remote Support 7.1 supports HP servers, storage, and networking devices, providing you with the following features and benefits:

- Automatically discovers and checks devices on your network to be monitored ahead of the installation
- Installed on your Windows Hosting Device or VMware, Citrix or Hyper-V virtual guest and easily configured to monitor your environment
- Quicker and easier to install than any of the previous versions of HP Insight Remote Support
- Scalable to support up to 2,500 devices (see Number of Monitored Devices supported section for details)
- 24x7 real-time hardware event monitoring and secure Internet event submission help you identify and prevent potentially critical problems for your environment
- Automatic service request submission saves time monitoring and reporting issues
- Intelligent analysis of issues provides faster restoration of your monitored devices to operational status
- Collection of configuration information from your devices to help HP resolve problems more quickly and accurately. Note, no business information is collected and the data is managed according to the HP Data Privacy policy
- HP or your Authorized Channel Partner can propose recommendations that may improve your environment if you give HP specific permission to do so
- Optional, integration into HP Systems Insight Manager and HP Insight Online is available
- Retains all configurations during upgrade for existing Insight RS customers (see [Appendix A](#) for details)

Insight RS checks every device's warranty and contract to make sure it has a valid HP warranty, CarePack or contract. If a device has no HP warranty or contract, the monitoring health indicator in the Insight RS Console will be red. If this is red, then no service events will be analyzed or sent to HP.

For customers, who have purchased an HP-UX Mission Critical Partnership or Proactive 24 contract from HP, who are monitoring NonStop or XP equipment, or require integration with SAP Solution Manager or HP Operations Manager, then they should install the HP Insight Remote Support Advanced software, not this product. HP Insight Remote Support Advanced will continue to work with supported versions of HP Systems Insight Manager (HP SIM) and the features will be included in a future version of HP Insight Remote Support 7.x via an automatic upgrade.

See [Appendix A](#) for information on HP Insight Remote Support Advanced future upgrade. For more details, please see www.hp.com/go/insightremotesupport.

Product architecture

HP Insight Remote Support leverages a distributed architecture that is divided into two types of systems: Hosting Device and Monitored Device.

- **Hosting Device:** This is a Windows ProLiant server or Windows virtual guest on a VMware, Citrix or Hyper-V virtual machine that hosts the HP Insight Remote Support application and initiates all central remote support operations. This includes the collection of events and configuration information from the monitored devices, and transmission of this information securely to HP for fast and effective problem resolution.
- **Monitored Device:** These are the supported hardware devices that are monitored for hardware events and from which configuration information is collected. The events and collections are gathered by the Insight Remote Support application on the Hosting Device and then securely transferred to HP. Response from HP or your preferred HP Authorized Channel Partner will be delivered in line with the warranty, HP Care Pack Service or contractual support agreement purchased for the device reporting a failure.

Product support

It is always advisable that you read the [HP Insight Remote Support Installation and Configuration Guide](#) before installation. This document is designed to help and guide you through a successful installation and configuration. However, if you need further support for HP Insight Remote Support then this is available through your local HP Response Center. Please refer to www.hp.com/go/rstechsupport, where you will find a wealth of information on HP Insight Remote Support. This includes access to FAQ's, peer to peer forums, and the contact details of HP Support.

Before contacting support, you can check if your issue has a solution available. Note that a valid contract and HP Passport log on is required to view issue solution documents. To view Insight RS issue solutions, complete the following steps:

1. Go to <http://www.hp.com> and browse to **Support** → **Support & troubleshooting**.
2. In the **Find by product** field, type **Insight Remote Support** and click **Go**.
3. In the search results, click **HP Insight Remote Support Next Gen Software**.
4. In the **Most viewed solutions** pane, click **View all** to see the solutions.

Supported HP Insight Remote Support versions

The support policy is to support the current and the previous major version of the HP Insight Remote Support solution and its software components. To this end, HP strongly advises that customers always upgrade to the latest HP Insight Remote Support version and its components when made available through the embedded software update capability.

Installation process and prerequisites

Installation management and software updates

The latest HP Insight Remote Support software is always available for download from [HP Software Depot](#). All subsequent updates will continue to be managed as you have defined during installation, but can be altered through the **Administrator Settings** → **Software Updates** page. HP always recommends installing the latest software available by enabling the *Automatically Download and Install* option from the Automatic Update Level drop-down list to benefit from the latest features and product support.

Content Level Updates

HP Insight Remote Support 7.1 includes a feature to be able to introduce new product support and new intelligent analysis rules on a regular basis. These automatic updates, where just these capabilities are updated, are known as Content Level Updates and are made available through the **Administrator Settings** → **Software Updates** page.

Content Level Updates (CLUs) are provided as additional content to a current release and are always incorporated into the next major release. If available, Content Level Updates are automatically applied to a new installation of a release and when two or several subsequent CLUs are made available, the latest version will automatically include any of the previous Content Level Updates.

Application Patch

Known issues are addressed with an Application Patch to a current release when required via the embedded software management capability. These updates are also incorporated into the next major release of HP Insight Remote Support.

Manual Software Updates

Insight Remote Support 7.1 offers optional manual software updates. This is applicable for customers, who have very specific requirements for controlling the source of any software in a production environment, it is possible to download and store a particular version of HP Insight Remote Support and disable the automatic software updates.

Important

HP strongly recommends that manual software updates are not enabled for any customer who does not have a legal or strong audit requirement to do so, since updates enable HP to automatically supply new software components that contain new product support, improved capabilities and fixes for any known issues including security. Also, manual software updates to these systems will require a re-installation of a new Software Depot image of all the components (configuration details are retained) rather than just accepting the new software made available through the embedded software management capabilities.

Only major versions of HP Insight Remote Support are made available for download and install from HP Software Depot. The intermediate updates that address known issues (Application Patch) and that add new device coverage (Content Level Updates) are only made available via the embedded software updates capability. These are included in the next major version for those wishing to do manual software updates.

Installation directory

HP Insight Remote Support 7.1 can be installed in a location other than the default directory (C: \ drive). This includes the default location for program files, configuration files, database files, and log files.

Note

Installation directories must be seen by Microsoft Windows as local drives and not network drives. Insight RS cannot be executed from a single shared disk by multiple computers.

Multi-byte character input is fully supported within the HP Insight Remote Support 7.1 software.

If you encounter any problems during installation, view the installation log file, located in the following location:

C:\ProgramData\HP\RS\LOG\rsinstall.log

This is the default file location, and it will be different if you chose a different log file location during installation.

Note

The C:\ProgramData folder is a hidden folder, so you may need to set your folder options to show hidden folders.

Connectivity prerequisites

Please ensure that the correct firewall openings are configured to allow communication with HP. Insight Remote Support communicates over HTTPS/443 to submit incidents to and retrieve entitlement information from HP Support. HP strongly recommends configuring only the alias, see [Table 4](#) below.

Table 4. Required firewall setting

	Alias	Protocol	Description
Firewall Setting	services.isee.hp.com	HTTPS	Used by the HP Insight Remote Support software to submit incidents to and retrieve contract and warranty information from the HP data center

You must open port **7906** on the Hosting Device to access the Insight Remote Support components on the Hosting Device from other systems inside of the same network. Also make sure that Windows firewall allows the connection to port 7906.

See the [Error! Reference source not found.](#) section for required port adjustments when upgrading Insight Remote Support.

Important

IPv4 networking protocol is the only supported version. Currently, IPv6 is **not** supported and needs to be disabled on the Hosting Device.

The Hosting Device requires a static IP address. Dynamic IP addresses are **not** supported.

To communicate with monitored devices that use SNMP, the Hosting Device must have SNMP installed and enabled, and the SNMP Trap Service Startup Type must be set to *Automatic*.

Hosting Device prerequisites

The HP Insight Remote Support software requires that the Hosting Device is an HP ProLiant server running Microsoft Windows, to allow the monitoring of itself, since this device is critical for the management and monitoring of your whole IT infrastructure. The Hosting Device can also be installed in a Windows virtual guest on a VMware, Citrix or Hyper-V virtual machine on a supported HP ProLiant server.

In addition, the Hosting Device needs to monitor itself for potential problems. This requires the installation and configuration of the appropriate HP Insight Management Agents or HP Insight Management WBEM Provider. Refer to the ProLiant servers section for more details.

Although it is not mandatory, HP strongly recommends that the HP Insight Remote Support Hosting Device is covered by a valid warranty or HP support contract obligation. The Hosting Device is a critical component of this solution so keeping it in a healthy condition is of prime importance to ensure effective monitoring.

Operating system and hardware model support are specific to the Hosting Device as follows.

Supported Hosting Device hardware

HP Insight Remote support is supported only on HP ProLiant servers:

- Any HP ProLiant G4 or above (x86 system) with Insight Management Agent or WBEM Provider support
- Any HP ProLiant G4 or above (x64 system) with Insight Management Agent or WBEM Provider support

Refer to the [ProLiant server](#) section below for more details of Insight Management Agent or WBEM Provider support.

Note

ProLiant 100 Series servers, with the exception of the ProLiant G6 1x0 Series servers, are not supported as a Hosting Device to host HP Insight Remote Support since they do not offer a diagnostic agent to monitor themselves.

ProLiant 1x5 series servers are not supported as they do not have any diagnostic agent support to monitor themselves.

Minimum and recommended Hosting Device specifications

The Hosting Device should be a Microsoft Windows ProLiant server that meets the following specifications in order to ensure that it performs and is available at a high level.

A large variety of Microsoft Windows ProLiant servers can be used as a Hosting Device for this purpose, dependent on the size of monitored and managed environment.

This section provides **guidance** that would make any particular Windows ProLiant model and configuration suitable or not beyond the operating systems and hardware platforms described above.

The section below provides some **examples** of Hosting Device server specifications compared to the number of devices that are required to be monitored. The specification can be affected by a number of factors:

- The type and power of the Windows ProLiant server selected
- The number of devices monitored and managed
- If the Hosting Device is also being used for other optional management applications (e.g. HP SIM)
- Any application sharing the same Hosting Device

Hence, it is not possible to give exact advice on which specification will be required. If performance degradation is observed, it is likely that the server may need to be compared to the following recommendations outlined below.

If problems are being encountered, you will be required to meet the **minimum** requirements in order to gain HP support. Not meeting the **minimum** specification can cause the solution not to load, to stop or to have significant performance degradation.

The following tables outline the **minimum** and **recommended** Hosting Device specifications based on the results of HP's quality assurance and performance testing for specific environments.

Since a large variety of Windows ProLiant servers can be used as a Hosting Device and processor speed alone does not indicate the power of a server, the following sizings are examples of recommended configurations according to the size of the monitored environment.

Table 5. Hosting Device sizing requirements based on number of managed devices

	Memory Size	Free Disk Space
Up to 100 devices	Minimum 4 GB for new installations	2 GB during a new full installation
	Recommended 6 GB, 8 GB if using HP SIM	4 GB for operation ¹
Up to 500 devices	Minimum 6 GB for new installations	2 GB during a new full installation
	Recommended 8 GB, 10 GB if using HP SIM	8 GB for operation ¹
Up to 2,500 devices	Minimum 8 GB for new installations	2 GB during a new full installation
	Recommended 12 GB, 16 GB if using HP SIM	28 GB for operation ¹

¹ The disk space requirements are affected by the number and type of devices if collections are configured (collections are enabled by default, are strongly recommended and in some cases a requirement of the contract type). Please see the [Configuration Collection capabilities](#) section below for details.

For larger number of devices, it is recommended during installation to configure the destination folder for the database and log files to be on different volumes to increase the performance of the application. See the *HP Insight Remote Support Installation and Configuration Guide* at www.hp.com/go/insightremotesupport/docs for details.

Important

If you are installing or retaining HP Systems Insight Manager on the same Hosting Device, then the extra resources and requirements needed for this application should be added accordingly. See the *HP Systems Insight Manager Installation and Configuration Guide for Windows* at www.hp.com/go/foundationmgmt/docs for details.

Number of Monitored Devices supported

This solution has been optimized to support up to **2,500** monitored devices per Hosting Device. If you need to manage more devices then HP strongly recommends that you leverage multiple Insight Remote Support installations, either on multiple physical servers or installed on its own supported virtual machine.

Normally, each physical device counts as **one** when calculating the overall maximum device number, e.g. a ProLiant server and its iLO 4 only count as a single device. However, there are some exceptions that need to be taken into account as listed below:

- HP ProLiant Gen8 servers using the embedded iLO 4 capabilities when AHS collections are turned on, count as 5 devices (without AHS collections, each server counts as one device)
- Each networking switch counts as 4 devices
- Each HP StoreVirtual 4xxx Storage Node counts as 30 devices
- Each HP StoreAll Network Storage System counts as 3 devices
- Each Tape Library counts as 4 devices
- Each HP P2000/MSA device counts as 4 devices
- Each HP P6000 Enterprise Virtual Array counts as 8 devices
- Each VMware vCenter server installation counts as 4 devices
- Any device that is configured as part of a SAN collection, adds an additional count of 4 devices

Configuration Collection capabilities

HP Insight Remote Support 7.1 has the ability to collect configuration information from your monitored devices managed centrally from the Hosting Device.

These services are initiated when the devices register and further collections are automatically scheduled by default. These configuration collections enable the following:

- HP Support to provide improved technical support
- Data collections provide HP (or your nominated HP Authorized Channel Partner) with information on the monitoring health of each of your devices. This is displayed in Insight Online if you have chosen this option
- Certain HP Proactive services have a mandatory requirement for remote support monitoring and collections enabled on all devices for the customer to receive all the features and service deliverables provided under the service. This means HP is not obligated to provide delivery of proactive entitlements for disabled collections for these devices until such time as the remote support monitoring & collection functionality is restored.
- Optionally, if during installation or subsequently you have requested HP or your preferred HP Authorized Channel Partner to provide recommendations that may improve your environment

Important

Dependent on the collection type, additional disk space needs to be allocated to allow configuration collections to operate correctly. Note, all collections have a number that are retained for historic records. Additionally, collections are compressed by a ratio of **ten to one** when they are retained but consideration for disk space should be given if multiple collections are run at the same time. The only exception is Active Health System (AHS) Collections that are not compressed. Please see [Table 6](#) for details on how to calculate the required disk space.

Table 6. Collection types and disk space requirements

	Schedule frequency (default schedule)	Average size per collection (compressed)	Number of collections retained	Note
Active Health System (AHS) Collection				
HP ProLiant Gen8	Weekly	25 MB	3	Applicable for HP ProLiant Gen8 servers only, independent if the server is using the embedded management capabilities in the iLO 4 or using a diagnostic agent installed on the operating system. For details, see the ProLiant Gen8 server section

Table 6. Collection types and disk space requirements

	Schedule frequency (default schedule)	Average size per collection (compressed)	Number of collections retained	Note
below.				
Server Basic Configuration Collection				
Windows and Linux on HP ProLiant	Monthly	200 Kbytes	5	
ESX/ESXi on HP ProLiant	Monthly	75 Kbytes	5	
HP-UX	Monthly	800 Kbytes	5	
HP Integrity Superdome 2 Onboard Administrator	Monthly	10 Kbytes	5	
HP ProLiant Superdome Onboard Administrator	Monthly	18 Kbytes	5	
HP ProLiant Superdome SLES partition	Monthly	29 Kbytes	5	
OpenVMS	Monthly	35 Kbytes	5	
Onboard Administrator for c-class Enclosures	Monthly	20 Kbytes	5	
StoreVirtual (P4000) Family Configuration Collection				
HP StoreVirtual 4xxx (P4000 SAN Solutions)	Daily	900 Kbytes	7	
Network Configuration Collection				
HP ProVision-based Switches (E-Series/ ProCurve)	Weekly	100 Kbytes	5	
HP ComWare-based Switches (A-Series/ 3Com)	Weekly	13 Kbytes	5	
VMware vCenter Server Collection				
VMware vCenter Server	Weekly	5 MB	3	This collection size includes all the configuration information from VMware vCenter and all of its virtual machines. NOTE: The size varies based on the size and complexity of the cluster being monitored. More virtual machines in the cluster will increase the size.
Storage Configuration Collection				
P6000 Enterprise Virtual Arrays	Weekly	250 Kbytes	5	
HP StoreFabric SAN switches	Weekly	100 Kbytes	5	

Table 6. Collection types and disk space requirements

	Schedule frequency (default schedule)	Average size per collection (compressed)	Number of collections retained	Note
HP StoreEasy Storage (Commercial NAS)	Monthly	450 Kbytes	5	
HP ESL/HP StoreEver EML/HP StoreEver MSL	Weekly	25 Kbytes	5	
HP SureStore 2000 (Modular Smart Arrays)	Weekly	100 Kbytes	5	
SAN Configuration Collection				
HP-UX	Weekly	800 Kbytes	5	These collections are in addition to the collections listed above but are only required to fulfill the deliverables of a SAN Proactive Services contract.
OpenVMS	Weekly	35 Kbytes	5	
Windows/Linux on HP ProLiant	Weekly	200 Kbytes	5	
P6000 Enterprise Virtual Arrays	Weekly	250 Kbytes	5	
HP ESL/HP StoreEver EML/HP StoreEver MSL	Weekly	25 Kbytes	5	
HP StoreFabric SAN switches	Weekly	100 Kbytes	5	
HP StoreVirtual 4xxx (P4000 SAN Solutions)	Weekly	900 Kbytes	7	
HP SureStore 2000 (Modular Smart Arrays)	Weekly	100 Kbytes	5	
Operational collections				
Support Data Collection	On demand	10 Mbytes	2	This collection is manual on request from HP Support.

Collections require no additional collection agent on your monitored devices and are by default turned on. Collections are not available for all devices; see [Appendix B](#) for details and protocol requirements.

Supported Hosting Device operating systems

HP Insight Remote Support 7.1 can be installed on a Windows HP ProLiant server or on a Windows virtual guest on a VMware, Citrix or Hyper-V virtual machine.

Supported Microsoft Windows operating systems

The following Microsoft Windows operating system versions are supported with English, French, Italian, German, Spanish, Dutch, Traditional Chinese, Simplified Chinese, Korean, and Japanese International Server:

- Microsoft Windows Server 2012 R2
 - Standard Edition
 - Datacenter Edition
- Microsoft Windows Server 2012
 - Standard Edition
 - Datacenter Edition

- Microsoft Windows Server 2008 R2 for x64 including Service Pack 1¹
 - Standard Edition
 - Enterprise Edition
- Microsoft Windows Server 2008 Service Pack 2 for x64
 - Standard Edition
 - Enterprise Edition
 - Datacenter Edition
- Microsoft Windows Server 2008 Service Pack 2 32-Bit¹
 - Standard Edition
 - Enterprise Edition
 - Datacenter Edition
- Microsoft Windows Web Server 2008 Service Pack 2¹ for x86 and x64

¹ Only 64-bit (x64) versions of this Microsoft Windows operating system are supported when used in combination with HP Systems Insight Manager.

Important

Microsoft Windows Server 2012 Essentials, Windows Server 2012 Foundation, Microsoft Windows 2000, Windows 2003, Windows Small Business Server, Windows Storage Server, Windows XP, Windows Vista, Windows 7 and Windows 8 operating systems are **not** supported as operating systems for the Hosting Device.

Installing or upgrading Insight Remote Support on a Microsoft Windows server configured as a domain controller is **not** supported.

Support for Microsoft Windows Server 2008, Windows Server 2008 R2, Windows Server 2012 and Windows 2012 R2 is limited to the full server version only and is not available for the core version as much of the required functionality is unavailable in this version. This also excludes Windows Server core versions running the Hyper-V role.

HP recommends installing and enabling HP Insight Management WBEM Providers on the Hosting Device in addition to SNMP.

HP SIM and Insight RS support different versions of the Microsoft Windows operating system. If you intend to synchronize Insight RS with HP SIM, make sure the Hosting Device operating system is supported by both HP SIM and Insight RS. For HP SIM operating system support, see the *HP Insight Management 7.x Support Matrix* at <http://www.hp.com/go/insightmanagement/docs>.

Virtualization operating system support

When running the Hosting Device in a virtual environment, HP recommends increasing the CPU and memory recommendations by **10%** when the Virtual Machine (VM) is created. Note, do this for each VM added to the ProLiant as it is possible to run multiple Insight Remote Support VMs on one physical server if enough resources are available.

Microsoft Hyper-V support

Hyper-V virtual machines are supported if the Microsoft Windows virtual guest operating system is a supported Hosting Device operating system.

The following Microsoft Windows versions are supported:

- Microsoft Hyper-V Server 2012 R2
- Microsoft Windows Server 2012 R2 using Hyper-V role
- Microsoft Hyper-V Server 2012
- Microsoft Windows Server 2012 using Hyper-V role
- Microsoft Windows Server 2008 R2 using Hyper-V role

VMware operating system support

The following VMware versions are supported:

- VMware ESX Server 4.0 and 4.1 including Update versions
- VMware ESXi Server 4.0, 4.1, 5.0
- VMware vSphere ESXi 5.1 including Update versions
- VMware vSphere ESXi 5.5 including Update 1

A compatibility support matrix for VMware ESX and ESXi can be found at:

<http://h18004.www1.hp.com/products/servers/vmware/supportmatrix/hpvmware.html>.

Support is provided on a VMware ESX or ESXi supported HP ProLiant server utilizing 32-bit or 64-bit VMware Guests running Windows Server 2008 or 2012 variants as described in the [Supported Microsoft Windows operating systems](#) section above.

Support is provided for the following VMware vSphere capabilities when the Hosting Device is installed in a VMware Windows virtual machine:

- VMware vSphere vMotion when the Hosting Device is moved to another server in the same cluster
- VMware vSphere Fault Tolerance to provide Hosting Device hardware resilience using two servers running in parallel for continuous fault tolerance for an Insight Remote Support installation. For details of this capability please refer to <http://www.vmware.com/products/vsphere/features/fault-tolerance.html>

Important

VMware vCenter features that are not supported on a Virtual Machine based Hosting Device includes VMware Distributed Resource Scheduler (DRS), VMware High Availability (HA), VM cloning, VM copying and Physical to Virtual (P2V) Migrations with the VMware vCenter Converter.

Citrix XenServer operating system support

The following Citrix XenServer versions are supported:

- Citrix XenServer 5.5 and 5.6 including Update versions
- Citrix XenServer 6.0, 6.1 and 6.2 including Update versions

A compatibility support matrix for HP ProLiant servers running Citrix XenServer can be found at <http://h18004.www1.hp.com/products/servers/software/citrix/hpcitrixcert.html>

Software prerequisite

.NET Framework requirements

- Microsoft .NET Framework 3.5 or later is required

This is a Windows component and can be found in the Add/Remove Features dialog in the Server Manager. If .NET Framework 3.5 is **not** listed, we strongly advise that you obtain it and any patches or updates on a regular basis from the Microsoft web site.

Access requirements

You must have *administrative rights* to Microsoft Windows on the Hosting Device. HP requires using the same Windows account on the Hosting Device to install and configure Insight Remote Support.

Important

Due to enhanced security features in Windows 2008 and later, HP recommends that you run the installation as user *administrator* or as a user in the *Administrators* group.

Compatibility with other applications

The HP Insight Remote Support software is compatible with the following applications, being installed on the same Hosting Device:

- HP Systems Insight Manager (HP SIM) 7.2 or 7.3

HP SIM and Insight RS support different versions of the Microsoft Windows operating system. If you intend to synchronize Insight RS with HP SIM, make sure the Hosting Device operating system is supported by both HP SIM and Insight RS. For HP SIM operating system support, see the HP Insight Management Support Matrix at www.hp.com/go/insightmanagement/docs.

For more details on the integration with Systems Insight Manager, please see the [Management Platform Integration](#) section below.

Supported Web browsers

- Microsoft Internet Explorer, versions 8.x, 9.x, 10.x, and 11.x
- Mozilla Firefox, versions 24.x Extended Support Release (ESR) and 29.x Mainstream
- Google Chrome, version 33.x

HP server requirements and recommendations

The following products are supported by HP Insight Remote Support 7.1 for monitoring and configuration collections. Please see the table in [Appendix B](#) for the appropriate providers to be installed and configured by hardware and operating system version.

HP ProLiant servers

The following HP ProLiant servers and their attached devices including Modular Smart Arrays (MSA) are supported when HP Insight Management (IM) Agents revision 7.1 or higher or HP Insight Management WBEM Providers revision 2.3.0.0 or higher are installed on these servers. It is strongly recommended that you upgrade to the latest SNMP Agent and WBEM Provider versions as some models are only supported with a later version.

Note

Not all ProLiant models are supported by the WBEM (WMI) providers. Refer to the provider supported product list to determine whether your model is supported; if it is not, use SNMP. The Service Pack for ProLiant (SPP) is a software bundle that includes drivers, utilities, and management agents for ProLiant device(s). The most current version is also available at: www.hp.com/go/spp/download. See the *Service Pack for ProLiant Server Support Guide* at www.hp.com/go/spp/documentation for specific server and management agent support.

The following HP ProLiant servers are supported with HP SNMP Agent or HP WBEM Provider support (See the Important note below):

Table 7. Supported HP ProLiant servers

	Server model
HP ProLiant BL servers	HP ProLiant BL Server Blades (p-class, c-class) including: HP ProLiant BL685c G7 servers
HP ProLiant DL servers	HP ProLiant DL 100, 300, 500, 700 and 900 Series servers including: - HP ProLiant DL580s G7 servers - HP ProLiant DL585 G7 servers
HP ProLiant ML servers	HP ProLiant ML 100, 300 and 500 Series servers
HP ProLiant SL servers	HP ProLiant SL Scalable Systems including: - HP ProLiant SL335 G7 servers - HP ProLiant SL4545 G7 servers
HP ProLiant Multi Node servers	HP ProLiant 1000-series Multi Node Servers
HP ProLiant workstation blades	HP ProLiant Workstation Blades including: HP ProLiant WS460c G6 Workstation Blades
HP ProLiant Superdome server	HP ProLiant Superdome Important: supports SUSE Linux Enterprise Server 11 operating system support only, and uses the WS-Man protocol for communication with Insight RS.

Important

HP only provides limited remote support for customers using HP ProLiant servers **prior to generation 4**. As with standard support, HP Insight Remote Support version 7.x will attempt to discover these products as remotely monitored HP products and send information about failure events to HP.

However, if there are issues with the operation of the remote monitoring features of HP Insight Remote Support version 7.x for these specific products, including the remote discovery or the reporting of failure events to HP, then HP will resolve such issues in a commercially reasonable manner but without guarantee of an immediate response or a resolution. If a failure event is successfully received at HP, it is managed according to the support level agreement.

HP ProLiant 1x5 series servers are **not** supported as they do not have any supported diagnostic agent.

HP ProLiant 100 G6/G7 series server support requires HP Insight Management v8.22 or higher for SNMP protocols or HP Insight Management WBEM Providers v2.4 or higher. HP Insight Management WBEM Providers are available for download from <http://h18013.www1.hp.com/products/servers/management/wbem/provider/downloads.html>.

HP ProLiant WS460c Workstation Blade support requires HP Insight Management Agents for Windows Server 2003/2008 v8.3 or higher, which is available for download from http://h18013.www1.hp.com/products/servers/management/im-agents/downloads.html?iumpid=req_R1002_USEN.

On the preceding servers, the following Operating Systems are supported by Insight Remote Support 7.1, providing they are also supported by that model of hardware:

Microsoft Windows support

For a detailed list of supported Windows operating system versions supported by ProLiant servers please see the following support page at www.hp.com/go/wincert.

- Microsoft Windows Server 2012 R2
 - Standard Edition
 - Datacenter Edition
- Microsoft Windows Storage Server 2012 R2¹
 - Standard Edition
- Microsoft Windows Server 2012
 - Standard Edition
 - Datacenter Edition
- Microsoft Windows Storage Server 2012¹
 - Standard Edition
- Microsoft Windows Server 2008 R2 including Service Pack 1
 - Standard Edition
 - Enterprise Edition
 - Datacenter Edition
- Microsoft Windows Server 2008
 - Standard for x64
 - Enterprise for x64
 - Datacenter for x64
 - Standard 32-Bit
 - Enterprise 32-Bit
 - Datacenter 32-Bit
 - Small Business Server
 - Web Server
 - Storage Server 2008¹
- Microsoft Windows Server 2003 R2
 - Standard Edition
 - Enterprise Edition
 - Standard x64 Edition
 - Enterprise x64 Edition
 - Datacenter x64 Edition
 - Small Business Server
- Microsoft Windows Server 2003
 - Standard Edition
 - Enterprise Edition
 - Datacenter Edition
 - Standard x64 Edition
 - Enterprise x64 Edition
 - Web Edition
 - Storage Server 2003¹
 - Small Business Server 2003

¹ Windows Storage Server is only supplied and supported when part of an HP Storage Server.

Important

Support for Windows 2008, Windows 2008 R2, Windows 2012 and Windows 2012 R2 is limited to the full server version only and is **not** available for the core version as much of the required functionality is unavailable for these versions.

Linux support

A compatibility support matrix for Linux operating systems on HP ProLiant servers can be found at <http://h18004.www1.hp.com/products/servers/linux/hplinuxcert.html>. Linux operating system support includes:

- Red Hat Enterprise Linux 6.x (AMD64, EM64T, x86)
- Red Hat Enterprise Linux 5.x (AMD64, EM64T, x86)
- Red Hat Enterprise Linux 4.x (AMD64, EM64T, x86)
- SUSE Linux Enterprise Server 11 (AMD64, EM64T, x86)
- SUSE Linux Enterprise Server 10 (AMD64, EM64T, x86)
- SUSE Linux Enterprise Server 9 (AMD64, EM64T, x86)

Important

Linux operating systems requires the appropriate **SNMP** Providers to be installed and configured. WBEM Providers are **not** supported.

SUSE Linux Enterprise Server for SAP Applications is based on the latest proven version of SUSE Linux Enterprise Server 11 Service Pack 2 and inherits all software and hardware certifications.

Virtualization support

- VMware ESX Server 4.1 including Update versions
- VMware ESX Server 4.0 including Update versions
- VMware vSphere ESXi Server 5.5 including Update versions
- VMware vSphere ESXi Server 5.1 including Update versions
- VMware ESXi Server 5.0 including Update versions
- VMware ESXi Server 4.1 including Update versions
- VMware ESXi Server 4.0 including Update versions

A compatibility support matrix for VMware ESX and ESXi can be found at:

<http://h18004.www1.hp.com/products/servers/vmware/supportmatrix/hpvmware.html>.

Important

VMware ESXi Stateless reboot mode is supported. If VMware ESXi stateless reboot mode is used, then monitoring subscriptions are not retained and although the Hosting Device will recover, it may take up to one day during which the server will not be monitored. Refer to the Online Help for how to manually refresh subscriptions to make sure your devices are monitored after a stateless reboot.

Important

VMware ESXi Lockdown Mode is supported. Insight RS supports ESXi hosts in lockdown mode when they are managed by vCenter in a cluster configuration. Standalone ESXi hosts managed by vCenter are not supported.

- Citrix XenServer 5.5 and 5.6

A compatibility support matrix for HP ProLiant servers running Citrix XenServer can be found at

<http://h18004.www1.hp.com/products/servers/software/citrix/hpcitrixcert.html>

- Microsoft Hyper-V Server 2012 R2
- Microsoft Windows Server 2012 R2 using Hyper-V role
- Microsoft Hyper-V Server 2012
- Microsoft Windows Server 2012 using Hyper-V role
- Microsoft Hyper-V Server 2008 R2
- Microsoft Windows Server 2008 R2 using Hyper-V role

A compatibility support matrix for virtualized operating systems on HP ProLiant servers running Microsoft Windows 2008 or Microsoft Windows 2012 Hyper-V can be found at: <http://h18004.www1.hp.com/products/servers/windows/index.html>.

Important

Support for Hyper-V is limited to the full server version only and is not available for the core version as much of the required software is unavailable for this version.

HP ProLiant Gen8 servers

The following HP ProLiant Gen8 servers are supported with this release:

Table 8. Supported HP ProLiant Gen8 servers

	Server model
HP ProLiant MicroServer	HP ProLiant MicroServer2 Gen8
HP ProLiant ML Gen8 servers	- HP ProLiant ML310e Gen8 servers - HP ProLiant ML310e Gen8 v2 Server - HP ProLiant ML350p Gen8 servers - HP ProLiant ML350e Gen8 servers¹
HP ProLiant DL Gen8 servers	- HP ProLiant DL160 Gen8 servers - HP ProLiant DL320e Gen8 servers - HP ProLiant DL320e Gen8 v2 servers - HP ProLiant DL360e Gen8 servers¹ - HP ProLiant DL360p Gen8 servers - HP ProLiant DL380e Gen8 servers¹ - HP ProLiant DL380p Gen8 servers - HP ProLiant DL385p Gen8 servers - HP ProLiant DL385 Gen8 servers - HP ProLiant DL560 Gen8 servers¹ - HP ProLiant DL580 Gen8 servers
HP ProLiant BL Gen8 servers	- HP ProLiant BL420c Gen8 servers¹ - HP ProLiant BL460c Gen8 servers - HP ProLiant BL465c Gen8 servers - HP ProLiant BL660c Gen8 servers¹
HP ProLiant SL Gen8 servers	- HP ProLiant SL140s Gen8 servers - HP ProLiant SL230s Gen8 servers - HP ProLiant SL250s Gen8 servers - HP ProLiant SL270s Gen8 servers - HP ProLiant SL4540 Gen8 Server - HP ProLiant SL2500 Scalable System - HP ProLiant t2500 Gen8 Chassis - HP ProLiant SL210t Gen8 servers
HP ProLiant workstation blades	HP ProLiant WS460c Gen8 Workstation Blades

¹ Insight RS offers enhanced support for Intel XEON E5 V2 processor upgrades to these ProLiant Gen8 models.

HP ProLiant Gen8 servers can be configured for Insight Remote Support 7.1 using one of the following three methods:

1. Register with an **Insight Remote Support 7.1** Hosting Device through the HP ProLiant Gen8 iLO 4 or Intelligent Provisioning interface.
2. Discover the **HP ProLiant Gen8 server iLO 4** directly from the Insight RS Console.

Important

The minimum supported iLO 4 firmware version to register Insight Remote Support through the iLO 4 is 1.10 or above. You can download the latest firmware from the HP website www.hp.com/support/ilo4 or when installing the HP Service Pack for ProLiant 2012.08.0 or higher. See www.hp.com/go/spp for details.

Ensure that the Agentless Management Service (AMS) is enabled, the operating system is running and the *Remote Insight Board Common Language Protocol (RIBCL)* credentials for the device are entered in the Insight RS Console **before** registering with HP Insight Remote Support.

Important

When setting up the iLO 4, it is important to set the time zone. If the time zone is not set, events sent to Insight Remote Support are displayed with a GMT offset. In iLO 4, browse to **Administration → Network → SNTP Settings** to set the correct time zone.

3. Install the appropriate diagnostic agents and then discover the HP ProLiant Gen8 itself (not the iLO 4) from the Insight RS Console.

This requires the installation and configuration of the appropriate HP Insight Management (IM) Agents or HP Insight Management WBEM Providers on these servers. HP recommends installing HP Service Pack for ProLiant (SPP) 2012.06.0 (B) or higher. For details see www.hp.com/go/spp.

Important

Only **one** configuration method should be selected; attempting to configure more than one will result in an unsupported configuration. For instructions on how to configure Insight Remote Support for HP ProLiant Gen8 servers, please see the *HP Insight Remote Support 7.1 Monitored Device Configuration Guide* at www.hp.com/go/insightremotesupport/docs.

For more information on using the Agentless Management Service compared to operating system agents, see the document *Considerations for choosing HP Agentless Management* at <http://h20000.www2.hp.com/bc/docs/support/SupportManual/c03488111/c03488111.pdf>.

For more information on iLO 4 and Agentless Management Service (AMS), see the *HP iLO 4 User Guide* available at www.hp.com/go/ilo.

On the proceeding servers, the following operating systems are supported, providing they are supported by that model of hardware:

For a detailed list of supported operating system versions and available install methods, see www.hp.com/go/supportos.

Microsoft Windows support

- Microsoft Windows Server 2012 R2
 - Standard Edition
 - Datacenter Edition
- Microsoft Windows Storage Server 2012 R2¹
 - Standard Edition
- Microsoft Windows Server 2012
 - Foundation Edition
 - Standard Edition
 - Datacenter Edition
- Microsoft Windows Storage Server 2012¹
 - Standard Edition
- Microsoft Windows Server 2008 (x86 and x64) SP2 and R2 w/ SP1
 - Standard Edition
 - Enterprise Edition
 - Web Server

¹ Windows Storage Server is only supplied and supported when part of an HP Storage Server.

Linux support

- Red Hat Enterprise Linux 6.x (x86 and EM64T/AMD64)
 - Red Hat Enterprise Linux 5.7 (x86 and EM64T/AMD64)
-

Note

There are kdump issues with Red Hat Enterprise Linux 6.1 which is fixed in version 6.2. Refer to the following [Red Hat Knowledge Base article](#) for more details.

- SUSE Linux Enterprise Server 11 (x86 and EM64T/AMD64) including Service Packs
- SUSE Linux Enterprise Server 10 SP4 (x86 and EM64T/AMD64)

Note

Installation of SUSE Linux Enterprise Server 11 SP1 does not recognize the chipset on HP ProLiant Gen8-Series servers using the kISO for installation. Refer to the [Customer Advisory](#) for more details.

SUSE Linux Enterprise Server for SAP Applications is based on the latest proven version of SUSE Linux Enterprise Server 11 Service Pack 2 and inherits all software and hardware certifications.

- Canonical Ubuntu 12.04

Note

The Canonical Ubuntu operating system is supported for HP ProLiant Gen8 servers when using the iLO 4 connectivity with or without the appropriate Agentless Management Service (AMS) installed. For a detailed list of supported Canonical Ubuntu operating system versions, see <http://h18004.www1.hp.com/products/servers/linux/hplinuxcert-canonical.html>.

- CentOS

Note

The CentOS operating system is supported for HP ProLiant Gen8 servers when using the iLO 4 connectivity with or without the appropriate Agentless Management Service (AMS) installed. For a detailed list of supported CentOS operating system versions, see <http://h18004.www1.hp.com/products/servers/software/centos/index.html>.

Virtualization support

- VMware ESX 4.1 Server including Update versions
- VMware vSphere ESXi Server 5.5 including Update versions
- VMware vSphere ESXi Server 5.1 including Update versions
- VMware ESXi Server 5.0 including Update versions
- VMware ESXi Server 4.1 including Update versions

Important

VMware ESX and ESXi 4.1 U2 support is limited to monitoring via the embedded capabilities in the HP iLO 4; agent support is currently not available.

HP Integrity servers

The current HP Integrity server family models supported by HP Insight Remote Support 7.x are listed below. Additional Integrity server models will be added to the supported models list as they are introduced.

Including automatic machine check abort analysis for all HP Integrity servers running HP-UX 11i v3 (See the [Machine Check Abort](#) section below for details).

Important

HP Integrity Superdome SD-A and SD-B servers are **not** supported, but can be monitored with the HP Insight Remote Support Advanced software. See [Appendix A](#) for details.

Table 9. Supported HP Integrity servers

	Server model
HP Integrity Superdome 2 servers	• HP Integrity Superdome 2 (HP-UX 11i v3 operating system support only)
HP Integrity servers	• HP Integrity rx1600 / rx1620 • HP Integrity rx2600 / rx2620 / rx2660 • HP Integrity rx2800 i2 (HP-UX 11i v3 and OpenVMS 8.4 operating system support only) • HP Integrity rx2800 i4 servers (HP-UX 11i v3 operating system support only) • HP Integrity rx3600 • HP Integrity rx4640 • HP Integrity rx5670 (HP-UX 11i v2, HP-UX 11i v3 and Microsoft Windows 2003 R2 operating system support only) • HP Integrity rx6600

- HP Integrity rx7620 / rx7640
- HP Integrity rx8620 / rx8640

HP Integrity BladeSystem servers

- HP Integrity BL860c and BL870c, including Service Media Library Links for BL860c/BL870c callouts
 - HP Integrity BL860c i2 Blade servers (HP-UX 11i v3, OpenVMS 8.4 and Windows 2008 R2 operating system only)
 - HP Integrity BL870c i2 Blade servers (HP-UX 11i v3, OpenVMS 8.4 and Windows 2008 R2 operating system only)
 - HP Integrity BL890c i2 Blade servers (HP-UX 11i v3, OpenVMS 8.4 and Windows 2008 R2 operating system only)
 - HP Integrity BL860c i4 server blades (HP-UX 11i v3 operating system support only)
 - HP Integrity BL870c i4 server blades (HP-UX 11i v3 operating system support only)
 - HP Integrity BL890c i4 server blades (HP-UX 11i v3 operating system support only)
-

Operating system support

The following operating systems are supported on HP Integrity servers:

HP-UX support

- HP-UX 11i v2 or higher (see the [HP-UX operating system prerequisites](#) section below for prerequisites)

For HP-UX operating system support on HP Integrity servers, see the HP-UX 11i Support Matrix at www.hp.com/go/hpuxservermatrix.

Important

HP Integrity BladeSystem servers using HP-UX 11i v3 as the operating system require the installation of the **Diagnostics Products Collection depot (B69191AAE)**. This is not an HP Insight Remote Support requirement, but an HP-UX requirement to provide support for these servers. A copy of the bundle is available from [HP Software Depot](#).

Please also see the HP-UX Errata for HP Integrity BL860c i2, BL870c i2 & BL890c i2 Server Blades document for details on required patches. This is not an HP Insight Remote Support requirement, but a HP-UX requirement to provide support for these servers. A copy of the document is available at <http://bizsupport2.austin.hp.com/bc/docs/support/SupportManual/c02111059/c02111059.pdf>

Linux support

Note

nPars are **not** supported on Linux Integrity servers.

- Red Hat Enterprise Linux 5 for Itanium-based Systems
 - Red Hat Enterprise Linux 4 for Itanium-based Systems
 - Red Hat Enterprise Linux 3 for Itanium-based systems
 - SUSE Linux Enterprise Server 11 for Itanium-based systems
 - SUSE Linux Enterprise Server 10 for Itanium-based systems
 - SUSE Linux Enterprise Server 9 for Itanium-based systems
 - SUSE Linux Enterprise Server 8 for Itanium-based systems
-

Important

HP strongly recommends installing the **HP Integrity Essentials Foundation Pack** rather than installing the HP Insight Management Agent or Insight Management WBEM Provider alone as it contains additional recommended component updates. For more details, visit <http://h20341.www2.hp.com/integrity/w1/en/os/linux-on-integrity-certification-matrix-novell-suse.html>.

Microsoft Windows support

HP recommends installing the HP Integrity Insight Management Agents (SNMP) or HP Integrity WBEM Providers from the HP Integrity Support Pack for Windows rather than installing the agents alone. For more information, visit <http://h20341.www2.hp.com/integrity/us/en/os/windows-on-integrity-releases.html>.

- Microsoft Windows Server 2008 R2 including Service Pack 1
- Microsoft Windows Server 2008 with SP1 or higher

Important

Microsoft Windows Server 2008 operating system support requires the installation and enablement of HP Insight Management WBEM Providers (WMI) on the monitored device. It does **not** support the SNMP protocol.

Support for Windows 2008 and Windows 2008 R2 is limited to the full server version only and is not available for the core version as much of the required functionality is unavailable for this version.

- Microsoft Windows Server 2003
 - Datacenter Edition
 - Enterprise Edition

Also ensure that you have the Event Log Monitoring Collector (ELMC) installed on the monitored device as this is required for event monitoring in addition to the agents or providers. Copy the appropriate (IA64 or x86/x86) ELMC client from the Insight Remote Support download folder on the Hosting Device:

%HP_RS_DATA%\ELMC

This folder defaults to C:\ProgramData\HP\RS\DATA\ELMC. This is a hidden folder, so you may need to set your folder options to show hidden folders. See [Appendix C](#) for more information on ELMC.

OpenVMS support

- OpenVMS V8.3-1 or higher
 - Dynamic Processor Resilience is also supported through the configuration of the Dynamic Processor Resilience Adapter
 - CPU Indictment is also supported

Important

OpenVMS WBEM providers must be installed and the credentials properly configured for OpenVMS monitored devices.

Important

OpenVMS 8.4 operating system support on the rx2800 i2 servers require the installation of VMS84I_UPDATE-V0500 or later. For more details, visit http://h71000.www7.hp.com/openvms/products/wbem/wbem_index.html.

Important

OpenVMS 8.4 operating system support on the BL8x0c i2 blade servers requires the installation of VMS84I_UPDATE-V0200 or later. For more details see http://h71000.www7.hp.com/openvms/products/wbem/wbem_index.html

Ensure that you have the Event Log Monitoring Collector (ELMC) installed on the monitored device as this is required for event monitoring in addition to the WBEM Provider. Copy the appropriate ELMC client from the Insight Remote Support download folder on the Hosting Device:

%HP_RS_DATA%\ELMC

This folder defaults to C:\ProgramData\HP\RS\DATA\ELMC. This is a hidden folder, so you may need to set your folder options to show hidden folders. See [Appendix C](#) for more information on ELMC.

For more information, visit the OpenVMS hardware support chart at http://h71000.www7.hp.com/openvms/hw_supportchart.html.

HP-UX operating system prerequisites

Important – Information for all HP-UX versions

It is Critical that System Fault Management (SFM) is the last software component installed or upgraded from the list below.

System Management Web is **optional**, but it allows you to take full advantage of System Fault Management's EVWEB GUI component which allows viewing of events handled by SFM on the host.

HP WBEM Services, OnlineDiag and SysMgmtWeb are available on the HP-UX Operating Environment (OE) media and can be selected for installation during the SFM installation.

Patches are available from [HP Support Center](#). After sign-in, click the **Patch Management** link from the left menu. Enter the patch name into the search box and click **GO**.

On the preceding HP Integrity servers, the following minimum HP-UX software components are required to make them eligible for HP Insight Remote Support 7.1:

Table 10. Required software components for HP-UX 11i v2

	Version required	Notes
HP-UX Operating Environment 11iv2	- September, 2004 11i v2 OE (minimum OE release) - May, 2005 11i v2 OE or later (required for vPars enablement)	While not required for HP-UX 11i v2, HP strongly recommends installing the latest <i>B.11.23.0712.070 Base Quality Pack Bundle for HP-UX 11i v2 (December 2007)</i> as it fulfills all patch requirements and provides a stable supported environment. However, it is not a compulsory requirement for Insight Remote Support.
Operating System Patch Requirements	BUNDLE11i patch bundle B.11.23.0409.3 (September, 2004) In addition, the following patches are required: - PHKL_36288 – 11.23 Cumulative diag2 driver and vPars enablement (use in place of PHKL_32653), requires a reboot after installation - PHKL_34795 – 11.23 Cumulative IPMI driver patch (reboot required after install) - PHSS_37552 – 1.0 Aries cumulative patch - PHSS_37947 – 1.0 linker +fdp cumulative patch - PHSS_35055 – aC++ Runtime (IA: A.06.10, PA: A.03.71) - PHSS_36345 – 11.23 Integrity Unwind Library	These six additional patches for HP-UX 11i v2 are not part of the Bundle11i and must be installed in addition to it. How to install patches for HP-UX 11iv2: Go to www.hp.com/go/hpsc and sign in using your HP Passport account. In the left menu, click the Patch management link. Enter the patch name into the Patch Management search box and click GO .
OpenSSL Secure Network Communications Protocol	A.00.09.07i.012 (December, 2006) or later	
Online Diagnostics	B.11.23.10.05 HPUX 11.23 Support Tools Bundle (December, 2007) or later	
WBEMSVcs (WBEM Services Core Product)	A.02.05.08 WBEM Services CORE Product (December, 2007) or later	You are advised to check the WBEM Services Release Notes including the WBEM Provider Compatibility Table for that product version, if you need to install or update this service.
System Management Web (recommended for event monitoring, required for	A.2.2.7 HP-UX Web Based System Management User Interface (December 2007) or later	System Management Web is optional, but it allows you to take full advantage of SFM's EVWEB GUI component which allows viewing of events handled by SFM on the host. If only SysMgmtHomepage version 2.2.6.2 is

Table 10. Required software components for HP-UX 11i v2

	Version required	Notes
configuration collection)		present on the server, then the following patch must also be applied: For HP-UX 11i v2 (11.23) OE apply patch PHSS_36870
System Fault Management (SFM)	B.07.01.01.yy System Fault Management (May, 2009) or later	See the System Fault Management Release Notes for more details and additional SFM prerequisites at www.hp.com/go/hpux-diagnostics-sfm-docs .

Table 11. Required software components for HP-UX 11i v3

	Version required	Notes
HP-UX Operating Environment 11i v3	- EVM-EventMgr B.11.31 or later - Baseboard Management Controller (BMC) firmware version 05.21 or later - SysMgmtBase B.00.02.03 or later	The Baseboard Management Controller firmware is only required for rx3600 and rx6600 servers to provide the correct Power & Cooling information to System Fault Manager.
OpenSSL Secure Network Communications Protocol	A.00.09.07e.013 or later	
Online Diagnostics: Diagnostic and Support Tools for HP-UX, including STM version A.49.10 or later and EMS version A.04.20 or later	B.11.31.01.yy or later (SysFaultMgmt version dependency see notes)	Important: You are advised to check the WBEM Services Release Notes including the WBEM Provider Compatibility Table for that product version, if you need to install or update this service.
System Management Web (recommended for event monitoring, required for configuration collection)	A.2.2.4 HP-UX Web Based System Management User Interfaces (December, 2007) or later	System Management Web is optional , but it allows you to take full advantage of SFM's EVWEB GUI component which allows viewing of events handled by SFM on the host. If only SysMgmtHomepage version 2.2.6.2 is present on the server, then the following patch must also be applied: For HP-UX 11i v3 (11.31) OE apply patch PHSS_36871
System Fault Management (SFM)¹	C.07.10.08.yy HPUX System Fault Management or later	See the System Fault Management Release Notes for more details and additional SFM prerequisites at www.hp.com/go/hpux-diagnostics-sfm-docs .

¹ HP recommends installing SFM through the WBEMMgmtBundle available at:<https://h20392.www2.hp.com/portal/swdepot/displayProductInfo.do?productNumber=WBEMMgmtBundle>**HP-UX machine check abort automatic analysis capabilities for HP-UX 11i v3**

HP-UX machine check abort automatic analysis is available for all HP Integrity servers.

Note

The following servers require the installation of a specific System Fault Management (SFM) version to enable this capability:

- HP Integrity BL8x0c i2 running System Fault Management April 2011 version or higher
- HP Integrity rx2800 i2 running System Fault Management April 2011 version or higher

This SFM version is delivered as a part of Diagnostics Products Collection depot (April 2011 release or higher) available from Software Depot at: h20392.www2.hp.com/portal/swdepot/displayInstallInfo.do?productNumber=DiagProdCollection.

HP BladeSystem Enclosures

HP Insight Remote Support monitoring is limited to the Enclosure and the Onboard Administrator (OA). Monitoring of the devices within the Enclosure requires the additional steps of discovery and configuration of those devices to be monitored.

Note

HP BladeSystem c-Class interconnect modules (Virtual Connect, Ethernet, Fibre Channel, InfiniBand and SAS interconnects) will automatically be monitored via the OA management module, if it is configured for monitoring.

The following HP BladeSystem c-Class Enclosures are supported:

- HP BladeSystem c3000 Enclosure
- HP BladeSystem c7000 Enclosure
- Includes Onboard Administrator

HP BladeSystem c-Class Enclosures can be configured for Insight Remote Support 7.1 using one of the two methods based on the Onboard Administrator (OA) firmware level:

Do **not** attempt to configure both configuration methods as this is not supported and monitoring will not work correctly.

1. OA firmware level 3.60 or above
 - Register with an **Insight Remote Support 7.1** Hosting Device through the OA to send service events to the Hosting Device for both the primary and standby OA

Note

If using OA firmware versions 3.55 or 3.56 HP recommends you upgrade to version 3.60.

2. OA firmware level prior to 3.55
 - If you have configured a primary and standby OA in your environment, you should configure the **SNMP** protocol to send traps to the Hosting Device
 - Discovery from the Insight Remote Support Hosting Device should be limited to one of the OAs and not both

The latest firmware software can be found on the HP website at: www.hp.com/support/oa.

HP 9000 servers

HP only provides limited remote support for customers using HP 9000 servers. HP Insight Remote Support will attempt to discover these products as remotely monitored HP products and send information about failure events to HP.

However, if there are issues with the operation of the remote monitoring features of HP Insight Remote Support version 7.x for these specific products, including the remote discovery or the reporting of failure events to HP, then HP will resolve such issues in a commercially reasonable manner but without guarantee of an immediate response or a resolution. If a failure event is successfully received at HP, it is managed according to the support level agreement.

The following HP 9000 servers have this limited support:

Table 12. HP 9000 Server models and operating system requirements

HP 9000 model	Notes
rp7400 (N-class)	HP-UX is the only supported operating system. For HP-UX operating system support on HP 9000 server, see the HP-UX 11i Support Matrix at www.hp.com/go/hpuxservermatrix .
rp7410	
rp7420	
rp7440	
rp8400	
rp8420	
rp8440	
rp3410	
rp3440	
rp4410	
rp4440	
Carrier-grade Servers (cx2620, cc3310)	
rp2400 series (A-Class)	

Table 12. HP 9000 Server models and operating system requirements

HP 9000 model	Notes
rp5400 series (L-Class)	
D,K,R,T,V (Class)	

HP NonStop systems

HP NonStop Server systems are currently **not** supported with the HP Insight Remote Support 7.1 software, but can be monitored with the HP Insight Remote Support Advanced software.

HP AlphaServer systems

HP only provides limited remote support for customers using HP Alpha servers. As with standard support, HP Insight Remote Support version 7.x will attempt to discover these products as remotely monitored HP products and send information about failure events to HP.

However, if there are issues with the operation of the remote monitoring features of HP Insight Remote Support version 7.x for these specific products, including the remote discovery or the reporting of failure events to HP, then HP will resolve such issues in a commercially reasonable manner but without guarantee of an immediate response or a resolution. If a failure event is successfully received at HP, it is managed according to the support level agreement.

The following HP Alpha Server systems have this limited support:

Table 13. HP Alpha Server models and operating system requirements

HP Alpha models ¹	Operating System requirements
HP AlphaServer DS10/DS10L/DS15/DS20/DS20E/DS25	OpenVMS V7.3.2 or higher
HP AlphaServer ES40/ES45	Tru64 UNIX V4.0F, V4.0G, V5.1A or higher
HP AlphaServer GS80/GS160/GS320	
HP AlphaServer TS80/ES47/ES80/GS1280/GS1280	
HP AlphaServer TS20/TS40	
HP AlphaServer TS202C	
Memory Channel	

¹ Legacy Alpha servers that require DECEvent as well as HP AlphaServer DS20L are **not** supported.

Selected non-HP servers

HP Insight Remote Support 7.1 provides remote monitoring support for select non-HP servers with a HP multivendor support or HP Integrated Support Management services contract.

SNMP needs to be configured and enabled for these non-HP servers to be able to send events to the Hosting Device. For setup instructions, see the *HP Insight Remote Support Monitored Devices Configuration Guide* available at www.hp.com/go/insightremotesupport/docs.

Note

Configuration collections are **not** supported.

The following selected non-HP servers are supported:

Table 14. Supported non-HP servers

	Hardware	Operating System	Agent support ¹
IBM Windows	IBM BladeCenter chassis and BladeCenter Servers IBM System x	Microsoft Windows 2008 Microsoft Windows 2008 R2	IBM Systems Director Common Agent version 6.1.1 or later
Dell Windows	Dell PowerEdge	Microsoft Windows 2008 Microsoft Windows 2008 R2	Dell OpenManage Server Administrator version 6.2.0 or later

¹ Insight Remote Support was tested with this agent version, but it is always recommended to install the latest agent version available from the vendor.

Monitoring support for non-HP servers requires special attention to server entitlement data. The serial and product numbers that are discovered do usually not match the serial and product number listed in the HP support contract. For a detailed description of how to configure remote monitoring for your eligible non-HP servers through HP Insight Remote Support 7.x, please contact your HP Account Support team to setup the customization for your delivery.

HP Storage

This release supports monitoring support for the following storage products. Please see the table in [Appendix B](#) for the appropriate providers to be installed and configured by hardware type.

HP P6000 Enterprise Virtual Array Systems

Ensure that the **Event Log Monitoring Collector (ELMC)** is installed on all servers where HP P6000 Command View is installed. ELMC is made available through the Insight RS Software Updates feature and needs to be manually installed on your Storage Management Server. This does not apply to EVAs using the Array Based Management (ABM) module. See [Appendix C](#) for details on ELMC.

Important

For all P6000/EVA devices the minimum requirement is HP P6000 Command View **9.4** or higher.

For specific requirements concerning HP P6000 Command View, see the *HP P6000 Enterprise Virtual Array Compatibility Reference* document, available from the HP Business Support Center web site at <http://www.hp.com/support/manuals>:

1. Under All HP products, click **Storage** → **Storage Software** → **Storage Device Management Software** → **HP EVA P6000 Device Management Software** → **HP P6000 Command View Software**.
 2. Click **HP Command View Software**.
 3. Under General Reference, click **HP P6000 Enterprise Virtual Array Compatibility Reference**.
-

The following HP P6000/ Enterprise Virtual Array Systems are supported with this release:

- EVA 3000/5000
- EVA 4000/6000/8000
- EVA 4100/6100/8100
- EVA 4400
- EVA 6400/8400
- HP P6300/6500 EVA
- HP P6350/P6550 EVA

Also you have the choice to configure HP P6000 Command View, the Hosting Device and the Storage Management Server (SMS) in different ways including the option to install all components on the same server. For details and restrictions, see the P6000 and Enterprise Virtual Array Configuration chapter in the *HP Insight Remote Support Monitored Devices Configuration Guide* available at www.hp.com/go/insightremotesupport/docs for the various options.

HP StoreVirtual Storage (formerly P4000 SAN Solutions/LeftHand Storage)

HP StoreVirtual Storage is the new name for HP LeftHand Storage and HP P4000 SAN solutions. LeftHand Operating System (LeftHand OS) is the new name for SAN/iQ. These name changes will be incorporated into documentation, solution materials and product components.

SNMP needs to be configured and enabled for each Storage Node to be able to send events to the Hosting Device. SNMP is enabled by default in HP LeftHand OS (formerly SAN/iQ) and should not be modified.

Each Storage Node counts as 30 monitored devices within HP Insight Remote Support. Ensure that you allocate enough disk space for HP StoreVirtual (P4000) collections. The required disk space is dependent on the number of HP StoreVirtual Storage Nodes. See the [Configuration Collection capabilities](#) section above for calculating the required disk space.

Supported hardware platforms

Table 15. Supported HP StoreVirtual Storage nodes

Solution name	Software Discoverable model name
LeftHand NSM2060 G2	P4300
HP P4300	

Table 15. Supported HP StoreVirtual Storage nodes

Solution name	Software Discoverable model name
HP P4300 G2	P4300G2
LeftHand NSM2120 G2 HP P4500	P4500
HP P4500 G2	P4500G2
LeftHand VSA	P4000 VSA (ESX)
HP P4800 G2	P4000sb G2 P4460sb G2
HP P4900 G2	P4900G2
HP LeftHand VSA	P4000 VSA (ESX) P4000 VSA (Hyper-V)
HP P4000 Failover Manager	Failover Manager (ESX) Failover Manager (Hyper-V)
HP Failover Manager (ESX)	HP Failover Manager (ESX)
HP Failover Manager (Hyper-V)	HP Failover Manager (Hyper-V)
HP StoreVirtual 4130	4130
HP StoreVirtual 4330	4330
HP StoreVirtual 4330 FC	4330 FC
HP StoreVirtual 4335	4335
HP StoreVirtual 4530	4530
HP StoreVirtual 4630	4630
HP StoreVirtual 4730	4730
HP StoreVirtual 4730 FC	4730 FC

Software requirements

- Each Storage Node requires HP LeftHand OS (formerly SAN/iQ) version 9.5, 10.0, 10.5, or 11.0
 - Each Storage Node running HP LeftHand OS version 9.5 requires Patch Set 05
- SNMP needs to be enabled and configured for each Storage Node
- HP StoreVirtual Centralized Management Console (CMC) 9.0, 9.5, 10.0, 10.5, or 11.0
- For new installations, HP recommends installing the HP StoreVirtual Centralized Management Console (CMC) on the Hosting Device, but it is also supported on a separate device

For details and future updates to supported platforms, see the *HP StoreVirtual 4000 Storage Compatibility Matrix* available at www.hp.com/go/StoreVirtualcompatibility.

HP P2000/Modular Smart Array Systems

Both **SNMP** and **WBEM** need to be configured and enabled for P2000 G3 monitored devices to be able to send events to the Hosting Device.

SNMP needs to be configured and enabled for MSA 15xx and MSA2xxx G1 monitored devices to be able to send events to the Hosting Device.

Both **SNMP** and **WBEM SMI-S Proxy Provider Software** are required for MSA23xx G2 monitored devices to be able to send events to the Hosting Device. For details, see the *HP Insight Remote Support Monitored Devices Configuration Guide* available at www.hp.com/go/insightremotesupport/docs.

Important

MSAs with SNMPv3 enabled require SNMPv3 credentials be configured in the Insight RS Console. Failure to supply SNMPv3 credentials in the Insight RS Console results in Insight RS displaying only one of the controllers of those MSAs.

All variants of HP P2000/Modular Smart Arrays are supported with this release. This includes:

- MSA1000 series
-

Important

The MSA1000 series is only supported when attached to a HP ProLiant server using SNMP protocol. It is not discovered or monitored as a separate device but supported through the diagnostic agent installed and configured on the server. The HP ProLiant's entitlement to service is applied for the MSA 1000 series.

- MSA15xx series
 - MSA2xxx series
 - MSA23xx G2 series
 - MSA23xxa G2 series
 - MSA23xxfc G2 series
 - MSA23xxi G2 series
 - P2000 G3 series (with T230, T240, T250 or T251 firmware)
 - HP MSA 2040 SAN Storage
 - HP MSA 2040 SAS Storage
 - HP MSA 1040 Storage
-

Important

MSA2xxx devices (2012fc, 2212fc, 2012i and 2012sa) do **not** support configuration collections, except when the MSA2xxx is part of a SAN collection.

HP StoreAll Storage (formerly HP IBRIX Storage)

SNMP needs to be configured and enabled on the File Serving Nodes to send hardware events to the Hosting Device. For setup instructions, see the *HP Insight Remote Support Monitored Devices Configuration Guide* available at www.hp.com/go/insightremotesupport/docs.

Note

HP StoreAll Operating System v6.5 supports RedHat Linux 5.8.

Important

All StoreAll nodes will be displayed in the Insight RS Console by their equivalent ProLiant server model names instead of the Ibrix or StoreAll model name.

The following HP StoreAll Storage Systems are supported:

- HP StoreAll 8200 Gateway
 - HP StoreAll 8800 Storage
 - HP IBRIX X9300 Network Storage Gateway
 - HP IBRIX X9320 Network Storage Systems
 - HP IBRIX X9720 Network Storage Systems
-

Important

Insight RS does **not** support the array controller and disk enclosure components of the X9720 solution, including model numbers X9700c and X9700cx or MSA2060 and MSA2070.

- HP IBRIX X9730 Network Storage Systems

HP StoreEasy Storage (formerly Commercial NAS)

WMI needs to be configured and enabled on the File Serving Nodes to send hardware events to the Hosting Device. For setup instructions, see the *HP Insight Remote Support Monitored Devices Configuration Guide* available at www.hp.com/go/insightremotesupport/docs.

The following HP StoreEasy Storage (formerly Network Attached Storage NAS) are supported:

- HP ProLiant Storage Server family (excluding 1xx series)
- HP All-in-One 600 and 1200 Storage Systems
- HP NAS Series including
 - HP X1000 Network Storage Systems
 - HP X3000 Network Storage Systems
 - HP X1800 G2 Network Storage Systems
 - HP X3800 G2 Network Storage Systems
 - HP X5520 G2 Network Storage Systems
- HP StoreEasy 1xx0 Storage
- HP StoreEasy 3xx0 Gateway Storage
- HP StoreEasy 5000 Storage
- HP 3PAR File Controller Storage
- HP 3PAR File Controller Storage V2

Note

The following HP Network Attached Storage (NAS) are not supported with the HP Insight Remote Support software:

- HP StorageWorks Storage Server (NAS) 1000s Network Attached Storage 1000s
 - HP StorageWorks Storage Server (NAS) 1200s Small Business Class Family Network Attached Storage 1200s
 - HP StorageWorks Storage Server (NAS) 1500s Network Attached Storage 1500s
 - HP StorageWorks Storage Server (NAS) s1000 Network Attached Storage S1000 Model 320/640
 - HP StorageWorks Storage Server (NAS) 8000 Network Attached Storage 8000
 - HP Surestore Storage Server (NAS) VA Solutions Network Attached, HP-UX based storage solution UNIX
 - Compaq Storage Server (NAS) N2400 Network Attached Storage 2400
 - HP StorageWorks AIO400 Storage System
-

HP Storage Blades

The following HP Storage Blades are supported with this release:

- HP All-in-One SB600c Storage System
- HP All-in-One SB920c Tape Blade
- HP D2000sb Storage Blades

HP Virtual Library Systems

SNMP needs to be configured in Command View for Virtual Library System (VLS) to send traps to the Hosting Device. For setup instructions, see the *HP Insight Remote Support Monitored Devices Configuration Guide* available at www.hp.com/go/insightremotesupport/docs.

Note

Configuration collections are currently **not** supported, except when the VLS is part of a SAN collection. See [Appendix B](#) for details.

The following HP Virtual Library Systems are supported with this release:

- HP 300 Virtual Library System EVA Gateway
- HP 12000 Virtual Library System EVA Gateway
- HP 9000 Series Virtual Library System
- HP 6000 Series Virtual Library System including:
 - HP VLS 6200 and 6500
 - HP VLS61xx, VLS65xx and VLS 68xx

HP StoreEver Tape Libraries

HP Insight Remote Support 7.1 supports HP StoreEver Tape Libraries that use HP Command View for Tape Libraries software version **3.1** or above. A copy of the software can be downloaded from www.hp.com/support/cvttl.

Note

Insight RS does not support standalone (non-library) tape drives.

SNMPv1 needs to be configured and enabled for the monitored devices to be able to send events to the Hosting Device. For instructions on how to configure the tape library management tool to send traps, see the *HP Insight Remote Support Monitored Devices Configuration Guide* available at www.hp.com/go/insightremotesupport/docs.

The following HP Tape Libraries are supported with this release:

- HP ESL G3 Tape Library
- HP ESL-e Tape Library
- HP EML Tape Library
- MSL8096 Tape Library
- MSL8048 Tape Library
- MSL4048 Tape Library
- MSL2024 Tape Library
- MSL G3 Tape Library
- HP StoreEver MSL G4 Tape Library
 - HP StoreEver MSL6480 Scalable Base Module
 - HP StoreEver MSL6480 Scalable Expansion Module
 - HP StoreEver MSL6480 2-LT05 Ultrium 3000 Fibre Channel Tape Library
 - HP StoreEver MSL6480 2-LT06 Ultrium 6400 Fibre Channel Tape Library

For details, see the Configuring StoreEver Tape Libraries chapter of the *HP Insight Remote Support Monitored Devices Configuration Guide* available at www.hp.com/go/insightremotesupport/docs.

HP Tape Blades

Note

Insight RS does not support standalone (non-library) tape blades.

HP Ultrium 448c Tape Blades are monitored via the diagnostic agent installed on the server to which they are attached.

Product support includes:

- HP Ultrium 448c Tape Blade

HP StoreOnce Backup (D2D)

Ensure that **SNMP** service is enabled and **public community credentials** are configured for the monitored device to be able to send events to the Hosting Device. For details, see the StoreOnce (D2D) Backup Systems Configuration chapter of the *HP Insight Remote Support Monitored Devices Configuration Guide* available at www.hp.com/go/insightremotesupport/docs.

Table 16. Supported HP StoreOnce (D2D) Backup Systems

	Product name	Note
Gen 2 single-node products	• HP D2D2502i Backup System	These backup systems require firmware version 2.1.03 or above.
	• HP D2D2504i Backup System	
	• HP D2D4312 Backup System	
	• HP D2D4112 Backup System	
	• HP D2D4106i Backup System	
	• HP D2D4106fc Backup System	
	• HP D2D2502i Backup System/S-Buy	
	• HP D2D2504i Backup System/S-Buy	
	• HP Capacity Upgrade (1TB) (D2D4112/D2D4312)	
	• HP D2D4106 Capacity Upgrade (12 x 500GB)	
	• HP D2D4324 18TB D2D Backup System	
	• HP D2D4324 18TB D2D Upgrade Kit	
	• HP D2D4324 18TB D2D Replication License	
	• HP D2D4324 18TB D2D e-delivery Replication License	
Gen 3 single-node products	• HP B6200 Backup System	
	• HP StoreOnce 2620 iSCSI Backup System	
	• HP StoreOnce 4210 iSCSI Backup System	
	• HP StoreOnce 4210 FC Backup System	
	• HP StoreOnce 4220 Backup System	
	• HP StoreOnce 4420 Backup System	
	• HP StoreOnce 4430 Backup System	

HP P9000/XP Disk Arrays

HP P9000/XP Disk Arrays are currently **not** supported with the HP Insight Remote Support 7.1 software, but can be monitored with the HP Insight Remote Support Advanced software.

HP 3PAR StoreServ Storage

HP 3PAR StoreServ storage is **not** supported with the HP Insight Remote Support 7.1 software, but can be monitored with its own monitoring solution.

HP Secure Key Manager

HP Secure Key Manager is currently **not** supported with the HP Insight Remote Support 7.1 software, but can be monitored with the HP Insight Remote Support Advanced software.

HP Enterprise Secure Key Manager

HP Enterprise Secure Key Manager is currently **not** supported with the HP Insight Remote Support 7.1 software, but can be monitored with the HP Insight Remote Support Advanced software.

HP StoreFabric (formerly SAN Fibre Channel Switches)

SNMPv1 or SNMPv2 needs to be configured and enabled for HP Storage Switches to be able to send events to the Hosting Device.

- B-series Fibre Channel (FC) Switches (Brocade) including
 - HP SN6000B Fibre Channel Switches
 - HP DC SAN Backbone Director Switches (DCX)
 - HP 1606 Extension SAN Switches
 - HP 8/80 SAN Switches
 - HP Brocade 8Gb SAN Switch for BladeSystem c-Class

Test trap support for HP B-series Fibre Channel switches requires the installation of Fabric Operating system **v6.3.0b** firmware or higher. See the HP Fabric OS 6.3.0b [Customer Advisory](#) or details.

- C-series Fibre Channel Switches including
 - Cisco MDS Fibre Channel switches, including support for Cisco NX-OS version 5.x
 - HP SN6000C Fibre Channel Switches
- H-series Fibre Channel Switches including
 - HP SN6000 Fibre Channel Switches
 - HP StoreFabric SN6500B 16Gb 96/96 Switches
 - HP 8/20q Fibre Channel Switches
 - HP 2/8q Fibre Channel Switches

Note

Older 1GB Brocade switches (1 GB) and M-Class Switches are **not** supported.

HP Networking Switches

HP Insight Remote Support 7.1 provides product support for selected HP Networking Switches. This includes HP ProVision-based (formerly HP E-Series/ProCurve) and HP ComWare-based (formerly A-Series or H3C/3COM) networking switches.

HP ProVision-based Switches (formerly E-Series/ProCurve)

HP ProVision-based switches require **SNMP** for discovery and remote monitoring. These devices ship with SNMP installed and enabled so that no additional configuration is needed.

Important

Switches configured to use switch stacking capabilities are currently not supported with HP Insight RS. HP Insight RS 7.1 only supports standalone mode for these switches.

For configuration collections, please ensure that either **TELNET** or **SSH** service is enabled. TELNET is enabled on HP ProVision-based Switches by default. If you prefer to use SSH, you will need to enable it. For instructions, see the *HP Insight Remote Support Monitored Devices Configuration Guide* available at www.hp.com/go/insightremotesupport/docs.

Table 17. Supported HP ProVision-based Switches

	Product description	HP Product Number
2510 switch series	• HP 2510-24G Switch • HP 2510-48G Switch	• J9279A • J9280A
2512 switch series	• HP ProCurve 2512 Switch	• J4812A
2520 switch series	• HP 2520-8-PoE Switch • HP 2520-8G-PoE Switch • HP 2520-24-PoE Switch • HP 2520-24G-PoE Switch	• J9137A • J9298A • J9138A • J9299A
2524 switch series	• HP ProCurve 2524 Switch	• J4813A

Table 17. Supported HP ProVision-based Switches

	Product description	HP Product Number
2530 switch series	• HP 2530-24G Switch • HP 2530-48G Switch • HP 2530-24G-PoE+ Switch • HP 2530-48G-PoE+ Switch • HP 2530 8G-PoE+ Switch • HP 2530 8G Switch • HP 2530 48-PoE+ Switch • HP 2530 48 Switch • HP 2530 24-PoE+ Switch • HP 2530 24 Switch • HP 2530 8-PoE+ Switch • HP 2530 8 Switch	• J9776A • J9775A • J9773A • J9772A • J9774A • J9777A • J9778A • J9781A • J9779A • J9782A • J9780A • J9783A
2600 switch series	• HP E2600-8-PoE Switch	• J8762A
2610 switch series	• HP 2610-24 Switch • HP 2610-24-PPoE Switch • HP 2610-24-PoE Switch • HP 2610-48 Switch • HP 2610-48-PoE Switch	• J9085A • J9086A • J9087A • J9088A • J9089A
2615 switch series	• HP 2915-8G-PoE Switch	• J9562A
262x switch series	• HP 2620-24 Switch • HP 2620-24-PPoE+ Switch • HP 2620-24-PoE+ Switch • HP 2620-48 Switch • HP 2620-48-PoE+ Switch • HP ProCurve Switch 2626 • HP ProCurve 2626 Switch • HP ProCurve Switch 2626 • HP ProCurve Switch 2626 Pwr	• J9623A • J9624A • J9625A • J9626A • J9627A • J4900A • J4900B • J4900C • J8164A
2650 switch series	• HP ProCurve Switch 2650 • HP ProCurve 2650 Switch • HP ProCurve Switch 2650 • HP ProCurve Switch 2650 Pwr	• J4899A • J4899B • J4899C • J8165A
2810 switch series	• HP 2810-24G Switch • HP 2810-48G Switch	• J9021A • J9022A
2824 switch serie	• HP ProCurve Switch 2824	• J4903A
2848 switch series	• HP ProCurve Switch 2848	• J4904A
2900 switch series	• HP ProCurve Switch 2900-24G • HP ProCurve Switch 2900-48G	• J9049A • J9050A
2910 switch series	• HP 2910-24G al Switch • HP 2910-24G-PoE+ al Switch • HP 2910-48G al Switch • HP 2910-48G-PoE+ al Switch	• J9145A • J9146A • J9147A • J9148A

Table 17. Supported HP ProVision-based Switches

	Product description	HP Product Number
2915 switch series	HP 2615-8-PoE Switch	J9565A
2920 switch series	- HP 2920-24G Switch¹ - HP 2920-24G-PoE+ Switch¹ - HP 2920-48G Switch¹ - HP 2920-48G-PoE+ Switch¹	- J9726A - J9727A - J9728A - J9729A
3400 cl switch series	- HP ProCurve Switch 3400cl-24G - HP E3400-48G cl Switch	- J4905A - J4906A
3500 switch series	- HP 3500-24G-PoE yl Switch - HP 3500-48G-PoE yl Switch - HP 3500-24G-PoE+ yl Switch - HP 3500-48G-PoE+ yl Switch - HP 3500-24 Switch - HP 3500-24-PoE Switch - HP 3500-48 Switch - HP 3500-48-PoE Switch	- J8692A - J8693A - J9310A - J9311A - J9470A - J9471A - J9472A - J9473A
3800 switch series	- HP 3800-24G-PoE+-2SFP+ Switch¹ - HP 3800-48G-PoE+-4SFP+ Switch¹ - HP 3800-24G-2SFP+ Switch¹ - HP 3800-48G-4SFP+ Switch¹ - HP 3800-24SFP-2SFP+ Switch¹ - HP 3800-24G-2XG Switch¹ - HP 3800-48G-4XG Switch¹ - HP 3800-24G-PoE+-2XG Switch¹ - HP 3800-48G-PoE+-4XG Switch¹	- J9573A - J9574A - J9575A - J9576A - J9584A - J9585A - J9586A - J9587A - J9588A
4200 vl switch series	- HP 4204 vl Switch Chassis - ProCurve Switch 4202 vl-48G - ProCurve Switch 4202 vl-72 - HP 4202-72 vl Switch - HP 4208 vl Switch Chassis - ProCurve Switch 4208 vl-64G - ProCurve Switch 4208 vl-96 - HP 4208-96 vl Switch - HP 4208-68G-4SFP vl Switch - HP 4204-44G-4SFP vl Switch	- J8770A - J8771A - J8772A - J8772B - J8773A - J8774A - J8775A - J8775B - J9030A - J9064A
5300xl switch series	- HP ProCurve 5308xl Switch - HP ProCurve 5304xl Switch - HP ProCurve 5304xl Switch - HP ProCurve 5348xl Switch - HP ProCurve 5348xl Switch - HP ProCurve 5372xl Switch - HP ProCurve 5372xl Switch - HP ProCurve 5308xl Switch	- J8167A - J8166A - J4850A - J4849B - J4849A - J4848B - J4848A - J4819A

¹ These networking switches have switch stacking capabilities that are currently not supported with HP Insight RS. HP Insight RS 7.1 only supports standalone mode for these switches.

Table 17. Supported HP ProVision-based Switches

	Product description	HP Product Number
5400 switch series	• HP 5406 8p 10GBASE-T 8p 10GbE SFP+ v2 zl Switch with Premium Software	• J9866A
	• HP 5406 zl Switch with Premium Software	• J9642A
	• HP 5406-44G-PoE+-4G-SFP v2 zl Switch with Premium Software	• J9539A
	• HP 5406-44G-PoE+-2XG v2 zl Switch with Premium Software	• J9533A
	• HP 5406-48G zl Switch	• J8699A
	• HP 5406-44G-PoE+-4SFP zl Switch	• J9447A
	• HP E5406 zl Switch Chassis	• J8697A
	• HP 5412-92G-PoE+-4SFP zl Switch	• J9448A
	• HP 5412-92G-PoE+-2XG v2 zl Switch with Premium Software	• J9532A
	• HP 5412-92G-PoE+-4G v2 zl Switch with Premium Software	• J9540A
	• HP 5412 zl Switch with Premium Software	• J9643A
	• HP 5412-96G zl Switch	• J8700A
	• HP E5412 zl Switch Chassis	• J8698A
6108 switch series	• HP ProCurve 6108 Switch	• J4902A
6120 switch series	• HP ProCurve 6120G/XG Blade Switch	• 498358-B21
	• HP ProCurve 6120XG Blade Switch	• 516733-B21
6200 switch series	• HP 6200-24G-mGBIC yl Switch	• J8992A
6400 cl switch series	• HP 6400-6XG cl Switch	• J8433A
	• HP 6410-6XG cl Switch	• J8474A
6600 switch series	• HP E6600-24G Switch	• J9263A
	• HP 6600-24G-4XG Switch	• J9264A
	• HP 6600-24XG Switch	• J9265A
	• HP E6600-24G Switch	• J9263A
	• HP 6600-24G-4XG Switch	• J9264A
	• HP 6600-24XG Switch	• J9265A
	• HP E6600-48G Switch	• J9451A
	• HP 6600-48G-4XG Switch	• J9452A
8200 switch series	• HP 8206 zl Switch with Premium Software	• J9640A
	• HP 8206-44G-PoE+-2XG v2 zl Switch with Premium Software	• J9638A
	• HP E8206 zl Switch Base System	• J9475A
	• ProCurve Switch 8212zl Base System	• J8715A
	• HP E8212 zl Switch Base System	• J8715B
	• ProCurve Switch 8212zl Chassis&Fan Tray	• J9091A
	• HP 8212-92G-PoE+-2XG v2 zl Switch with Premium Software	• J9639A
	• HP 8212 zl Switch with Premium Software	• J9641A

HP ComWare-based Switches (formerly A-Series or H3C/3Com)

HP ComWare-based (formerly known as A-Series or H3C/3Com) networking switches require **SNMP** for discovery and remote monitoring. Ensure that public community credentials are configured for these devices to communicate with the Hosting Device.

For configuration collections, please ensure that either **TELNET** or **SSH** service is enabled. TELNET is enabled on HP ComWare-based Switches by default. If you prefer to use SSH, you will need to enable it. For instructions, see the *HP Insight Remote Support Monitored Devices Configuration Guide* available at www.hp.com/go/insightremotesupport/docs.

Insight RS 7.1 supports Intelligent Resilient Framework (IRF) technology, and can detect the following IRF alerts:

- Power supply failures
- Fans and fan tray failures
- Module and board failures
- Over-temperature conditions

For setup instructions, see the *HP Insight Remote Support Monitored Devices Configuration Guide* at www.hp.com/go/insightremotesupport/docs.

Table 18. Supported HP ComWare-based Switches

	Product description	HP Product Number
3100 v2 switch series¹	• HP 3100-24-PoE v2 EI Switch • HP 3100-8 v2 EI Switch • HP 3100-16 v2 EI Switch • HP 3100-24 v2 EI Switch • HP 3100-8 v2 SI Switch • HP 3100-16 v2 SI Switch • HP 3100-24 v2 SI Switch	• JD313B • JD318B • JD319B • JD320B • JG221A • JG222A • JG223A
3600 v2 switch series¹	• HP 3600-24 v2 EI Switch • HP 3600-48 v2 EI Switch • HP 3600-24-PoE+ v2 EI Switch • HP 3600-48-PoE+ v2 EI Switch • HP 3600-24-SFP v2 EI Switch • HP 3600-24 v2 SI Switch • HP 3600-48 v2 SI Switch • HP 3600-24-PoE+ v2 SI Switch • HP 3600-48-PoE+ v2 SI Switch	• JG299A • JG300A • JG301A • JG302A • JG303A • JG304A • JG305A • JG306A • JG307A
5120 EI switch series	• HP 5120-24G EI TAA-compliant Switch with 2 Interface Slots • HP 5120-24G-PoE+ EI Switch with 2 Interface Slots • HP 5120-24G-PoE+ EI TAA-compliant Switch with 2 Slots • HP 5120-48G EI TAA-compliant Switch with 2 Interface Slots • HP 5120-48G-PoE+ EI Switch with 2 Interface Slots • HP 5120-48G-PoE+ EI TAA-compliant Switch with 2 Slot • HP A5120-24G EI Switch • HP A5120-24G EI Switch with 2 Interface Slots • HP A5120-48G EI Switch • HP A5120-48G EI Switch with 2 Interface Slots • HP A5120-24G-PoE EI 2-slot Switch • HP A5120-48G-PoE EI 2-slot Switch	• JG245A • JG236A • JG247A • JG246A • JG237A • JG248A • JE066A • JE068A • JE067A • JE069A • JE070A • JE071A

¹ These switches are only supported on Comware software version 5.x.

Table 18. Supported HP ComWare-based Switches

	Product description	HP Product Number
5120 SI switch series	- HP 5120-16G SI Switch - HP 5120-48G SI Switch - HP 5120-24G SI Switch - HP 5120-24G-PoE+ (370W) SI Switch - HP 5120-24G-PoE+ (170W) SI Switch	- JE072A - JE073A - JE074A - JG091A - JG092A
5500 EI switch series	- HP 5500-24G DC EI Switch - HP 5500-24G EI Switch - HP 5500-24G EI TAA-compliant Switch with 2 Interface Slots - HP 5500-24G-PoE EI Switch - HP 5500-24G-PoE+ EI Switch with 2 Interface Slots - HP 5500-24G-PoE+ EI TAA-compliant Switch with 2 Interface Slots - HP 5500-24G-SFP EI Switch - HP 5500-24G-SFP EI TAA-compliant Switch with 2 Interface Slots - HP 5500-48G EI Switch - HP 5500-48G EI TAA-compliant Switch with 2 Interface Slots - HP 5500-48G-PoE+ EI Switch with 2 Interface Slots - HP 5500-48G-PoE+ EI TAA-compliant Switch with 2 Interface Slots - HP 5500-24G-SFP DC EI Switch - HP 5500-48G-PoE EI Switch - HP 5500-24G SI Switch - HP 5500-48G SI Switch - HP 5500-24G-PoE SI Switch - HP 5500-48G-PoE SI Switch - HP 5500-24G-PoE+ SI Switch with 2 Interface Slots - HP 5500-48G-PoE+ SI Switch with 2 Interface Slots	- JD373A - JD377A - JG250A - JD378A - JG241A - JG252A - JD374A - JG249A - JD375A - JG251A - JG240A - JG253A - JD379A - JD376A - JD369A - JD370A - JD371A - JD372A - JG238A - JG239A
5500 HI switch series	- HP 5500-24G-4SFP HI Switch with 2 Interface Slots - HP 5500-48G-4SFP HI Switch with 2 Interface Slots	- JG311A - JG312A
5800 switch series	- HP 5800-24G Switch - HP 5800-24G TAA-compliant Switch - HP 5800-24G-PoE Switch - HP 5800-24G-PoE+ TAA-compliant Switch - HP 5800-24G-SFP Switch - HP 5800-24G-SFP TAA-compliant Switch with 1 Interface Slot - HP 5800-48G Switch - HP 5800-48G Switch with 2 Slots - HP 5800-48G TAA-compliant Switch with 1 Interface Slot - HP 5800-48G-PoE Switch - HP 5800-48G-PoE+ TAA-compliant Switch with 1 Interface Slot - HP 5800-48G-PoE+ TAA-compliant Switch with 2 Interface Slots - HP 5800AF-48G Switch	- JC100A - JG255A - JC099A - JG254A - JC103A - JG256A - JC105A - JC101A - JG258A - JC104A - JG257A - JG242A - JG225A
5820 switch series¹	- HP 5820-24XG-SFP+ Switch - HP 5820-14XG-SFP+ Switch with 2 Slots - HP 5820AF-24XG Switch - HP 5820-24XG-SFP+ TAA-compliant Switch - HP 5820X-14XG-SFP+ TAA Switch w 2 Slots	- JC102A - JC106A - JG219A - JG243A - JG259A

¹ These switches are only supported on Comware software version 5.x.

Table 18. Supported HP ComWare-based Switches

	Product description	HP Product Number
5830 switch series¹	- HP A5830AF-48G Switch w/1 Interface Slot - HP A5830AF-96G Switch - HP 5830AF-48G TAA Switch w/1 Intf Slot - HP 5830AF-96G TAA Switch	- JC691A - JC694A - JG316A - JG374A
5900 AF switch series²	- HP 5900AF-48XG-4QSFP+ Switch - HP 5900AF-48XGT-4QSFP+ Switch - HP 5900AF-48G-4XG-2QSFP+ Switch - HP 5900AF-48XG-4QSFP+ TAA Switch	- JC772A - JG336A - JG510A - JG554A
5920 AF switch series²	- HP 5920AF-24XG TAA-compliant Switch - HP 5920AF-24XG Switch	- JG555A - JG296A
7500 switch series	- HP 7502 Switch Chassis - HP 7503 Switch Chassis - HP 7503 Switch Chassis with 1 Fabric Slot - HP 7506 Switch Chassis - HP 7506 Vertical Switch Chassis - HP 7510 Switch Chassis - HP 7502 Switch Chassis - HP 7503 Switch Chassis	- JD242B - JD240B - JD243B - JD239B - JD241B - JD238B - JD242A - JD240A
7500 switch series (continued)	- HP 7503 Switch Chassis with 1 Fabric Slot - HP 7506 Switch Chassis - HP 7506 Vertical Switch Chassis - HP 7510 Switch Chassis	- JD243A - JD239A - JD241A - JD238A
10500 switch series¹	- HP 10504 Switch Chassis - HP 10508 Switch Chassis - HP 10508-V Switch Chassis - HP 10512 Switch Chassis	- JC613A - JC612A - JC611A - JC748A
12500 switch series¹	- HP 12508 DC Switch Chassis - HP 12508 Switch Chassis - HP 12508 Switch Chassis - HP 12518 DC Switch Chassis - HP 12518 Switch Chassis - HP 12518 Switch Chassis - HP 12508 Switch Chassis - HP 12508 Switch Chassis - HP 12518 Switch Chassis - HP 12518 Switch Chassis - HP 12504 AC Switch Chassis - HP 12504 DC Switch Chassis	- JC652A - JF431B - JF431C - JC653A - JF430B - JF430C - JC086A - JF431A - JC085A - JF430A - JC654A - JC655A

¹ These switches are only supported on Comware software version 5.x.² These switches are only supported on Comware software version 7.x.

HP Solutions

Insight RS does not recognize HP solutions, but can monitor the components of Solutions. Solution components can be organized as solutions within the Insight RS Console. Details about how to create, modify or delete a Solution are available in the Online Help.

Insight RS provides component support for the following HP Solutions:

- HP CS300 for Microsoft Analytics Platform (previously called HP AppSystem for Microsoft SQL Server 2012 Parallel Data Warehouse)
- HP AppSystems for SAP HANA
 - HANA Scale Out 1.2
 - HANA Scale Out 1.1
 - Business Suite on HANA – 2TB and 4TB
 - Virtual HANA (Single Node Large with Virtualization)
- HP ConvergedSystem CS500 for SAP HANA
 - CS500 for SAP HANA Single Node (or Scale Up)
 - CS500 for SAP HANA Scale Out
- HP CloudSystem Matrix 7.x
- HP CloudSystem 8.0
- HP ConvergedSystems for Vertica
 - CS300 for Vertica
- HP ConvergedSystems for Virtualization
 - CS300 for Virtualization
- HP E5000 Messaging Systems
 - HP E5000 G1
 - HP E5000 G2

For more information about solution support and solution component support, see the *HP Insight Remote Support Solution Support FAQ* document at:

http://h20564.www2.hp.com/portal/site/hpsc/public/kb/docDisplay?docId=emr_na-c03911757.

Rack and Power

HP Modular Cooling System

Modular Cooling Systems are monitored through the management module that is installed on the Modular Cooling System. Insight Remote Support automatically detects management modules as part of the device discovery process. The management module should be installed and running before attempting discovery, and **SNMP** must be configured on the Modular Cooling System so that Insight Remote Support can communicate with it.

HP Insight Remote Support 7.1 provides recommended service actions and automated event submission to HP for the following failures:

- IIC Communications Failure
- Condensation Pump Threshold Exceeded
- Fan Failures
- Water Unit Input/Output Temp Sensor Failure
- Water Valve Failure
- Water flow Sensor Failure
- Fan Temp Sensor Failures
- Heat Exchanger Sensor Failures

Note

Configuration collections are **not** supported.

HP Rack-mountable and Tower Uninterruptible Power Systems

The Uninterruptible Power Systems (UPS) Management Module and UPS Network Module are options in several HP Rack-Mountable and Tower UPS units. When the option card is present, support is provided for the following devices:

Current HP Uninterruptible Power Systems	Legacy HP Uninterruptible Power Systems
R1500 G3	T1000xr
R/T3000 G2	T1500xr
R5000	T2200xr
R7000	R1500xr
R8000/3	R1500 G2
R12000/3	R3000xr
RP36000/3	R3000
	R/T3000
	R5550xr
	R5500
	R12000xr

SNMP needs to be configured on the UPS Management Module to send traps to the Hosting Device. For setup instructions, see the HP UPS Management Module User Guide located at www.hp.com/go/rackandpower.

Recommended service actions and automated event submission to HP are provided for whole unit, battery, and ERM (Extended Runtime Module) failures.

Note

Configuration collections are **not** supported for HP Rack-Mountable and Tower UPS units.

For additional details, please see the support matrix at: http://h18004.www1.hp.com/cpq-products/servers/proliantstorage/power-protection/software/module/ups/sup_oss.html.

Management Platform Integration

HP Systems Insight Manager

HP Insight Remote Support 7.1 offers the ability to synchronize service incidents with HP Systems Insight Manager (HP SIM) 7.2 or 7.3. This is enabled by configuring this option in the **Integration Adapters** menu.

This option only supports HP SIM being installed on the **same** Hosting Device. If HP SIM is installed on the Hosting Device before installing HP Insight Remote Support, then the HP SIM Adapter is automatically installed. If HP SIM was installed after installing HP Insight Remote Support, then the HP SIM Adapter needs to be manually installed. For details, see the *HP Insight Remote Support Installation and Configuration Guide* at www.hp.com/go/insightremotesupport/docs.

Important

HP SIM and Insight RS support different versions of the Microsoft Windows operating system. If you intend to synchronize Insight RS with HP SIM, make sure the Hosting Device operating system is supported by both HP SIM and Insight RS. For HP SIM operating system support, see the *HP Insight Management Support Matrix* at <http://www.hp.com/go/insightmanagement/docs>.

Whenever there is a change in the status of a service incident, the new incident status is also updated in HP SIM. The most important incident status changes are the creation and assignment of a case (ticket) in HP's service workflow and the closure of the incident once it is completed.

When a case is opened at HP, the case ID is appended to the HP SIM event. This means that customer's IT support personnel can provide the case ID whenever they want to communicate with HP.

When configuring this option, you will be able to specify various synchronization options that will allow changes made in HP SIM to be automatically reflected in HP Insight Remote Support. For details, please see the *HP Insight Remote Support 7.1 Installation and Configuration Guide* at www.hp.com/go/insightremotesupport/docs.

HP strongly advises that customers always upgrade to the latest supported HP SIM version and its components. See [Table 19](#) for supported HP SIM versions:

Table 19. Insight RS 7.1 and SIM Compatibility Support Matrix

HP SIM release version	HP SIM version supported with Insight RS 7.1?	HP SIM end of support date
7.3.2 ¹	Y	Active
7.3.1 ¹	Y	Active
7.3 ¹	Y	Active
7.2.2 ¹	Y	Active (02/28/2015)
7.2 ¹	Y	Active (08/31/2014)
7.1 and older	N	Not supported

¹ HP always recommends installing the latest HotFix. See h18013.www1.hp.com/products/servers/management/hpsim/download.html for details.

For reference, see the HP SIM Support Matrix summarizing the different HP SIM release versions with the corresponding release and end of support date: <http://h18013.www1.hp.com/products/servers/management/hpsim/supportmatrix.html>

HP SNMP Service Event Adapter

The SNMP Service Event Adapter provides the ability to forward an SNMP trap to another management application or ticketing system when an event has been sent to HP for intervention. It contains the same information as displayed in the user interface but may need formatting to be readable in the receiving application.

Note

Insight Remote Support sends the SNMP trap in the SNMP MIB Type 3 format.

HP Operations Manager

Incident synchronization is currently only available in this version for HP Operations Manager using the HP SNMP Service Event Adapter, described above. Customers can alternatively install HP Insight Remote Support Advanced to obtain a full integration service.

HP SAP Solution Manager

Incident synchronization is currently only available in this version for SAP Solution Manager using the HP SNMP Service Event Adapter, described above. Customers can alternatively install HP Insight Remote Support Advanced to obtain a full integration service.

HP Insight Online integration

HP Insight Online is an addition to the HP Support Center portal for one stop, secure access to product and HP support information personalized to your IT environment. It is available at no additional cost as part of your warranty, HP Care Pack Service, or contractual support agreement with HP.

You can configure automatic integration into the HP Insight Online portal when installing HP Insight Remote Support or subsequently, by entering your HP Passport ID and password. On login into HP Support Center, within the *My IT Environment* view, you will automatically see all devices that are registered with HP Insight Remote Support 7.x.

If all HP Insight Remote Support registered devices do not appear automatically in HP Insight Online, it may be possible that the device was already registered to another person in your company. To see this device in your view, you need them to share or transfer ownership to yourself. For details and prerequisites, please see the *Getting Started with HP Insight Online Guide* at www.hp.com/go/insightremotesupport/docs for details.

Important

When you disable your connection to Insight Online or change to a different HP Passport account, the change takes time to be reflected in Insight Online. Wait until all of your devices have been removed from your current Insight Online account before connecting to a new account.

Issues and suggested actions

Microsoft Internet Explorer window may hang or display black screen

When using the 64-bit version of Internet Explorer 8.x, rapid selections of the main menu drop-down list can cause the user interface to hang and display a black screen. If you encounter this behavior, HP recommends using the 32-bit version of Internet Explorer 8.x or using Internet Explorer 9.x.

HP ProLiant Gen8 servers are displayed by their serial number

The HP ProLiant Gen8 server device name may be displayed as a serial number (indicated by an S/N prefix) in the Insight RS Console in the *System Name* column. This will happen if remote support for the server is enabled while the server's operating system is not running or the Agentless Management Service (AMS) is not installed and enabled. To enable the IP address to be displayed instead of the serial number, the following steps can be taken:

- Before registering for Insight Remote Support via the iLO 4, or before initiating the discovery of the HP ProLiant Gen8 server's iLO 4 from the Insight RS console:
 - Ensure that the minimum supported firmware version (1.10 or later) is installed to register Insight RS through the iLO 4
 - Ensure that the Agentless Management Service (AMS) is enabled, and the operating system is running
 - Ensure that the Remote Insight Board Common Language Protocol (RIBCL) credentials for the server are entered in the Insight RS Console
- If you have already successfully registered or discovered the HP ProLiant Gen8 server in Insight RS:
 - Ensure that the Agentless Management Service (AMS) is enabled, and the operating system is running
 - Ensure that the Remote Insight Board Common Language Protocol (RIBCL) credentials for the server are entered in the Insight RS Console
- Click on the serial number in the System Name column and then choose Discover Device. The re-discovery of the device will result in the IP address being displayed.

HP Authorized Channel Partner default settings may not be retained

The default HP Authorized Channel Partner *Provider ID*, if entered in the Hosting Device Setup Wizard, may not be retained in this version. When the installation is completed, please check in the Main Menu, select **Company Information** -> **Channel Partner** tab and re-set the information if it has not been retained. For details, please see the *HP Insight Remote Support Installation and Configuration Guide* at www.hp.com/go/insightremotesupport/docs.

How to unregister a Gen8 server from Insight RS

If you wish to no longer temporarily monitor your HP ProLiant Gen8 server, you should clear the **Enabled** check box from the **Device Summary** tab within the **Devices** section of the HP Insight RS Console. If you wish to no longer permanently monitor your HP ProLiant Gen8 server, you should delete the device from the Insight RS Console by selecting the device from the **Device Summary** view and then choose the **Delete Device** button from the **Device** tab.

Unregistering your server directly from the iLO4 will also stop monitoring and collections but it will not be reflected correctly in the Insight RS Console and hence is not recommended.

Service events display an incorrect timestamp in the Insight RS Console

When viewing events and collections in the HP Insight RS Console using a web browser, then any time displayed will convert to the time zone set in that browser. This is to ensure that the user can see the event timing using their local time zone. If there are discrepancies between the event time and the event processed time, then you should check the time and time zone setting on the monitored device. If this is being set externally from a time server or via DHCP, please ensure that these are correctly connected and set to the appropriate time. Note, even if this issue is seen, it will not affect the efficient delivery of service by HP or an HP Authorized Service Partner as the Hosting Device time is used as a reference for service delivery.

A device appears without a discovery taking place

If a customer configures an SNMP diagnostic agent on a monitored device with the trap destination set to the Insight RS Hosting Device, it is assumed that the intention is to have this device monitored. Hence, if this device sends an SNMP trap to the Hosting Device, it will automatically initiate a discovery.

Note, that default credentials are applied and you should check to make sure that event monitoring and configuration collections are working correctly for this device.

Another way that a device can be discovered without Hosting Device initiation is if a customer registers an HP ProLiant Gen8 server for remote monitoring through its iLO 4 registration process.

Duplicate records created in Insight Online when the same device is discovered twice

Two records can be created in HP Insight Online for a device in the following scenarios:

- Scenario 1: A device is partially discovered by Insight RS, detecting OS and network information, but no serial number or product number information. When discovered again, full information is discovered.
- Scenario 2: A device has SNMP trap forwarding set to the Hosting Device and the device was not discovered by Insight RS prior to receiving the event.

Suggested action: Duplicate records cannot be removed at this time.

Unexpected device discovery

A larger group of devices can be discovered in the following situations:

- When discovery settings are setup, a larger range of devices specified than expected.
- When Insight RS 7.1 is installed on a server that uses the same IP address as the previous server Insight RS was installed on. This happens when monitored devices in the IT environment still have the SNMP trap destination or WMI/WBEM subscription in place that sends events to that IP address. When these events are sent, this will trigger a discovery and that device will appear in the Insight RS Console.

Suggested action: Delete or disable the devices that you don't want Insight RS to monitor.

Multiple location ID and partner configured

In a small percentage of cases, HP can store more than one partner location ID for the same partner user in our backend system.

In most cases, if you are a partner user, you can determine your partner location ID by logging in to the HP Global Partner portal. The location ID you see in the top left hand corner of the screen is your location ID. If after installing Insight Remote

Support using this location ID you are not able to see the My Customer tab in Insight Online, then HP Support can help you determine the correct location ID to use.

Suggested action: Contact HP Support to determine which partner location ID is active in Insight Online/Insight RS. Case information will be sent to the service provider listed in Insight RS for the customer. The HPSC Insight Online My Customer system will display the correct data for the partner if the partner uses the login verified by HP Support.

Unhealthy Monitoring & Collections even when protocols are setup correctly

When Insight RS 7.1 is configured to work with HP SIM, Insight RS detects all of the monitored device protocols that HP SIM has detected. An issue can occur when these protocols are not installed or configured correctly on the device or the protocols are not valid for use with Insight RS. In these cases, Insight RS displays a failed or unhealthy status in the Monitoring & Collections section of the Insight RS Console, even though the protocols are not being used by Insight RS.

Suggested action: To work around this issue, do not select the **Automatically sync new/deleted credentials from HP SIM** check box in the HP SIM Adapter.

Cannot log on to the Insight RS Console as an Administrator

You are using a domain user account and this account is a member of a domain group which in turn is a member of the domain Administrators group. Additionally, User Account Control (UAC) is turned on. For example:

- You cannot log on to the Insight RS Console with user MYDOMAIN\myusername and,
- MYDOMAIN\myusername is a member of the group MYDOMAIN\specialusers.
- MYDOMAIN\specialusers has been added to the MYDOMAIN\Administrators group.
- User Account Control (UAC) is turned on.

Suggested action: To work around this issue, any of the following actions enable you to log on as an Administrator:

- Turn off User Account Control (UAC) on the Hosting Device
- Add your user account to a local Administrators group on the Hosting Device. For example, add MYDOMAIN\myusername to the local HostingDevice\Administrators group
- Add your user account directly to the domain Administrators group. For example, add MYDOMAIN\myusername to the MYDOMAIN\Administrators group directly.
- Create a new local Administrators account and use that to log on to the Hosting Device. For example, create an Administrative account named HostingDevice\AdminAccount and log on with that.

Sign up to receive Insight Remote Support communications

The HP Insight Remote Support product team uses HP's Support Communication process to communicate important news such as Engineering Advisories, Customer Advisories, Engineering Notices, and Customer Notices.

To sign up to receive Support Communications using HP Subscribers Choice, go to:
<https://h30046.www3.hp.com/SubChoice/country/us/en/signin.aspx>.

When you subscribe, search for *Insight Remote Support*.

We appreciate your feedback

If you have comments about this document, you can [contact the documentation team](#) by email. If an email client is configured on this system, click the link above and an email window opens with the following information in the subject line:

Feedback on Insight Remote Support, 7.1 Release Notes

Just add your feedback to the email and click send.

If no email client is available, copy the information above to a new message in a web mail client, and send your feedback to techdocs_feedback@hp.com

Appendix A – Updating existing Insight RS installations

Upgrading from version 5.x

HP Insight Remote Support 7.1 replaces all of the capabilities and product coverage found in HP Insight Remote Support Standard (RSS). Additionally, Insight RS 7.1 can also be used as an alternative to Insight Remote Support Advanced (RSA) with the exceptions listed in [Table 20](#) below. These exceptions include:

- Monitoring specific Insight RSA devices
- Requiring the integration with SAP Solution Manager/HP Operations Manager
- Using Insight RSA with Mission Critical Partnership or Proactive 24 contracts
- Customers with Proactive Care Service are advised that HP Insight Remote Support 7.x is the preferred version.

Existing Insight RSA version 5.80 customers will **not** be automatically upgraded to Insight RS 7.1 at the time of release. If you wish to upgrade, this can be achieved by downloading the Insight Remote Support 7.1 software package from [HP Software Depot](#) and following the installation procedure. The installation process will assist you in this upgrade.

When upgrading to Insight Remote Support 7.1 and you are also upgrading HP SIM to version 7.2 or 7.3, make sure you install or upgrade to HP SIM 7.2 or 7.3 before you upgrade Insight Remote Support to 7.1. If you do not install a supported version of SIM first, the SIM Adapter will be uninstalled as part of the upgrade, and you will need to install and enable the SIM Adapter after installing a supported version of SIM.

Note

Customers using a version of HP Insight Remote Support prior to 5.60 cannot directly upgrade. For details, please see the upgrade instructions provided in the *HP Insight Remote Support Upgrade Guide* available at www.hp.com/go/insightremotesupport/docs.

Table 20. Insight RS 5.x functionality **not** available in Insight RS 7.1

Hosting Device	• All Microsoft Windows 2003 operating system versions. Note, this will not be supported on any Insight RS 7.x versions.
Product coverage for monitored devices	• HP Superdome SD-A and SD-B (Insight RSA only) • P9000/HP XP Disk Arrays (Insight RSA only) • HP Enterprise Secure Key Manager (Insight RSA only) • HP Secure Key Manager (Insight RSA only) • HP NonStop servers (Insight RSA only) • IBM AIX servers (Insight RSA only) • Sun Solaris servers (Insight RSA only)
Mission Critical Service Delivery (Insight RSA only)	Capabilities to deliver mission critical services such as • Revision and configuration management for HP-UX • Assessments including patch, firmware, configuration analysis for HP-UX • HP-UX System Health Check assessments • Availability analysis for HP-UX • TAM-S and CCMon Services • Unreachable Device Notification
Products that will not be supported by any 7.x version	• HP Dynamic Smart Cooling • HP SAN Virtualization Services Platform • HP Modular Array • HP Enterprise Modular Array • HP Raid Array • HP Enterprise Storage Array • M-series Switches (McData)

Port adjustments needed

TCP/IP port **7905** needs to be opened for Insight RS 7.x to communicate with monitored devices that use WBEM/WMI.

Insight RSS and RSA use TCP/IP port 7906 to communicate from the monitored devices to the Hosting Device/Central Management Server. Insight RS 7.x now uses port 7906 for the Insight RS Console and when using the Onboard Administrator and HP ProLiant Gen8 iLO 4 embedded Insight Remote Support capabilities.

Insight RS 7.x uses port 7905 to communicate with monitored devices that use WBEM/WMI, such as HP-UX, Linux and Windows servers. If you secured port 7905 when using Insight RSS or RSA, you must now make sure TCP/IP port 7905 is open on your monitored devices, the Hosting Device and any firewalls between the two. For more information about specific port settings, see the [*HP Insight RS Security White Paper*](#).

Upgrading from previous versions of 7.x

Upgrading by uninstalling a previous version of Insight RS 7.x and then installing the latest version is not a supported method to upgrade Insight RS. When the 7.x software is uninstalled, residual data is left behind in case the same version is going to be re-installed, and mismatches in this data can cause Insight RS to shut down some processes. Upgrade using one of the supported methods provided in the *HP Insight Remote Support Upgrade Guide* available at www.hp.com/go/insightremotesupport/docs.

Appendix B – Required Protocols and Components

Table 21 below describes what protocols and software components need to be installed and configured to enable remote monitoring, basic configuration collections or SAN configuration collections for the devices monitored by Insight Remote Support.

Important

If you have not configured the required protocols and software for your monitored devices and added the protocol within the Insight RS Console, Insight Remote Support will not be able to communicate with the device.

If you change the username/password that Insight RS uses to connect to your monitored devices, or if the credentials expire as part of your security policies, you must modify those corresponding credentials in the Insight RS Console to continue monitoring your monitored devices.

The required protocols and software are determined by your monitored device type. In some cases more than one protocol will be required. Some protocols may be used by the Insight RS Console to discover monitored devices while other protocols may be used to monitor hardware events or retrieve configuration collection information from the monitored devices. The following table highlights the requirements, but read the chapter for your monitored device type for more detail.

Note

HP Insight RS supports the secure SNMPv3 protocol when it is supported on the monitored device.

Table 21. Required Communication Protocols and Components for HP Insight Remote Support Services

Required protocols and components		Discovery	Monitoring	Basic Collections	SAN Collections	Notes
HP Servers						
ProLiant Gen8	Remote Insight Board Common Language (RIBCL) Protocol	✓	✓	✓		HP ProLiant Gen8 servers can be monitored using the embedded Remote Support functionality available through iLO 4 and Intelligent Provisioning or using a diagnostic agent installed on the operating system. Note , if you want to monitor attached devices you need to install the HP Service Pack for ProLiant as detailed in the ProLiant server section that corresponds to the operating system below. RIBCL credentials are required for all HP ProLiant Gen8 servers regardless if the embedded capabilities or the diagnostic agent are used. See the “Configuring ProLiant Gen8 Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .
Windows on ProLiant	Simple Network Management Protocol (SNMP)	✓	✓	✓		Must install the HP Service Pack for ProLiant and all providers that ship with it. Customer can choose to use either SNMP or WMI, however to gather SAN Collections for a ProLiant Windows server, you must use WMI. Insight RS requires Insight Management WBEM Providers version 2.8 or later, but HP recommends installing the most recent version available for your device.
	Windows Management Instrumentation (WMI)	✓	✓	✓	✓	See the “Configuring ProLiant Windows Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .
Linux on ProLiant	Simple Network Management Protocol (SNMP)	✓	✓	✓		Must install the HP Service Pack for ProLiant and all providers that ship with it. Customer can choose to use either Telnet or SSH to gather SAN Collections for a ProLiant Linux server.
	Telnet				✓	See the “Configuring ProLiant Linux Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .
	Secure Shell (SSH)				✓	
ESX on ProLiant	Simple Network Management Protocol (SNMP)	✓	✓	✓		See the “Configuring ProLiant VMware ESX Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .
	Secure Shell (SSH)				✓	
ESXi on ProLiant	Web-Based Enterprise Management (WBEM)	✓	✓	✓	✓	See the “Configuring ProLiant VMware ESXi Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .

Table 21. Required Communication Protocols and Components for HP Insight Remote Support Services (*continued*)

Required protocols and components		Discovery	Monitoring	Basic Collections	SAN Collections	Notes
HP Servers						
Citrix Xen Server on ProLiant	Simple Network Management Protocol (SNMP)	✓	✓	✓		See the “Configuring ProLiant Citrix Xen Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .
	Telnet				✓	Customer can choose to use either Telnet or SSH to gather SAN Collections for a ProLiant Citrix Xen server.
	Secure Shell (SSH)				✓	
Hyper-V on ProLiant	(See Note)					Configuration collections are not supported. Follow the configuration instructions for a ProLiant Windows server. See the “Configuring ProLiant Windows Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .
HP ProLiant Superdome Onboard Administrator (OA)	Web Services Management Protocol (WS-Man)	✓	✓	✓		The Linux partitions are monitored through the OA using WS-Man. Collections on the partitions also use WS-Man, but Insight RS communicates directly with the partition. See the “Configuring ProLiant Superdome Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .
Windows 2003 on Integrity	Windows Management Instrumentation (WMI)	✓	✓	✓	✓	Must install the Integrity Support Pack and all providers that ship with it. This includes the installation of SNMP and WMI.
	Simple Network Management Protocol (SNMP)	✓	✓	✓		See the “Configuring Integrity Windows 2003 Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .
	Event Log Monitoring Collector (ELMC)		✓			
Windows 2008 on Integrity	Windows Management Instrumentation (WMI)	✓	✓	✓	✓	Must install the HP Integrity Support Pack and all providers that ship with it. See the “Configuring Integrity Windows 2008 Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .
Linux on Integrity	Web-Based Enterprise Management (WBEM)	✓	✓			Configuration collections are not supported, except when the server is part of a SAN collection. Customer can choose to use either Telnet or SSH to gather SAN collections for an Integrity Linux server. See the “Configuring Integrity Linux Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .
	Telnet				✓	
	Secure Shell (SSH)				✓	
HP-UX on Integrity	Web-Based Enterprise Management (WBEM)	✓	✓	✓		Install the proper WBEM providers on HP-UX. These generally are part of the feature set of HP-UX and will update through patches and software updates on the device as appropriate.
	Telnet				✓	Customer can choose to use either Telnet or SSH to gather SAN collections for an Integrity HP-UX server.
	Secure Shell (SSH)				✓	See the “Configuring Integrity HP-UX Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .
HP Integrity Superdome 2 Onboard Administrator (OA)	Web Services Management Protocol (WS-Man)	✓	✓			Discovery uses WS-Man and collections use HTTPS. The OA is monitored using WS-Man, but the Superdome 2 partitions are monitored using WBEM.
	HTTPS			✓		See the “Configuring Integrity Superdome 2 Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .
OpenVMS on Integrity	Web-Based Enterprise Management (WBEM)	✓	✓	✓	✓	Must install the OpenVMS WBEM provider. Configuration collections and discovery only works when the WBEM providers are installed and the credentials are properly configured.
	Event Log Monitoring Collector (ELMC)		✓			See the “Configuring OpenVMS Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .

Table 21. Required Communication Protocols and Components for HP Insight Remote Support Services (*continued*)

Required protocols and components		Discovery	Monitoring	Basic Collections	SAN Collections	Notes
HP Servers						
OpenVMS on AlphaServer	Simple Network Management Protocol (SNMP)	✓	✓			Configuration collections are not supported, except when the OpenVMS server is part of a SAN collection.
	Event Log Monitoring Collector (ELMC)		✓			See the HP AlphaServer systems section for information about support for this platform.
	Telnet				✓	See the “Configuring OpenVMS Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .
Tru64 UNIX on AlphaServer	Simple Network Management Protocol (SNMP)	✓	✓			Configuration collections are not supported, except when the Tru64 server is part of a SAN collection.
	Event Log Monitoring Collector (ELMC)		✓			Customer can choose to use either Telnet or SSH to gather SAN Collections for a Tru64 UNIX server.
	Telnet				✓	See the HP AlphaServer systems section for information about support for this platform.
	Secure Shell (SSH)				✓	See the “Configuring Tru64 UNIX Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .
E5000 Messaging Systems	Simple Network Management Protocol (SNMP)	✓	✓	✓		These devices should be configured the same as a Windows ProLiant server.
	Windows Management Instrumentation (WMI)	✓	✓	✓	✓	Customer can choose to use SNMP or WMI, however to gather SAN Collections, you must use WMI. Configuration collections for the chassis connector use HTTP.
	Hypertext Transfer Protocol (http)			✓		See the “Configuring ProLiant Windows Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .
Multivendor Servers						
Windows on IBM Servers	Simple Network Management Protocol (SNMP)	✓	✓			Configuration collections are not supported. See the “Configuring IBM Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .
Windows on Dell PowerEdge	Simple Network Management Protocol (SNMP)	✓	✓			Configuration collections are not supported. See the “Configuring Dell PowerEdge Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .
HP BladeSystems						
HP Onboard Administrator for c-class Enclosures	Simple Network Management Protocol (SNMP)	✓	✓			HP BladeSystem c-Class Enclosures can be monitored using the embedded management capabilities in the HP Onboard Administrator (OA) or by configuring SNMP in the OA.
	Hypertext Transfer Protocol Secure (https)			✓		See the “Configuring c-Class BladeSystem Enclosures” chapter in the <i>Monitored Devices Configuration Guide</i> .
HP ProLiant BladeSystem Servers	(See Notes)					Supported ProLiant BladeSystem servers are monitored independent of the c-Class Enclosure in which they are installed. ProLiant BladeSystem servers can be configured using the instructions for ProLiant servers. For configuration details, see the ProLiant server section that corresponds to the operating system installed on the ProLiant BladeSystem server.
HP Integrity BladeSystem Servers	(See Notes)					Supported Integrity BladeSystem servers are monitored independent of the c-Class Enclosure in which they are installed. Integrity BladeSystem servers can be configured using the instructions for Integrity servers. For configuration details, see the Integrity server section that corresponds to the operating system installed on the Integrity BladeSystem server.

Table 21. Required Communication Protocols and Components for HP Insight Remote Support Services (*continued*)

Required protocols and components		Discovery	Monitoring	Basic Collections	SAN Collections	Notes
HP BladeSystems						
Storage Blades	(See Notes)					Configuration collections are not supported. Storage Blades are monitored through the Storage Agents installed on the partner server blade. The partner server blade is the adjacent server blade connected directly to the storage blade.
Tape Blades	(See Notes)					Configuration collections are not supported. Tape Blades are monitored through the Storage Agents installed on the partner server blade. The partner server blade is the adjacent server blade connected directly to the tape blade.
HP Disk Arrays						
P6000 Enterprise Virtual Arrays SBM	HP P6000 Command View	✓	✓	✓	✓	See the “Configuring P6000 Enterprise Virtual Arrays using Server Based Management” chapter in the <i>Monitored Devices Configuration Guide</i> .
	Event Log Monitoring Collector (ELMC)		✓			
P6000 Enterprise Virtual Arrays ABM	HP P6000 Command View	✓	✓	✓	✓	See the “Configuring P6000 Enterprise Virtual Arrays using Array Based Management” chapter in the <i>Monitored Devices Configuration Guide</i> .
HP StoreVirtual 4xxx (formerly P4000 SAN Solutions/ LeftHand Storage)	Simple Network Management Protocol (SNMP)	✓	✓			See the “Configuring StoreVirtual P4000 Storage Systems” chapter in the <i>Monitored Devices Configuration Guide</i> .
	HP LeftHand OS (SAN/IQ)		✓	✓	✓	
HP MSA 2040	Simple Network Management Protocol (SNMP)	✓	✓			Both SNMP and WBEM must be installed and configured. See the “Configuring P2000 and Modular Smart Arrays” chapter in the <i>Monitored Devices Configuration Guide</i> .
	Web-Based Enterprise Management (WBEM)	✓	✓	✓	✓	
HP P2000 G3 MSA	Simple Network Management Protocol (SNMP)	✓	✓			Both SNMP and WBEM must be installed and configured. See the “Configuring P2000 and Modular Smart Arrays” chapter in the <i>Monitored Devices Configuration Guide</i> .
	Web-Based Enterprise Management (WBEM)	✓	✓	✓	✓	
HP MSA23xx G2	Simple Network Management Protocol (SNMP)	✓	✓			Install the WBEM SMI-S Proxy Provider on the host server and not the MSA itself. See the “Configuring P2000 and Modular Smart Arrays” chapter in the <i>Monitored Devices Configuration Guide</i> .
	Web-Based Enterprise Management (WBEM)	✓		✓	✓	
HP MSA2xxx G1	Simple Network Management Protocol (SNMP)	✓	✓		✓	Configuration collections are not supported, except when the MSA2xxx G1 is part of a SAN collection. See the “Configuring P2000 and Modular Smart Arrays” chapter in the <i>Monitored Devices Configuration Guide</i> .
HP MSA 15xx	Simple Network Management Protocol (SNMP)	✓	✓	✓	✓	See the “Configuring P2000 and Modular Smart Arrays” chapter in the <i>Monitored Devices Configuration Guide</i> .
StoreEasy Commercial NAS	Windows Management Instrumentation (WMI)	✓	✓	✓	✓	See the “Configuring StoreEasy Storage Systems” chapter in the <i>Monitored Devices Configuration Guide</i> .
HP StoreAll Network Storage Systems (formerly HP IBRIX Storage)	Simple Network Management Protocol (SNMP)	✓	✓	✓		See the “Configuring StoreAll Network Storage Systems” chapter in the <i>Monitored Devices Configuration Guide</i> .

Table 21. Required Communication Protocols and Components for HP Insight Remote Support Services (*continued*)

Required protocols and components		Discovery	Monitoring	Basic Collections	SAN Collections	Notes
Data Protection						
HP StoreOnce Backup (D2D)	Simple Network Management Protocol (SNMP)	✓	✓			Configuration collections are not supported, except when the HP StoreOnce Backup System is part of a SAN collection.
	Telnet				✓	See the “Configuring StoreOnce Backup (D2D) Systems” chapter in the <i>Monitored Devices Configuration Guide</i> .
HP Virtual Library System (VLS)	Simple Network Management Protocol (SNMP)	✓	✓			Configuration collections are not supported, except when the VLS is part of a SAN collection.
	Secure Shell (SSH)				✓	See the “Configuring Virtual Library Systems” chapter in the <i>Monitored Devices Configuration Guide</i> .
HP StoreEver MSL (formerly Modular Systems Library)	Simple Network Management Protocol (SNMP)	✓	✓	✓		See the “Configuring StoreEver Tape Libraries” chapter in the <i>Monitored Devices Configuration Guide</i> .
HP ESL (formerly Enterprise Systems Library)	Simple Network Management Protocol (SNMP)	✓	✓			Customer can choose to use either Telnet or SSH to gather SAN Configuration Collections for all types of HP ESL Tape libraries including G3.
	Web-Based Enterprise Management (WBEM)			✓		See the “Configuring StoreEver Tape Libraries” chapter in the <i>Monitored Devices Configuration Guide</i> .
	Telnet				✓	
	Secure Shell (SSH)				✓	
HP StoreEver EML (formerly Enterprise Modular Library)	Simple Network Management Protocol (SNMP)	✓	✓			Customer can choose to use either Telnet or SSH to gather SAN Configuration Collections for all types of HP StoreEver EML Tape libraries including G3.
	Web-Based Enterprise Management (WBEM)			✓		See the “Configuring StoreEver Tape Libraries” chapter in the <i>Monitored Devices Configuration Guide</i> .
	Telnet				✓	
	Secure Shell (SSH)				✓	
HP StoreFabric SAN switches						
B-Series SAN Switch	Simple Network Management Protocol (SNMP)	✓	✓			Customer can choose to use either Telnet or SSH to gather SAN Collections for B-Series SAN switches.
	Telnet			✓	✓	See the “Configuring StoreFabric B-Series Switches” chapter in the <i>Monitored Devices Configuration Guide</i> .
	Secure Shell (SSH)			✓	✓	
C-Series SAN Switch	Simple Network Management Protocol (SNMP)	✓	✓	✓	✓	See the “Configuring StoreFabric C-Series Switches” chapter in the <i>Monitored Devices Configuration Guide</i> .
H-Series SAN Switch	Simple Network Management Protocol (SNMP)	✓	✓	✓	✓	See the “Configuring StoreFabric H-Series Switches” chapter in the <i>Monitored Devices Configuration Guide</i> .

Table 21. Required Communication Protocols and Components for HP Insight Remote Support Services (*continued*)

Required protocols and components		Discovery	Monitoring	Basic Collections	SAN Collections	Notes
HP Networking Switches						
HP ProVision-based Switches (formerly E-Series/ProCurve)	Simple Network Management Protocol (SNMP)	✓	✓			Customer can choose to use either Telnet or SSH to gather Network Configuration Collections for ProVision-based switches.
	Telnet			✓		See the “Configuring ProVision-based Networking Switches” chapter in the <i>Monitored Devices Configuration Guide</i> .
	Secure Shell (SSH)			✓		
HP ComWare-based Switches (formerly A-Series or H3C/3Com)	Simple Network Management Protocol (SNMP)	✓	✓			Customer can choose to use either Telnet or SSH to gather Network Configuration Collections for ComWare-based switches.
	Telnet			✓		See the “Configuring ComWare-based Networking Switches” chapter in the <i>Monitored Devices Configuration Guide</i> .
	Secure Shell (SSH)			✓		
Rack and Power						
HP Rack-mountable and Tower UPS	Simple Network Management Protocol (SNMP)	✓	✓			Configuration collections are not supported. See the “Configuring UPS Network Modules” in the <i>Monitored Devices Configuration Guide</i> .
HP Modular Cooling System	Simple Network Management Protocol (SNMP)	✓	✓			Configuration collections are not supported. See “Configuring Modular Cooling Systems” in the <i>Monitored Devices Configuration Guide</i> .
Applications						
VMware vCenter Server on ProLiant	VMware VirtualCenter Web Service interface	✓		✓		Gathers configuration collections on the ESX and ESXi virtual machines in the VMware vCenter cluster. See the “Configuring VMware vCenter Servers” chapter in the <i>Monitored Devices Configuration Guide</i> .

Appendix C – Event Log Monitoring Collector

The Event Log Monitoring Collector (ELMC) provides error condition detection of the event log of specific monitored endpoint system and communicates these events to HP Insight Remote Support for analysis.

The ELMC software is made available on the Hosting Device by downloading it from the **Administrators → Software Updates** page. The device specific ELMC versions will be made available in the download folder on the Hosting Device:

`%HP_RS_DATA%\ELMC`

This folder defaults to `C:\ProgramData\HP\RS\DATA\ELMC`. This is a hidden folder, so you may need to set your folder options to show hidden folders.

The appropriate ELMC software should be distributed and installed on the monitored device. Note that when the **Software Updates** page shows a status of *Installed*, this only means that the ELMC package has been installed on the Hosting Device. You must still distribute and install ELMC on your monitored devices.

This includes ELMC versions for:

- OpenVMS on HP Integrity servers
- Windows 2003 on HP Integrity servers
- Windows on ProLiant servers (x86, x64) when monitoring EVAs with P6000 Command View

Note

ELMC installation is **required** for Storage Management Servers (SMS) monitoring EVA P6000 storage devices.

The following ELMC versions are supported with HP Insight Remote Support 7.1:

- ELMC 6.2 and above

HP always recommends installing the latest version.

Note

When upgrading to ELMC version 6.4, the incorrect version number is displayed in the upgrade window. After performing the upgrade, the correct version number of 6.4 will show in the **Programs and Features** window and when you run the `wccproxy` version command.

Documentation

Refer to the following for more information regarding the topics discussed in this document.

HP Insight Remote Support

All HP Insight Remote Support and Insight Online documentation is available on the Web at www.hp.com/go/insightremotesupport/docs.

- HP Insight Remote Support Quick Installation Guide
This document highlights critical processes necessary for a successful HP Insight Remote Support 7.x installation.
- HP Insight Remote Support Installation and Configuration Guide
This document provides information about installing and configuring HP Insight Remote Support 7.x.
- HP Insight Remote Support Monitored Devices Configuration Guide
This document provides the necessary information to configure the devices that will be monitored by HP Insight Remote Support 7.x.
- The HP Insight Remote Support Upgrade Guide
This document provides information about upgrading previous HP Insight Remote Support 5.x versions to 7.x.
- The HP Insight Remote Support Security White Paper
This document provides an overview of the security features available in HP Insight Remote Support.
- HP Insight Online User's Guide
This document is optional and explains how to get started with HP Insight Online.
- HP Insight Online Frequently Asked Questions
This document is optional and answers general questions about HP Insight Online.

- HP Insight Online Reporting Guide
This guide describes the Reports tab on the HP Insight Online main page, enabled through HP Insight Remote Support. Use this guide as an introduction to the available reports and as a reference for your reporting needs.
- HP Insight Remote Support forum at <http://h30499.www3.hp.com/t5/Insight-Remote-Support/ct-p/itrc-302> for discussions about HP Insight Remote Support.
- HP Insight Remote Support Solution FAQ
This document answers general questions about solution support within HP Insight Remote Support.

For more information, please visit www.hp.com/go/insightremotesupport.

Related Information

- HP ProLiant Gen8 Server Management Information Library
www.hp.com/go/proliantgen8/docs
- HP ProLiant Gen8 Server with HP iLO Management Engine Setup Guide
www.hp.com/go/proliantgen8/docs
- HP Service Pack for ProLiant Information Library
www.hp.com/go/spp/documentation
- HP iLO 4 User Guide
www.hp.com/go/ilomgmtengine/docs
- HP Intelligent Provisioning User Guide
www.hp.com/go/intelligentprovisioning/docs
- HP ProLiant Gen8 Server Troubleshooting Guide
www.hp.com/go/proliantgen8/docs
- HP Systems Insight Manager Information Library
www.hp.com/go/foundationmgmt/docs

Learn more at

hp.com/go/insightremotesupport

