KPS PUBLIC SCHOOLS • STUDENT TECH BENCH PROGRAM

Evaluator Key — managers only

# Tier 3 — Advanced Repair

T3

System boards, daughterboards, heat sinks, liquid damage and full transplants.

## In this guide


1 Answer key

2 Scoring the knowledge check

3 Running the practical exam

4 Awarding the certification


Rev 1.0 • October 2026

**Keep this away from candidates.** This key is for lead techs and managers. Don't leave it on the bench or share the file.

# 1 Answer key

| # | Answer | Why |
|---|---|---|
| 1 | **C** — Daughterboard | Tier 3: motherboard, daughterboard, other major parts. |
| 2 | **A** — S1, S2, S3, known-good charger/battery, connectors reseated | Most dead boards turn out to be something cheaper. |
| 3 | **D** — System board or warranty | USB-C ports are soldered to the board on these models; no soldering at the bench. |
| 4 | **B** — The order printed on the heat sink | Even pressure protects the processor. |
| 5 | **B** — A pea-size dot, or the supplied pad | Too much is as bad as too little. |
| 6 | **D** — Power it on to test | Power through liquid causes the corrosion that kills boards. |
| 7 | **A** — On the system board | That's why board swaps need the lead tech. |
| 8 | **C** — Recovery if needed, re-enroll, full diagnostics | The device must be managed and fully working. |
| 9 | **D** — By its edges, ESD strap on | Static and pressure on chips damage boards. |
| 10 | **B** — Stop and escalate | Burn marks are a fire hazard and board-level work. |
| 11 | **C** — No, never | The processor can overheat in seconds. |
| 12 | **A** — The lead tech, using the fee schedule | Combinations can move a claim up a tier. |
| 13 | **A** — Shallow, under about 3 mm, away from the display cable | A deep pick cuts the cable or punctures the battery. |
| 14 | **C** — Corrosion: clean lightly or escalate | Corrosion keeps spreading if left. |
| 15 | **D** — Run the guide's verify checks and look inside before closing | Your check-off is the quality gate. |

# 2 Scoring the knowledge check

- One point per question. Score 90% or better (14 of 15).
- Go over every missed question with the candidate, using the "Why" column, before they leave.
- A candidate who misses the pass mark can retake a different-order version after a week. Shuffle the answer letters when you reprint.

# 3 Running the practical exam

- Allow about 90 minutes. Set up the devices and any planted faults before the candidate arrives.
- Watch, don't coach. Step in only for safety.
- Mark each task Pass or Fail against the "To pass" column. All tasks must pass.
- Any automatic-fail item ends the exam immediately.

| Task | Set up beforehand | Watch for |
|---|---|---|
| **Board diagnosis** | Given a "dead" device, decide whether the board is at fault. | Works through S1/S2/S3, charger, battery and connectors in order; correct conclusion; notes written. |
| **Board or daughterboard swap** | Swap a board (or daughterboard) on a practice unit. | Photos, ESD-safe handling, every connector reseated, device boots. |
| **Heat sink** | Remove and refit a heat sink with new paste. | Correct order, clean surfaces, correct amount, no power without the heat sink. |
| **Liquid response** | Talk through and demonstrate the first 10 minutes of a spill. | Force off, unplug, tent, battery out, no power-on, correct dry time. |
| **Mentor check** | Check off a planted student repair that has one hidden fault. | Finds the fault, explains it clearly, records the check-off correctly. |

**Automatic fail items.** Powering on a board without a heat sink; Powering on a wet device; Handling a board without ESD protection; Ordering a board without the documented checks; Prying near a battery or display cable on a glued device.

# 4 Awarding the certification

- Check every requirement on the sign-off page is signed, including the prerequisite.
- Sign and date the candidate's sign-off page.
- In the portal, open Certifications, find the candidate, and click the box for this certification. It's recorded with your name and the date, and logged.
- If a certified student has a safety violation or repeated comebacks, remove the certification in the portal (click the check again) and note why in the audit log reason or the student's file.