

Radio button in HTML

1. Line 17 19 21 inside input **type attribute set to radio**
2. Line 17 19 21 **name attribute should have the same value** in order to select one button out of many.
3. Line 17 19 21 **value attribute needs to be defined** which will required at server side

```
14 <p>
15 <h2>Radio button</h2>
16 <p>Select the one of the following</p>
17 <input type="radio" name="workplan" id="" value="hybrid mode">
18 <label for="workplan">hybrid mode</label><br>
19 <input type="radio" name="workplan" id="" value="work from home">
20 <label for="workplan">work from home</label><br>
21 <input type="radio" name="workplan" id="" value="work from office">
22 <label for="workplan">work from office</label>
23 </p>
```

Checkbox in HTML

1. Line 27 **type attribute set to checkbox.**
2. Line 27 **name attribute is used to link the checkbox with the label.**

```
25 <p>
26 <h2>checkbox</h2>
27 <input type="checkbox" name="terms" id="terms">
28 <label for="terms">Check this to agree terms and condition</label>
29 </p>
```

Select box in HTML

1. Below is the demo of checkbox.

```
31 <p>
32 <h2>select</h2>
33 <label for="chooseCollege">Choose your college</label>
34 <select name="chooseCollege" id="chooseCollege">
35   <option value="preset">Select your option</option> <!-- this value is shown at starting -->
36   <option value="MSIT">Maharaja surajmal institue of technology</option>
37   <option value="MAIT">Maharaja agrsain intitute of technology</option>
38   <option value="BVP">Bhartiya vidyapeeth college of engineering</option>
39   <option value="BPIT">Bhagwan parshuram institute of technology</option>
40
41 </select>
42 </p>
```