240VAC

240VAC UPS SUPPLY
FROM F16-DB-202
2000-F16-TLD-EL-10056

N

Q002
25A

Q002

Q004
0040
6A
30 mA

F18CAM101-CP
2000-ME035-D04-10002

004N

F18CAM101-CP
JAMESON CELLS FROTH
CAMERA CONTROL PANEL
240VAC POWER SUPPLY

Q006
6A
30 mA

SPARE
240VAC POWER SUPPLY

Q008
6A
30 mA

SPARE
240VAC POWER SUPPLY

Q012
0120
6A

240VAC - 54VDC
POWER SUPPLY
170W

Q012-N

F18RIO002-PS3
CISCO
PWR-IE170W-PC-AC
POWER SUPPLY

0134
(+54VDC)
(0VDC)
0135

Q017
0172
6A

CCTV PoE SWITCH
NOTE 4

F18-ETH-144
CISCO
IE-3300-8P2S-E
CCTV PoE SWITCH

Q021
0212
6A

CCTV PoE INJECTOR

F18ETH144-POE01
VIVOTEK
AW-IHB-0100

0020

0029

Q028
16A

Q029
16A

0280

0296

F18RIO002-PS1
PHOENIX
QUINT4-PS/1AC/24DC/40
240VAC/24VDC, 40A POWER SUPPLY

F18RIO002-PS2
PHOENIX
QUINT4-PS/1AC/24DC/40
240VAC/24VDC, 40A POWER SUPPLY

F18RIO002PS1+24VDC
DC OK
F18RIO002PS1
POWER SUPPLY 1
24VDC HEALTHY
2000-F18-TER-IC-10232

F18RIO002PS2+24VDC
DC OK
F18RIO002PS2
POWER SUPPLY 2
24VDC HEALTHY
2000-F18-TER-IC-10232

(+24VDC)
(0VDC)
0352
0357
0351
0358

F18RIO002-RM
PHOENIX
QUINT-ORING/24DC/2x40/1x80
REDUNDANCY MODULE

0424
(+24VDC)
(0VDC)

Q045
40A

0450
0425

0450
24VDC SUPPLY
CONT'D ON LINE 51
0425

(+24VDC)
0450
24VDC SUPPLY
CONT'D FROM LINE 48
0425
(0VDC)

24VDC TRANSIENT
SURGE FILTER

F18RIO002-SD
TRANSTECH
TLP-SF40-1P-24VDC
SURGE FILTER

0563
(+24VDC)
(0VDC)
0566

Q057
40A

0570

Q060
0600
6A

S060
RH DOOR
0605
WH
0VDC
1
PANEL LIGHTS

S062
CENTRE DOOR
0625
WH

S064
LH DOOR

Q070
0700
2A

FIT18057
2000-F18-TER-IC-10237

0VDC
2

FIT18057
F18-CF-501 CLEANER FLOT CELL WASH
WATER FLOW INDICATING TRANSMITTER
24VDC POWER SUPPLY

Q072
0720
2A

FIT18227-P1-0720

FIT18227
2000-F18-TER-IC-10237

FIT18227-P1-0VDC

0VDC
3

FIT18227
F18-PP-511/512 CLEANER SCAVENGER FLOT
CELL RECIRCULATION PUMPS DISCH. FLOW
IND. TRANSMITTER 24VDC POWER SUPPLY

Q074
0740
2A

DIT18227-P1-0740

DIT18237
2000-F18-TER-IC-10237

DIT18237-P1-0VDC

0VDC
4

DIT18237
F18-PP-513/514 CLEANER SCAVENGER FLOT
CELL TAILS PUMPS DISCHARGE DENSITY
IND. TRANSMITTER 24VDC POWER SUPPLY

Q076
0760
2A

FIT18237-P1-0760

FIT18237
2000-F18-TER-IC-10237

FIT18237-P1-0VDC

0VDC
5

FIT18237
F18-PP-513/514 CLEANER SCAVENGER FLOT
CELL TAILS PUMPS DISCHARGE FLOW
IND. TRANSMITTER 24VDC POWER SUPPLY

Q078
0780
2A

FIT18257
2000-F18-TER-IC-10237

0VDC
6

FIT18257
F18-CF-511 CLEANER-SCAVENGER FLOT
CELL WASH WATER FLOW INDICATING
TRANSMITTER 24VDC POWER SUPPLY

Q080
2A

0VDC
7

SPARE
24VDC POWER SUPPLY

Q082
2A

0VDC
8

SPARE
24VDC POWER SUPPLY

0570
24VDC SUPPLY
CONT'D ON LINE 101
0566

## NOTES

1. TERMINALS ON TERMINAL STRIPS ABOVE 50VAC SHALL HAVE A SEPARATE PERSPEX SHROUD AND SHALL BE LABELLED "DANGER xxxVAC".
2. WIRE NUMBER FERRULES ON TERMINAL STRIP SHALL BE PREFIXED WITH EQUIPMENT NUMBER e.g. F18RIO002-xxxx.
3. EACH WIRE SHALL BE IDENTIFIED AT BOTH ENDS WITH FERRULES.
4. FOR NETWORK CONNECTION & BUS CABLING DETAILS REFER TO RIO PANEL COMMUNICATIONS TERMINATION DIAGRAMS.
5. INSTRUMENT EARTH BAR TO BE BONDED TO MAIN EARTH BAR WITH SOLID COPPER LINK.

## LEGEND

- FIELD TERMINAL
- DCS OR I/O TERMINAL
- MARSHALLING TERMINAL
- DEVICE TERMINAL
- INDICATION LAMP, cc = COLOUR
- EARTH BAR
- INSTRUMENT EARTH BAR

# 2000-F18-SCM-IC-10231_Rev1

Cleaner & cleaner scavenger flotation F18-RIO-002 cleaner flotation field n-IO panel schematic diagram sheet 1