33 kV FROM HV SWITCHBOARD
F00-SW-010
2000-F00-SLD-EL-10002

F21-SR-001
415V CIL4 SWITCHROOM

F21-TR-006
TRANSFORMER ROOM

F21-TR-006
33/0.433kV
2500kVA
Dyn11
z=6%
ANAF

SWR EARTH BAR
Tx EARTH BAR
NOTE 3
4000/ 1A
2.5VA
5P20

1600A
4 POLE
F21-GE-006
415V
1000kVA

F21-SW-006
CIL4 415V MOTOR CONTROL CENTRE No.1

MCC EARTH BAR
NEUTRAL BAR
NOTE 1
1/700A
4000/ 5A
5VA
Cl 1
4000/ 5A
30VA
Cl0.5
1600/ 5A
5VA
Cl 1
1600/ 1A
2.5VA
5P20
TEST
PM
AFD
ACB
00F-08
01F-8
1600A
4000A
20A
63A
2A
32A
2A
63A
240VAC SPRING
CHARGE SUPPLY
60G
50
50G
51
51G
24VDC CONTROL POWER SUPPLY
NOTE 7
100A
100A
SD
NOTE 6
ATS

CONTINUED ON SHT 2
2000-F22-SLD-EL-10202

EMERGENCY BUS 415V 3NE~ 50Hz 4000A 65kA for 1sec
INC
INC

06F-01
250A
2A
32A
90A
250A
250A

02R-01
32A
2A
32A
70A
32A
32A

03R-01
250A
2A
32A
90A

06F-09
160A
2A
32A
70A
ECR

05F-05
630A
2A
32A
250A
EOL

04F-05
630A
2A
32A
250A
EOL

03F-05
630A
2A
32A
250A
EOL

05R-05
630A
2A
32A
250A
EOL

69kW
F21-DB-001
CIL4
415V SWITCHROOM
L&SP DB
2000-F21-SCM-EL-10205

ISL
F21UPS001-ISL
240VAC UPS
MAINTENANCE
BYPASS SWITCH
2000-F21-SCM-EL-10206

10kW
F21-DB-201
CIL4
415V SWITCHROOM
240VAC UPS DB
2000-F21-TLD-EL-10054

UPS
10kW
F21-UPS-001
CIL4
415V SWITCHROOM
240VAC UPS
2000-F21-TLD-EL-10054

E-SHUT
F21SR001-LCS
NOTE 12

69kW
F21-DB-301
CIL4
L&SP DB
2000-F21-SCM-EL-10207

CR
54kW
F21-CR-441
CIL4 AREA
MAINTENANCE CRANE
2000-F21-SCM-EL-10213

RTD
M
3~
250kW
F21-AG-411
CIL4 TANK 1
AGITATOR
2000-F21-SCM-EL-10208

F21-AG-412
CIL4 TANK 2
AGITATOR
2000-F21-SCM-EL-10209

F21-AG-413
CIL4 TANK 3
AGITATOR
2000-F21-SCM-EL-10210

F21-AG-414
CIL4 TANK 4
AGITATOR
2000-F21-SCM-EL-10211

NORTHERN STAR RESOURCES

Approved	X
Approved as Noted	
Not Approved	
For Information Only	

ACCEPTANCE DOES NOT RELIEVE THE SUPPLIER / CONTRACTOR OF ITS RESPONSIBILITY OR LIABILITIES UNDER THE PURCHASE ORDER / CONTRACT

NOTES

1. EARTH-NEUTRAL LINK SHALL BE INSTALLED IN INCOMER TIER. SIGNAGE SHALL BE PLACED ON MCC, TRANSFORMER, GENERATOR INCOMER AND GENERATOR READING "M.E.N. LINK LOCATED IN F21-SW-006 INCOMER TIER". CABLE SHALL BE IDENTIFIED C/W LABEL STATING "M.E.N. LINK - DO NOT REMOVE".
2. SWITCHBOARD SHALL BE EXTENSIBLE AND BE PROVIDED WITH THE FACILITY TO EXTEND THE MAIN BUSBAR AND APPEND ADDITIONAL TIERS AT ONE END WITHOUT MAJOR STRUCTURAL DISASSEMBLY.
3. UPSTREAM TRANSFORMER FEEDER SHALL BE TRIPPED ON ACTIVATION OF SWITCHROOM EMERGENCY PUSHBUTTON, DETECTION OF EARTH FAULT OR ARC FAULT DETECTION.
4. SWITCHBOARD VENDOR SHALL SELECT SWITCHGEAR TO PROVIDE TYPE-2 CO-ORDINATION SUITABLE FOR HIGH EFFICIENCY MOTORS.
5. ALL DRIVE I/O VIA COMMS NETWORK TO DCS. FOR COMMUNICATIONS BLOCK DIAGRAM REFER 2000-F21-BLK-IC-10001.
6. SURGE DIVERTERS SHALL PROVIDE FEEDBACK TO DCS VIA VOLT-FREE CONTACTS. SURGE DIVERTER FUSES SHALL BE SIZED BY VENDOR TO SUIT DUTY.
7. MINIATURE CIRCUIT BREAKERS SHALL BE SIZED AND RATED TO SUIT ACB AND INCOMER REQUIREMENTS.
8. THERMAL OVERLOAD UNITS MAY BE SUBSTITUTED WITH ELECTRONIC (MAGNETIC) OVERLOAD UNITS TO SUIT DUTY.
9. TOLs TO BE MOUNTED IN PURPOSE-BUILT ENCLOSURE BENEATH VSD. TOLs MAY BE INCLUDED IN MCC MODULE WITH ENGINEERING APPROVAL.
10. ANY DRIVE RTDs SHALL BE WIRED TO DEDICATED REMOTE I/O CARDS IN THE FIELD. RTD RELAYS MAY BE INCLUDED IN THE MCC MODULE WITH ENGINEERING APPROVAL.
11. CIRCUIT BREAKER TO BE SUBSTITUED FOR FUSED-SWITCH WHERE REQUIRED BY EQUIPMENT MANUFACTURERS GUIDELINES.
12. EMERGENCY SHUTDOWN (E-SHUT) PUSH BUTTON N/O WIRED TO SHUNT TRIP NOMINATED CIRCUIT BREAKERS.

LEGEND

- DIRECT ON-LINE MOTOR STARTER GENERIC - NOTE 4, 5
- DIRECT ON-LINE MOTOR STARTER REVERSING - NOTE 4, 5
- EOL — ELECTRONIC OVERLOAD UNIT NOTE 4, 5
- THERMAL OVERLOAD UNIT NOTE 8
- VARIABLE SPEED DRIVE NOTE 4, 5
- EARTH LEAKAGE RELAY NOTE 4, 5
- FIELD-MOUNTED DECONTACTOR
- MOTOR THERMISTOR (ONLY REQ. FOR MOTORS >37kW - 250kW)
- RTD — MOTOR RTD (ONLY REQ. FOR MOTORS >250kW)
- MOTOR HEATERS (ONLY REQ. FOR MOTORS >90kW)
- 49 63 71 — TRANSFORMER PROTECTIVE DEVICES (REFER ANSI STANDARDS FOR DESCRIPTIONS)
- CIRCUIT BREAKER (NOTE 12)
- xxxA ST TRIP SET POINT
- xxxA CB SIZE
- AFD — ARC FLASH DETECTION
- ECR — EARTH CONTINUITY RELAY
- 1 E-SHUT — SWITCHROOM EMERGENCY SHUTDOWN
- 63A 3 PHASE SOCKET OUTLET

2000-F21-SLD-EL-10201_Rev1

Flotation tailings CIL4 F21-SW-006 415V MCC single line diagram sheet 1

11:07AM HOTSEAT04
CIL