F72-SR-001
REAGENTS 415V SWITCHROOM

F72-SW-072
REAGENTS 415V MCC
2000-F72-TER-IC-10101

(NOTE 4)
F72-ETH-021
F72-ETH-025
INCOMER
F72SW072-GWY
F72SW072-INC INCOMER ACB
F72SW072-PQM POWER METER
F72SW072-AFD ARC FLT. DET. SYS.
RS485 BUS
EOL 1
EOL n
DOL STARTER MODULES ON FRONT & REAR OF MCC
(NOTE 1, 2 & 3)

LV VSDS
1
n
F72-UPS-001 240VAC UPS
(NOTE 5)
F72-FIP-001 FIRE PANEL

F72-SW-172
REAGENTS EMERGENCY 415V MCC
2000-F72-TER-IC-10103
(NOTE 4)
F72-ETH-026
EOL 1
EOL n
DOL STARTER MODULES ON FRONT & REAR OF MCC
(NOTE 1, 2 & 3)

F72-DCS-413
REAGENTS 415V SWITCHROOM DCS PANEL
2000-F72-TER-IC-10011
F72-FCS-413
F72FCS413-NU01
(NOTE 1, 2 & 3)

F72-COM-001
REAGENTS
415V SWITCHROOM COMMUNICATIONS RACK
2000-F72-TER-IC-10001
F72-ETH-001 (MODBUS COMMS SWITCH 1)
F72-ETH-002 (MODBUS COMMS SWITCH 2)
STACK CABLES NOTE 1.
LV SWITCHROOM MODBUS CONNECTIONS DISTRIBUTED ACROSS 2 ETHERNET SWITCHES
F72-ETH-011 (VNET IP1 LAN DCS SWITCH)
F72-ETH-012 (VNET IP2 LAN DCS SWITCH)
F72-FOB-001
F72-FOB-002
FIBRE BACKBONE THROUGH-PATCHING AS REQ'D
F72-FOB-004A
F72-FOB-004B
(NOTE 1, 2 & 3)

F72-RIO-003
REAGENTS N-IO PANEL
2000-F72-TER-IC-10500/10501
F72-FOB-031
F72FCS413-NU02
F72-FOB-032
F72FCS413-NU03
(NOTE 1, 2 & 3)

F72-RIO-004
REAGENTS N-IO PANEL
2000-F72-TER-IC-10600/10601
1
F72-FOB-041
F72FCS413-NU04
F72-FOB-042
F72FCS413-NU05
(NOTE 1, 2 & 3)

F72-GE-172
REAGENTS EMERGENCY SUPPLY 415V GENERATOR
2000-EL019-D04-10002

FROM F22-SR-001
CARBON REGEN & ELUTION 415V SWITCHROOM
2000-F22-BLK-IC-10001

TO F28-SR-002
ULTRAFINE GRINDING 415V SWITCHROOM
2000-F28-BLK-IC-10001

NOTES

1. FOR INTERNAL FIBRE OPTIC, CAT6 PATCH LEAD (& STACK CABLING IN SWITCHROOM COMMS CABINETS) EQUIPMENT CONNECTION DETAILS REFER TO SPECIFIC TERMINATION DIAGRAMS.
2. REFER TO SPECIFIC COMMUNICATIONS TERMINATION DRAWINGS FOR EXTERNAL EQUIPMENT CONNECTION DETAIL.
3. COM CABINET, DCS PANEL, RIO PANEL, MCC & SWITCHBOARD HARDWARE/INTERCONNECTIONS (E.G. NIO NODE) & INTER-FOBOT PATCHING NOT SHOWN FOR CLARITY. REFER TO SPECIFIC COMMUNICATIONS TERMINATION DRGS FOR DETAIL.
4. ETHERNET SWITCHES LOCATED IN CABLE ZONE OF 415VAC MCC, FRONT & BACK - AS REQUIRED.
5. FIRE INDICATION PANELS SHALL BE ON A FIBRE OPTIC RING AND WILL TIE-IN TO EXISTING MAIN PLANT FIRE ANNUNCIATOR PANEL. FIP CONNECTS TO FIBRE INFRASTRUCTURE VIA 2 FIBRE OPTIC PATCH CABLES.

NORTHERN STAR RESOURCES LIMITED

Approved	X
Approved as Noted	
Not Approved	
For Information Only	

ACCEPTANCE DOES NOT RELIEVE THE SUPPLIER / CONTRACTOR OF ITS RESPONSIBILITY OR LIABILITIES UNDER THE PURCHASE ORDER / CONTRACT

LEGEND

- FOB — FIBRE OPTIC BREAK OUT TRAY
- ETH — ETHERNET SWITCH HIRSCHMANN = DCS NETWORKS CISCO = ALL OTHER NETWORKS
- FCS — YOKOGAWA FIELD CONTROL UNIT
- U xxxFCS4xx-NUxx D — YOKOGAWA NODE INTERFACE UNIT (DUAL OPTICAL ESB PORTS: U = UPLINK, D = DOWNLINK) TAG RELATED TO PARENT FCS
- GWY — COMMUNICATIONS GATEWAY
- MC — FIBRE TO CAT6 MEDIA CONVERTER
- xxx — EQUIPMENT OR VENDOR PACKAGE PANELS AS NOTED WITHIN BLOCK.
- EOL — MCC MODULE DOL INTELLIGENT ELECTRONIC DEVICE/OVERLOAD
- UPS — UNINTERRUPTIBLE POWER SUPPLY
- VSD - VARIABLE SPEED DRIVE (WALL MOUNTED)
- MULTI CORE FIBRE OPTIC CABLE OR DUPLEX PATCH LEADS
- CAT6 — CAT6 ETHERNET CABLE CONNECTION

2000-F72-BLK-IC-10001_Rev1

F72-SR-001 - 415V switchroom & N-IO panels - communications block diagram