415V FROM
F72-SW-072
2000-F72-SCM-EL-10223

R W B N E

415V FROM
F72-GE-172
2000-F72-SLD-EL-10211

E R W B N

EARTH BAR

F72-SW-172
MOTOR CONTROL CENTRE

F72-SD-172
415VAC SURGE DIVERTER
106kA
SD OK
24VDC
SD
LINE 227
2000-F72-SCM-EL-10232

E20 F105 E21 L1
E40 F105 E41 L2
E60 F105 E61 L3
100A
N3 400A
E80 N
PE

E10 F110 E11 L1
E30 E31 L2
E50 E51 L3
N1 2A 32A
E70 N
PE
LLI RD

E22 F111 E23 L1
E42 E43 L2
E62 E63 L3
N2 2A 32A
E81 N
PE
LLI RD

E12
E32
E52
E71

F116 E12 E32 E52
2A 32A

E24 F121
E44
E64
2A 32A

A116
ATYSC65CIP
ATS CONTROL INTERFACE
PART OF

F1 E13
F2 E33
F3 E53
6A 32A N1 E71
F4 E25
F5 E45
F6 E65
6A 32A N2 E82

A115
ATyS C65 CONTROLLER
PART OF
NOTE 3, 6.

SOURCE 1
MAIN
SUPPLY
L1 L2 L3 N

SOURCE 2
GENERATOR
SUPPLY
L1 L2 L3 N

END OF BUS
RESISTOR
4829 0180
RJ45
CAT6

DIGIS IO-10
4829 0140
MODULE 2
RJ45 RJ45
CAT6 – CAT6 – CAT6

DIGIS IO-10
4829 0140
MODULE 1
RJ45 RJ45
CAT6 – CAT6 – CAT6 – CAT6

DIGIWARE
BUS
RJ45 RJ45
CAT6 – CAT6 – CAT6 – CAT6

Q131
630A
S0 S1

U131
MOTOR OPERATION
UNIT
TERASAKI
TEMBREAK
PRO B MODEL
MCCB
MOTOR OPERATOR
(PART OF)
P1 P2 E

Q132
630A
S0 S1

U132
MOTOR OPERATION
UNIT
TERASAKI
TEMBREAK
PRO B MODEL
MCCB
MOTOR OPERATOR
(PART OF)
P1 P2 E

MAIN PWR
(ORANGE)
2
1
PART
OF

CPSR

CONT LINE 241

LINE 234
B2 24VDC
B1 0VDC

CURRENT
TRANSFORMER
I1 I2 I3 IN GND GND
NOT USED

RS485
NC - +

USB

415V 3NE~ 50Hz 630A 65kA for 1 sec
R
W
B
N

NOTES

1. SURGE DIVERTERS SHALL PROVIDE FEEDBACK TO DCS VIA VOLT-FREE CONTACTS. SURGE DIVERTER FUSES SHALL BE SIZED BY VENDOR TO SUIT DUTY.
2. MINIATURE CIRCUIT BREAKERS SHALL BE SIZED AND RATED TO SUIT ACB AND INCOMER REQUIREMENTS.
3. ALL TERMINATIONS ABOVE 50VAC SHALL BE TO IP2x OR ABOVE, IF NOT, TO HAVE A SEPARATE PERSPEX SHROUD FITTED AND SHALL BE LABELLED "DANGER xxxVAC".
4. WIRE NUMBER FERRULES ON TERMINAL STRIP SHALL BE PREFIXED WITH EQUIPMENT NUMBER e.g. F72SW172-0600 UNLESS NOTED OTHERWISE.
5. EACH WIRE SHALL BE IDENTIFIED AT BOTH ENDS WITH FERRULES.
6. ATS TO BE CONFIGURED SUCH THAT LOSS OF MAINS POWER SHALL START GENERATOR AND TRANSFER SUPPLY SOURCE. UPON DETECTION OF MAINS POWER ATS SHALL AUTO TRANSFER TO MAINS AND SHUTDOWN GENERATOR WITH A NOMINAL DELAY OF 5 MINUTES.

LEGEND

- 00/01/00 — DCS DIGITAL INPUT
- 00/02/00 — DCS DIGITAL OUTPUT
- MCC TERMINAL
- VSD TERMINAL
- FIELD TERMINAL
- DCS OR I/O TERMINAL
- MARSHALLING TERMINAL
- DEVICE TERMINAL
- INDICATION LAMP
  cc = COLOUR

2000-F72-SCM-EL-10231_Rev2

F72-SW-172 F72-SW-172 415V emergency MCC incomer schematic diagram sheet 1