F00-SR-001
PLANT 33kV HV DISTRIBUTION SWITCHROOM

F00-SW-010
PLANT 33kV HV DISTRIBUTION SWITCHBOARD

B01 B02 B03 B04

36kV 2000A 3~E 31.5kA FOR 3s

630A 630A CLOSE TRIP PR SEL 751 50 50G 27 51 51G NOTE 1 AFD

300/1A 2.5VA 5P20 TEST
300/1A 1VA 10P10 TEST
NOTE 2

B03: 500/1A 2.5VA 5P20 TEST

PR SEL 787-4 50 51

TRANSFORMER PROTECTION ALARM & TRIP CONTACTS (NOTE 6)

110V AC BUS VOLTAGE SUPPLY FROM INCOMER INC-1 BUS VT (PANEL B05)

CONT'D ON SHEET 2 DRG 2000-F00-SLD-EL-10003

F13TR402-JB
BALL MILL VSD TRANSFORMER JUNCTION BOX
3x2 3x2 3x2 3x2 3x2 3x2

TRANSFORMER PROTECTION DEVICES

F13-TR-402
33/3.8/3.8kV 33/3.8/3.8kV
33/0.415/0.415kV
Dyd Dyd Yyd - (NOTE 10)
TOTAL : 25400kVA
PRIMARY : 12000kVA
: 12000kVA
: 1400kVA
SECONDARY : 2x6000 kVA
: 2x6000 kVA
2x700 kVA
KNAN

CT's 1200/1A 5VA SP20 3x2 3

TRANSFORMER SECONDARY CT's

SWITCHROOM E-SHUT (REFER NOTE 4)
CIRCUIT BREAKER TRIP COMMAND
CIRCUIT BREAKER CLOSE COMMAND
DISCONNECTOR STATUS SIGNAL
CIRCUIT BREAKER CLOSED SIGNAL
110V AC BUS VOLTAGE SUPPLY

ACTIVATION OF SWITCHROOM E-SHUT (REFER NOTE 4)
DETECTION OF ARC FAULT (REFER NOTE 5)

F13-TR-014
RECYCLE CRUSHING MCC 33/0.433kV TRANSFORMER

F13-SW-014
RECYCLE CRUSHING 415V MCC INCOMER

REFER DRG 2000-F13-SLD-EL-10401

F13-TR-003
BALL MILL MCC 33/0.433kV TRANSFORMER

F13-SW-003
BALL MILL 415V MCC INCOMER

REFER DRG 2000-F13-SLD-EL-10901

F13MB401A-VS
BALL MILL MOTOR 1 HV VSD (MASTER) 3.8/3.5kV

F13MB401B-VS
BALL MILL MOTOR 2 HV VSD (SLAVE) 3.8/3.5kV

BALL MILL MOTOR 1 EXCITER PANEL
BALL MILL MOTOR 2 EXCITER PANEL
BALL MILL VSD (MASTER) AUXILIARY PANEL

F13MB401AVS-ISL03 F13MB401AVS-ISL01 F13MB401AVS-ISL02 F13MB401BVS-ISL01 F13MB401BVS-ISL02 F13MB401BVS-ISL03

ISOLATOR PANEL
ISOLATOR PANEL A
ISOLATOR PANEL B
ISOLATOR PANEL
ISOLATOR PANEL A
ISOLATOR PANEL B
ISOLATOR PANEL

CONT'D FROM SHEET 2 DRG 2000-F00-SLD-EL-10003

F13-SR-003
SAG & BALL MILLS VSD SWITCHROOM

EXCITER M 3~ 10000 kW RTD
F13-MB-401A
BALL MILL MOTOR 1
2000-ME001.3-D02-50007

EXCITER M 3~ 10000 kW RTD
F13-MB-401B
BALL MILL MOTOR 2
2000-ME001.3-D02-50007

33kV SPARE (1)
FULLY EQUIPPED
-

NOTES

1. THE FEEDER PROTECTION RELAY VOLTAGE INPUT SHALL BE WIRED FROM THE CORRESPONDING INCOMER BUS VT.
2. ARC FLASH POINT DETECTORS SHALL BE PLACED IN CABLE ZONES AND CONNECTED DIRECTLY TO THE SEL PROTECTION RELAYS IN EACH PANEL.
3. SWITCHBOARD SHALL BE EXTENSIBLE FOR FUTURE EXPANSION AND SUPPLIED WITH ONE SPARE TIER PER BUS SECTION AS SHOWN.
4. TRANSFORMER 33kV FEEDER SHALL BE TRIPPED ON THE ACTIVATION OF THE SWITCHROOM EMERGENCY SHUTDOWN (E-SHUT) PUSHBUTTON VIA A CONTACT HARDWIRED DIRECT TO SHUNT TRIP THE CIRCUIT BREAKER.
5. TRANSFORMER 33kV FEEDER SHALL BE TRIPPED ON THE ARC FAULT DETECTION OF THE DOWNSTREAM MCC INCOMER ACB.
6. TRANSFORMER INSTRUMENTATION ALARM & TRIP CONTACTS SHALL BE HARDWIRED TO THE SEL787 TRANSFORMER FEEDER PROTECTION RELAYS.
7. THE INTERTRIP OF THE TRANSFORMER 33kV FEEDER SHALL BE HARDWIRED FROM THE 11kV SWITCHBOARD INCOMER PROTECTION RELAY EITHER ON A TRANSFORMER TRIP, EARTH FAULT DETECTION OR ARC FAULT DETECTION.
8. THE ACTIVATION OF THE PLANT 33kV DISTRIBUTION SWITCHROOM F00-SR-001 EMERGENCY SHUTDOWN (E-SHUT) PUSHBUTTON VIA A CONTACT HARDWIRED DIRECT TO SHUNT TRIP ALL THREE INCOMER CIRCUIT BREAKERS AND THE CORRESPONDING UPSTREAM POLE MOUNTED RECLOSERS.
9. PROTECTION TRIP FROM THE INCOMER CIRCUIT BREAKER SHALL INTERTRIP THE UPSTREAM POLE MOUNTED RECLOSER.
10. REFER TO NAMEPLATE DRAWING 2000-ME001.3-D05-50001 FOR LV WINDING PHASE SHIFT ANGLES.

LEGEND

- PR — INCOMER / FEEDER PROTECTION RELAY NOTES 1 & 2
- PQM — POWER QUALITY AND REVENUE METERING
- ARC FLASH SENSOR (POINT TYPE) NOTE 2
- CAPACITIVE VOLTAGE INDICATION
- MECHANICAL OR ELECTRICAL INTERLOCK DEVICE
- 27 — UNDER VOLTAGE
- 50 — INSTANTANEOUS OVERCURRENT
- 50G 50N — INSTANTANEOUS EARTH/NEUTRAL OVERCURRENT
- 51 — TIMED OVERCURRENT
- 51G 51N — TIMED EARTH/NEUTRAL OVERCURRENT
- 59 — OVER VOLTAGE
- 64 — EARTH FAULT
- 67 67G — DIRECTIONAL OVERCURRENT/EARTH FAULT
- AFD — ARC FLASH DETECTION

DRG No.	REFERENCES	REV	DATE	DESCRIPTION	DRAW	CHECK	DESIGN	TECH APP	PROJ APP
		5	10SEP26	KCGM GROWTH PROJECT - SP1 AS-BUILT	RT	M.M.	MJB	MJB	MJB
2000-F00-SLD-EL-10051	F00-SW-010 33kV PLANT HV DISTRIBUTION SWITCHBOARD INTERLOCKING SLD SHEET 1 OF 5	4	30MAY25	FAT REDLINES INCORPORATED					
2000-F00-DRG-EL-10001	F00-SR-010 33kV PLANT HV DISTRIBUTION SWITCHROOM ELECTRICAL EQUIPMENT LAYOUT	3	11NOV24	REVISED F13-TR-402, F13TR402-JB AND NOTE 11					
2000-F00-SLD-EL-10003	F00-SW-010 33kV PLANT HV DISTRIBUTION SWITCHBOARD SINGLE LINE DIAGRAM SHEET 2 OF 5	2	24MAY24	TIER ORDER REVISED.					
2000-F00-SLD-EL-10001	OVERALL SITEWIDE SINGLE LINE DIAGRAM	1	05APR24	TIER ORDER REVISED. REISSUED FOR CONSTRUCTION					
2000-F00-STD-EL-10001	GENERAL NOTES AND STANDARD DRAWINGS INDEX	0	07MAR24	APPROVED FOR CONSTRUCTION					

NORTHERN STAR RESOURCES LIMITED

INFORMATION AND REPRESENTATIONS ON THIS DRAWING ARE THE INTELLECTUAL PROPERTY OF PRIMERO UNLESS SPECIFICALLY IDENTIFIED OTHERWISE. ALL RIGHTS INCLUDING USE RESERVED

PRIMERO
primero.com.au | DESIGN | CONSTRUCT | OPERATE

PRIMERO PROJECT NUMBER: 23517

PROJECT: NORTHERN STAR RESOURCES LTD
KCGM GROWTH PROJECT

TITLE: GENERAL FIMISTON SITE
F00-SW-010 33kV SWITCHBOARD
SINGLE LINE DIAGRAM SHEET 1

SHEET	SCALE	DRG No.	REVISION
A1	NONE	2000-F00-SLD-EL-10002	5

O:\CAD PROJECTS\23S NORTHERN STAR RESOURCES LTD\23517 KCGM GROWTH PROJECT\03 DELIVERABLES\ELV\F00 - GENERAL FIMISTON SITE\2000-F00-SLD-EL-10002.DWG 14SEP26 7:06AM ROBIN.LAW