F13-PO-402
RECYCLE CRUSHER C
LUBRICATION PUMP 2

11 kW

EOL
ALLEN BRADLEY
E300 SENSING MODULE

TOROID
NOTE 4

0.5-30A
193-ESM-I-30A-T

Q102
32A
LINE 145
LINE 114
LINE 142
C70
C71
F106
2A
32A
F108
6A
32A
1061
1062
1063
LLI
RD
K116

N
FROM LINE 105

Q116
2A
1160
K124
1166
K116
240VN
MAIN CONTACTOR
[102,103,104]
K117
DRIVE ISOLATED RELAY
123

24VDC
CONTROL
TO NEXT
MODULE
Q120
4A
1200
LINE 146
COMMISSIONING
BYPASS
K117
1230
LOS
START
1242
1262
1282
RELAY 0
IN 0
IN 1
IN 2
IN 3
RELAY 1
1246
K124
START RELAY
116
LOS HEALTHY
FIELD START
SPARE INPUT
SPARE INPUT
SPARE OUTPUT

ALLEN BRADLEY
E300 I/O MODULE
193-EIO-GP-42-24D

0VDC
CONTROL
TO NEXT
MODULE
0VDC

THERMISTOR INPUT
(NOT USED)

E300 HMI MODULE
193-EOS-SCS
(DOOR MOUNTED)
BUS
BUS — BUS — BUS
BUS

E300 COMMS MODULE
ANYBUS-E300-MBTCP
ENET 1
ENET 2
CAT6 — CAT6 — CAT6
TO MCC ETHERNET SWITCH
F13-ETH-325
2000-F13-TER-IC-10162

(DOOR MOUNTED)
K142
TEST
RESET
TRIP
C70
C71
LINE 106
Q102
1453
MCCB SHUNT TRIP COIL
102
LINE 121
EARTH LEAKAGE RELAY
NHP RD1E21HBN (IME DELTA 72-SJ)
NOTE 5

CABLE ZONE
24VDC TERMINALS

Q120	4A	F13SW014-2720
1		F13SW014-2730
2		F13SW014-2730
3		F13PO402-1200
4		F13PO402-1230
5		F13PO402-1230
6		F13PO402-1242
7		F13PO402-1262
8		F13PO402-1282
9		
10		
11		
12		
13		
14		
15		EARTH

NOTE 2

24VDC
LOOPED POWER
NEXT MODULE
PREV MODULE
COMMISSIONING
BYPASS
GNYE

F13PO402LCS-C1
1.5 mm² 4C+E

F13PO402-LCS
LOCAL CONTROL STATION
LOS
START
GNYE

NOTES

1. TERMINALS ON TERMINAL STRIPS ABOVE 50VAC SHALL HAVE A SEPARATE PERSPEX SHROUD AND SHALL BE LABELLED "DANGER xxxVAC".
2. WIRE NUMBER FERRULES ON TERMINAL STRIP SHALL BE PREFIXED WITH EQUIPMENT NUMBER e.g. F13PO402-1200, UNLESS OTHERWISE NOTED.
3. EACH WIRE SHALL BE IDENTIFIED AT BOTH ENDS WITH FERRULES.
4. NHP TDGB2
   IN:70A IΔN MIN:0.03A TOROID TO SUIT CABLE DIAMETER.
5. EARTH LEAKAGE RELAY (ELV) USER INTERFACE TO BE MOUNTED ON MCC MODULE DOOR. RELAY ENERGISED (NORMALLY CLOSED CONTACT OPEN) IN NORMAL OPERATION.

LEGEND

- 00/01/00 — DCS DIGITAL INPUT
- 00/02/00 — DCS DIGITAL OUTPUT
- MCC TERMINAL
- VSD TERMINAL
- FIELD TERMINAL
- DCS OR I/O TERMINAL
- MARSHALLING TERMINAL
- DEVICE TERMINAL
- INDICATION LAMP cc = COLOUR

TERMINATION LEGEND

Q120	4A	F13SW014-2xxx
1		F13SW014-2xxx
2		F13SW014-2xxx
3		F13PO402-1200
4		F13PO402-1230
5		F13PO402-1230
6		EARTH

RD
BK
GNYE

CORE COLOUR/ IDENTIFIER
BARRIER
FERRULE
JUMPER/DISCONNECT/ FUSE/EARTH
TERMINAL No.
DESTINATION

2000-F13-SCM-EL-10422_Rev1

F13-SW-014 F13-PO-402 recycle crusher c lubrication pump 2 schematic and termination diagram

O:\CAD PROJECTS\235 NORTHERN STAR RESOURCES LTD\23517 KCGM GROWTH PROJECT\03 DELIVERABLES\EL\F13 - MILLING & CLASSIFICATION\2000-F13-SCM-EL-10422.DWG 14 JUL 25 12:36PM HOTSEAT04