24VDC SUPPLY FROM Q216
INCOMER MODULE
2000-F13-SCM-EL-10903

F13-SW-003

2160
2170

Q104
6A

104

2000-F13-SCM-EL-10902
LINE 108

COM 2	1/B/2:14	1/B/2:13	VAMP 321 ARC SENSOR RELAY	COM 1

TIER F00 CONTROL PANEL

I/O TERMINALS	FUNCTION
1/B/2:1	GND
1/B/2:2	+24V
1/B/2:5	T1
1/B/2:6	
1/B/2:7	A1
1/B/2:8	
1/B/2:9	
1/B/2:10	SF
1/B/2:11	
1/B/2:12	

2000-F13-SCM-EL-10902
LINE 174

SLOT 2	
2/B/1:15	T2
2/B/1:16	
2/B/2:3	LINE SIDE ACB
2/B/2:4	

2000-F13-SCM-EL-10902
LINE 191

SLOT 9	
9/C/1	9/C/1

NOTE 3.

CAT6 - CAT6

F13-ETH-121
TO MCC ETHERNET SWITCH
2000-F13-TER-IC-10121

VX001

VAMP 1

COM 1	X2-1	X2-2	VAMP 10LDSE I/O UNIT	COM 2

TIER 1F CABLE ZONE	
ADDRESS 001	
DIP SWITCHES - SW1	
SW8	ON
SW7	OFF
SW6	OFF
SW5	OFF
SW4	OFF
SW3	ON
SW2	ON
SW1	ON
ARC SENSOR CONNECTION	
I/O TERMINALS	ARC SENSOR ID
X1:1 / X1:2	1F-05
X1:3 / X1:4	1F-09
X1:5 / X1:6	1F-13
X1:7 / X1:8	1F-17
X1:9 / X1:10	1F-21
X1:11 / X1:12	2F-01
X1:13 / X1:14	2F-05
X1:15 / X1:16	2F-09
X1:17 / X1:18	2F-13
X1:19 / X1:20	

VAMP 2

TIER 3F CABLE ZONE	
ADDRESS 002	
DIP SWITCHES - SW1	
SW8	OFF
SW7	ON
SW6	OFF
SW5	OFF
SW4	OFF
SW3	ON
SW2	ON
SW1	ON
ARC SENSOR CONNECTION	
I/O TERMINALS	ARC SENSOR ID
X1:1 / X1:2	2F-17
X1:3 / X1:4	2F-21
X1:5 / X1:6	3F-01
X1:7 / X1:8	3F-05
X1:9 / X1:10	3F-09
X1:11 / X1:12	3F-13
X1:13 / X1:14	3F-17
X1:15 / X1:16	3F-21
X1:17 / X1:18	4F-01
X1:19 / X1:20	4F-05

VAMP 3

TIER 5F CABLE ZONE	
ADDRESS 003	
DIP SWITCHES - SW1	
SW8	ON
SW7	ON
SW6	OFF
SW5	OFF
SW4	OFF
SW3	ON
SW2	ON
SW1	ON
ARC SENSOR CONNECTION	
I/O TERMINALS	ARC SENSOR ID
X1:1 / X1:2	4F-11
X1:3 / X1:4	5F-01
X1:5 / X1:6	5F-05
X1:7 / X1:8	5F-11
X1:9 / X1:10	6F-01
X1:11 / X1:12	6F-04
X1:13 / X1:14	6F-07
X1:15 / X1:16	6F-10
X1:17 / X1:18	6F-14
X1:19 / X1:20	7F-01

VAMP 4

TIER 8F CABLE ZONE	
ADDRESS 004	
DIP SWITCHES - SW1	
SW8	OFF
SW7	OFF
SW6	ON
SW5	OFF
SW4	OFF
SW3	ON
SW2	ON
SW1	ON
ARC SENSOR CONNECTION	
I/O TERMINALS	ARC SENSOR ID
X1:1 / X1:2	6F-19
X1:3 / X1:4	6F-22
X1:5 / X1:6	8F-01
X1:7 / X1:8	8F-05
X1:9 / X1:10	8F-09
X1:11 / X1:12	8F-13
X1:13 / X1:14	8F-17
X1:15 / X1:16	8F-21
X1:17 / X1:18	
X1:19 / X1:20	

VAMP 5

TIER 8R CABLE ZONE	
ADDRESS 005	
DIP SWITCHES - SW1	
SW8	ON
SW7	OFF
SW6	ON
SW5	OFF
SW4	OFF
SW3	ON
SW2	ON
SW1	ON
ARC SENSOR CONNECTION	
I/O TERMINALS	ARC SENSOR ID
X1:1 / X1:2	8R-01
X1:3 / X1:4	8R-07
X1:5 / X1:6	8R-11
X1:7 / X1:8	8R-15
X1:9 / X1:10	
X1:11 / X1:12	
X1:13 / X1:14	
X1:15 / X1:16	
X1:17 / X1:18	
X1:19 / X1:20	

VAMP 6

TIER 6R CABLE ZONE	
ADDRESS 006	
DIP SWITCHES - SW1	
SW8	OFF
SW7	ON
SW6	ON
SW5	OFF
SW4	OFF
SW3	ON
SW2	ON
SW1	ON
ARC SENSOR CONNECTION	
I/O TERMINALS	ARC SENSOR ID
X1:1 / X1:2	6R-01
X1:3 / X1:4	6R-05
X1:5 / X1:6	6R-09
X1:7 / X1:8	6R-13
X1:9 / X1:10	6R-17
X1:11 / X1:12	6R-21
X1:13 / X1:14	5R-01
X1:15 / X1:16	5R-04
X1:17 / X1:18	5R-07
X1:19 / X1:20	5R-11

VAMP 7

TIER 4R CABLE ZONE	
ADDRESS 007	
DIP SWITCHES - SW1	
SW8	ON
SW7	ON
SW6	ON
SW5	OFF
SW4	OFF
SW3	ON
SW2	ON
SW1	ON
ARC SENSOR CONNECTION	
I/O TERMINALS	ARC SENSOR ID
X1:1 / X1:2	4R-01
X1:3 / X1:4	4R-05
X1:5 / X1:6	4R-09
X1:7 / X1:8	4R-13
X1:9 / X1:10	3R-01
X1:11 / X1:12	3R-04
X1:13 / X1:14	3R-08
X1:15 / X1:16	3R-13
X1:17 / X1:18	2R-19
X1:19 / X1:20	

VAMP 8

TIER 2R CABLE ZONE	
ADDRESS 008	
DIP SWITCHES - SW1	
SW8	OFF
SW7	OFF
SW6	OFF
SW5	ON
SW4	OFF
SW3	ON
SW2	ON
SW1	ON
ARC SENSOR CONNECTION	
I/O TERMINALS	ARC SENSOR ID
X1:1 / X1:2	2R-01
X1:3 / X1:4	2R-04
X1:5 / X1:6	2R-07
X1:7 / X1:8	2R-13
X1:9 / X1:10	1R-01
X1:11 / X1:12	1R-05
X1:13 / X1:14	1R-09
X1:15 / X1:16	1R-13
X1:17 / X1:18	1R-17
X1:19 / X1:20	1R-21

NOTE 5

F13-SW-103

VAMP 9

COM 1	X2-1	X2-2	VAMP 10LDSE I/O UNIT	COM 2

NOTE 5

TIER 00F CABLE ZONE	
ADDRESS 009	
DIP SWITCHES - SW1	
SW8	ON
SW7	OFF
SW6	OFF
SW5	ON
SW4	OFF
SW3	ON
SW2	ON
SW1	ON
ARC SENSOR CONNECTION	
I/O TERMINALS	ARC SENSOR ID
X1:1 / X1:2	00F-05
X1:3 / X1:4	01F-07
X1:5 / X1:6	01F-10
X1:7 / X1:8	01F-15
X1:9 / X1:10	00F-20
X1:11 / X1:12	1F-01
X1:13 / X1:14	1F-05
X1:15 / X1:16	1F-09
X1:17 / X1:18	1F-12
X1:19 / X1:20	1F-15

1

NOTES

1. CABLE NUMBER FOR ARC FLASH SENSOR VA1DA SHALL BE THE EQUIPMENT NUMBER FOLLOWED BY COM FOR COMMUNICATION AND A SEQUENTIAL NUMBER e.g. F13SW003-COMx.
2. EACH CABLE SHALL BE IDENTIFIED AT BOTH ENDS WITH CABLE NUMBER.
3. VAMP 321 ARC FAULT PROTECTION RELAY SHALL BE MOUNTED TO THE DOOR OF THE PANEL INCOMER CONTROL CUBICLE.
4. VAM 10LDSE INTERFACE SHALL BE MOUNTED ON THE CABLE ZONE DOOR.
5. MAXIMUM 16 VAM10LDSE I/O UNITS IN SERIES.
6. MAXIMUM LENGTH OF VX001 CABLE BETWEEN 2 UNITS (I/O UNITS OR VAMP321 UNIT) IS 30m & TOTAL LENGTH OF THE BUS CABLE FROM THE START TO THE END OF 100m SHALL NOT BE EXCEEDED.

LEGEND

F13SW014-COMx

CABLE MARKER LABEL

24VDC SUPPLY CABLE

COMMUNICATION CABLE

DIP SWITCHES KEY VAMP 10LDSE		
	ON	OFF
SW8	1	0
SW7	2	0
SW6	4	0
SW5	8	0
SW4	16	0
SW3	L>	L> + I>
SW2	LATCH	NON LATCHING
SW1	L> INT	L> EXT

L = LIGHT / I = CURRENT

DRG No.	REFERENCES
2000-F13-SLD-EL-10901	F13-SW-003 415V MCC SINGLE LINE DIAGRAM SHEET 1
2000-F00-STD-EL-10001	GENERAL NOTES AND STANDARD DRAWINGS INDEX

REV	DATE	DESCRIPTION	DRAW	CHECK	DESIGN	TECH APP	PROJ APP
1	20AUG25	FAT REDLINES INCORPORATED					
0	07AUG24	APPROVED FOR CONSTRUCTION					

NORTHERN STAR RESOURCES LIMITED

PRIMERO
primero.com.au | DESIGN | CONSTRUCT | OPERATE

PRIMERO PROJECT NUMBER: 23517

INFORMATION AND REPRESENTATIONS ON THIS DRAWING ARE THE INTELLECTUAL PROPERTY OF PRIMERO UNLESS SPECIFICALLY IDENTIFIED OTHERWISE. ALL RIGHTS INCLUDING USE RESERVED

PROJECT: NORTHERN STAR RESOURCES LTD
KCGM GROWTH PROJECT

TITLE: MILLING & CLASSIFICATION - F13-SW-003
F13-SW-003 ARC FLASH DETECTION SYSTEM
SCHEMATIC DIAGRAM

SHEET	SCALE	DRG No.	REVISION
A1	NONE	2000-F13-SCM-EL-10904	1

O:\CAD PROJECTS\235 NORTHERN STAR RESOURCES LTD\23517 KCGM GROWTH PROJECT\03 DELIVERABLES\EL\F13 - MILLING & CLASSIFICATION\2000-F13-SCM-EL-10904.DWG 25SEP25 12:51PM HOTSEAT04