240VAC

240VAC UPS SUPPLY
FROM F13-DB-203
2000-F13-TLD-EL-10032

N

Q002
25A

Q002

Q004
6A
30 mA

SPARE
240VAC POWER SUPPLY

Q006
6A
30 mA

SPARE
240VAC POWER SUPPLY

Q008
6A
30 mA

SPARE
240VAC POWER SUPPLY

Q012
6A

0120

240VAC - 54VDC
POWER SUPPLY
240W

012N

F13RIO022-PS3
MEAN WELL
NDR240-48
POWER SUPPLY

0134

(+54VDC)

(0VDC)

0135

Q017
6A

0172

FIELD MODBUS SWITCH
NOTE 4

0VDC
1

F13-ETH-243
CISCO
IE-3300-8P2S-E
FIELD MODBUS SWITCH

Q021
6A

0212

CCTV PoE SWITCH
NOTE 4

0VDC
2

F13-ETH-244
CISCO
IE-3300-8P2S-E
CCTV POE SWITCH

Q024
6A

0242

PoE SWITCH

F13ETH142-POE01
PLANET
IPOE-470-12V

0020

Q028
16A

0280

Q028N

Q029
16A

0296

Q029N

F13RIO022-PS1
PHOENIX
QUINT4-PS/1AC/24DC/40
240VAC/24VDC, 40A POWER SUPPLY

DC OK
13
14
PS1+24VDC
F13RIO022PS1
POWER SUPPLY 1
24VDC HEALTHY
TO 2000-F13-TER-IC-10632

F13RIO022-PS2
PHOENIX
QUINT4-PS/1AC/24DC/40
240VAC/24VDC, 40A POWER SUPPLY

DC OK
13
14
PS2+24VDC
F13RIO022PS2
POWER SUPPLY 2
24VDC HEALTHY
TO 2000-F13-TER-IC-10632

(+24VDC)

(0VDC)

0352

0357

0351

0358

F13RIO022-RM
PHOENIX
QUINT-ORING/24DC/2x40/1x80
REDUNDANCY MODULE

0424

(+24VDC)

(0VDC)

Q045
40A

0450

0425

0450

24VDC SUPPLY
CONT'D ON LINE 51

(+24VDC)

0450

24VDC SUPPLY
CONT'D FROM LINE 48

0425

(0VDC)

24VDC TRANSIENT
SURGE DIVERTER

F13RIO022-SD
TRANSTECH
TLP-SF40-1P-24VDC
SURGE FILTER

0563

(+24VDC)

(0VDC)

0566

Q057
40A

0570

Q060
6A

0600

S060
RH DOOR

0605

WH

0VDC
1

PANEL LIGHTS

S062
CENTRE DOOR

0625

WH

S064
LH DOOR

Q070
6A

Q070

TS2-1

F13LU413-JB01
2000-F13-TER-IC-10632

TS2-2

0VDC
2

TCV13629
F13-LU-413 SAG MILL MAIN BEARINGS
LUBRICATION SYSTEM HEAT EXCHANGER
TEMPERATURE CONTROL VALVE
24VDC POWER SUPPLY

Q072
2A

Q072

TS4-29

F13LU413-JB02
2000-F13-TER-IC-10640

TS4-30

0VDC
3

FIT13640
F13-LU-413 SAG MILL MAIN BEARINGS
LUBRICATION SYSTEM FLOW DIVIDER
FEED FLOW INDICATING TRANSMITTER
24VDC POWER SUPPLY

Q074
2A

Q074

YD24703A
2000-F13-TER-IC-10635

0VDC
4

YD24703A
F13-LU-413 SAG MILL MAIN BEARINGS
LUB. SYSTEM INFRARED FLAME DETECTOR A
24VDC POWER SUPPLY

Q076
2A

Q076

YD24703B
2000-F13-TER-IC-10635

0VDC
5

YD24703B
F13-LU-413 SAG MILL MAIN BEARINGS
LUB. SYSTEM INFRARED FLAME DETECTOR B
24VDC POWER SUPPLY

Q078
2A

0VDC
6

SPARE
24VDC POWER SUPPLY

Q080
2A

0VDC
7

SPARE
24VDC POWER SUPPLY

0570

24VDC SUPPLY
CONT'D ON LINE 101

0566

NOTES

1. TERMINALS ON TERMINAL STRIPS ABOVE 50VAC SHALL HAVE A SEPARATE PERSPEX SHROUD AND SHALL BE LABELLED "DANGER xxxVAC".
2. WIRE NUMBER FERRULES ON TERMINAL STRIP SHALL BE PREFIXED WITH EQUIPMENT NUMBER e.g. F13RIO022-xxxx.
3. EACH WIRE SHALL BE IDENTIFIED AT BOTH ENDS WITH FERRULES.
4. FOR NETWORK CONNECTION & BUS CABLING DETAILS REFER TO RIO PANEL COMMUNICATIONS TERMINATION DIAGRAMS.
5. INSTRUMENT EARTH BAR TO BE BONDED TO MAIN EARTH BAR WITH SOLID COPPER LINK.

LEGEND

- FIELD TERMINAL
- DCS OR I/O TERMINAL
- 0VDC TERMINAL FOR 24VDC
- 0VDC TERMINAL FOR 54VDC
- DEVICE TERMINAL
- INDICATION LAMP (cc = COLOUR)
- EARTH BAR
- INSTRUMENT EARTH BAR

2000-F13-SCM-IC-10631_Rev2

SAG mill F13-RIO-022 SAG mill field n-IO panel schematic diagram sheet 1

O:\CAD PROJECTS\235 NORTHERN STAR RESOURCES LTD\23517 KCGM GROWTH PROJECT\03 DELIVERABLES\IC\F13 - MILLING & CLASSIFICATION\2000-F13-SCM-IC-10631.DWG 26AUG26 1:13PM