

Procedural Retro Instrument Encoding in the BTRON: Synthesis Topology, Waveform Modelling, and Extensible Shim Architecture for the Lil Cu 64 B-Game Engine

Maxim Sokhatsky (Namdak Tonpa)

Synrc Research Center / Groupoid Infinity / BTRON Cleanroom Working Group

Kyiv, Ukraine

maxim@synrc.com

October 2026

Abstract

The BTRON B-Game Engine (Lil Cu 64 / リル・キューブ64, `src/demo/`) implements a **zero-asset procedural audio architecture** in which every acoustic or electro-mechanical instrument is encoded as a self-contained, stateless *Sound Shim*—a deterministic DSP node graph instantiated at runtime via the W3C Web Audio API [15] in the HTML5 prototype (`index.html`) and ported to native C via the VirtIO Sound stack (`lilcu64_wa.c`) for the BTRON native application. The library carries 23 shim functions whose total audio-asset disk footprint is exactly zero bytes; all timbres emerge entirely from first-principles signal processing: oscillators, noise buffers, biquad filters, wave-shapers, and gain automations.

This article makes two primary contributions. **First**, we document all 23 shims precisely as implemented in `index.html`, including exact frequency constants, oscillator waveform types, biquad filter parameters, and ADSR envelope timings—providing the 1:1 isomorphic reference required to port the shim library to the native BTRON `src/demo/` application. **Second**, we provide a rigorous six-step recipe for extending the library with new retro instruments, grounded in the BTRON Sound Shim Compatibility Contract and the Zero Memory Leak Theorem.

We situate the encoding strategies within the canonical academic literature on Karplus-Strong string synthesis [2], frequency-modulation synthesis [1], digital waveguide networks [3], physical modelling of the Fender Rhodes [6, 7], and acoustic characterisation of the Gibson archtop guitar [8–10].

Keywords—BTRON, Sound Shim, Procedural Audio, Karplus-Strong, FM Synthesis, Fender Rhodes, Gibson L-5, Web Audio API, Retro Instruments, VirtIO Sound, Lil Cu 64, DSP, Comb Filter.

1 Introduction

The BTRON Lil Cu 64 demoscene specification [21] establishes an **Audio-Visual Shim Principle**: every fundamental 3D kinematic action of the mascot character maps 1-to-1 to a deterministic procedural DSP algorithm. This eliminates all external audio assets and delivers four properties critical for the embedded native port:

1. **Zero loading latency**: shims are instantiated in-flight at $t_0 = \text{AudioContext.currentTime} + \Delta$.
2. **Zero byte footprint**: no WAV, OGG, or AIFF files anywhere in the repository.
3. **Perfect phase-lock**: the `AudioContext.currentTime` clock is shared between the 60 FPS render loop and the audio scheduler.
4. **Sub-100 KB code size**: the entire shim engine, including all 23 instrument generators, the 4-track score sequencer, and the master bus, compiles to under 100 KB of JavaScript or equivalent C [21].

The article is structured as follows. Section 2 reviews the synthesis paradigms. Section 3 describes the audio lifecycle infrastructure. Section 4 documents all 23 shims 1:1 with `index.html`. Sections 5 and 6 provide deep physical-modelling analyses of `shimGuitar` (Gibson L-5) and `shimFloat` (Fender Rhodes). Section 7 covers the DSP primitives. Section 9 provides the six-step extension recipe. Section 8 maps shims to the four level score tracks.

2 Background: Synthesis Paradigms

2.1 Additive Synthesis

Additive synthesis directly sums K sinusoidal partials [5]:

$$y(t) = \sum_{k=1}^K A_k(t) \sin(2\pi f_k t + \phi_k) \quad (1)$$

In BTRON, `shimPulseSquash` (6 sine partials), `shimPulseBell` (8 sine partials), and `shimGrandPiano` (3 harmonics) all employ this model with individuated ADSR envelopes $A_k(t)$ per partial.

2.2 Subtractive Synthesis

A spectrally rich oscillator waveform (sawtooth, triangle, pulse, noise) is filtered by resonant biquad filters [15]. The canonical biquad transfer function is:

$$H(z) = \frac{b_0 + b_1 z^{-1} + b_2 z^{-2}}{1 + a_1 z^{-1} + a_2 z^{-2}} \quad (2)$$

The guitar (`shimGuitar`), cello (`shimCello`), industrial bass (`shimIndustrialBass`), cyber lead (`shimCyberLead`), and flute (`shimSaxFlute`) all employ subtractive filtering.

2.3 FM Synthesis

Chowning’s 1973 model [1] uses a modulator oscillator to vary the instantaneous frequency of a carrier:

$$y(t) = A_c \sin(2\pi f_c t + I(t) \sin(2\pi f_m t)) \quad (3)$$

The spectral content is governed by Bessel functions $J_n(I)$. Inharmonic frequency ratios ($r = f_m/f_c \notin \mathbb{Z}$) produce bell-like metallic timbres. `shimPulseBell` uses the additive superposition of 8 sine partials rather than a feedback-FM topology, but the target timbre (golden spiritual bell / chi drone) is equivalent to a 2-Op FM bell with $r \approx 2.76$.

2.4 Karplus-Strong and Comb Filter Synthesis

Karplus and Strong [2] showed that feeding a noise burst into a delay loop of length $N = f_s/f_0$ with a one-pole lowpass averager produces a convincing plucked-string tone. Smith’s digital waveguide interpretation [3] identifies the feedback delay as a bi-directional travelling wave model. The BTRON guitar shim uses an implicit comb resonance via the body lowpass filter sweep and frequency decay [2].

2.5 WaveShaper Non-Linear Saturation

The BTRON industrial instrument suite (`shimIndustrialBass`, `shimCyberLead`,

`shimIndustrialKick`, `shimIndustrialSnare`) applies a Chebyshev-inspired soft-saturation curve [13]:

$$C(x) = \frac{(3+k) \cdot x \cdot 20^\circ}{\pi + k|x|} \quad (4)$$

where k is the distortion amount (default $k = 25$), $x \in [-1, 1]$, and $20^\circ = 20\pi/180$. The curve is precomputed once and cached in `_distCurve` for zero per-shim allocation cost.

3 Audio Lifecycle Infrastructure

3.1 Global State Variables

The BTRON shim engine is bootstrapped with three module-level globals:

Listing 1: Audio lifecycle state (index.html, line 3184).

```
1 window._trackOscillators = [];
2 window._trackTimeouts = [];
3 window.currentActiveTrack = 0;
```

Every oscillator, buffer source, and scheduled timeout created by any shim is registered into these arrays, enabling deterministic cleanup on track stop.

3.2 registerTrackOsc

Listing 2: `registerTrackOsc` — push into GC tracking array (line 3188).

```
1 function registerTrackOsc(osc) {
2   if (window._trackOscillators)
3     window._trackOscillators.push(osc);
4 }
```

3.3 scheduleTrackTimeout

Listing 3: `scheduleTrackTimeout` — cancellable timeout (line 3194).

```
1 function scheduleTrackTimeout(fn, delayMs) {
2   const tid = setTimeout(fn, delayMs);
3   if (window._trackTimeouts)
4     window._trackTimeouts.push(tid);
5   return tid;
6 }
```

3.4 stopAllTracks

Listing 4: `stopAllTracks` — deterministic graph teardown (line 3202).

```
1 window.stopAllTracks = function (immediate=true, isLoop=
2   false) {
3   window._trackTimeouts.forEach(t => clearTimeout(t));
4   window._trackTimeouts = [];
5   if (immediate) {
6     window._trackOscillators.forEach(osc => {
7       try { osc.stop(); osc.disconnect(); } catch (
8         e){}
9     });
10  }
```

```

8   }
9   window._trackOscillators = [];
10  };

```

3.5 Noise Buffer Primitive

A deterministic 2-second white-noise buffer is lazily allocated and reused across all percussive shims (`shimSnare`, `shimHiHat`, `shimSaxFlute`, `shimViolin`, `shimTimpani`, `shimPedalSwoosh`, `shimIndustrialSnare`):

Listing 5: `getNoiseBuffer` — single shared noise buffer (line 3508).

```

1  let _noiseBuffer = null;
2  function getNoiseBuffer(ctx) {
3    if (!_noiseBuffer) {
4      const bufferSize = ctx.sampleRate * 2;
5      _noiseBuffer = ctx.createBuffer(1, bufferSize,
6                                     ctx.sampleRate);
7
8      const data = _noiseBuffer.getChannelData(0);
9      for (let i = 0; i < bufferSize; i++)
10         data[i] = Math.random() * 2 - 1;
11    }
12    return _noiseBuffer;
13  }

```

3.6 WaveShaper Cache

Listing 6: `getDistortionCurve` — cached Chebyshev WaveShaper (line 3715).

```

1  let _distCurve = null;
2  function getDistortionCurve(amount = 25) {
3    if (!_distCurve) {
4      const n = 44100, deg = Math.PI / 180;
5      _distCurve = new Float32Array(n);
6      const maxVal = (((3+amount)*20*deg)/(Math.PI+
7          amount));
8      for (let i = 0; i < n; ++i) {
9        const x = (i*2)/n - 1;
10        _distCurve[i] = (((3+amount)*x*20*deg)/
11            (Math.PI+amount*Math.abs(x))) / maxVal;
12      }
13      return _distCurve;
14    }
15  }

```

Definition 1 (BTRON Sound Shim Compatibility Contract). A function $S(t_0, \dots)$ is a valid BTRON Sound Shim if and only if:

1. **Stateless:** no global audio state read/written beyond *AudioContext* and the registration arrays.
2. **Self-contained:** all *AudioNode* objects are created, connected, and started within a single synchronous call.
3. **Garbage-collectible:** every oscillator/source node is passed to `registerTrackOsc()`.
4. **Silent on error:** the entire body is wrapped in `try{ } catch(e){ }`.

Theorem 1 (Zero Memory Leak Property). If every shim satisfies the Compatibility Contract, then for any track stop at time t_{stop} , the call `stopAllTracks()` guarantees: $\lim_{t \rightarrow t_{\text{stop}}^+} |\mathcal{N}(t)| = 0$, where $\mathcal{N}(t)$ is the set of live

AudioNode objects. Proof sketch: `stopAllTracks` calls `osc.stop()` and `osc.disconnect()` on every registered node and clears the array; V8/JSC GC reclaims all objects with no live references. $\square$

4 The BTRON Shim Palette: 23 Instruments

Table 1 presents all 23 shims exactly as implemented in `index.html`. The “Index” column gives the [SHIM N] comment label used in the source.

5 Deep Dive: Gibson L-5 Hollowbody (shimGuitar)

5.1 Physical Acoustics

The Gibson L-5 archtop, introduced in 1922, is the archetypal jazz hollowbody guitar modelled on Kazumi Watanabe’s instrument in *Green Caterpillar*. Three physical mechanisms define its tone:

1. **String inharmonicity:** Steel wound strings behave as stiff bars; partial frequencies deviate from kf_0 by a stiffness coefficient B [11]:

$$f_k = kf_0 \sqrt{1 + Bk^2}, \quad B = \frac{\pi^3 E d^4}{64 T L^2} \quad (5)$$

2. **Helmholtz air resonance A_0 :** The f -holes admit air flow; the lowest resonance lies at ~ 100 Hz, equivalent to a second-order bandpass resonator [9]:

$$H_{\text{body}}(s) = \sum_n \frac{G_n \omega_n^2}{s^2 + (\omega_n/Q_n)s + \omega_n^2} \quad (6)$$

3. **Top-plate mode T_1 :** The carved spruce plate resonates at ~ 150 – 200 Hz [10], adding warmth and volume to the mid-range.

5.2 BTRON Implementation (shimGuitar)

The actual implementation in `index.html` (line 3623) uses the following topology:

Listing 7: `shimGuitar`: Watanabe hollowbody (`index.html` line 3623).

```

function shimGuitar(timeOffset=0, notes=null, volMul
=1.0) {
  // Default phrase: single D5 note 280ms
  const phrase = notes || [{f:587.33, d:0.28, v:0.16, t
:0}];
  phrase.forEach(n => {
    const noteT = startT + n.t;
    const osc = c.createOscillator();
    registerTrackOsc(osc);
    osc.type = 'triangle'; // warm jazz body tone
    osc.frequency.setValueAtTime(n.f, noteT);
    if (n.slide) // optional portamento

```

Table 1: BTRON 23-Shim Sound Bank (1:1 with `index.html`)

No.	Shim Function	Acoustic Analogue	Exact DSP Topology
1A	shimPulseSquash	Singing harmonic ascending triad	6 sine OSCs at C4–E6; pitch +3% glide (10ms), exp. decay 1.4–2.4 s
1B	shimFrogCroak	Cuica / frog croak 蛙	Sawtooth+triangle pitch scoop; bandpass formant $f_c = 2.2f_0$, $Q = 3.8$; 32 Hz AM pulse train at 0.031 s intervals
1C	shimPulseBell	FM spiritual bell / chi drone	8 sine OSCs at C3–C6; pitch −1.5% glide (140ms), exp. decay 1.9–3.5 s
2	shimWaddle	Fukui acoustic walking bass	Single triangle; pitch $\times 0.82$ glide over <code>duration</code> ; gain 0.12, exp. decay
3	shimFloat	Imada Fender Rhodes modal chord	4-note polyphonic sine stack; 4% pitch glide (40ms); stagger 35 ms; decay 0.5–0.75 s
4	shimDance	Crystalline cascade / arpeggio	5 sine OSCs; freq D5–F#6 ($\times \text{pitchScale}$); stagger 85 ms; exp. decay
5	shimDing	High crystal chime / ride cymbal	Single sine; default 1760 Hz (A6); attack 12 ms to 0.15 V; exp. decay
6	shimKick	Obara acoustic bass drum	Sine; freq $\times 2.2 \rightarrow \times 0.75$ exp. sweep; initial gain 0.24
7	shimSnare	Jazz snare / rimshot	Triangle 175/220 Hz $\rightarrow \times 0.65$; + bandpass noise 2400/3200 Hz $Q = 2$
8	shimHiHat	Cymbal chick / sizzle	HP noise 7500 Hz + sine ping 8400/6200 Hz (closed/open; dur 55/280 ms)
9	shimGuitar	Watanabe Gibson hollowbody	Triangle; LP sweep 2800 $\rightarrow$ 1400 Hz; gentle 15 ms pick attack
10	shimGrandPiano	Krüger/Imada concert grand	3 harmonics (sine $\times 1.0$, tri $\times 2.002$, sine $\times 3.006$); 8 ms felt-hammer attack
11	shimPedalBass	Sforzando sub-bass A0/A1	Triangle; freq $\times 0.98$ glide; gain 0.20; exp. decay over <code>duration</code>
12	shimIndustrialKick	Reznor heavy distorted sub-punch	Sine 160 $\rightarrow$ 42 Hz (22ms); + triangle 380 $\rightarrow$ 55 Hz LP 1800 Hz + WaveShaper
13	shimIndustrialSnare	Cyber clank / gated noise	BP noise 2600/3600 Hz + WaveShaper(30); + square+triangle ring 220/352 Hz
14	shimIndustrialBass	16th-note analog overdrive bass	Sawtooth + square ($\times 1.005$); LP 2600 $\rightarrow$ 420 Hz $Q = 4.5$; WaveShaper(20)
15	shimSwaratron	Dewan 8-voice ribbon cluster	8 sawtooth OSCs at $\pm \text{spreadCents}$ (default 24¢); LP 950 $\rightarrow$ 1450 $\rightarrow$ 800 Hz; 400 ms fade-in
16	shimGlitchZap	Terminal data pulse / TRON zap	Sawtooth $\times 2.5f \rightarrow$ 80 Hz; HP 1800 Hz; 80 ms
17	shimCyberLead	NIN TRON overdriven sync lead	Sawtooth + square ($\times 1.004$); LP 3800 $\rightarrow$ 1600 Hz $Q = 4$; WaveShaper(25)
18	shimSaxFlute	Imada jazz flute / melodica	Triangle + BP noise ($\times 1.8f$, $Q = 5$); LP 2400 Hz; 25 ms attack
19	shimPianoHammer	Krüger felt hammer impact	Triangle 120 $\rightarrow$ 40 Hz in 35 ms; gain 0.12; pure click transient
20	shimPedalSwoosh	Damper pedal lift / sympathetic	BP noise 450 $\rightarrow$ 280 Hz, $Q = 3.5$; gain 0.05; 80 ms rise, 400 ms total
21	shimViolin	Bowed solo/section violin	Rosin noise burst (3200 Hz BP); dual saw ($\times 1.002$ detune); LFO 5.8 Hz vibrato; peaking body EQ 520/2800 Hz
22	shimCello	Orchestral bowed/pizz. cello	Sawtooth + triangle; LP 520/1200 Hz (arco/pizz.), $Q = 2.2$; bowed or plucked ADSR
23	shimTimpani	Concert kettledrum	Sine $\times 1.55f \rightarrow f$ (50ms); + sine overtone $\times 1.48f$; + LP noise 260 Hz mallet

```

11     osc.frequency.exponentialRampToValueAtTime(
12         n.slide, noteT + n.d * 0.7);
13
14     // Body lowpass: warmth + high-freq rolloff
15     const filter = c.createBiquadFilter();
16     filter.type = 'lowpass';
17     filter.frequency.setValueAtTime(2800, noteT);
18     filter.frequency.exponentialRampToValueAtTime(
19         1400, noteT + n.d); // tonal darkening over time
20
21     const gain = c.createGain();
22     gain.gain.setValueAtTime(0.0001, noteT);
23     gain.gain.linearRampToValueAtTime(
24         n.v * volMul, noteT + 0.015); // gentle thumb-
25         pick
26     gain.gain.exponentialRampToValueAtTime(
27         0.0001, noteT + n.d);
28     osc.connect(filter);
29     filter.connect(gain);
30     gain.connect(c.destination);
31     osc.start(noteT); osc.stop(noteT + n.d);
32 }

```

Key design decisions:

- **Triangle waveform:** captures the warm, fundamental-dominated tone of a clean hollowbody pickup without the brightness of a sawtooth.
- **Lowpass sweep 2800 $\rightarrow$ 1400 Hz:** models high-frequency string damping over time (equivalent to the

H_{lp} in a Karplus-Strong loop [2]).

- **Portamento (`n.slide`):** implements jazz guitar glissando ornaments (e.g., the bebop slides in *Green Caterpillar*).

- **15 ms attack:** models the thumb-pick transient, slower than a plectrum but faster than a bowed instrument.

The signal flow is:

Triangle Osc $\xrightarrow{\text{freq sweep}}$ LP Filter (2800 $\rightarrow$ 1400 Hz) $\xrightarrow{\text{env}}$ Gain
VCA $\rightarrow$ Destination

6 Deep Dive: Fender Rhodes E-Piano (`shimFloat`)

6.1 Electro-Mechanical Acoustics

The Fender Rhodes, as played by Masaru Imada in *Green Caterpillar* (1975, Three Blind Mice), produces its distinctive tone from three coupled subsystems [6, 7]:

1. **Tine beam modes:** A clamped-free steel tine produces inharmonic partials:

$$f_n = f_1 \cdot \lambda_n^2 / \lambda_1^2, \quad f_2 / f_1 \approx 6.27 \quad (7)$$

2. **Pickup non-linearity:** electromagnetic saturation introduces odd harmonic distortion ($3f_0$ component) at high velocities [6].
3. **Felt hammer ADSR:** attack $\lesssim 10$ ms; decay $\tau \in [0.2, 0.8]$ s (treble to bass).

6.2 BTRON Implementation (shimFloat)

Listing 8: `shimFloat`: Imada Fender Rhodes / glass harp (line 3408).

```

1 function shimFloat(timeOffset=0, baseFreq=523.25,
2                   volMul=1.0, chordNotes=null,
3                   stagger=0.035, noteDuration=0.65) {
4   // Default 4-note rolling chord at baseFreq ratio
5   const ratio = baseFreq / 523.25;
6   const notes = chordNotes || [
7     {f:523.25*ratio, v:0.12*volMul, d:0.55, t:0},
8     {f:659.25*ratio, v:0.10*volMul, d:0.50, t:0.06},
9     {f:783.99*ratio, v:0.11*volMul, d:0.65, t:0.12},
10    {f:1046.50*ratio, v:0.08*volMul, d:0.75, t:0.18}
11  ];
12  notes.forEach(n => {
13    const osc = c.createOscillator();
14    registerTrackOsc(osc);
15    osc.type = 'sine'; // clean tine fundamental
16    osc.frequency.setValueAtTime(n.f*0.985, noteT);
17    osc.frequency.exponentialRampToValueAtTime(
18      n.f, noteT + 0.04); // 4ms pitch settle
19    gain.gain.setValueAtTime(0.0001, noteT);
20    gain.gain.linearRampToValueAtTime(n.v, noteT+0.03);
21    gain.gain.exponentialRampToValueAtTime(
22      0.0001, noteT + n.d);
23    // ... connect and start
24  });
25 }
```

Physical model correspondence: The -1.5% pitch glide (settling in 40 ms) mirrors the initial frequency transient of a struck tine returning to its rest frequency. The default 4-note stagger ($t = 0, 60, 120, 180$ ms) models the slight roll of an improvising jazz pianist’s wrist gesture. The pure sine waveform captures the tine’s single fundamental without the inharmonic overtone ($f_2 = 6.27f_1$); the latter is omitted in the BTRON implementation to keep the shim stateless and polyphony-safe (the inharmonic partial would require per-note FM modulation that conflicts with the note-stagger model).

7 DSP Primitives and Signal Flow

7.1 Master Audio Graph

All shims route to `AudioContext.destination` (or the `VirtIO virtio_sound_write()` ring buffer in the native port). The master bus is:




Figure 1: BTRON master audio signal flow graph.

7.2 Equal-Temperament Frequency Formula

All notes follow ISO 16 ($A4 = 440.00$ Hz):

$$f(n) = 440.0 \times 2^{(n-69)/12} \quad (8)$$

Canonical pitch references used across the shim library:

Note	Hz	Note	Hz
A0	27.50	C4	261.63
A1	55.00	A4	440.00
E2	82.41	E5	659.25
A2	110.00	G5	783.99
C3	130.81	A5	880.00
G3	196.00	E6	1318.51
C5	523.25	A6	1760.00

7.3 Dynamic Gain Staging

Dynamic	Symbol	Gain Range
Pianissimo	<i>pp</i>	$v \in [0.08, 0.12]$
Mezzo-Piano	<i>mp</i>	$v \in [0.14, 0.18]$
Mezzo-Forte	<i>mf</i>	$v \in [0.20, 0.26]$
Forte	<i>f</i>	$v \in [0.28, 0.36]$
Fortissimo	<i>ff</i>	$v \in [0.38, 0.45]$

With 7 simultaneous voices at *ff*: $7 \times 0.45 = 3.15$, handled by the master compressor.

8 Track Score Architecture

The four level score tracks use the following shim assignments:

Each track uses `scheduleTrackTimeout` to align mascot kinematic state transitions with musical milestones (see `LILCU64-DEMOSCENE.txt`, Section 5.3 for the full choreography table).

Table 2: Track Score: Shim Assignment per Level

Track	Shims Used
Track 1 鐘のキャロル 168 BPM, E minor, 3/4	shimDing (G5/F#5/E5 bells), shimWaddle (E2/B2/E3 bass), shimPulseSquash (chiptune lead), shimDance (star arpeggio), shimFloat (modal chord backing), shimKick, shimSnare, shimHiHat, shimSaxFlute (flute counterpoint), shimPulseBell (ambient drone)
Track 2 Green Caterpillar 98 BPM, F major, 4/4	shimFrogCroak (nocturnal cuica rasp), shimGuitar (Watanabe hollowbody leads), shimWaddle (Fukui upright bass), shimSaxFlute (woodwind phrases), shimPulseBell, shimPulseSquash, shimFloat (Rhodes piano), shimDing, shimKick, shimSnare, shimHiHat, shimGrandPiano, shimPedalBass
Track 3 朝日のあたる家 72 BPM, A minor, 6/8	shimGrandPiano (Krüger 6/8 arpeggios), shimPedalBass (A0/A1 rumble), shimPianoHammer (felt attacks), shimPedalSwoosh (pedal lift), shimGuitar (clean voicings), shimFloat (modal pads), shimWaddle, shimDing (A6/E7 morning star), shimPulseSquash, shimSaxFlute
Track 4 TRON Init 132 BPM, E minor, 4/4	shimIndustrialBass (16th-note overdrive ostinato), shimCyberLead (searing sync leads), shimSwarmatron (8-voice ribbon glissando), shimGlitchZap (terminal data bursts), shimIndustrialKick (heavy sub-punch), shimIndustrialSnare (metallic clank), shimHiHat, shimDing, shimPulseSquash

9 Extending the Library: Six-Step Recipe

9.1 Step 1: Acoustic Spectral Analysis

Record the target instrument dry at 44.1 kHz / 24-bit and compute the STFT:

$$X(m, k) = \sum_{n=0}^{N-1} x(n + mH) w(n) e^{-j2\pi kn/N} \quad (9)$$

From the spectrogram identify: harmonic vs. inharmonic partial structure, spectral tilt, noise components, and resonant body peaks.

9.2 Step 2: Choose the Synthesis Topology

Perceptual Feature	Module
Harmonic partials	Additive sine stack
Plucked/struck string	LP sweep on triangle (shimGuitar pattern)
Bell / metallic	Multi-sine at inharmonic ratios
Bowed sustained	Sawtooth + LFO vibrato (shimViolin)
Body resonance	Peaking BiquadFilter ($Q = 2-8$)
Noise component	getNoiseBuffer() + filter
Overdrive	getDistortionCurve() WaveShaper
Ensemble spread	$N \times$ detuned OSCs (shimSwarmatron pattern)

9.3 Step 3: Derive ADSR Parameters

Measure from the envelope of the recording:

1. t_{attack} : onset to peak (typically 2–45 ms).
2. τ_{decay} : fit $A(t) = V_{\text{peak}} e^{-t/\tau}$ post-peak.

3. S : sustain fraction ($S = 0$ for percussion).

4. t_{release} : note-off to -60 dBFS.

9.4 Step 4: Tune Filter Parameters

For each body resonance peak at f_n with -3 dB bandwidth Δf_n : set BiquadFilterNode type='bandpass' (or 'peaking'), frequency= f_n , Q= $f_n/\Delta f_n$.

9.5 Step 5: Implement and Register the Shim

Follow the BTRON signature: `shimCamelCase(timeOffset, ..., volMul)`. Wrap the body in `if (!window.soundEnabled) return;` and `try{ } catch(e){ }`. Register every node:

Listing 9: Mandatory shim skeleton for new instruments.

```
function shimMyInstrument(timeOffset=0, freq=440,
                          volMul=1.0) {
  if (!window.soundEnabled) return;
  try {
    const ctx = getAudioContext();
    const startT = ctx.currentTime + timeOffset;
    const osc = ctx.createOscillator();
    registerTrackOsc(osc); // GC registration
    // ... configure, connect, start/stop
  } catch(e) {}
}
```

9.6 Step 6: Integrate into playTrack Score

Add a new `else if (trackNum === N)` block inside `window.playTrack()` and schedule with `scheduleTrackTimeout`:

Listing 10: Tracker integration for a new shim.

```
} else if (trackNum === 5) {
  const beat = 60 / 120; // 120 BPM
  const bar = beat * 4;
  for (let b = 0; b < 8; b++)
    shimMyInstrument(bar*b, 440, 0.22);
  scheduleTrackTimeout(() =>
    shimMyInstrument(bar*8, 880, 0.18), bar*8*1000);
}
```

10 Related Work

Chowning [1] and the Yamaha DX7 defined the golden era of digital FM instrument design. Karplus and Strong [2] and Smith [3, 4] established the digital waveguide framework for plucked and bowed string synthesis, still used in commercial plugins (Applied Acoustics String Studio VS-3, AAS Chromaphone).

For the Fender Rhodes, Bank and Sujbert [6] derived a parametric tine model with acoustic validation; Petersen [7] surveyed physical modelling strategies. For archtop guitar acoustics, Elejabarrieta et al. [10] characterise plate and air cavity modes, and Caldersmith [9] analyses the f -hole

Helmholtz resonance. The bowed string friction model underlying `shimViolin` follows Serafin and Smith [12].

Farnell [14] is the canonical procedural game audio reference; the BTRON shim architecture is a Web Audio realisation of Farnell’s node-graph composition methodology, extended with the BTRON Sound Shim Compatibility Contract and the VirtIO sound streaming requirement [21].

11 Conclusion

We have presented a 1:1 isomorphic documentation of the BTRON Sound Library for Games as implemented in `index.html`, providing the precise engineering reference necessary to port the 23-shim library to the native BTRON `src/demo/` application via VirtIO Sound PCM streaming.

The key engineering results are:

1. The exact oscillator waveform types, frequency constants, filter parameters, and ADSR timings for all 23 shims, confirmed by direct code inspection of `index.html` lines 3184–4323.
2. A formal Compatibility Contract and Zero Memory Leak Theorem that guarantee zero audio resource leaks across hours of gameplay.
3. A six-step instrument extension recipe that maps acoustic spectral analysis directly into a valid, lifecycle-managed BTRON shim.
4. An academic citation framework linking each DSP topology to its physical-modelling literature origin.

References

- [1] J. M. Chowning, “The Synthesis of Complex Audio Spectra by Means of Frequency Modulation,” *J. Audio Engineering Society*, vol. 21, no. 7, pp. 526–534, 1973.
- [2] K. Karplus and A. Strong, “Digital Synthesis of Plucked String and Drum Timbres,” *Computer Music Journal*, vol. 7, no. 2, pp. 43–55, 1983.
- [3] J. O. Smith III, “Physical Modeling using Digital Waveguides,” *Computer Music Journal*, vol. 16, no. 4, pp. 74–91, 1992.
- [4] J. O. Smith III, *Physical Audio Signal Processing*. W3K Publishing, Stanford, CA, 2010. <https://ccrma.stanford.edu/~jos/pasp/>
- [5] J. W. Beauchamp (Ed.), *Analysis, Synthesis, and Perception of Musical Sounds*. Springer, New York, 2007.
- [6] B. Bank and L. Sujbert, “Generation of Longitudinal Vibrations in Piano Strings,” *J. Acoust. Soc. Amer.*, vol. 117, no. 4, pp. 2268–2278, 2005.
- [7] D. Petersen and A. Lehr, “Physical Modelling of the Fender Rhodes Electric Piano,” in *Proc. DAFx-11*, Paris, France, 2011.
- [8] B. E. Richardson and G. W. Roberts, “The Adjustment of Mode Frequencies in Guitars,” in *Proc. Stockholm Musical Acoustics Conf.*, 1983, pp. 285–302.
- [9] G. Caldersmith, “Designing a Guitar Family,” *Applied Acoustics*, vol. 46, no. 1, pp. 3–17, 1995.
- [10] M. J. Elejabarrieta, A. Ezcurra, and C. Santamaría, “Coupled Modes of the Resonance Box of the Guitar,” *J. Acoust. Soc. Amer.*, vol. 111, no. 5, pp. 2283–2292, 2002.
- [11] N. H. Fletcher and T. D. Rossing, *The Physics of Musical Instruments*, 2nd ed. Springer, New York, 1998.
- [12] S. Serafin and J. O. Smith III, “Bowed String Simulation Using an Elasto-Plastic Friction Model,” in *Proc. SMAC 03*, Stockholm, 2003, pp. 95–98.
- [13] J. Pakarinen and D. T. Yeh, “A Review of Digital Techniques for Modeling Vacuum-Tube Guitar Amplifiers,” *Computer Music Journal*, vol. 33, no. 2, pp. 85–100, 2009.
- [14] A. Farnell, *Designing Sound*. MIT Press, Cambridge, MA, 2010.
- [15] P. Adenot, H. Choi, and C. Wilson (Eds.), “Web Audio API,” W3C Recommendation, June 2021. <https://www.w3.org/TR/webaudio/>
- [16] J. Wright, “An Introduction to Chiptune,” *IEEE Consumer Electronics Mag.*, vol. 6, no. 3, pp. 74–79, 2017.
- [17] L. Hammond and J. M. Hanert, “Electrical Musical Instrument,” U.S. Patent 2,230,836, February 4, 1941.
- [18] T. Reznor and A. Ross, *TRON: Ares — Original Motion Picture Soundtrack*. Walt Disney Records, 2025.
- [19] K. Sakamura, “The TRON Project: A New Approach to OS Architecture,” *IEEE Micro*, vol. 7, no. 2, pp. 8–14, 1987.
- [20] M. Sokhatsky, “Microkernels, Unikernels, and the Actor Core,” Synrc Research Report, 2026.
- [21] M. Sokhatsky, “BTRON Lil Cu 64 Demoscene: Native OpenGL & VirtIO Sound Architecture,” B-System Technical Specification `LILCU64-DEMOSCENE.txt`, 2026.
- [22] M. Sokhatsky, “BTRON Lil Cu 64 Game Audio-Visual Architecture & Procedural Sound Engine,” B-System Technical Specification `SOUND.txt`, 2026.