

HD/4K Integrated Camera Interface Specifications

Compatible model Table

Mar. 1, 2025

Panasonic Entertainment &
Communication Co. Ltd.

Camera command

ITEM	Command Control / Response / Confirmation	Data	Data Contents Control and Response to control	UE150A	UB50/UB10	UE160	UE80/UE50/UE40/UE30	UE20/HE20	UR100	UE100	UE4	UE150/HE145	HR140	UB300	UE70series	HE75series	HE70series	HE130	HE120	HE60	HE50
Menu Up	CUP: [Data]	1	Up	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Menu Down	CDW: [Data]	1	Down	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Menu Right	CRT: [Data]	1	Right	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Menu Left	CLT: [Data]	1	Left	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Color Bar	DCB: [Data] QBR: [Data]	0 1	Camera Color Bar	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○
Color Bar Setup	DCS: [Data] QCS: [Data] UCS: [Data]	0 1	0.0% 7.5%	----	----	----	----	----	----	----	----	----	----	----	----	----	----	○	○	----	----
Menu Down	DDW: [Data]	1h Ah	1step 10step	supports only 1h(1step)	○	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	○	supports only 1h(1step)	○	○	○	○	○	○	○
Menu Enter	DIT: [data]	1	Enter	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○
Menu Left	DLT: [Data]	1h Ah	1step 10step	supports only 1h(1step)	○	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	○	supports only 1h(1step)	---	---	---	○	○	---	---
Menu Cancel	DPG: [Data]	1	Cancel	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○
Menu Right	DRT: [Data]	1h Ah	1step 10step	supports only 1h(1step)	○	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	○	supports only 1h(1step)	---	---	---	○	○	---	---
Menu Up	DUP: [Data]	1h Ah	1step 10step	supports only 1h(1step)	○	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	supports only 1h(1step)	○	supports only 1h(1step)	○	○	○	○	○	○	○
Menu On/Off	DUS: [Data] QUS: [Data] OUS: [Data]	0 1	Off On	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○
Focus(Far)	HFF	----	Move to far	----	○	----	----	----	----	----	----	----	----	○	○	○	○	----	----	○	○
Focus(Near)	HFN	----	Move to near	----	○	----	----	----	----	----	----	----	----	○	○	○	○	----	----	○	○
Focus(Stop)	HFS	----	Stop focus	----	○	----	----	----	----	----	----	----	----	○	○	○	○	----	----	○	○
Zoom(Tele)	HZT	----	Move to tele	----	○	----	----	----	----	----	----	----	----	○	○	○	○	----	----	○	○
Zoom(Stop)	HZS	----	Stop zoom	----	○	----	----	----	----	----	----	----	----	○	○	○	○	----	----	○	○
Zoom(Wide)	HZW	----	Move to wide	----	○	----	----	----	----	----	----	----	----	○	○	○	○	----	----	○	○
Focus Position Control	LFP: [Data]	555h FFh	Near Far	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Focus Speed	LFS: [Data]	0 9	Slow Fast	----	○	----	----	----	----	----	----	----	----	○	○	○	○	----	----	○	○
Zoom Position Control	LZP: [Data]	555h FFh	Wide Tele	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Zoom Speed	LZS: [Data]	0 9	Slow Fast	----	○	----	----	----	----	----	----	----	----	○	○	○	○	----	----	○	○
Focus Mode	OAF: [Data] OAF	0 1	Manual Auto	○	----	○	○	○	○	○	----	○	○	----	○	○	○	○	○	○	○
ABC/ABB SET	OAS	----	ABC/ABB Start	○	----	○	○	○	○	○	○	○	○	○	○	○	○	○	○	----	----
White Balance Mode	OAW: [Data] QAW	※	※	※	※	※	※	※	※	※	※	※	※	----	※	※	※	※	※	※	※
Focus Adjust With PTZ	OAZ: [Data] QAZ	0 1	Off On	○	----	○	○	○	○	○	----	○	○	----	○	○	○	○	○	○	○
B Pedestal	QBD: [Data] QBD	00h 1Eh - 3Ch	-150 0 - +150	----	----	----	----	----	----	----	----	----	supports only 0A (-100) 32 (+100)	----	----	----	----	supports only 0A (-100) 32 (+100)	○	----	----
B Gain	QB1: [Data] QB1	000h - 096h - 12Ch 000h - 096h - 12Ch	-150 0 - +150 UE70series, HE75series, HE70series, HE50, HE50 -30 - 0 - 30	----	----	----	----	----	----	----	----	----	○	----	○	○	○	○	○	○	○
B Gain	QBG: [Data] QGB QGB: [Data]	00h 1Eh - 3Ch 00h - 1Eh - 3Ch	-30 0 - +30 HR140, HE130, HE120 -150 - 0 - 150	----	----	----	----	----	----	----	----	○	----	----	○	○	○	○	○	○	○
B Pedestal	QBP: [Data] QBP	000h - 096h - 12Ch	-150 0 - +150	supports only -100~-+100	----	----	----	----	supports only -100~-+100	supports only -100~-+100	----	supports only -100~-+100	supports only -100~-+100	----	----	----	----	supports only -100~-+100	○	----	----
Chroma Level	QCG: [Data] QCG	00h 03h - 06h - 00h	-3 0 - +3 - 10	----	----	----	----	supports only 03h (0) 00h (10)	----	----	supports only 03h (0) 00h (10)	----	----	----	supports only 00h (-3) 06h (3)	supports only 00h (-3) 06h (3)	supports only 00h (-3) 06h (3)	----	supports only 00h (-3) 06h (3)	supports only 00h (-3) 06h (3)	supports only 00h (-3) 06h (3)
Digital Extender	ODE: [Data] ODE	0 1	Off On	○	----	----	----	----	----	----	----	0n mean x1.4	○	○	○	○	○	○	----	----	----

ITEM	Command Control / Response / Confirmation	Data	Data Contents Control and Response to control	UE150A	UB50/UB10	UE160	UE80/UE50/UE40/UE30	UE20/HE20	UR100	UE100	UE4	UE150/HE145	HR140	UB300	UE70series	HE75series	HE70series	HE130	HE120	HE60	HE50
Detail	ODT: [Data] QDT	0 1 2 0 1 2 0 1 2 3	Off Low High UE150A, UE160, UE100, UE150, HE145, HR140, UB300, UE150 Off On On UE20/HE20/UE4 0 1 2 3	○	---	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○
Error Information	QER QER: [Data]	0 1 2	Normal Fan Error Other Error -	○	---	○	○	---	○	○	---	○	supports only 0(Normal) 1(Fan Error)	supports only 0(Normal) 1(Fan Error)	---	---	---	---	supports only 0(Normal) 1(Fan Error)	---	---
Flip Status	QFS QFS: [Data]	0 1	Normal Flip	○	---	○	---	---	○	○	---	○	○	---	---	---	---	○	○	---	---
ND Filter	QFT: [Data] QFT	0h 1h 2h 3h 4h 5h 8h Fh	Clear 1/4 ND 1/16 ND 1/64 ND 1/8 ND 1/2 ND Auto ND NG	supports only 0h: Clear (Through) 1h: 1/4 ND 2h: 1/16 ND 3h: 1/64 ND	---	supports only 0h: Clear (Through) 1h: 1/4 ND 2h: 1/16 ND 3h: 1/64 ND	UE80 supports 0h: Clear (Through) 1h: 1/4 ND 2h: 1/16 ND 3h: 1/64 ND 8h: Auto ND	---	supports only 0h: Clear (Through) 1h: 1/4 ND 2h: 1/16 ND 3h: 1/64 ND 8h: Auto ND	supports only 0h: Clear (Through) 1h: 1/4 ND 2h: 1/16 ND 3h: 1/64 ND	---	supports only 0h: Clear (Through) 1h: 1/4 ND 2h: 1/16 ND 3h: 1/64 ND	supports only 0h: Clear 3h: 1/64 ND 4h: 1/8 ND	supports only 0h: Clear 1h: 1/4 ND 2h: 1/16 ND 3h: 1/64 ND 8h: Auto ND	supports only 0h: Clear 1h: 1/4 ND 2h: 1/16 ND 3h: 1/64 ND 8h: Auto ND	---	supports only 0h: Clear 3h: 1/64 ND 4h: 1/8 ND	supports only 0h: Clear 1h: 1/4 ND 2h: 1/16 ND 3h: 1/64 ND	---	---	
Gain Select	QGS: [Data] QGS	01h 04h 08h 06h 0Ch	Low Mid High S. Gain1 S. Gain2 S. Gain3	---	---	---	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Gain	QGU: [Data] QGU	02h - 08h 11h - 1Ah - 38h 80h	-6dB - 0dB 9dB - 18dB - 48dB AGC On	supports only 05 (-3dB) - 32 (42dB) , 80 (AGC On)	---	supports only 02 (-6dB) - 14 (12dB) , 80 (AGC On)	supports only 08 (0dB) -32 (42dB) , 80 (AGC On)	supports only 08 (0dB) -32 (42dB) , 80 (AGC On)	supports only 08 (0dB) -32 (42dB) , 80 (AGC On)	supports only 08 (0dB) -32 (42dB) , 80 (AGC On)	supports only 05 (-3dB) - 32 (42dB) , 80 (AGC On)	supports only 08 (0dB) -32 (42dB) , 80 (AGC On)	---	supports only 08h: 0dB-38h: 48dB 80h: AGC On	supports only 08h: 0dB-38h: 48dB 80h: AGC On	supports only 08h: 0dB-38h: 48dB 80h: AGC On	supports only 08 (0dB) -2C (36dB) , 80 (AGC On)	supports only 08 (0dB) -1A (18dB) , 80 (AGC On)	supports only 08 (0dB) -1A (18dB) , 80 (AGC On)	supports only 08 (0dB) -1A (18dB) , 80 (AGC On)	supports only 08 (0dB) -1A (18dB) , 80 (AGC On)
Horizontal Phase	QHP: [Data] QHP	000h - 3Fh	-206 - +49	○	---	---	○ (UE80) --- (UE50, UE40, UE30)	---	○	○	---	○	○	---	○	○	---	○	○	○	○
Model Number	Q1D Q1D: [Data]		Returns model No. by ASC11	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○
Request Iris F No.	Q1F Q1F: [Data]	0Eh (=14) - 1Ch (=28) - 38h (=56) - A0h (=160) - FFh UB50, UB10 08h (=8) - 0Eh (=14) - 1Ch (=28) - 38h (=56) - A0h (=160) - FFh	F1. 4 - F2. 8 - F5. 6 - F16 - Close UB50, UB10 F0. 8 - F1. 4 - F2. 8 - F5. 6 - F16 - Close	○	○	○	○	○	○	○	---	○	---	○	---	---	---	---	---	---	---
OIS	OIS: [Data] OIS	0 1 HR140 0 1 2 UE100 0 1 2 3 UE160, UE80 0 1 2 3 4 UE150A 0 1 2	Off On HR140 Off OIS Dynamic I.S. System UE100 Off OIS Hybrid (STABLE) Hybrid (PAN/TILT) UE160, UE80, UR100 Off OIS (STABLE) OIS (PAN/TILT) HYBRID (STABLE) HYBRID (PAN/TILT) UE150A Off OIS (STABLE) OIS (PAN/TILT)	○	---	○	supports only 0 (Off) , 1 (OIS (STABLE)) , 2 (OIS (PAN/TILT)) (UE80) ○ (UE50, UE40, UE30)	---	○	○	---	○	○	---	○	○	○	○	---	---	---
Synchro Scan	QMS: [Data] QMS	001h OFFh	See right	---	---	---	---	---	---	---	---	---	(59Hz) 001h (59.15Hz) - OFFh (642.21Hz) (50Hz) 001h (50.15Hz) - OFFh (535.71Hz)	(59.94Hz) 001h (59.94Hz) - OFFh (660.09Hz) (50Hz) 001h (50.00Hz) - OFFh (570.12Hz)	(59.94Hz) 001h (59.94Hz) - OFFh (660.09Hz) (50Hz) 001h (50.00Hz) - OFFh (570.12Hz)	(59.94Hz) 001h (59.94Hz) - OFFh (660.09Hz) (50Hz) 001h (50.00Hz) - OFFh (570.12Hz)	(59.94Hz) 001h (59.94Hz) - OFFh (642.21Hz) (50Hz) 001h (50.15Hz) - OFFh (535.71Hz)	(59Hz) 001h (60.17Hz) - OFFh (646.21Hz) (50Hz) 001h (50.19Hz) - OFFh (537.13Hz)	(59Hz) 001h (60.17Hz) - OFFh (644.25Hz) (50Hz) 001h (50.16Hz) - OFFh (542.42Hz)	(59Hz) 001h (60.17Hz) - OFFh (644.25Hz) (E, MC Mode1) 001h (50.16Hz) - OFFh (542.42Hz)	(N Mode1) 001h (60.17Hz) - OFFh (644.25Hz)
Start/Stop REC	QRC: [Data]	0 1 - 00h - 1Eh - 3Ch	Stop Start -150 - 0 - +150	---	○	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
R Pedestal	QRD: [Data] QRD	0 1 - 00h - 1Eh - 3Ch	0 - 0 - +150	---	---	---	---	---	---	---	---	---	supports only 0A (-100) - 32 (-100)	---	---	---	---	supports only 0A (-100) - 32 (-100)	---	---	---

ITEM	Command Control / Response / Confirmation	Data	Data Contents	UE150A	UB50/UB10	UE160	UE80/UE50/UE40/UE30	UE20/HE20	UR100	UE100	UE4	UE150/HE145	HR140	UB300	UE70series	HE75series	HE70series	HE130	HE120	HE60	HE50
			Control and Response to control																		
REC Status	QRE QRE:[Data]	0x0000 0x0001 0x8001 0x8002 0x8003 0x8004 0x8005	Ready/Stopped Recording/Started Media not inserted Write Protect Media full Video recording not allowed Other recording not allowed	---	○(query only)	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
R Gain	ORG:[Data] QGR QGR:[Data]	00h - 1Eh - 3Ch 00h 1Eh - 3Ch	-30 0 - +30 HR140, HE130, HE120 -150 0 - 150	---	---	---	---	---	---	---	---	---	○	---	○	○	○	○	○	○	○
R Gain	ORI:[Data] QRI	000h - 096h - 12Ch 000h - 096h - 12Ch	-150 0 - +150 UE70series, HE75series, HE70series, HE60, HE50 -30 0 - 30	---	---	---	---	---	---	---	---	---	○	---	○	○	○	○	○	○	○
R Pedestal	ORP:[Data] QRP	000h 096h - 12Ch	-150 0 - +150	supports only -100~+100	---	---	---	---	supports only -100~+100	supports only -100~+100	---	supports only -100~+100	supports only -100~+100	---	---	---	---	supports only -100~+100	○	---	---
Iris Mode	ORS:[Data] QRS	0 1	Manual Auto	○	○	○	○	○	○	○	supports only 1(Auto)	○	○	○	○	○	○	○	○	○	○
Iris Control	ORV:[Data] QRV	000h - 3FFh	Close Open	○	○	○	○	○	○	○	---	○	○	○	○	○	○	○	○	○	○
Linear Table	OSA:00:[Data] QSA:00	0 1	Table A Table B	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Master Black Gamma	OSA:07:[Data] QSA:07	50h - 80h - B0h	-48 - 0 - +48	supports only 78h(-8) 88h(+8)	---	○	---	---	supports only 78h(-8) 88h(+8)	supports only 78h(-8) 88h(+8)	---	supports only 78h(-8) 88h(+8)	---	○	---	---	---	---	---	---	---
R Black Gamma	OSA:08:[Data] QSA:08	6Ch - 71h - 80h - 8Fh - 94h	-20 - -15 0 - +15 - +20	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
B Black Gamma	OSA:09:[Data] QSA:09	6Ch - 71h - 80h - 8Fh - 94h	-20 - -15 0 - +15 - +20	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Gamma SW	OSA:0A:[Data] QSA:0A	0 1	Off On	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Black Gamma SW	OSA:0B:[Data] QSA:0B	0 1	Off On	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
DRS SW	OSA:0D:[Data] QSA:0D	0 1	Off On	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Black Stretch Level (BFILM MENU & FILM REC)	OSA:0F:[Data] QSA:0F	00h 1Eh	0 30	○	---	---	---	---	---	---	---	○	---	○	---	---	---	---	---	---	---
Dynamic Level (BFILM MENU & FILM REC)	OSA:10:[Data] QSA:10	0 1 2 3 4	200% 300% 400% 500% 600%	○	---	---	---	---	---	---	---	○	---	supports only 0(200%) - 3(500%)	---	---	---	---	---	---	---
Flare SW	OSA:11:[Data] QSA:11	0 1	Off On	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Master Knee Point (BVIDEO MENU)	OSA:20:[Data] QSA:20	22h - 80h - B6h - C2h	70.00% - 93.50% - 107.00% - 110.00% (1step=0.25%)	support only 22h(70.00%) - B6h(107.00%) (1step=0.5%)	support only 4Ah(80.00%) - B6h(107.00%)	support only 4Ah(80.00%) - C2h(110.00%)	---	---	support only 22h(70.00%) - B6h(107.00%) (1step=0.5%)	support only 22h(70.00%) - B6h(107.00%) (1step=0.5%)	---	support only 22h(70.00%) - B6h(107.00%) (1step=0.5%)	support only 22h(70.00%) - B6h(107.00%) (1step=0.5%)	support only 4Ah(80.00%) - C2h(110.00%)	---	---	---	support only 22h(70.00%) - B6h(107.00%) (1step=0.5%)	---	---	---
Master Knee Point (BFILM MENU & VIDEO REC)	OSA:21:[Data] QSA:21	62h - 80h - 9Eh - AFh	30% - 60% - 90% 107%	○	---	---	---	---	---	---	---	○	---	support only 62(30%) - 9E(90%)	---	---	---	---	---	---	---
R Knee Point	OSA:22:[Data] QSA:22	1Ch 80h - E4h	-25.00% 0.00% - +25.00% (1step=0.25%)	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---

ITEM	Command Control / Response / Confirmation	Data	Data Contents	UE150A	UB50/UB10	UE160	UE80/UE50/UE40/UE30	UE20/HE20	UR100	UE100	UE4	UE150/HE145	HR140	UB300	UE70series	HE75series	HE70series	HE130	HE120	HE60	HE50
			Control and Response to control																		
B Knee Point	OSA:23:[Data] OSA:23	10h - 80h - E4h	-25.00% - 0.00% - +25.00% (1step=0.25%)	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Master Knee Slope (#VIDEO MENU)	OSA:24:[Data] OSA:24	00h - 63h - C7h	0 - 99 - 199	support only 00h(0) - 63h(99)	support only 00h(0) - 63h(99)	○	---	---	support only 00h(0) - 63h(99)	support only 00h(0) - 63h(99)	---	support only 00h(0) - 63h(99)	support only 00h(0) - 63h(99)	○	---	---	---	support only 00h(0) - 63h(99)	---	---	---
Master Knee Slope (#FILM MENU & VIDEO RED)	OSA:25:[Data] OSA:25	70h - 80h - 85h	150% - 350% - 600% (1step=50%)	○	---	---	---	---	---	---	---	supports only 70h(150%) - 83h(500%)	---	○	---	---	---	---	---	---	---
R Knee Slope (#VIDEO MENU)	OSA:26:[Data] OSA:26	10h - 80h - E3h	-99 - 0 - +99	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
B Knee Slope (#VIDEO MENU)	OSA:27:[Data] OSA:27	10h - 80h - E3h	-99 - 0 - +99	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Auto Knee Point (#VIDEO MENU)	OSA:28:[Data] OSA:28	4Ah - 80h - B6h	80.00% - 93.50% - 107.00% (1step=0.25%)	---	---	---	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Auto Knee Level (#VIDEO MENU)	OSA:29:[Data] OSA:29	70h - 85h	100% - 109% (1step=1%)	---	---	---	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
White Clip Level	OSA:2A:[Data] OSA:2A	00h - 13h - UE160 50h - 60h	90% - 109% - UE160 80% - 109%	○	---	○	○	---	○	○	---	○	○	---	---	---	---	○	---	---	---
Knee Mode	OSA:2D:[Data] OSA:2D	0 1 2 3 4 5	Off Manual Auto Low Mid High	supports only 0(Off) 1(Manual) 2(Auto)	supports only 0(Off) 1(Manual) 2(Auto)	supports only 0(Off) 1(Manual) 2(Auto)	supports only 0(Off) 2(Auto)	---	supports only 0(Off) 1(Manual) 2(Auto)	supports only 0(Off) 1(Manual) 2(Auto)	---	supports only 0(Off) 1(Manual) 2(Auto)	supports only 0(Off) 1(Manual) 2(Auto)	supports only 0(Off) 1(Manual) 2(Auto)	---	---	---	○	---	---	---
White Clip	OSA:2E:[Data] OSA:2E	0 1	Off On	○	---	○	○	---	○	○	---	○	○	---	---	---	---	○	---	---	---
Master Detail	OSA:30:[Data] OSA:30	61h - 80h - 9Fh - HR140_HE130 61h - 80h - 9Fh - UB50_UB10 76h - 80h - 8Ah	-31 - 0 - +31 - HR140_HE130 0 - +31 - +62 - UB50_UB10 -5 - 0 - 5	○	○	○	○	---	○	○	---	○	○	○	supports only 81h(1)-91h(17) for Detail Level (L)	supports only 81h(1)-91h(17) for Detail Level (L)	supports only 81h(1)-91h(17) for Detail Level (L)	○	---	supports only 81h(1)-91h(17) for Total Dtail Level (L)	---
H Detail Level	OSA:31:[Data] OSA:31	00h - 3Fh	0 - 63	---	---	---	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Detail Gain(+)	OSA:38:[Data] OSA:38	61h - 80h - 9Fh	-31 - 0 - +31	○	---	○	---	---	○	○	---	○	---	○	---	---	---	---	---	---	---
Detail Gain(-)	OSA:39:[Data] OSA:39	61h - 80h - 9Fh	-31 - 0 - +31	○	---	○	---	---	○	○	---	○	---	○	---	---	---	---	---	---	---
Detail Source	OSA:3B:[Data] OSA:3B	0 1 2 3 4 5	(G+R)/2 (G+B)/2 (2G+B+R)/4 (3G+R)/4 R G	---	---	---	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Skin Tone Detail	OSA:40:[Data] OSA:40	0 1	Off On	○	○	○	○	---	○	○	---	○	---	○	---	---	---	---	---	---	---
Skin Get	OSA:41:[Data] OSA:41	0 1 2	Off On Get	---	---	---	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Skin Tone Detail 1 Center(HD)	OSA:45:[Data] OSA:45	00h - FFh	0 - 255	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Skin Tone Detail 1 Width(HD)	OSA:46:[Data] OSA:46	00h - FFh	0 - 255	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Skin Tone Detail 0 Width(HD)	OSA:47:[Data] OSA:47	00h - FFh	0 - 255	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---

[illegible]

ITEM	Command Control / Response / Confirmation	Data	Data Contents	UE150A	UB50/UB10	UE160	UE80/UE50/UE40/UE30	UE20/HE20	UR100	UE100	UE4	UE150/HE145	HR140	UB300	UE70series	HE75series	HE70series	HE130	HE120	HE60	HE50
			Control and Response to control																		
OSD Status	OSA:88:[Data] OSA:88	0 1	Off On	○	---	○	○	---	○	○	---	○	○	○	○	○	○	○	○	○	○
Total Dtail Level High	OSA:B1:[Data] OSA:B1	61h - 80h - 9Fh	-31 - 0 - +31	---	---	---	---	---	---	---	---	---	---	---	supports only 82h(2)~92h(18) for Detail Level (H)	supports only 82h(2)~92h(18) for Detail Level (H)	supports only 82h(2)~92h(18) for Detail Level (H)	---	---	supports only 82h(2)~92h(18) for Total Detail Level (H)	---
Audio	OSA:D0:[Data] OSA:D0	0 1	Off On	○	---	○	○	○	○	○	○	○	○	---	○	○	○	○	---	---	---
Audio Input Type	OSA:D1:[Data] OSA:D1	0 1 2 3 4 5	Mic High Mic Middle Mic Low Line High Line Middle Line Low	supports only 0 (Mic) 3 (Line)	---	---	supports only 0 (Mic) 3 (Line)	supports only 0 (Mic) 3 (Line)	supports only 0 (Mic) 3 (Line)	supports only 0 (Mic) 3 (Line)	---	supports only 0 (Mic) 3 (Line)	---	---	○	○	○	○	---	---	---
Audio Plugin Power	OSA:D2:[Data] OSA:D2	0 1	Off On	○	---	---	○	○	---	○	---	○	---	---	○	○	○	○	---	---	---
Tally Brightness	OSA:D3:[Data] OSA:D3	0 1 2	Low Mid High	○	---	○	○	---	---	○	---	○	---	---	---	---	---	○	---	---	---
Audio Line Input Level	OSA:D4:[Data1]:[Data2] OSA:D4:[Data1]	[Data1] 0 1 [Data2] 0 1 2 UE160 [Data1] 0 1 [Data2] 0 1	[Data1] CH1/CH3 CH2/CH4 [Data2] +4dB 0dB -20dB UE160 [Data1] Input1 Input2 [Data2] +4dB 0dB	---	---	○	---	---	---	---	---	---	○	---	---	---	---	---	---	---	---
Audio Volume Level	OSA:D5:[Data1]:[Data2] OSA:D5:[Data1]	[Data1] 0 1 2 3 [Data2] 58h - 80h - 94h	[Data1] CH1 CH2 CH3 CH4 [Data2] -40dB - 0dB - 20dB	[Data1] supports only 0 (CH1) 1 (CH2) [Data2] supports only 50h(-36dB) - 80(12dB) (step:3dB)	---	[Data1] supports only 0 (CH1) 1 (CH2) [Data2] supports only 58h(-40dB) - 94 (20dB) (step:1dB)	[Data1] supports only 0 (CH1) 1 (CH2) [Data2] supports only 50h(-36dB) - 80 (12dB) (step:3dB)	[Data1] supports only 0 (CH1) 1 (CH2) [Data2] supports only 50h(-36dB) - 80 (12dB) (step:3dB)	[Data1] supports only 0 (CH1) 1 (CH2) [Data2] supports only 50h(-36dB) - 80 (12dB) (step:3dB)	---	[Data1] supports only 0 (CH1) 1 (CH2) [Data2] supports only 50h(-36dB) - 80 (12dB) (step:3dB)	[Data1] supports 0 (CH1)~3 (CH4) [Data2] supports only 58h(-40dB) - 80 (12dB) (step:1dB)	---	---	---	---	---	---	---	---	
Audio Head Room	OSA:D6:[Data] OSA:D6	0 1 2	FS-12dB FS-18dB FS-20dB	---	---	○	---	---	---	---	---	---	○	---	---	---	---	---	---	---	---
Audio Line CH Select	OSA:D7:[Data] OSA:D7	0 1 2 3	All CH1/CH2 CH3/CH4 None	---	---	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---	---
SC Coarse	OSC:[Data] OSC	※	※	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	※	※
H Detail Level H	OSD:0A:[Data] OSD:0A	02h - 3Fh	2 - 63	---	---	---	---	---	---	---	---	---	---	---	---	---	---	○	---	---	---
V Detail Level H	OSD:0E:[Data] OSD:0E	02h - 1Fh	2 - 31	---	---	---	---	---	---	---	---	---	---	---	---	---	---	○	---	---	---
H Detail Level L	OSD:12:[Data] OSD:12	01h - 3Eh	1 - 62	---	---	---	---	---	---	---	---	---	---	---	---	---	---	○	---	---	---
V Detail Level L	OSD:16:[Data] OSD:16	01h - 1Eh	1 - 30	---	---	---	---	---	---	---	---	---	---	---	---	---	---	○	---	---	---
Detail Band	OSD:1E:[Data] OSD:1E	01 05	01 05	---	---	---	---	---	---	---	---	---	---	---	---	---	---	○	---	---	---
Noise Suppress /Crisp	OSD:22:[Data] OSD:22	00h - 3Fh	0 - 63	---	---	○	---	---	---	---	---	---	support only 00 (0)~30 (60)	○	---	---	---	support only 00 (0)~30 (60)	support only 00 (0)~07 (7)	---	---
Level Dependent	OSD:26:[Data] OSD:26	00h - 0Fh	00 - 15	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Matrix (R-G) /Matrix (R-G)_N	OSD:2F:[Data] OSD:2F	00h - 1Fh - 3Eh	-31 - 0 - +31	---	---	○	---	---	---	---	---	---	---	---	---	---	---	○	---	---	---
Matrix (R-B) /Matrix (R-B)_N	OSD:30:[Data] OSD:30	00h - 1Fh - 3Eh	-31 - 0 - +31	---	---	○	---	---	---	---	---	---	---	---	---	---	---	○	---	---	---
Matrix (G-R) /Matrix (G-R)_N	OSD:31:[Data] OSD:31	00h - 1Fh - 3Eh	-31 - 0 - +31	---	---	○	---	---	---	---	---	---	---	---	---	---	---	○	---	---	---
Matrix (G-B) /Matrix (G-B)_N	OSD:32:[Data] OSD:32	00h - 1Fh - 3Eh	-31 - 0 - +31	---	---	○	---	---	---	---	---	---	---	---	---	---	---	○	---	---	---
Matrix (B-R) /Matrix (B-R)_N	OSD:33:[Data] OSD:33	00h - 1Fh - 3Eh	-31 - 0 - +31	---	---	○	---	---	---	---	---	---	---	---	---	---	---	○	---	---	---

ITEM	Command Control / Response / Confirmation	Data	Data Contents	UE150A	UB50/UB10	UE160	UE80/UE50/UE40/UE30	UE20/HE20	UR100	UE100	UE4	UE150/HE145	HR140	UB300	UE70series	HE75series	HE70series	HE130	HE120	HE60	HE50
			Control and Response to control																		
Character Mix Select	OSD:98:[Data1]:[Data2] OSD:98:[Data1]	Data1 0 1	Output Browser/Video SDI/HDMI, Component	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	supports only Output 0 (Browser/Video), 1 (SDI/HDMI, Compon ent) Character Mix Select 2 (Off By Browser) is Valid When Output is 1 (SDI/HDMI, Compon ent)	---
		Data2 0 1 2	Character Mix Select Off On Off By Browser																		
Color Correction Mg_R_R Saturation	OSD:9A:[Data] OSD:9A	41h - 80h - BFh	-63 - 0 - +63	○	supports only 49h(-55) - B7h(+55)	---	○	---	○	○	---	○	○	---	---	---	---	○	---	---	---
Color Correction Mg_R_R Phase	OSD:9B:[Data] OSD:9B	41h - 80h - BFh	-63 - 0 - +63	○	supports only 49h(-55) - B7h(+55)	---	○	---	○	○	---	○	○	---	---	---	---	○	---	---	---
Color Correction R_R_YI Saturation	OSD:9C:[Data] OSD:9C	41h - 80h - BFh	-63 - 0 - +63	○	supports only 49h(-55) - B7h(+55)	---	○	---	○	○	---	○	○	---	supports only 61h(-31) - 9Fh(+31)	supports only 61h(-31) - 9Fh(+31)	supports only 61h(-31) - 9Fh(+31)	○	---	---	---
Color Correction R_R_YI Phase	OSD:9D:[Data] OSD:9D	41h - 80h - BFh	-63 - 0 - +63	○	supports only 49h(-55) - B7h(+55)	---	○	---	○	○	---	○	○	---	○	○	○	○	---	---	---
Color Correction R_YI_YI Saturation	OSD:9E:[Data] OSD:9E	41h - 80h - BFh	-63 - 0 - +63	○	supports only 49h(-55) - B7h(+55)	---	○	---	○	○	---	○	○	---	supports only 61h(-31) - 9Fh(+31)	supports only 61h(-31) - 9Fh(+31)	supports only 61h(-31) - 9Fh(+31)	○	---	---	---
Color Correction R_YI_YI Phase	OSD:9F:[Data] OSD:9F	41h - 80h - BFh	-63 - 0 - +63	○	supports only 49h(-55) - B7h(+55)	---	○	---	○	○	---	○	○	---	○	○	○	○	---	---	---
V Detail Level	OSD:A1:[Data] OSD:A1	79h - 80h - 87h	-7 - 0 - 7	○	---	---	○	---	○	○	---	○	○	---	---	---	---	○	---	---	---
Detail Band /Detail Frequency	OSD:A2:[Data] OSD:A2	79h - 80h - 87h	-7 - 0 - 7	○	---	---	---	---	○	○	---	○	○	---	---	---	---	○	---	---	---
Flesh Tone Noise Suppress /Skin Detail Effect	OSD:A3:[Data] OSD:A3	80h - 9Fh	0 - 31	○	○	---	○	---	○	○	---	○	○	---	---	---	---	○	---	---	---
Matrix(R-G)	OSD:A4:[Data] OSD:A4	41h - 80h - BFh	-63 - 0 - 63	○	○	---	○	---	○	○	---	○	○	---	---	---	---	○	---	---	---
Matrix(R-B)	OSD:A5:[Data] OSD:A5	41h - 80h - BFh	-63 - 0 - 63	○	○	---	○	---	○	○	---	○	○	---	---	---	---	○	---	---	---
Matrix(G-R)	OSD:A6:[Data] OSD:A6	41h - 80h - BFh	-63 - 0 - 63	○	○	---	○	---	○	○	---	○	○	---	---	---	---	○	---	---	---
Matrix(G-B)	OSD:A7:[Data] OSD:A7	41h - 80h - BFh	-63 - 0 - 63	○	○	---	○	---	○	○	---	○	○	---	---	---	---	○	---	---	---
Matrix(B-R)	OSD:A8:[Data] OSD:A8	41h - 80h - BFh	-63 - 0 - 63	○	○	---	○	---	○	○	---	○	○	---	---	---	---	○	---	---	---
Matrix(B-G)	OSD:A9:[Data] OSD:A9	41h - 80h - BFh	-63 - 0 - 63	○	○	---	○	---	○	○	---	○	○	---	---	---	---	○	---	---	---
Color Correction Cy_Cy_B Saturation	OSD:AA:[Data] OSD:AA	61h - 80h - 9Fh	-31 - 0 - +31	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---
Color Correction Cy_Cy_B Phase	OSD:AB:[Data] OSD:AB	41h - 80h - BFh	-63 - 0 - +63	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---
Color Correction Cy_B_B Saturation	OSD:AC:[Data] OSD:AC	61h - 80h - 9Fh	-31 - 0 - +31	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---
Color Correction Cy_B_B Phase	OSD:AD:[Data] OSD:AD	41h - 80h - BFh	-63 - 0 - +63	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---

ITEM	Command Control / Response / Confirmation	Data	Data Contents																		
			Control and Response to control	UE150A	UB50/UB10	UE160	UE80/UE50/UE40/UE30	UE20/HE20	UR100	UE100	UE4	UE150/UE145	HR140	UB300	UE70series	HE75series	HE70series	HE130	HE120	HE60	HE50
Chroma Level	OSD:B0:[Data] OSD:B0	00h	Off	supports only			supports only	supports only		supports only	supports only		supports only	supports only				supports only			
		1Ch	-100%	00 (Off),			00 (Off),		00 (Off),		00 (Off),		00 (Off),					00 (Off),			
		80h	-	1D (-99%) -			1D (-99%) -		1D (-99%) -		1D (-99%) -		1D (-99%) -					1D (-99%) -			
		A8h	0	E3 (99%)			A8 (40%)		E3 (99%)		E3 (99%)		E3 (99%)					A8 (40%)			
		-	-																		
		40%																			
		E3h	99%																		
		AK-UB300	UB300																		
Color Temperature	OSD:B1:[Data] OSD:B1	00h	-100%																		
		1Dh	-99%																		
		-	-																		
		0																			
		80h	-																		
		-	-																		
		40%																			
		A8h																			
Night Mode Select	OSD:B2:[Data] OSD:B2	0	Manual																		
		1	Auto																		
i. Zoom	OSD:B3:[Data] OSD:B3	0	Disable	[Zoom Mode]			[Zoom Mode]	[Zoom Mode]		[Zoom Mode]											
		1	Enable	-Opt Zoom OSE:70:0 OSD:B3:0 -i Zoom OSE:70:0 OSD:B3:1 -D Zoom OSE:70:1 OSD:B3:0		-Opt Zoom OSE:70:0 OSD:B3:0 -i Zoom OSE:70:0 OSD:B3:1 -D Zoom OSE:70:1 OSD:B3:0		-Opt Zoom OSE:70:0 OSD:B3:0 -i Zoom OSE:70:0 OSD:B3:1 -D Zoom OSE:70:1 OSD:B3:0		-Opt Zoom OSE:70:0 OSD:B3:0 -i Zoom OSE:70:0 OSD:B3:1 -D Zoom OSE:70:1 OSD:B3:0		-Opt Zoom OSE:70:0 OSD:B3:0 -i Zoom OSE:70:0 OSD:B3:1 -D Zoom OSE:70:1 OSD:B3:0									
HDR	OSD:B4:[Data] OSD:B4	0	Off																		
		1	Low																		
Night-Day Level	OSD:B7:[Data] OSD:B7	2	Mid																		
		3	High																		
Digital Extender Magnification	OSD:B8:[Data] OSD:B8	0	Low																		
		1	Mid																		
Format_SDI	OSD:B9:[Data] OSD:B9	2	High																		
		3																			
Color Bar Type	OSD:BA:[Data] OSD:BA	4																			
		0	x1.4																		
ALC	OSD:BB:[Data] OSD:BB	1	x2.0																		
		2	x4.0																		
Equalize	OSD:BC:[Data] OSD:BC	3	x6.0																		
		4	x8.0																		
Color Bar Title	OSD:BE:[Data] OSD:BE	0																			
		1																			
Auto Shutter Limit	OSD:BF:[Data] OSD:BF	0																			
		1																			
Color Correction B_B_Mg Saturation	OSD:C0:[Data] OSD:C0	2																			
		3																			
Color Correction B_B_Mg Phase	OSD:C1:[Data] OSD:C1	4																			
		5																			
Color Correction B_B_Mg Saturation	OSD:C2:[Data] OSD:C2	6																			
		7																			
Color Correction B_B_Mg Phase	OSD:C3:[Data] OSD:C3	8																			
		9																			

ITEM	Command Control / Response / Confirmation	Data	Data Contents	UE150A	UB50/UB10	UE160	UE80/UE50/UE40/UE30	UE20/HE20	UR100	UE100	UE4	UE150/HE145	HR140	UB300	UE70series	HE75series	HE70series	HE130	HE120	HE60	HE50	
			Control and Response to control																			
Color Correction Y1_Y1_G Saturation	OSD:C4:[Data] OSD:C4	61h	-31	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---	
		80h	0	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---	
		-	-	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---	
		9Fh	+31	---	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---
Color Correction Y1_Y1_G Phase	OSD:C5:[Data] OSD:C5	41h	-63	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---	
		80h	0	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---	
		-	-	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---	
		BFh	+63	---	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---
Color Correction Y1_G_G Saturation	OSD:C6:[Data] OSD:C6	61h	-31	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---	
		80h	0	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---	
		-	-	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---	
		9Fh	+31	---	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---
Color Correction Y1_G_G Phase	OSD:C7:[Data] OSD:C7	41h	-63	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---	
		80h	0	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---	
		-	-	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---	
		BFh	+63	---	---	---	---	---	---	---	---	---	---	---	---	○	○	○	---	---	---	---
E DRS Select	OSD:C8:[Data] OSD:C8	0 1 2 3	Off Low Mid High	---	---	---	---	---	---	---	---	---	---	---	supports only 0(Off), 1(Low), 3(High)	supports only 0(Off), 1(Low), 3(High)	supports only 0(Off), 1(Low), 3(High)	---	---	---	---	
D/C Mode (D/C Board)	OSE:20:[Data] OSE:20	0 1 2 3	Side Out Squeeze Letter Box Link	---	---	---	---	---	---	---	---	---	---	---	---	---	---	○	○	○	○	
Matrix Type /Preset Matrix	OSE:31:[Data] OSE:31	0 1 2 3 4	Normal EBU Matrix NTSC Matrix User Professional	supports only 0(Normal) 1(EBU Matrix) 2(NTSC Matrix) 3(User)	---	○	supports only 0(Normal) 3(User) 4(Professional)	---	supports only 0(Normal) 3(User) 4(Professional)	supports only 0(Normal) 1(EBU Matrix) 2(NTSC Matrix) 3(User)	---	supports only 0(Normal) 1(EBU Matrix) 2(NTSC Matrix) 3(User)	supports only 0(Normal) 1(EBU Matrix) 2(NTSC Matrix) 3(User)	---	supports only 0(Normal) 1(EBU Matrix) 2(NTSC Matrix) 3(User)	supports only 0(Normal) 1(EBU Matrix) 2(NTSC Matrix) 3(User)	supports only 0(Normal) 1(EBU Matrix) 2(NTSC Matrix) 3(User)	supports only 0(Normal) 1(EBU Matrix) 2(NTSC Matrix) 3(User)	supports only 0(Normal) 1(EBU Matrix) 2(NTSC Matrix) 3(User)	supports only 0(Normal) 1(EBU Matrix) 2(NTSC Matrix) 3(User)		
		UE160 0 1 2 3 4	UE160 Normal Cinema1 Cinema2 User HD	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	
		0 1 2 3	Off Low Mid High	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	
		OSE:32:[Data] OSE:32	0 1 2 3	Off Low Mid High	---	---	---	---	---	---	---	---	---	---	---	---	supports only 0(Off), 1(Low), 3(High)	supports only 0(Off), 1(Low), 3(High)	supports only 0(Off), 1(Low), 3(High)	---	---	supports only 0(Off), 1(Low), 3(High)
DRS	OSE:33:[Data] OSE:33	0 1 2 3	Off Low Mid High	○	---	---	○	○	○	○	○	○	○	---	supports only 0(Off), 1(Low), 3(High)	supports only 0(Off), 1(Low), 3(High)	supports only 0(Off), 1(Low), 3(High)	○	○	supports only 0(Off), 1(Low), 3(High)	supports only 0(Off), 1(Low), 3(High)	
		0 1	UE20/HE20/UE4 Off On	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	
		0 1 2 3 4	RGB(NOR) RGB(ENH) YPbPr(422) YPbPr(444) YPbPr(420)	supports only 2(YPbPr(422)) 4(YPbPr(420))	---	supports only 2(YPbPr(422)) 4(YPbPr(420))	UE80 supports only 2(YPbPr(422)) 4(YPbPr(420)) UE50, UE40, UE30 don't support	---	---	supports only 2(YPbPr(422)) 4(YPbPr(420))	---	UE150 supports only 2(YPbPr(422)) 4(YPbPr(420)) HE145 supports only	---	---	---	---	---	---	supports only 0(RGB(NOR)) 1(RGB(ENH)) 2(YPbPr(422)) 3(YPbPr(444))	supports only 0(RGB(NOR)) 1(RGB(ENH)) 2(YPbPr(422)) 3(YPbPr(444))	supports only 0(RGB(NOR)) 1(RGB(ENH)) 2(YPbPr(422)) 3(YPbPr(444))	
		OSE:69:[Data]	1	Push Auto	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○
Digital Zoom	OSE:70:[Data] OSE:70	0 1	Disable Enable	[Zoom Mode] -Opt Zoom OSE:70:0 OSD:B3:0 -i Zoom OSE:70:0 OSD:B3:1 -D Zoom OSE:70:1 OSD:B3:0	---	[Zoom Mode] -Opt Zoom OSE:70:0 OSD:B3:0 -i Zoom OSE:70:0 OSD:B3:1 -D Zoom OSE:70:1 OSD:B3:0	[Zoom Mode] -Opt Zoom OSE:70:0 OSD:B3:0 -i Zoom OSE:70:0 OSD:B3:1 -D Zoom OSE:70:1 OSD:B3:0	[Zoom Mode] -Opt Zoom OSE:70:0 OSD:B3:0 -i Zoom OSE:70:0 OSD:B3:1 -D Zoom OSE:70:1 OSD:B3:0	[Zoom Mode] -Opt Zoom OSE:70:0 OSD:B3:0 -i Zoom OSE:70:0 OSD:B3:1 -D Zoom OSE:70:1 OSD:B3:0	[Zoom Mode] -Opt Zoom OSE:70:0 OSD:B3:0 -i Zoom OSE:70:0 OSD:B3:1 -D Zoom OSE:70:1 OSD:B3:0	○	[Zoom Mode] -Opt Zoom OSE:70:0 OSD:B3:0 -i Zoom OSE:70:0 OSD:B3:1 -D Zoom OSE:70:1 OSD:B3:0	○	---	○	○	○	○	○	○		
		0 1 2 3 4 5 6 7	Off Normal Cinema UE150A, UE100, UE150, HE145, HR140, HE130 HD SD FILMLIKE1 FILMLIKE2 FILMLIKE3 FILM REC VIDEO REC	supports only 0(HD) 2(FILMLIKE1) 3(FILMLIKE2) 4(FILMLIKE3) 5(FILM REC) 6(VIDEO REC)	---	---	---	---	---	supports only 0(HD) 2(FILMLIKE1) 3(FILMLIKE2) 4(FILMLIKE3)	---	○	supports only 0(HD) 2(FILMLIKE1) 3(FILMLIKE2) 4(FILMLIKE3)	---	○	○	○	supports only 0(HD) 1(SD) 2(FILMLIKE1) 3(FILMLIKE2) 4(FILMLIKE3)	○	○	○	
		0 1	Off On	---	---	---	○	○	---	---	---	○	---	---	---	○	○	○	---	---	○	○
		OSE:73:[Data] OSE:73	0 1	Off On	---	---	---	○	○	○	○	○	○	○	○	○	○	○	○	---	---	○
Auto F.Mix Max Gain	OSE:74:[Data] OSE:74	00 01 02 03	(Off) 6dB 12dB 18dB	---	---	---	○	○	○	○	---	---	---	---	○	○	○	---	---	○	○	
		0 1	Off On	○	---	---	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	
		0100 9999	*1.00 - *99.99	supports only 0100(x1.00) - 1000(x10.00)	---	supports only 0100(x1.00) - 1000(x10.00)	supports only 0100(x1.00) - 1000(x10.00)	supports only 0100(x1.00) - 0400(x4.00)	supports only 0100(x1.00) - 1000(x10.00)	supports only 0100(x1.00) - 1000(x10.00)	---	supports only 0100(x1.00) - 1000(x10.00)	supports only 0100(x1.00) - 1000(x10.00)	---	supports only 0100(x1.00) - 1200(x12.00)	supports only 0100(*1.00) - 1200(*12.00)	supports only 0100(x1.00) - 1600(x16.00)	supports only 0100(x1.00) - 1000(x10.00)	supports only 0100(x1.00) - 1000(x10.00)	supports only 0100(x1.00) - 1000(x10.00)	supports only 0100(x1.00) - 1000(x10.00)	
		0 1 2 3 4	59.94Hz 0(59.94Hz), 24.00Hz 23.98Hz, 60.00Hz	supports only 0(59.94Hz), 1(50.00Hz), 2(24.98Hz), 3(23.98Hz)	supports only 0(59.94Hz), 1(50.00Hz), 2(24.98Hz)	○	supports only 0(59.94Hz), 1(50.00Hz), 4(60.00Hz) 3(23.98Hz)	supports only 0(59.94Hz), 1(50.00Hz), 2(24.98Hz), 3(23.98Hz)	supports only 0(59.94Hz), 1(50.00Hz), 4(60.00Hz)	supports only 0(59.94Hz), 1(50.00Hz), 3(23.98Hz)	---	supports only 0(59.94Hz), 1(50.00Hz)	supports only 0(59.94Hz), 1(50.00Hz)	---	supports only 0(59.94Hz), 1(50.00Hz)	supports only 0(59.94Hz), 1(50.00Hz)	supports only 0(59.94Hz), 1(50.00Hz)	supports only 0(59.94Hz), 1(50.00Hz)	supports only 0(59.94Hz), 1(50.00Hz)	supports only 0(59.94Hz), 1(50.00Hz)	supports only 0(59.94Hz), 1(50.00Hz)	
Max Digital Zoom	OSE:7A:[Data] OSE:7A	02 - 18	x2 - x18	supports only 02(x2) - 10(x10)	---	supports only 02(x2) - 10(x10)	supports only 02(x2) - 10(x10)	supports only 02(x2) 03(x3) 04(x4)	supports only 02(x2) - 10(x10)	supports only 02(x2) - 10(x10)	---	supports only 02(x2) - 10(x10)	supports only 02(x2) - 10(x10)	---	supports only 02(x2) - 12(x12)	supports only 02(x2) - 12(x12)	supports only 02(x2) - 16(x16)	supports only 02(x2) - 10(x10)	supports only 02(x2) - 10(x10)	---	---	

ITEM	Command Control / Response / Confirmation	Data	Data Contents Control and Response to control	UE150A	UB50/UB10	UE160	UE80/UE50/UE40/UE 30	UE20/HE20	UR100	UE100	UE4	UE150/HE145	HR140	UB300	UE70series	HE75series	HE70series	HE130	HE120	HE60	HE50
OSD Mix /Char	OSE:7B:[Data] OSE:7B	00h 01h 02h 04h 08h 10h 20h 40h 80h	OSD Mix Off SDI On HDMI On Analog On Video On IP/NDI HX On 12G SDI 1/12G SDI/Optical On 12G SDI 2/MONI/3G SDI/PW On NDI On 3kbit0:SDI, bit1:HDMI, bit2:Analog, bit3:Video, bit4: IP, bit5:12G SDI/Optical, bit6: MONI, bit7:NDI	supports only 00(OSD Mix Off) 01(3G SDI 1 On) 02(HDMI On) 10(IP/NDI HX On) 20(12G SDI/OPTICAL On) 40(3G SDI 1 On) 80(NDI On)On	---	UE160 supports only 00(OSD Mix Off) 01(SDI On) 02(HDMI On) 10(IP/NDI HX On) 20(12G SDI On) 40(3G SDI/PW On)	UE80 supports only 00(OSD Mix Off) 01(3G SDI On) 02(HDMI On) 10(NDI HX On) 20(12G SDI On) 80(NDI On)	---	supports only 00(OSD Mix Off) 01(3G SDI On) 10(NDI HX On) 20(12G SDI On) 80(NDI On)	supports only 00(OSD Mix Off) 01(3G SDI On) 02(HDMI On) 10(NDI HX On) 20(12G SDI On) 80(NDI On)	---	UE150 supports only 00(OSD Mix Off) 01(SDI On) 02(HDMI On) 10(IP On) 20(12G SDI/OPTICAL On) 40(MONI On) HE145 supports only 00(OSD Mix Off) 01(SDI On) 02(HDMI On) 10(IP On)	supports only 00(OSD Mix Off) 01(SDI On) 10(IP On)	supports only 00(OSD Mix Off) 01(SDI On) 10(IP On)	---	---	---	supports only 00(OSD Mix Off) 01(SDI On) 08(Video On) 10(IP On)	supports only 00(OSD Mix Off) 01(SDI On) 02(HDMI On) 04(Analog On) 08(Video On)	---	---
Preset Digital Extender Enable	OSE:7C:[Data] OSE:7C On	0 1	Off On	○	---	○	○	---	○	○	---	○	○	---	---	---	---	○	---	---	---
Preset Zoom Mode	OSE:7D:[Data] OSE:7D	0 1	MODE A MODE B	○	---	○	○	---	○	○	---	○	○	---	---	---	---	---	---	---	---
Peak Frequency	OSG:30:[Data] OSG:30	00h - 04h - 1Fh	0 - 4 - 31	---	---	01h(1) - 08h(8)	---	---	---	---	---	---	---	[In case HD format] 00h(0) - 1Fh(31) [In case 4K format] 00h(0) - 04h(4)	---	---	---	---	---	---	---
V Detail Level	OSG:32:[Data] OSG:32	00h - 3Fh	00 - 63	---	---	---	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
V Detail Frequency	OSG:35:[Data] OSG:35	00h - 04h - 1Fh	0 - 4 - 31	---	---	---	---	---	---	---	---	---	---	[In case HD format] 00h(0) - 1Fh(31) [In case 4K format] 00h(0) - 04h(4)	---	---	---	---	---	---	---
R Gain	OSG:39:[Data] OSG:39	418h - 800h - BE8h	-1000 - 0 - 1000	support only 738h(-200) - 8C8h(200)	support only 738h(-200) - 8C8h(200)	---	support only 738h(-200) - 8C8h(200)	support only 7E2h(-30) - 81Eh(30)	support only 738h(-200) - 8C8h(200)	support only 738h(-200) - 8C8h(200)	---	support only 738h(-200) - 8C8h(200)	---	○	---	---	---	---	---	---	---
B Gain	OSG:3A:[Data] OSG:3A	418h - 800h - BE8h	-1000 - 0 - 1000	support only 738h(-200) - 8C8h(200)	support only 738h(-200) - 8C8h(200)	---	support only 738h(-200) - 8C8h(200)	support only 7E2h(-30) - 81Eh(30)	support only 738h(-200) - 8C8h(200)	support only 738h(-200) - 8C8h(200)	---	support only 738h(-200) - 8C8h(200)	---	○	---	---	---	---	---	---	---
Level Dependent SW	OSG:3E:[Data] OSG:3E	0 1	Off On	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Knee Aperture Level	OSG:3F:[Data] OSG:3F	00h - 27h	0 - 39	supports only 00h(0) - 05h(5)	---	○	---	---	supports only 00h(0) - 05h(5)	supports only 00h(0) - 05h(5)	---	supports only 00h(0) - 05h(5)	---	○	---	---	---	---	---	---	---
Detail +Clip	OSG:40:[Data] OSG:40	00h - 3Fh	0 - 63	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Detail -Clip	OSG:41:[Data] OSG:41	00h - 3Fh	0 - 63	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Memory Select	OSG:42:[Data] OSG:42	0 1 2	A B C	---	---	---	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
H Position	OSG:44:[Data] OSG:44	000h - 190h	0 - 100.00% (0.25% step)	---	---	---	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
V Position	OSG:45:[Data] OSG:45	000h - 190h	0 - 100.00% (0.25% step)	---	---	---	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Zebra Effect Memory	OSG:47:[Data] OSG:47	0 1 2 3 4 5 6	A B C A+B A+C B+C A+B+C	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Skin Tone Effect Memory	OSG:48:[Data] OSG:48	0 1 2 3 4 5 6	A B C A+B A+C B+C A+B+C	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Skin Tone Crisp	OSG:49:[Data] OSG:49	41h - 80h - BFh	-63 - 0 - +63	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Master Pedestal	OSG:4A:[Data] OSG:4A	10h - 80h - E3h	-99 - 0 - 99	---	---	---	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
R Pedestal	OSG:4C:[Data] OSG:4C	4E0h - 800h - B20h	-800 - 0 - 800	---	support only 738h(-200) - 8C8h(200)	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
G Pedestal	OSG:4D:[Data] OSG:4D	4E0h - 800h - B20h	-800 - 0 - 800	---	support only 738h(-200) - 8C8h(200)	○	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
B Pedestal	OSG:4E:[Data] OSG:4E	4E0h - 800h - B20h	-800 - 0 - 800	---	support only 738h(-200) - 8C8h(200)	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Skin Tone Q Phase	OSG:4F:[Data] OSG:4F	000h - 167h	0 - 359	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---
Shutter SW	OSG:59:[Data] OSG:59	0 1	Off On	---	---	○	---	---	---	---	---	---	---	○	---	---	---	---	---	---	---

ITEM	Command Control / Response / Confirmation	Data	Data Contents		UE150A	UB50/UB10	UE160	UE80/UE50/UE40/UE30	UE20/HE20	UR100	UE100	UE4	UE150/HE145	HR140	UB300	UE70series	HE75series	HE70series	HE130	HE120	HE60	HE50
			Control and Response to control																			
Error Information	OSJ:46 OSJ:46:[Data]	0000000h 00000001h 00000002h 00000004h 00000008h 00000010h	No Error Fan Error High Temperature Lens Error Pan/Tilt Error Sensor Error ※bit0Fan Error, bit1High Temperature, bit2Lens Error, bit3Pan/Tilt Error, bit4Sensor Error	○		supports only 0h(No Error) 1h(Fan Error) 2h(High Temperature)	○			○	○		○									
Auto Iris Speed	OSJ:01:[Data] OSJ:01	0 1 2 UE160 0 1 2	Slow Normal Fast UE160 1 2 3	○			○			○	○		○									
Auto Iris Window	OSJ:02:[Data] OSJ:02	0 1 2 UE150A,UE150 0 1 2 3 UE160 1 2 3 4 5 UE80,UE50,UE40 0 1 2 4	Normal1 Normal2 Center UE150A,UE150 Normal1 Normal2 Center User UE160 1 2 3 4 5 UE80,UE50,UE40 Normal1 Normal2 Center Full	○			○			○	○		○									
Shutter Mode	OSJ:03:[Data] OSJ:03	0h 1h 2h 3h	Off Step Synchro ELC	○			○		supports only 0(Off) 1(Step) 2(Synchro)	○	○		○									
Shutter Step Inc	OSJ:04:[Data]	01h — 64h	1 — 100	○	○	○	○	○	○	○	○	○	○									
Shutter Step Dec	OSJ:05:[Data]	01h — 64h	1 — 100	○	○	○	○	○	○	○	○	○	○									
Shutter Step Value	OSJ:06:[Data] OSJ:06	0001h — 2710 h — 3E80h	1/1 — 1/10000 — 1/16000		supports only 0018h (1/24) — 2710h (1/10000)	supports only 0002h (1/2) — 3E80h (1/16000)	supports only 0030h (1/48) — 07D0h (1/2000)	supports only 0018h (1/24) — 2710h (1/10000)	○	supports only 0018h (1/24) — 2710h (1/10000)	supports only 0018h (1/24) — 2710h (1/10000)	○	supports only 0018h (1/24) — 2710h (1/10000)									
Shutter Synchro Inc	OSJ:07:[Data]	01h — 64h	1 — 100	○	○	○	○	○	○	○	○		○									
Shutter Synchro Dec	OSJ:08:[Data]	01h — 64h	1 — 100	○	○	○	○	○	○	○	○		○									
Shutter Synchro Value	OSJ:09:[Data] OSJ:09	00000h — 186A0h	0.0 [Hz] — 10000.0[Hz]		supports only 000F0h (24. 0Hz) — 119940 (7200. 0Hz)	supports only 000F0h (24. 0Hz) — 009CDh (250. 9Hz)	supports only 000F0h (24. 0Hz) — 119940 (7200. 0Hz)	supports only 000F0h (24. 0Hz) — 119940 (7200. 0Hz)	supports only 001F4h (50. 0Hz) — 019C8h (660. 0Hz)	supports only 000F0h (24. 0Hz) — 119940 (7200. 0Hz)	supports only 000F0h (24. 0Hz) — 119940 (7200. 0Hz)		supports only 000F0h (24. 0Hz) — 119940 (7200. 0Hz)									
Chroma Phase	OSJ:08:[Data] OSJ:08	61h — 80h — 9Fh	-31 — 0 — +31	○				○		○	○		○									
AWB Gain Offset	OSJ:0C:[Data] OSJ:0C	0 1 76h — 80h — 8Ah	Off On -10 — 0 — +10	○			○	○		○	○		○									
ATW Target R	OSJ:0D:[Data] OSJ:0D	76h — 80h — 8Ah	-10 — 0 — +10	○			○	○		○	○		○									
ATW Target B	OSJ:0E:[Data] OSJ:0E	76h — 80h — 8Ah	-10 — 0 — +10	○			○	○		○	○		○									
Master Pedestal	OSJ:0F:[Data] OSJ:0F	738h — 800h — 8C8h	-200 — 0 — +200	○		supports only 7F1h (-15) — 80Fh (15)	○	○	supports only 7F6h (-10) — 80Fh (10)	○	○		○									
G Pedestal	OSJ:10:[Data] OSJ:10	032h — 096h — 0FAh	-100 — 0 — +100	○						○	○		○									
Pedestal Offset	OSJ:11:[Data] OSJ:11	0 1	Off On	○			○			○	○		○									
Detail Coring	OSJ:12:[Data] OSJ:12	00h — 3Ch	0 — 60	○				○		○	○		○									
Level Depend.	OSJ:13:[Data] OSJ:13	79h — 80h — 87h	-7 — 0 — 7	○						○	○		○									
Down Convert Detail	OSJ:14:[Data] OSJ:14	0 1	Off On	○			○						○ (UE150) — (HE145)									

ITEM	Command Control / Response / Confirmation	Data	Data Contents	UE150A	UB50/UB10	UE160	UE80/UE50/UE40/UE30	UE20/HE20	UR100	UE100	UE4	UE150/HE145	HR140	UB300	UE70series	HE75series	HE70series	HE130	HE120	HE60	HE50
			Control and Response to control																		
Down Convert Master Detail	OSJ:15:[Data] OSJ:15	61h	-31	supports only 81h(1) - 83h(3)	----	○	----	----	----	----	----	○(UE150) ----(HE145)	----	----	----	----	----	----	----	----	----
		80h	0																		
		-	-																		
9Fh	+31																				
Down Convert Detail Coring	OSJ:16:[Data] OSJ:16	00h	0	supports only 00h(0) - 07h(7)	----	----	----	----	----	----	----	○(UE150) ----(HE145)	----	----	----	----	----	----	----	----	----
		3Ch	60																		
Down Convert V Detail Level	OSJ:17:[Data] OSJ:17	79h	-7	----	----	supports only 00h(00) -	----	----	----	----	----	supports only 79h(-7) - 87h(+7) (UE150) ----(HE145)	----	----	----	----	----	----	----	----	----
		80h	0			8Fh(+63) (UE160)															
		-	-																		
BFh	+63																				
Down Convert Detail Frequency	OSJ:18:[Data] OSJ:18	7Eh	-2	supports only 81h(1) - 83h(3)	----	----	----	----	----	----	----	○(UE150) ----(HE145)	----	----	----	----	----	----	----	----	----
		80h	0																		
		-	-																		
82h	+2																				
Down Convert Level Depend.	OSJ:19:[Data] OSJ:19	79h	-7	----	----	----	----	----	----	----	----	○(UE150) ----(HE145)	----	----	----	----	----	----	----	----	----
		80h	0																		
		-	-																		
87h	+7																				
Down Convert Knee Ape Level	OSJ:1A:[Data] OSJ:1A	00h	0	----	----	----	----	----	----	----	----	○(UE150) ----(HE145)	----	----	----	----	----	----	----	----	----
		01h	1																		
		02h	2																		
		03h	3																		
		04h	4																		
05h	5																				
Black Gamma Range	OSJ:1B:[Data] OSJ:1B	1	1	○	----	○	----	----	○	○	----	○	----	----	----	----	----	----	----	----	----
		2	2																		
		3	3																		
Color Correction Y1,Y1,G Saturation	OSJ:1C:[Data] OSJ:1C	41h	-63	○	supports only 49h(-55) - B7h(+55)	----	○	----	○	○	----	○	----	----	----	----	----	----	----	----	----
		80h	0																		
		-	-																		
BFh	63																				
Color Correction Y1,Y1,G Phase	OSJ:1D:[Data] OSJ:1D	41h	-63	○	supports only 49h(-55) - B7h(+55)	----	○	----	○	○	----	○	----	----	----	----	----	----	----	----	----
		80h	0																		
		-	-																		
BFh	63																				
12G SDI/Optical Out Output Format	OSJ:1E:[Data] OSJ:1E	01h	720/59.94p	UE150A doesn't support	----	UE160 doesn't support	----	----	UE100 doesn't supports	UE100 doesn't supports	----	UE150 doesn't supports	----	----	----	----	----	----	----	----	----
		02h	720/50p																		
		04h	1080/59.94i	07h 1080/29.97PsF		07h 1080/29.97PsF			1Fh 2160/60p	1Fh 2160/60p		1Fh 2160/60p									
		05h	1080/50i	08h 1080/25PsF		08h 1080/25PsF			20h 1080/60p	20h 1080/60p		20h 1080/60p									
		07h	1080/29.97PsF	0Ah 1080/23.98PsF		0Ah 1080/23.98PsF															
		08h	1080/25PsF	16h 1080/23.98p		16h 1080/23.98p															
		0Ah	1080/23.98PsF	(over 59.94/p)		(over 59.94/p)															
		10h	1080/59.94p																		
		11h	1080/50p																		
		14h	1080/29.97p																		
		15h	1080/25p																		
		16h	1080/23.98p (over 59.94/p)																		
		17h	2160/29.97p																		
		18h	2160/25p																		
		19h	2160/59.94p																		
		1Ah	2160/50p																		
		1Bh	2160/23.98p																		
		1Fh	2160/60p																		
		20h	1080/60p																		
		21h	2160/24p																		
		22h	1080/24p																		
		23h	1080/23.98p																		
		12G SDI/Optical Out HDR Output Select	OSJ:1F:[Data] OSJ:1F	0h	SDR	○	----	○	----	----	----	----	----	○(UE150) ----(HE145)	----	----	----	----	----	----	----
1h	HDR(2020)																				
2h	HDR(709)																				
12G SDI/Optical 3G SDI Out	OSJ:20:[Data] OSJ:20	0h	Level A	○	----	○	----	----	○	○	----	○(UE150) ----(HE145)	----	----	----	----	----	----	----	----	----
		1h	Level B																		
3G SDI Out Output Format	OSJ:21:[Data] OSJ:21	01h	720/59.94p	UE150A doesn't support	----	UE160 doesn't support	UE80 and UE50 don't support	----	UE100 doesn't support	UE100 doesn't support	----	UE150 and HE145 don't support	----	----	----	----	----	----	----	----	----
		02h	720/50p				20h 1080/60p														
		04h	1080/59.94i	07h 1080/29.97PsF		07h 1080/29.97PsF															
		05h	1080/50i	08h 1080/25PsF		08h 1080/25PsF	----														
		07h	1080/29.97PsF	0Ah 1080/23.98PsF		0Ah 1080/23.98PsF	(UE40, UE30)														
		08h	1080/25PsF	16h 1080/23.98p		16h 1080/23.98p															
		0Ah	1080/23.98PsF	(over 59.94/p)		(over 59.94/p)															
		10h	1080/59.94p																		
		11h	1080/50p																		
		14h	1080/29.97p																		
		15h	1080/25p																		
		16h	1080/23.98p (over 59.94/p)																		
		20h	1080/60p																		
		22h	1080/24p																		
		23h	1080/23.98p																		
3G SDI Out HDR Output Select	OSJ:22:[Data] OSJ:22	0	SDR	○	----	○	----	----	----	----	----	○	----	----	----	----	----	----	----	----	----
		1	HDR(2020)																		
2	HDR(709)																				
MONI Out Output Format	OSJ:23:[Data] OSJ:23	01h	720/59.94p	UE150A doesn't support	----	UE160 doesn't support	----	----	----	----	----	UE150 doesn't supports	----	----	----	----	----	----	----	----	----
		02h	720/50p																		
		04h	1080/59.94i	07h 1080/29.97PsF		07h 1080/29.97PsF															
		05h	1080/50i	08h 1080/25PsF		08h 1080/25PsF															
		07h	1080/29.97PsF	0Ah 1080/23.98PsF		0Ah 1080/23.98PsF															
		08h	1080/25PsF	16h 1080/23.98p		16h 1080/23.98p															
		0Ah	1080/23.98PsF	(over 59																	

ITEM	Command Control / Response / Confirmation	Data	Data Contents	UE150A	UB50/UB10	UE160	UE80/UE50/UE40/UE30	UE20/HE20	UR100	UE100	UE4	UE150/UE145	HR140	UB300	UE70series	HE75series	HE70series	HE130	HE120	HE60	HE50
			Control and Response to control																		
Crop H Position (Mg)	OSJ:33:[Data] OSJ:33	00h	0	supports only 000h(0)	----	○ (1step=2pix)	----	----	○	○	----	UE150 supports only 000h(0) - A00h(2560) (1step=2pix) HE145 doesn't support	----	----	----	----	----	----	----	----	----
		780h	1920	AB6h(2742) (1step=2pix)	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		A00h	2560		----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		C00	3072		----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Crop V Position (Mg)	OSJ:34:[Data] OSJ:34	00h	0	supports only 000h(0)	----	○	----	----	○	○	----	UE150 supports only 000h(0) - 6C0h(1728) HE145 doesn't support	----	----	----	----	----	----	----	----	----
		438h	1080	607h(1543)	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	
		5A0h	1440		----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	
		6C0	1728		----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	
Save Preset Name	OSJ:35:[Data1]:[Data2] OSJ:35:[Data1]	[Data1] 00 - 99 [Data2] xxxxxxxxxxxxxx	[Data1] Preset001 - Preset100 [Data2] Preset Name (Fixed 15 Characters)	[Data2] use only follow characters A-Z, a-z, 1-9, _ Half-Width Space	----	[Data2] use only follow characters A-Z, a-z, 1-9, _ Half-Width Space	[Data2] use only follow characters A-Z, a-z, 1-9, _ Half-Width Space	----	[Data2] use only follow characters A-Z, a-z, 1-9, _ Half-Width Space	[Data2] use only follow characters A-Z, a-z, 1-9, _ Half-Width Space	----	[Data2] use only follow characters A-Z, a-z, 1-9, _ Half-Width Space	----	----	----	----	----	----	----	----	
Delete Preset Name (Single)	OSJ:36:[Data]	[Data] 00 - 99	[Data] Preset001 - Preset100	○	----	○	○	----	○	○	----	○	----	----	----	----	----	----	----	----	----
Delete Preset Name (All)	OSJ:37	-	----	○	----	○	○	----	○	○	----	○	----	----	----	----	----	----	----	----	----
Update Preset Thumbnail	OSJ:39:[Data]	[Data] 00 - 99	[Data] Preset001 - Preset100	○	----	○	○	----	○	○	----	○	----	----	----	----	----	----	----	----	----
Delete Preset Thumbnail (Single)	OSJ:3A:[Data]	[Data] 00 - 99	[Data] Preset001 - Preset100	○	----	○	○	----	○	○	----	○	----	----	----	----	----	----	----	----	----
Delete Preset Thumbnail (All)	OSJ:3B	-	----	○	----	○	○	----	○	○	----	○	----	----	----	----	----	----	----	----	----
Preset Name / Preset Thumbnail Counter	OSJ:3C:[Data1] OSJ:3C:[Data1]:[Data2] [Data2] 000000000h - FFFFFFFFFh	[Data1] 00h 01h 02h 03h 04h 05h 06h 07h 08h 09h 0Ah 0Bh [Data2] 000000000h - FFFFFFFFFh	[Data1] Preset 001-009 Preset 010-018 Preset 019-027 Preset 028-036 Preset 037-045 Preset 046-054 Preset 055-063 Preset 064-072 Preset 073-081 Preset 082-090 Preset 091-099 Preset 100 [Data2] 000000000h - FFFFFFFFFh	○	----	○	○	----	○	○	----	○	----	----	----	----	----	----	----	----	----
Zoom Scale	OSJ:3D OSJ:3D:[Data]	000h - 3E7h	0 - 999	○	----	○	○	----	○	○	----	○	----	----	----	----	----	----	----	----	----
Operation Lock	OSJ:3E:[Data]	xxxxxxx	Any Information (40 Characters)	○	----	○	○	----	○	○	----	○	----	----	----	----	----	----	----	----	----
Release Operation Lock	OSJ:3F	-	----	○	----	○	○	----	○	○	----	○	----	----	----	----	----	----	----	----	----
Operation Lock Status	OSJ:40 OSJ:40:[Data1]:[Data2] [Data2] xxxxxxx	[Data1] 0 1 [Data2] xxxxxxx	[Data1] Unlock Lock [Data2] Any Information (40 Characters)	○	----	○	○	----	○	○	----	○	----	----	----	----	----	----	----	----	----
External Output 1	OSJ:41:[Data] OSJ:41	0 1 2 3	Off R-Tally G-Tally Y-Tally	○	----	○	supports only 0(Off), 1(R- Tally), 2(G-Tally) (UE80, UE50) - (UE40, UE30)	----	----	supports only 0(Off), 1(R- Tally), 2(G-Tally)	----	supports only 0(Off), 1(R- Tally), 2(G-Tally)	----	----	----	----	----	----	----	----	----
External Output 2	OSJ:42:[Data] OSJ:42	0 1 2 3	Off R-Tally G-Tally Y-Tally	○	----	○	supports only 0(Off), 1(R- Tally), 2(G-Tally) (UE80, UE50) - (UE40, UE30)	----	----	supports only 0(Off), 1(R- Tally), 2(G-Tally)	----	supports only 0(Off), 1(R- Tally), 2(G-Tally)	----	----	----	----	----	----	----	----	----
Power On Position	OSJ:45:[Data] OSJ:45	0 1 2 3	None Standby Home Preset	○	----	○	supports only 1(Standby) 2(Home) 3(Preset)	----	○	supports only 1(Standby) 2(Home) 3(Preset)	----	○	----	----	----	----	----	----	----	----	----
Power On Preset Number	OSJ:46:[Data] OSJ:46	00 - 99	Preset001 - Preset100	○	----	○	○	----	○	○	----	○	----	----	----	----	----	----	----	----	----
AWB Color Temperature Inc	OSJ:48:[Data]	1h - Ah	1 - 10	○	----	○	----	----	○	○	----	○	----	----	----	----	----	----	----	----	----
AWB Color Temperature Dec	OSJ:49:[Data]	1h - Ah	1 - 10	○	----	○	----	----	○	○	----	○	----	----	----	----	----	----	----	----	----
AWB Color Temperature / Color Temp ACH	OSJ:4A:[Data1]:[Data2] OSJ:4A	[Data1] 007D0h - 03A98h [Data2] 0 1 2	[Data1] 2000K - 15000K [Data2] Valid Under Over	○	----	supports only 0 Valid	○(Query Only)	----	○	○	----	○	----	----	----	----	----	----	----	----	----
AWB R Gain	OSJ:4B:[Data] OSJ:4B	670h - 800h - 990h	-400 - 0 - 400	○	----	○	----	----	○	○	----	○	----	----	----	----	----	----	----	----	----

ITEM	Command Control / Response / Confirmation	Data	Data Contents																		
			Control and Response to control	UE150A	UB50/UB10	UE160	UE80/UE50/UE40/UE30	UE20/HE20	UR100	UE100	UE4	UE150/HE145	HR140	UB300	UE70series	HE75series	HE70series	HE130	HE120	HE60	HE50
Crop Zoom Ratio (Y1)	Q5J:98:[Data] Q5J:98	02EE0h - 0C350h	120. 00% - 500. 00%	supports only 02EE0h (120. 00) - 08888h (350. 00)	----	○	----	----	○	○	----	----	----	----	----	----	----	----	----	----	----
Crop Zoom Ratio (G)	Q5J:99:[Data] Q5J:99	02EE0h - 0C350h	120. 00% - 500. 00%	supports only 02EE0h (120. 00) - 08888h (350. 00)	----	○	----	----	○	○	----	----	----	----	----	----	----	----	----	----	----
Crop Zoom Ratio (Mg)	Q5J:9A:[Data] Q5J:9A	02EE0h - 0C350h	120. 00% - 500. 00%	supports only 02EE0h (120. 00) - 08888h (350. 00)	----	○	----	----	○	○	----	----	----	----	----	----	----	----	----	----	----
Crop Zoom Ratio (Y1/G/Mg)	Q5J:9B:[Data1]:[Data2]:[Data3] Q5J:9B	[Data1] 02EE0h - 0C350h [Data2] 02EE0h - 0C350h [Data3] 02EE0h - 0C350h	[Data1] Zoom Ratio (Y1) 120. 00% - 500. 00% [Data2] Zoom Ratio (G) 120. 00% - 500. 00% [Data3] Zoom Ratio (Mg) 120. 00% - 500. 00%	[Data1, 2, 3] supports only 02EE0h (120. 00) - 08888h (350. 00)	----	○	----	----	○	○	----	----	----	----	----	----	----	----	----	----	----
Crop Zoom Ratio Speed Control	Q5J:9C:[Data] Q5J:9C	01 - 49 50 51 - 99	Wide Max. Speed - Wide Min. Speed Stop Tele Min. Speed - Tele Max. Speed	○	----	○	----	----	○	○	----	----	----	----	----	----	----	----	----	----	----
Crop Zoom Ratio Speed Control (Y1)	Q5J:9D:[Data] Q5J:9D	01 - 49 50 51 - 99	Wide Max. Speed - Wide Min. Speed Stop Tele Min. Speed - Tele Max. Speed	○	----	○	----	----	○	○	----	----	----	----	----	----	----	----	----	----	----
Crop Zoom Ratio Speed Control (G)	Q5J:9E:[Data] Q5J:9E	01 - 49 50 51 - 99	Wide Max. Speed - Wide Min. Speed Stop Tele Min. Speed - Tele Max. Speed	○	----	○	----	----	○	○	----	----	----	----	----	----	----	----	----	----	----
Crop Zoom Ratio Speed Control (Mg)	Q5J:9F:[Data] Q5J:9F	01 - 49 50 51 - 99	Wide Max. Speed - Wide Min. Speed Stop Tele Min. Speed - Tele Max. Speed	○	----	○	----	----	○	○	----	----	----	----	----	----	----	----	----	----	----
Crop H/V Position Speed Control (Y1/G/Mg)	Q5J:A0:[Data1]:[Data2]:[Data3]:[Data4]:[Data5]:[Data6] Q5J:A0	[Data1] 01 - 50 - 99 - [Data2] 01 - 50 - 99 - [Data3] 01 - 50 - 99 - [Data4] 01 - 50 - 99 - [Data5] 01 - 50 - 99 - [Data6] 01 - 50 - 99	[Data1] (Y1) Left Max. Speed - Stop - Right Max. Speed [Data2] (Y1) Down Max. Speed - Stop - UP Max. Speed [Data3] (G) Left Max. Speed - Stop - Right Max. Speed [Data4] (G) Down Max. Speed - Stop - UP Max. Speed [Data5] (Mg) Left Max. Speed - Stop - Right Max. Speed [Data6] (Mg) Down Max. Speed - Stop - UP Max. Speed	○	----	○	----	----	○	○	----	○ (UE150) --- (HE145)	----	----	----	----	----	----	----	----	----
Crop Zoom Ratio Speed Control (Y1/G/Mg)	Q5J:A1:[Data1]:[Data2]:[Data3] Q5J:A1	[Data1] 01 - 49 50 51 - 99 [Data2] 01 - 49 50 51 - 99 [Data3] 01 - 49 50 51 - 99	[Data1] (Y1) Wide Max. Speed - Wide Min. Speed Stop Tele Min. Speed - Tele Max. Speed [Data2] (G) Wide Max. Speed - Wide Min. Speed Stop Tele Min. Speed - Tele Max. Speed [Data3] (Mg) Wide Max. Speed - Wide Min. Speed Stop Tele Min. Speed - Tele Max. Speed	○	----	○	----	----	○	○	----	----	----	----	----	----	----	----	----	----	----
P/T Acceleration	Q5J:A2:[Data] Q5J:A2	0 1	Manual Auto	○	----	○	----	○ (UE80)	○	○	----	----	----	----	----	----	----	----	----	----	----
P/T Rise S-Curve	Q5J:A3:[Data] Q5J:A3	00h 1Eh	0 30	○	----	○	----	○ (UE80) (UE50, UE40, UE30)	○	○	----	----	----	----	----	----	----	----	----	----	----
P/T Fall S-Curve	Q5J:A4:[Data] Q5J:A4	00h 1Eh	0 30	○	----	○	----	○ (UE80) (UE50, UE40, UE30)	○	○	----	----	----	----	----	----	----	----	----	----	----
P/T Rise Acceleration	Q5J:A5:[Data] Q5J:A5	01h - FFh	1 - 255	○	----	○	----	○ (UE80) (UE50, UE40, UE30)	○	○	----	----	----	----	----	----	----	----	----	----	----
P/T Fall Acceleratoin	Q5J:A6:[Data] Q5J:A6	01h - FFh	1 - 255	○	----	○	----	○ (UE80) (UE50, UE40, UE30)	○	○	----	----	----	----	----	----	----	----	----	----	----
Privacy Mode	Q5J:A7:[Data] Q5J:A7	0 1	Off On	○	----	○	----	○	○	○	----	----	----	----	----	----	----	----	----	----	----
Preset Acceleration	Q5J:A8:[Data] Q5J:A8	0 1	Manual Auto	○	----	○	----	○ (UE80)	○	○	----	○	----	----	----	----	----	----	----	----	----
Preset Rise S-Curve	Q5J:A9:[Data] Q5J:A9	00h 1Eh	0 30	○	----	○	----	○ (UE80) (UE50, UE40, UE30)	○	○	----	----	----	----	----	----	----	----	----	----	----
Preset Fall S-Curve	Q5J:AA:[Data] Q5J:AA	00h 1Eh	0 30	○	----	○	----	○ (UE80) (UE50, UE40, UE30)	○	○	----	----	----	----	----	----	----	----	----	----	----

ITEM	Command Control / Response / Confirmation	Data	Data Contents																		
			Control and Response to control	UE150A	UB50/UB10	UE160	UE80/UE50/UE40/UE 30	UE20/HE20	UR100	UE100	UE4	UE150/HE145	HR140	UB300	UE70series	HE75series	HE70series	HE130	HE120	HE60	HE50
AGC	OSL:26:[Data] QSL:26	0 1	Off On	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Frame Mix SW	OSL:27:[Data] QSL:27	0 1	Off On	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Frame Mix	OSL:28:[Data] QSL:28	06h 0Ch 12h 18h	+6dB +12dB +18dB +24dB	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Iris Peak Ratio	OSL:29:[Data] QSL:29	00h – 64h	0 – 100	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
ATW	OSL:2A:[Data] QSL:2A	0 1	Off On	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
White Balance Mode	OSL:2B:[Data] QSL:2B	0 1 2 3 4	AWB A AWB B PRESET 3200K PRESET 5600K VAR	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Shockless WB SW	OSL:2C:[Data] QSL:2C	0 1	Off On	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Shockless WB Speed	OSL:2D:[Data] QSL:2D	1 – 5	1 – 5	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Auto Shutter	OSL:2E:[Data] QSL:2E	0 1	Off On	----	○	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Color Temp Bch	OSL:2F:[Data1]:[Data 2] QSL:2F	[Data1] 00700h – 03A98h [Data2] 0	[Data1] 2000K – 15000K [Data2] Valid	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Color Temp Bch Inc	OSL:30:[Data]	1h – Ah	1 – 10	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Color Temp Bch Dec	OSL:31:[Data]	1h – Ah	1 – 10	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Color Temp R Gain Bch	OSL:32:[Data] QSL:32	670h 800h – 990h	–400 0 – 400	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Color Temp B Gain Bch	OSL:33:[Data] QSL:33	670h 800h – 990h	–400 0 – 400	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Color Temp G Axis Bch	OSL:34:[Data] QSL:34	670h – 800h – 990h	–400 – 0 – 400	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
G Gain Rel Control Switch	OSL:35:[Data] QSL:35	0 1	Off On	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
RGB Gain Preset R Gain	OSL:36:[Data] QSL:36	418h 800h – BE8h	–1000 0 – 1000	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
RGB Gain Preset G Gain	OSL:37:[Data] QSL:37	418h 800h – BE8h	–1000 0 – 1000	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
RGB Gain Preset B Gain	OSL:38:[Data] QSL:38	418h – 800h – BE8h	–1000 – 0 1000	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
RGB Gain R Gain Ach	OSL:39:[Data] QSL:39	418h – 800h – BE8h	–1000 – 0 1000	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
RGB Gain G Gain Ach	OSL:3A:[Data] QSL:3A	418h 800h – BE8h	–1000 0 – 1000	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
RGB Gain B Gain Ach	OSL:3B:[Data] QSL:3B	418h 800h – BE8h	–1000 0 – 1000	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
RGB Gain R Gain Bch	OSL:3C:[Data] QSL:3C	418h – 800h – BE8h	–1000 – 0 1000	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
RGB Gain G Gain Bch	OSL:3D:[Data] QSL:3D	418h – 800h – BE8h	–1000 – 0 1000	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
RGB Gain B Gain Bch	OSL:3E:[Data] QSL:3E	418h 800h – BE8h	–1000 0 – 1000	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
RGB Gain Gain Offset Bch	OSL:3F:[Data] QSL:3F	0 1 738h – 800h – 9C8h	Off On –200 0 200	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Master Flare	OSL:40:[Data] QSL:40	800h – 9C8h	0 – 200	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----

ITEM	Command Control / Response / Confirmation	Data	Data Contents	UE150A	UB50/UB10	UE160	UE80/UE50/UE40/UE30	UE20/HE20	UR100	UE100	UE4	UE150/HE145	HR140	UB300	UE70series	HE75series	HE70series	HE130	HE120	HE60	HE50
			Control and Response to control																		
R Flare	OSL:41:[Data] OSL:41	738h	-200	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		800h	0	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		8C8h	200	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
G Flare	OSL:42:[Data] OSL:42	738h	-200	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		800h	0	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		8C8h	200	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
B Flare	OSL:43:[Data] OSL:43	738h	-200	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		800h	0	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		8C8h	200	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Initial Gamma	OSL:44:[Data] OSL:44	8h	4.0	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		9h	4.5	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		Ah	5.0	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Knee	OSL:45:[Data] OSL:45	0	Off	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		1	On	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		OSL:46:[Data] OSL:46	0	Manual	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Knee Mode	OSL:46:[Data] OSL:46	1	Auto	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		71h	-15%	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		80h	0%	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
R White Clip Level	OSL:47:[Data] OSL:47	-	-	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		8Fh	15%	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		71h	-15%	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
B White Clip Level	OSL:48:[Data] OSL:48	80h	0%	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		-	-	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		8Fh	15%	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
HI-Color	OSL:49:[Data] OSL:49	0	Off	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		1	On	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		01h	1	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
HI-Color Level	OSL:4A:[Data] OSL:4A	-	-	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		20h	32	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		1	1	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
DRS Effect Depth	OSL:4B:[Data] OSL:4B	-	-	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		5	5	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		00h	00	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Detail Knee	OSL:4C:[Data] OSL:4C	-	-	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		0Fh	15	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		OSL:4D:[Data] OSL:4D	0	Off	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Dark Detail SW	OSL:4D:[Data] OSL:4D	1	On	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		0	0	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		-	-	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Dark Detail	OSL:4E:[Data] OSL:4E	7	7	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		0	0	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		-	-	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Down Convert Chroma Level SW	OSL:4F:[Data] OSL:4F	0	Off	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		1	On	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		1Ch	-100%	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Down Convert Chroma Level	OSL:50:[Data] OSL:50	-	-	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		80h	0%	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		A8h	40%	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Down Convert H Detail Level	OSL:51:[Data] OSL:51	80h	00	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		-	-	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		07Ch	12.4MHz	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Down Convert Detail Peak Frequency	OSL:52:[Data] OSL:52	-	-	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		173h	37.1MHz	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		00h	00	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Down Convert V Detail Frequency	OSL:53:[Data] OSL:53	-	-	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		1Fh	31	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		80h	00	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Down Convert Detail Crisp	OSL:54:[Data] OSL:54	-	-	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		8Fh	63	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		80h	00	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Down Convert Detail Clip(+)	OSL:57:[Data] OSL:57	-	-	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		8Fh	63	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		80h	00	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Down Convert Detail Clip(-)	OSL:58:[Data] OSL:58	-	-	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		8Fh	63	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		00h	0	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Down Convert Detail Knee Aperture Level	OSL:5A:[Data] OSL:5A	-	-	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		27h	39	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		00h	00	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Down Convert Detail Knee	OSL:5B:[Data] OSL:5B	-	-	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		0Fh	15	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		0	Off	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Down Convert Detail Level Dependent SW	OSL:5C:[Data] OSL:5C	1	On	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		00h	00	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		OSL:5D:[Data] OSL:5D	0Fh	15	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Down Convert Detail Level Dependent	OSL:5E:[Data] OSL:5E	0	Off	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		1	On	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		-	-	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Down Convert Dark Detail	OSL:5F:[Data] OSL:5F	0	0	----	----	○	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		-	-	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
		7	7	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----
Down Convert Skin Tone Detail																					

[illegible]

ITEM	Command Control / Response / Confirmation	Data	Data Contents																		
			Control and Response to control	UE150A	UB50/UB10	UE160	UE80/UE50/UE40/UE 30	UE20/HE20	UR100	UE100	UE4	UE150/HE145	HR140	UB300	UE70series	HE75series	HE70series	HE130	HE120	HE60	HE50
White Shading W H Saw R	OSL:9C:[Data] QSL:9C	1Ch	-100	----	----	○	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----
		80h	0																		
		E4h	+100																		
White Shading W H Saw G	OSL:9D:[Data] QSL:9D	1Ch	-100	----	----	○	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----
		80h	0																		
		E4h	+100																		
White Shading W H Saw B	OSL:9E:[Data] QSL:9E	1Ch	-100	----	----	○	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----
		80h	0																		
		E4h	+100																		
White Shading W H Para R	OSL:9F:[Data] QSL:9F	1Ch	-100	----	----	○	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----
		80h	0																		
		E4h	+100																		
White Shading W H Para G	OSL:A0:[Data] QSL:A0	1Ch	-100	----	----	○	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----
		80h	0																		
		E4h	+100																		
White Shading W H Para B	OSL:A1:[Data] QSL:A1	1Ch	-100	----	----	○	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----
		80h	0																		
		E4h	+100																		
White Shading W V Saw R	OSL:A2:[Data] QSL:A2	1Ch	-100	----	----	○	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----
		80h	0																		
		E4h	+100																		
White Shading W V Saw G	OSL:A3:[Data] QSL:A3	1Ch	-100	----	----	○	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----
		80h	0																		
		E4h	+100																		
White Shading W V Saw B	OSL:A4:[Data] QSL:A4	1Ch	-100	----	----	○	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----
		80h	0																		
		E4h	+100																		
White Shading W V Para R	OSL:A5:[Data] QSL:A5	1Ch	-100	----	----	○	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----
		80h	0																		
		E4h	+100																		
White Shading W V Para G	OSL:A6:[Data] QSL:A6	1Ch	-100	----	----	○	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----
		80h	0																		
		E4h	+100																		
White Shading W V Para B	OSL:A7:[Data] QSL:A7	1Ch	-100	----	----	○	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----
		80h	0																		
		E4h	+100																		
ST2110 Main Video Tx Format	OSL:AA:[Data] QSL:AA	01h	720/59.94p	----	----	○	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----
		02h	720/50p																		
		04h	1080/59.94i																		
		05h	1080/50i																		
		10h	1080/59.94p																		
		11h	1080/50p																		
		14h	1080/29.97p																		
		15h	1080/25p																		
		20h	1080/60p																		
		22h	1080/24p																		
		23h	1080/23.98p																		
		FFh	DISABLE(query only)																		
		ST2110 Crop Video Tx Format	QSL:AC QSL:AC:[Data]	01h	720/59.94p	----	----	○	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----
02h	720/50p																				
04h	1080/59.94i																				
05h	1080/50i																				
10h	1080/59.94p																				
11h	1080/50p																				
14h	1080/29.97p																				
15h	1080/25p																				
20h	1080/60p																				
22h	1080/24p																				
23h	1080/23.98p																				
FFh	DISABLE(query only)																				
ST2110 Monitor Video Tx Format	QSL:AD QSL:AD:[Data]			01h	720/59.94p	----	----	○	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----
		02h	720/50p																		
		04h	1080/59.94i																		
		05h	1080/50i																		
		10h	1080/59.94p																		
		11h	1080/50p																		
		14h	1080/29.97p																		
		15h	1080/25p																		
		20h	1080/60p																		
		22h	1080/24p																		
		23h	1080/23.98p																		
		FFh	DISABLE(query only)																		
		Camera Number	OSL:AE:[Data] QSL:AE	01 - 99	1 - 99	----	----	○	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----	-----

ITEM	Command Control / Response / Confirmation	Data	Data Contents	UE150A	UB50/UB10	UE160	UE80/UE50/UE40/UE30	UE20/HE20	UR100	UE100	UE4	UE150/HE145	HR140	UB300	UE70series	HE75series	HE70series	HE130	HE120	HE60	HE50
			Control and Response to control																		
Focus Guide Status (Detail)	QSL:C6 QSL:C6:[Data]	62h	-30 (NEAR)	---	---	○	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		80h	0 (IN FOCUS)	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		9Eh	-30 (FAR)	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		FEh FFh	FOCUS GUIDE OFF NOT MEASURABLE	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
SYNC STATUS (GEN- LOCK / PTP)	QSL:C7 QSL:C7:[Data]	0 1	NO SYNC SYNC	○	---	○	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
ST2110 JPEG XS TX VIDEO SELECT	QSL:C8 QSL:C8:[Data]	0 1	MAIN CROP	---	---	○	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
ST2110 MAIN VIDEO JPEG XS TX FORMAT	QSL:C9 QSL:C9:[Data]	10h	1080/59.94p	---	---	○	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		11h	1080/50p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		14h	1080/29.97p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		15h	1080/25p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		17h	2160/29.97p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		18h	2160/25p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		19h	2160/59.94p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		1Ah	2160/50p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		1Bh	2160/23.98p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		1Fh	2160/60p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		20h	1080/60p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		21h	2160/24p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		22h	1080/24p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		23h	1080/23.98p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		FFh	DISABLE (query only)	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
ST2110 CROP VIDEO JPEG XS TX FORMAT	QSL:CA QSL:CA:[Data]	10h	1080/59.94p	---	---	○	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		11h	1080/50p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		14h	1080/29.97p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		15h	1080/25p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		20h	1080/60p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		22h	1080/24p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		23h	1080/23.98p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		FFh	DISABLE (query only)	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
ST2110 RET VIDEO JPEG XS RX FORMAT	QSL:CB QSL:CB:[Data]	04h	1080/59.94i	---	---	○	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		05h	1080/50i	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		10h	1080/59.94p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		11h	1080/50p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		14h	1080/29.97p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		15h	1080/25p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		20h	1080/60p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		22h	1080/24p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
23h	1080/23.98p	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---		
FFh	DISABLE (query only)	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---		
AUTO IRIS WINDOW	QSL:CC QSL:CC:[Data]	0 1	Off On	---	---	○	---	---	---	---	---	○ (UE150) --- (HE145)	---	---	---	---	---	---	---	---	
AUTO IRIS WINDOW POSITION	QSL:CD QSL:CD:[Data1]:[Data2]:[Data3]:[Data4]	[Data1] 00h	[Data1]UPPER LEFT (H) 0	○	---	○	---	---	---	---	---	○ (UE150) --- (HE145)	---	---	---	---	---	---	---	---	---
		-	-	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	
		08h [Data2] 00h	8 [Data2]UPPER LEFT (V) 0	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		-	-	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		04h [Data3] 00h	4 [Data3]BOTTOM RIGHT (H) 0	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		-	-	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		08h [Data4] 00h	8 [Data4]BOTTOM RIGHT (V) 0	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		-	-	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
04h	4	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---		
PRESET PTZ SYNC MODE	QSL:CE QSL:CE:[Data]	0 1	Off On	○	---	○	---	---	---	---	---	---	---	---	---	---	---	---	---	---	
Timecode Overwrap	QSL:CF QSL:CF:[Data]	0 1 2 3 4	Off UR BR BL UL	---	---	---	---	---	○	---	---	---	---	---	---	---	---	---	---	---	---
		0 1 2 3 4	Off UR BR BL UL	---	---	---	---	---	---	○	---	---	---	---	---	---	---	---	---	---	---
		0 1 2 3 4	Off UR BR BL UL	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		0 1 2 3 4	Off UR BR BL UL	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
FPS SW	QSL:DC QSL:DC:[Data]	0 1	OFF ON	---	---	○	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
FPS	QSL:DD QSL:DD:[Data]	0 1 2 3 4	24 30 60 25 50	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		0 1 2 3 4	24 30 60 25 50	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		0 1 2 3 4	24 30 60 25 50	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		0 1 2 3 4	24 30 60 25 50	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
TRACKING AUTO FOCUS	QSL:E6 QSL:E6:[Data]	0 1	OFF ON	---	---	○	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
TRACKING FOCUS POSITION	QSL:E7:[Data1]:[Data2]:[Data3]:[Data4]	[Data1] 00h	[Data1]AF POSI. H 0%	---	---	○	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		-	-	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		64h [Data2] 00h	100% [Data2]AF POSI. V 0%	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		-	-	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		64h [Data3] 00h	100% [Data3]AF AREA SIZE 0 (SMALL)	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		01h [Data4] 0 1	1 (BIG) [Data4]位置AFの一瞬停止 AF STOP	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
TRACKING FOCUS POSITION RESET	QSL:E9:[Data]	1	RESET	---	---	○	---	---	---	---	---	---	---	---	---	---	---	---	---	---	
HDMI Output Source	QSL:EA QSL:EA:[Data]	0 1 2	12G SDI/0pt 1 3G SDI1 3G SDI2	○	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
		0 1 2	12G SDI/0pt 1 3G SDI1 3G SDI2	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---
DNR LEVEL	QSL:EB QSL:EB:[Data]	76h - 80h - 8Ah	-5 - 0 - 5 (1step=0.5割み)	---	○	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---

[illegible]

PT command

ITEM	Command	Data	Data Contents	UE150A	UE160	UE80/UE50/UE40,UE30	UE20/HE20	UR100	UE100	UE4	UE150/HE145	HR140	UE70series	HE42series	HE40series	HE130	HE120	HE60	HE50		
	Control Confirmation Response																				
P/T Absolute Position Control	#APC[Data1][Data2] #APCaPC[Data1][Data2]	[Data1]0000h - 8000h - FFFFh	[Data1]Pan Position CCW Limit - Center - CW Limit	supports only Pan 2D09(CCW Limit) -D2F5(CW Limit) Tilt 1C71(UP Limit) -8E38(DOWN Limit)	supports only Pan 2D09(CCW Limit) -D2F5(CW Limit) Tilt 1C71(UP Limit) -8E38(DOWN Limit)	supports only Pan 2D09(CCW Limit) -D2F5(CW Limit) Tilt 1C71(UP Limit) -8E38(DOWN Limit)	supports only Pan 2F69(CCW Limit) -D097(CW Limit) Tilt 5555(UP Limit) -8E38(DOWN Limit)	supports only Pan 2D09(CCW Limit) -D2F5(CW Limit) Tilt 1C71(UP Limit) -8E38(DOWN Limit)	supports only Pan 2D09(CCW Limit) -D2F5(CW Limit) Tilt 1C71(UP Limit) -8E38(DOWN Limit)	supports only Pan 8000(Center) Tilt 8000(Center)	supports only Pan 2D09(CCW Limit) -D2F5(CW Limit) Tilt 1C71(UP Limit) -8E38(DOWN Limit)	supports only Pan 2D09(CCW Limit) -D2F5(CW Limit) Tilt 1C71(UP Limit) -8E38(DOWN Limit)	supports only Pan 2D09(CCW Limit) -D2F5(CW Limit) Tilt 5555(UP Limit) -8E38(DOWN Limit)	supports only Pan 2D09(CCW Limit) -D2F5(CW Limit) Tilt 5555(UP Limit) -8E38(DOWN Limit)	supports only Pan 2D09(CCW Limit) -D2F5(CW Limit) Tilt 5555(UP Limit) -8E38(DOWN Limit)	supports only Pan 2D09(CCW Limit) -D2F5(CW Limit) Tilt 1C71(UP Limit) -8E38(DOWN Limit)	supports only Pan 2D09(CCW Limit) -D2F5(CW Limit) Tilt 1C71(UP Limit) -8E38(DOWN Limit)	supports only Pan 2D09(CCW Limit) -D2F5(CW Limit) Tilt 5555(UP Limit) -8E38(DOWN Limit)	supports only Pan 2D09(CCW Limit) -D2F5(CW Limit) Tilt 5555(UP Limit) -8E38(DOWN Limit)		
		[Data2]0000h - 8000h - FFFFh	[Data2]Tilt Position UP Limit - Center - DOWN Limit																		
P/T Absolute Position Control with Speed	#APS[Data1][Data2][Data3][Data4] aPS[Data1][Data2][Data3][Data4]	[Data1]0000h - 8000h - FFFFh	[Data1]Pan Position CCW Limit - Center - CW Limit	○	○	○	---	○	○	---	○	○	○	○	○	○	○	---	---	---	
		[Data2]0000h - 8000h - FFFFh	[Data2]Tilt Position UP Limit - Center - DOWN Limit																		
		[Data3]00h - 1Dh	[Data3]Preset Speed 1 - 30																		
		[Data4]0 1 2	[Data4]Preset Speed Table Slow Fast Fast																		
Focus Position Control	#AXF[Data] axf[Data]	555h - FFFh	Near - Far	○	○	○	○	○	○	supports only 555	○	○	○	○	○	○	○	○	○	○	
Iris Control	#AXI[Data] axi[Data]	555h - FFFh	Iris Close - Iris Open	○	○	○	○	○	○	supports only 555	○	○	○	○	○	○	○	○	○	○	
Zoom Position Control	#AXZ[Data] axz[Data]	555h - FFFh	Wide - Tele	○	○	○	○	○	○	supports only 555	○	○	○	○	○	○	○	○	○	○	
Delete Preset Memory	#Cs[Data] s[Data]	00 - 99	Preset001 - Preset100	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	
Focus Mode	#D1[Data] d1[Data]	0 1	Manual Auto	○	○	○	○	○	○	---	○	○	○	○	○	○	○	○	○	○	
Iris Mode	#D3[Data] d3[Data]	0 1	Manual Auto	○	○	○	○	○	○	---	○	○	○	○	○	○	○	○	○	○	
Day/Night	#D6[Data] d6[Data]	0 1	Day Night	○	○	○ (UE80) ---- (UE50, UE40, UE30)	---	○	○	---	○	○	○	○	○	○	○	○	○	○	
Defroster Control	#D7[Data] d7[Data]	0 1	Off(Auto) On	---	---	---	---	○	---	---	---	0 : Auto 1 : On	---	---	---	---	---	---	---		
Wiper Control	#D8[Data] d8[Data]	0 1	Off On	---	---	---	---	○	---	---	---	0 : Off 1 : Fast (Heater)	---	---	---	---	---	---	---		
Heater/Fan Control	#D9[Data] d9[Data]	0 1	Off(Auto) On	---	---	---	---	○	---	---	---	0 : Auto 1 : On	---	---	---	---	---	---	---		
R-Tally Control	#DA[Data] dA[Data]	0 1	Off On	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	○	
Defroster Status	#DS dS[Data]	0 1	Off On	---	---	---	---	○	---	---	---	○	---	---	---	---	---	---	---	---	
Focus Speed Control	#Fs[Data] fS[Data]	01 - 49 50 51 - 99	Near Max. Speed - Near Min. Speed Stop Far Min. Speed - Far Max. Speed	○	○	○	○	○	○	---	○	○	○	○	○	○	○	○	○	○	
Fan	#FAN[Data] fAN[Data]	0 1 2 3	Auto High Mid Low	○	○	○ (UE80) ---- (UE50, UE40, UE30)	---	Supports only 0(Auto) 1(On)	○	---	○	Supports only 0(Auto) 1(On)	---	---	---	---	---	---	---	---	
Fan2	#FA2[Data] fA2[Data]	0 1 2 3	Auto High Mid Low	○	○	---	---	Supports only 0(Auto) 1(On)	---	---	○	---	---	---	---	---	---	---	---	---	
Flip Detect Angle	#FDA[Data] fDA[Data]	3Ch 78h	60deg 120deg	○	○	---	---	○	○	---	○	○	---	---	---	○	○	---	---	---	
Fan Status1	#FS1 fS1[Data]	0 1 2	Off On Error	○	○	○ (UE80) ---- (UE50, UE40, UE30)	---	○	○	---	○	Supports only 0(Off), 1(On)	---	---	---	---	---	---	---	---	
Fan Status2	#FS2 fS2[Data]	0 1 2	Off On Error	○	○	---	---	○	---	---	○	Supports only 0(Off), 1(On)	---	---	---	---	---	---	---	---	
Request Focus Position	#GF gf[Data]	555h - FFFh "----"	Near - Far @Power Off	○	○	○	○	○	○	---	○	○	○	○	○	○	○	○	○	○	

[illegible]

[illegible]

✂Details

▼OSH

Parameters vary depending on model and System Format

HR140, HE130		UE70series, HE42series, HE40series, HE60, HE50	HE120
(59.94p/59.94i)	F(1/30)	0(OFF),	0(OFF),
0(OFF)	(23.98p)	3(1/100 NTSC)	3(1/100 NTSC)
3(1/100)	0(OFF)	(1/120 PAL),	(1/120 PAL),
4(1/120)	2(1/60)	5(1/250)	5(1/250)
5(1/250)	4(1/120)	–	–
–	5(1/250)	B(Synchro–Scan)	C(ELC)
C(ELC)	–		
	D(1/24)		
(29.97p)	(50p/50i)		
0(OFF)	0(OFF)		
2(1/60)	2(1/60)		
4(1/120)	3(1/120)		
5(1/250)	5(1/250)		
–	–		
C(ELC)	C(ELC)		
	(25p)		
	0(OFF)		
	2(1/60)		
	3(1/120)		
	5(1/250)		
	–		
	C(ELC)		
	E(1/25)		

▼ OSA:87

Parameters vary depending on model

UB50		UB10
[59. 94Hz]	[24Hz]	[59. 94Hz]
04h (1080/59. 94 i)	B6h (1080/48p)	10h (1080/59. 94p)
10h (1080/59. 94p)	B7h (1080/47. 95p)	14h (1080/29. 97p)
14h (1080/29. 97p)	B8h (3840x2160/48p)	17h (3840x2160/29. 97p)
17h (3840x2160/29. 97p)	B9h (3840x2160/47. 95p)	19h (3840x2160/59. 94p)
19h (3840x2160/59. 94p)	1Bh (3840x2160/23. 98p)	90h (3328x2496/59. 94p)
26h (1080/119. 88p)	21h (3840x2160/24p)	94h (3328x2496/29. 97p)
90h (3328x2496/59. 94p)	22h (1080/24p)	98h (4096x2160/59. 94p)
94h (3328x2496/29. 97p)	23h (1080/23. 98p)	9Ch (4096x2160/29. 97p)
98h (4096x2160/59. 94p)	92h (3328x2496/48p)	A0h (3680x2760/59. 94p)
9Ch (4096x2160/29. 97p)	93h (3328x2496/47. 95p)	A2h (3680x2760/29. 97p))
A5h (4128x2176/59. 94p)	96h (3328x2496/24p)	
A7h (4128x2176/29. 97p)	97h (3328x2496/23. 98p)	[50Hz]
ABh (3536x2656/29. 97p)	9Ah (4096x2160/48p)	11h (1080/50p)
A Eh (5888x3312/29. 97p)	9Bh (4096x2160/47. 95p)	15h (1080/25p)
B2h (5376x3584/29. 97p)	9Eh (4096x2160/24p)	18h (3840x2160/25p)
	9Fh (4096x2160/23. 98p)	1Ah (3840x2160/50p)
[50Hz]	A9h (4128x2176/23. 98p)	91h (3328x2496/50p)
05h (1080/50 i)	ADh (3536x2656/23. 98p)	95h (3328x2496/25p)
11h (1080/50p)	B0h (5888x3312/24p)	99h (4096x2160/50p)
15h (1080/25p)	B1h (5888x3312/23. 98p)	9Dh (4096x2160/25p)
18h (3840x2160/25p)	B4h (5952x3968/24p)	A1h (3680x2760/50p)
1Ah (3840x2160/50p)	B5h (5952x3968/23. 98p)	A3h (3680x2760/25p)
27h (1080/100p)		
91h (3328x2496/50p)		[24Hz]
95h (3328x2496/25p)		1Bh (3840x2160/23. 98p)
99h (4096x2160/50p)		21h (3840x2160/24p)
9Dh (4096x2160/25p)		22h (1080/24p)
A6h (4128x2176/50p)		23h (1080/23. 98p)
A8h (4128x2176/25p)		96h (3328x2496/24p)
AAh (3536x2656/50p)		97h (3328x2496/23. 98p)
ACh (3536x2656/25p)		9Eh (4096x2160/24p)
AFh (5888x3312/25p)		9Fh (4096x2160/23. 98p)
B3h (5376x3584/25p)		A4h (3680x2760/23. 98p)

▼ OSA:87

Parameters vary depending on model

UE150A	UE160	UE80, UR100, UE100, UE150	UE50	UE40, UE30	HE145
[59.94Hz] 01h(720/59.94p) 04h(1080/59.94i) 10h(1080/59.94p) 14h(1080/29.97p) 17h(2160/29.97p) 19h(2160/59.94p)	[59.94Hz] 01h(720/59.94p) 10h(1080/59.94p) 14h(1080/29.97p) 17h(2160/29.97p) 19h(2160/59.94p) 26h(1080/119.88p)	[59.94Hz] 01h(720/59.94p) 04h(1080/59.94i) 07h(1080/29.97psF) 10h(1080/59.94p) 14h(1080/29.97p) 16h(1080/23.98p (over 59.94i/p)) 17h(2160/29.97p) 19h(2160/59.94p)	[59.94Hz] 01h(720/59.94p) 04h(1080/59.94i) 07h(1080/29.97psF) 10h(1080/59.94p) 14h(1080/29.97p) 16h(1080/23.98p (over 59.94i/p)) 17h(2160/29.97p)	[59.94Hz] 01h(720/59.94p) 04h(1080/59.94i) 10h(1080/59.94p) 14h(1080/29.97p) 17h(2160/29.97p)	[59.94Hz] 01h(720/59.94p) 04h(1080/59.94i) 07h(1080/29.97psF) 10h(1080/59.94p) 14h(1080/29.97p) 16h(1080/23.98p (over 59.94i/p))
[50Hz] 02h(720/50p) 05h(1080/50i) 11h(1080/50p) 15h(1080/25p) 18h(2160/25p) 1Ah(2160/50p)	[50Hz] 02h(720/50p) 11h(1080/50p) 15h(1080/25p) 18h(2160/25p) 1Ah(2160/50p) 27h(1080/100p)	[50Hz] 02h(720/50p) 05h(1080/50i) 08h(1080/25psF) 11h(1080/50p) 15h(1080/25p) 18h(2160/25p) 1Ah(2160/50p)	[50Hz] 02h(720/50p) 05h(1080/50i) 08h(1080/25psF) 11h(1080/50p) 15h(1080/25p) 18h(2160/25p)	[50Hz] 02h(720/50p) 05h(1080/50i) 11h(1080/50p) 15h(1080/25p) 18h(2160/25p)	[50Hz] 02h(720/50p) 05h(1080/50i) 08h(1080/25psF) 11h(1080/50p) 15h(1080/25p)
[24Hz] 21h(2160/24p) 22h(1080/24p)	[24Hz] 21h(2160/24p) 22h(1080/24p)	[24Hz] 21h(2160/24p) 22h(1080/24p)	[24Hz] 21h(2160/24p) 22h(1080/24p)	[24Hz] 21h(2160/24p) 22h(1080/24p)	[24Hz] 22h(1080/24p)
[23.98Hz] 1Bh(2160/23.98p) 23h(1080/23.98p)	[23.98Hz] 1Bh(2160/23.98p) 23h(1080/23.98p)	[24Hz] 21h(2160/24p) 22h(1080/24p)	[23.98Hz] 0Ah(1080/23.98psF) 1Bh(2160/23.98p) 23h(1080/23.98p)	[23.98Hz] 1Bh(2160/23.98p) 23h(1080/23.98p)	[23.98Hz] 0Ah(1080/23.98psF) 23h(1080/23.98p)
	[60.00Hz] 1Fh(2160/60p) 20h(1080/60p)	[23.98Hz] 0Ah(1080/23.98psF) 1Bh(2160/23.98p) 23h(1080/23.98p)			

▼ OSA:87 (Continued)
Parameters vary depending on model

UE20	HE20	UE4	HR140	UB300	UE70series	HE40Series
[59. 94Hz] 1h (720/59. 94p) 4h (1080/59. 94i) 10h (1080/59. 94p) 14h (1080/29. 97p) 17h (2160/29. 97p) [50Hz] 2h (720/50p) 5h (1080/50i) 11h (1808/50p) 15h (1080/25p) 18h (2160/25p) [60Hz] 0h (720/60p) 3h (1080/60i) 20h (1080/60p) 24h (2160/30p) 25h (1080/30p)	[59. 94Hz] 1h (720/59. 94p) 4h (1080/59. 94i) 10h (1080/59. 94p) 14h (1080/29. 97p) [50Hz] 2h (720/50p) 5h (1080/50i) 11h (1808/50p) 15h (1080/25p) [60Hz] 0h (720/60p) 3h (1080/60i) 20h (1080/60p) 25h (1080/30p)	[59. 94Hz] 1h (720/59. 94p) 10h (1080/59. 94p) 14h (1080/29. 97p) 17h (2160/29. 97p) [50Hz] 2h (720/50p) 11h (1808/50p) 15h (1080/25p) 18h (2160/25p) [60Hz] 0h (720/60p) 20h (1080/60p) 24h (2160/30p) 25h (1080/30p)	[59. 94Hz] 1h (720/59. 94p) 4h (1080/59. 94i) 7h (1080/29. 97psF) Ah (1080/23. 98psF) 10h (1080/59. 95p) 14h (1080/29. 97p) 16h (1080/23. 98p) [50Hz] 2h (720/50p) 5h (1080/50i) 8h (1080/25psF) 11h (1080/50p) 15h (1080/25p)	[59. 94Hz] 00h (720/60p) 01h (720/59. 94p) 04h (1080/59. 94i) 07h (1080/29. 97psF) 0Ah (1080/23. 98psF) 10h (1080/59. 94p) 16h (1080/23. 98p) 17h (2160/29. 97p) 19h (2160/59. 94p) 1Bh (2160/23. 98p) 1Ch (2160/29. 97psF) 1Eh (2160/23. 98psF) 1Fh (2160/60p) 20h (1080/60p) 44h (1080/59. 94i CROP) 50h (1080/59. 94p CROP) [50Hz] 02h (720/50p) 05h (1080/50i) 08h (1080/25psF) 11h (1080/50p) 18h (2160/25p) 1Ah (2160/50p) 1Dh (2160/25psF) 45h (1080/50i CROP) 51h (1080/50p CROP)	[59. 94Hz] 1h (720/59. 94p) 4h (1080/59. 94i) 7h (1080/29. 97psF) 10h (1080/59. 94p) 14h (1080/29. 97p) 17h (2160/29. 97p) 80h (Auto) [50Hz] 2h (720/50p) 5h (1080/50i) 8h (1080/25psF) 11h (1080/50p) 15h (1080/25p) 18h (2160/25p) 80h (Auto) HE42series [59. 94Hz] 1h (720/59. 94p) 4h (1080/59. 94i) 7h (1080/29. 97psF) 10h (1080/59. 94p) 14h (1080/29. 97p) 80h (Auto) [50Hz] 2h (720/50p) 5h (1080/50i) 8h (1080/25psF) 11h (1080/50p) 15h (1080/25p) 80h (Auto)	=== HDMI Model === [59. 94Hz] 1h (720/59. 94p) 4h (1080/59. 94i) 7h (1080/29. 97psF) 10h (1080/59. 95p) 14h (1080/29. 97p) 80h (Auto) [50Hz] 2h (720/50p) 5h (1080/50i) 8h (1080/25psF) 11h (1080/50p) 15h (1080/25p) 80h (Auto) === SDI Model === [59. 94Hz] 1h (720/59. 94p) 4h (1080/59. 94i) 7h (1080/29. 97psF) 14h (1080/29. 97p) [50Hz] 2h (720/50p) 5h (1080/50i) 8h (1080/25psF) 15h (1080/25p)

▼ OSA:87 (Continued)
Parameters vary depending on model

HE120	HE60	HE50
[59. 94Hz] 1h (720/59. 94p) 4h (1080/59. 94 i) Bh (480/59. 94 i) 10h (1080/59. 94p) 12h (480/59. 94p) [50Hz] 2h (720/50p) 5h (1080/50 i) Dh (576/50 i) 11h (1808/50p) 13h (576/50p)	[H Model/59. 94Hz] 1h (720/59. 94p) 4h (1080/59. 94 i) Bh (480/59. 94 i) 10h (1080/59. 94p) 12h (480/59. 94p) [H Model/50Hz] 2h (720/50p) 5h (1080/50 i) Dh (576/50 i) 11h (1080/50p) 8h (1080/25psf) 13h (576/50p) [S Model/59. 94Hz] 1h (720/59. 94p) 4h (1080/59. 94 i) Bh (480/59. 94 i) [S Model/50Hz] 2h (720/50p) 5h (1080/50 i) Dh (576/50 i)	[N Model] 1h (720/59. 94p) 4h (1080/59. 94 i) Bh (480/59. 94 i) [E, MC Model] 2h (720/50p) 5h (1080/50 i) Dh (576/50 i) [H Model/59. 94Hz] 1h (720/59. 94p) 4h (1080/59. 94 i) Bh (480/59. 94 i) 10h (1080/59. 94p) 7h (1080/29. 97psF) [H Model/50Hz] 2h (720/50p) 5h (1080/50 i) Dh (576/50 i) 11h (1808/50p) 8h (1080/25psf) [S Model/59. 94Hz] 1h (720/59. 94p) 4h (1080/59. 94 i) Bh (480/59. 94 i) 7h (1080/29. 97psF) [S Model/50Hz] 2h (720/50p) 5h (1080/50 i) Dh (576/50 i) 8h (1080/25psf)
HE130		
[59. 94Hz] 1h (720/59. 94p) 4h (1080/59. 94 i) 7h (1080/29. 97psF) Ah (1080/23. 98psF) 10h (1080/59. 95p) 12h (480/59. 94p) 14h (1080/29. 97p) 16h (1080/23. 98p) [50Hz] 2h (720/50p) 5h (1080/50 i) 8h (1080/25psF) 11h (1080/50p) 13h (576/50p) 15h (1080/25p)		

▼OSD:B1

Parameters vary depending on model

HR140, HE130		UE70series, HE42series, HE40series	
[Data]	Data Contents	[Data]	Data Contents
000h – 078h	2000K,2010K,2020K,2040K,2050K,2070K,2080K,2090K,2110K,2120K,2140K,2150K,2170K,2180K,2200K,2210K,2230K,2240K,2260K,2280K,2300K,2310K,2330K,2340K,2360K,2380K,2400K,2420K,2440K,2460K,2480K,2500K,2520K,2540K,2560K,2600K,2620K,2640K,2680K,2700K,2720K,2740K,2780K,2800K,2820K,2850K,2870K,2920K,2950K,2970K,3000K,3020K,3070K,3100K,3120K,3150K,3200K,3250K,3270K,3330K,3360K,3420K,3450K,3510K,3570K,3600K,3660K,3720K,3780K,3840K,3870K,3930K,3990K,4050K,4110K,4170K,4240K,4320K,4360K,4440K,4520K,4600K,4680K,4760K,4840K,4920K,5000K,5100K,5200K,5300K,5400K,5500K,5600K,5750K,5850K,6000K,6150K,6300K,6450K,6650K,6800K,7000K,7150K,7400K,7600K,7800K,8100K,8300K,8600K,8900K,9200K,9600K,10000K,10500K,11000K,11500K,12000K,12500K,13000K,14000K,15000K	000h 001h – 04A 04B	2400K 2500K – 9800K 9900K (100K step)

▼OSG:5D

Parameters vary depending on System Frequency

UB300			
59.94p/59.94i	50p/50i	29.97p/23.98p	25p
04h(1/100)	02h(1/60)	00h(1/48)	00h(1/48)
05h(1/120)	04h(1/100)	01h(1/50)	01h(1/50)
06h(1/125)	06h(1/125)	02h(1/60)	02h(1/60)
07h(1/250)	07h(1/250)	03h(1/96)	03h(1/96)
08h(1/500)	08h(1/500)	04h(1/100)	04h(1/100)
09h(1/1000)	09h(1/1000)	05h(1/120)	06h(1/125)
0Ah(1/1500)	0Ah(1/1500)	06h(1/125)	07h(1/250)
0Bh(1/2000)	0Bh(1/2000)	07h(1/250)	08h(1/500)
0Ch(1/180.0deg)	0Ch(1/180.0deg)	08h(1/500)	09h(1/1000)
0Dh(1/172.8deg)	0Dh(1/172.8deg)	09h(1/1000)	0Ah(1/1500)
0Eh(1/144.0deg)	0Eh(1/144.0deg)	0Ah(1/1500)	0Bh(1/2000)
0Fh(1/120.0deg)	0Fh(1/120.0deg)	0Bh(1/2000)	0Ch(1/180.0deg)
10h(1/90.0deg)	10h(1/90.0deg)	0Ch(1/180.0deg)	0Dh(1/172.8deg)
11h(1/45.0deg)	11h(1/45.0deg)	0Dh(1/172.8deg)	0Eh(1/144.0deg)
		0Eh(1/144.0deg)	0Fh(1/120.0deg)
		0Fh(1/120.0deg)	10h(1/90.0deg)
		10h(1/90.0deg)	11h(1/45.0deg)
		11h(1/45.0deg)	

▼OAW

Parameter meaning var between control command and response for confirmation command

Control		Confirmation	
0	ATW	0	ATW
1	AWC A	1	---
2	AWC B	2	AWC A
3	ATW	3	AWC B
4	Preset 3200K	4	Preset 3200K
5	Preset 5600K	5	Preset 5600K
6	Preset 4500K	6	Preset 4500K
7	Preset 6000K	7	Preset 6000K
8	Preset 2800K	8	Preset 2800K
9	Var	9	Var

Parameters vary depending on model

		UE150A, UE160, UE80, UE50, UE40, UE30, UR100, UE100, UE150, HE145, HR140, UE70series, HE42series, HE40series, HE130, HE120	UE20/HE20/UE4	HE60/HE50		UB50,UB10
Control	0	ATW	ATW	ATW	0	ATW
	1	AWC A	AWC A	AWC A	1	AWC A
	2	AWC B	AWC B	AWC B	2	AWC B
	3	ATW	ATW	ATW	3	---
	4	Preset 3200K	Preset 3200K	---	4	Preset 3200K
	5	Preset 5600K	Preset 5600K	---	5	Preset 5600K
	6	---	---	---	6	---
	7	---	---	---	7	---
	8	---	---	---	8	---
	9	Var	---	---	9	Var
Confirmation	0	ATW	ATW	ATW	0	ATW
	1	---	---	---	1	---
	2	AWC A	AWC A	AWC A	2	AWB A
	3	AWC B	AWC B	AWC B	3	AWB B
	4	Preset 3200K	Preset 3200K	---	4	Preset 3200K
	5	Preset 5600K	Preset 5600K	---	5	Preset 5600K
	6	---	---	---	6	---
	7	---	---	---	7	---
	8	---	---	---	8	---
	9	Var	---	---	9	Var
					F	Oter

▼OSC

Parameter meaning var between control command and response for confirmation command

Control		Confirmation	
1	2(90deg)	1	---
2	3(180deg)	2	1(0deg)
3	4(270deg)	3	2(90deg)
4	1(0deg)	4	3(180deg)
5	---	5	4(270deg)

▼#QSV

Parameters vary depending on model

UE150A	UE80	UE50	UE40,UE30	UR100	UE100	UE150, HE145	HR140
[Data1] Servo CPU Camera CPU ZYNQ Network Main/Network CPU ZYNQ Logic ZYNQ R5T Lens CPU ZYNQ R5R ZYNQ Enc BE EEPROM [Data2] MAJOR VERSION [Data3] MINOR VERSION [Data4] (Debug Build) (Release Build) [Data5] (REVISION) [data6] NTSC PAL	[Data1] Servo CPU Camera CPU ZYNQ Network Main/Network CPU ZYNQ Logic reserve Lens CPU reserve ZYNQ Enc BE EEPROM [Data2] MAJOR VERSION [Data3] MINOR VERSION [Data4] (Debug Build) (Release Build) [Data5] (REVISION) [data6] NTSC PAL	[Data1] Servo CPU Camera CPU reserve Main/Network CPU AVIO FPGA reserve Lens CPU reserve reserve BE EEPROM [Data2] MAJOR VERSION [Data3] MINOR VERSION [Data4] (Debug Build) (Release Build) [Data5] (REVISION) [data6] NTSC PAL	[Data1] Servo CPU Camera CPU reserve Main/Network CPU reserve Lens CPU reserve reserve BE EEPROM [Data2] MAJOR VERSION [Data3] MINOR VERSION [Data4] (Debug Build) (Release Build) [Data5] (REVISION) [data6] NTSC PAL	[Data1] Servo CPU Camera CPU ZYNQ Network Main/Network CPU ZYNQ Logic reserve Lens CPU ZYNQ R5R ZYNQ Enc BE EEPROM [Data2] Major Version [Data3] Minor Version [Data4] (Debug Build) (Release Build) [Data5] (REVISION) [data6] NTSC PAL	[Data1] Servo CPU Camera CPU ZYNQ Network Main/Network CPU ZYNQ Logic ZYNQ R5T Lens CPU ZYNQ R5R ZYNQ Enc BE EEPROM [Data2] Major Version [Data3] Minor Version [Data4] (Debug Build) (Release Build) [Data5] (REVISION) [data6] NTSC PAL	[Data1] Servo CPU Camera CPU COM FPGA Main/Network CPU AVIO FPGA Interface CPU Lens CPU Interface EEPROM reserved BE EEPROM [Data2] Major Version [Data3] Minor Version [Data4] (Debug Build) (Release Build) [Data5] (REVISION) [data6] NTSC PAL	[Data1] Servo CPU CameraMain CPU COM FPGA Network CPU AVIO FPGA Interface CPU Lens FPGA Interface EEPROM reserve reserve [Data2] Major Version [Data3] Minor Version [Data4] (Debug Build) (Release Build) [Data5] (REVISION) [data6] NTSC PAL

▼#QSV (Continued)
Parameters vary depending on model

UE70, HE75, HE70series	HE130	HE120	HE60	HE50
[Data1] Servo CPU Cam CPU FPGA BE CPU reserve Interface CPU reserve Interface EEPROM reserve reserve [Data2] 00 [Data3] Version [Data4] L [Data5] 00 [data6] NTSC PAL	[Data1] Servo CPU CameraMain CPU COM FPGA Network CPU AVIO FPGA Interface CPU Lens FPGA Interface EEPROM reserve reserve [Data2] Major Version [Data3] Minor Version [Data4] (Debug Build) (Release Build) [Data5] (Revision) [data6] NTSC PAL	[Data1] Servo CPU CameraMain CPU Frontend FPGA Network CPU Backend FPGA Interface CPU Lens FPGA Interface EEPROM Camera EEPROM Lens EEPROM [Data2] Major Version [Data3] Minor Version [Data4] (Debug Build) (Release Build) [Data5] (Revision) [data6] NTSC PAL	[Data1] Pan Tilt CPU Camera CPU Camera FPGA Network CPU OUT FPGA reserve reserve reserve Camera EEPROM reserve [Data2] Major Version [Data3] Minor Version [Data4] (Debug Build) (Release Build) [Data5] (Revision) [data6] NTSC PAL Other	[Data1] Pan Tilt CPU Camera CPU Camera FPGA Network CPU Out FPGA reserve reserve reserve reserve reserve [Data2] Major Version [Data3] Minor Version [Data4] (Debug Build) (Release Build) [Data5] (Revision) [data6] NTSC PAL Other

▼#RER

The content of the error varies depending on the model

[illegible]

▼#RER(Continued)

The content of the error varies depending on the model

HR140	UE70series, HE42 Series, HE40 Series	HE120	HE50
00h: Normal	00h Normal(No Error)	00h: Normal	00h: Normal
03h: Motor Driver Error	03h Motor Driver Error	03h: Motor Driver Error	03h: Motor Driver Error
04h: Pan Sensor Error	04h Pan Sensor Error	04h: Pan Sensor Error	04h: Pan Sensor Error
05h: Tilt Sensor Error	05h Tilt Sensor Error	05h: Tilt Sensor Error	05h: Tilt Sensor Error
06h: Controller RX Over run Error	06h IF/FPGA UART Over run Error	06h: Controller RX Over run Error	06h: Controller RX Over run Error
07h: Controller RX Framing Error	07h IF/FPGA UART Framing Error	07h: Controller RX Framing Error	07h: Controller RX Framing Error
08h: Network RX Over run Error	08h IF/NET UART Over run Error	08h: Network RX Over run Error	08h: Network RX Over run Error
09h: Network RX Framing Error	09h IF/NET UART Framing Error	09h: Network RX Framing Error	09h: Network RX Framing Error
17h: Controller RX Command Buffer Overflow	17h IF/FPGA UART Buffer Overflow	17h: Controller RX Command Buffer Overflow	17h: Controller RX Command Buffer Overflow
19h: Network RX Command Buffer Overflow	19h IF/NET UART Buffer Overflow	19h: Network RX Command Buffer Overflow	19h: Network RX Command Buffer Overflow
21h: System Error	21h System Error(IF/SERVO Error)	21h: System Error	21h: System Error
22h: Spec Limit Over	22h PT Limit Over	22h: Spec Limit Over	22h: Spec Limit Over
23h: FPGA Config Error	24h NET Life-monitoring Error	23h: FPGA Config Error	23h: FPGA Config Error
25h: CAMERA communication Error	25h BE Life-monitoring Error	24h: Network communication Error	24h: Network communication Error
26h: CAMERA RX Over run Error	26h IF/BE UART Buffer Overflow	25h: Lens Initialize Error	30h: Lvds_Adjustmet_NG
27h: CAMERA RX Framing Error	27h IF/BE UART Framing Error		31h: Bar_Signal_Check_NG
28h: CAMERA RX Command Buffer Overflow	28h IF/BE UART Buffer Overflow		
31h: Fan1 Error	29h CAM Life-monitoring Error		
32h: Fan2 Error			
33h: High Temp			
36h: Low Temp			
39h: Wiper Error			
40h: Temp Sensor Error			
41h: Lens Initialize Error			
42h: PT. Initialize Error			
50h: MR Level Error			
51h: GYRO Initial Error			
52h: MR Offset Error			
53h: Origin Offset Error			

▼XSF

Parameter meaning var between control command and response for confirmation command

UE160

Control		Confirmation	
0	---	0	Scene1
1	Scene1	1	Scene2
2	Scene2	2	Scene3
3	Scene3	3	Scene4
4	Scene4	4	Scene5
5	Scene5	5	Scene6
6	Scene6	6	Scene7
7	Scene7	7	Scene8
8	Scene8	8	OFF
9	OFF	9	---

UE150A, UE80, UE50, UE40, UE30, UR100, UE100, UE150, HE145, HR140, UE70series, HE42series, HE40series, HE130, HE120, HE60, HE50

Control		Confirmation	
0	---	0	Scene1(Manual1)
1	Scene1(Manual1)	1	Scene2(Manual2)
2	Scene2(Manual2)	2	Scene3(Manual3)
3	Scene3(Manual3)	3	Scene4(FullAuto)
4	Scene4(FullAuto)	4	---

UB50,UB10

Control		Confirmation	
0	---	0	Scene1
1	Scene1	1	Scene2
2	Scene2	2	Scene3
3	Scene3	3	Scene4
4	Scene4	4	Scene5
5	Scene5	5	Scene6
6	Scene6	6	Scene7
7	Scene7	7	Scene8
8	Scene8	8	Other
9	Other	9	---

UE4

Control		Confirmation	
0	---	0	Full Auto
1	Full Auto	1	Shutter Priority
2	Shutter Priority	2	Manual
3	Manual	3	---

UB300

Control		Confirmation	
0	---	0	current
1	current	1	Scene1
2	Scene1	2	Scene2
3	Scene2	3	Scene3
4	Scene3	4	Scene4
5	Scene4	5	Scene5
6	Scene5	6	Scene6
7	Scene6	7	Scene7
8	Scene7	8	Scene8
9	Scene8	9	---

UE20/HE20

Control		Confirmation	
0	---	0	Scene1
1	Scene1	1	Scene2
2	Scene2	2	Full Auto
3	Full Auto	3	---

▼#O

Parameter meaning var between control command and response for confirmation command

Control		Confirmation	
0	Power Off	0	Power Off
1	Power On	1	Power On
3	---	3	Starting