

VHD VX-90 — Companion module handleiding

VHD VX-90 PTZ Camera

Controls the VHD VX-90 PTZ camera over **VISCA-over-IP (TCP)**.

Connection

- **IP address:** the camera's LAN IP.
- **Port:** 5678 by default (this is the VX-90's own "PTZ port" setting, found in the camera's network configuration — confirmed from the camera's firmware, not guessed).
- **VISCA address:** 1 by default (matches the camera's factory default).

Where these commands come from

This module is built directly from VHD's official VX-90 VISCA command reference ([VX90_VISCA_EN_20250729](#)). Most commands are identical to Sony's public VISCA specification (which is why the generic Bitfocus "Sony VISCA" module already works for basic pan/tilt/zoom/focus/iris/gain and presets on this camera).

A number of actions are marked **[VHD-ext]** in their name — these use command bytes that are specific to VHD and are *not* part of Sony's public VISCA spec (mostly under command category `0x0A / 0x0B` , one under the unusual `0x2A`). These will not work through a generic Sony VISCA module; this module implements them directly.

Known limitations / things to verify on real hardware

- The byte layouts here come from VHD's documentation table and cross-checking against the camera's firmware — they have **not all been individually tested against a live VX-90** for every single action. Basic PT/zoom/focus/iris/gain/presets are known-good (already confirmed working through the generic Sony module). The **[VHD-ext]** actions (ND filter, tally, tracking, motion sync, EIS, image style, audio input, IR address, restart, factory reset) should be spot-checked the first time you use them.
- Inquiry/query commands (reading back the camera's current state) are **not implemented yet** — VHD's own documentation only lists a partial set of query commands, and this first version focuses on control actions. A `connected` feedback (green when the TCP connection is up) is included, but there's no per-parameter feedback yet.
- The `Restart Camera` and `Factory Reset IP + Password` actions do exactly what they say — use with care, ideally behind a confirmation step in your button setup.

Support

Internal module built for AP Audiovisuele Producties. For questions about the underlying VISCA command set, see the VHD documentation or the technical contact at VHD.