Embedded Controller

System Tick Timer


Young-Keun Kim
School of Mechanical & Control Engineering

Handong Global University

Last modified: 2026.8

System Tick Timer (SysTick)


- **System Tick (SYSTICK)**
  - Cortex M3/M4 have a built-in system tick timer called SysTick (24-bit timer)
  - Generate regular timer interrupts
    - Periodic interrupt
    - Time measurement
    - OS timekeeping





```
void SysTick_Handler(void){
  ...
}
```

System Tick Timer (SysTick)

- **SysTick Timer**
  - 24-bit down counter






Refer to Program manual [PM]

System Tick Timer (SysTick)

Example: Down counting from 6 to 0




SysTick Interrupt Time Period = (SysTick_LOAD + 1) × Clock Period = 7 × Clock Period


한동대학교 HANDONG GLOBAL UNIVERSITY

System Tick Timer (SysTick)

Registers of SysTick

- **SysTick_CTRL**: Control and Status register
- **SysTick_LOAD:** Reload value register (24 bits, ~0x00FF FFFF)
- **SysTick_VAL**: Current Value





System Tick Timer (SysTick)

Calculating Reload Value

- Example
  - System CLK = 84MHz
  - RELOAD value for SysTick of 10ms ?

$$Tick\ Period = (Reload + 1) * Clock\ Period$$

$$Reload = \frac{Tick\ Period}{Clock\ Period} - 1$$

$$= \boldsymbol{Tick\ Period} * Clock\ Freq. - 1$$


$$= 0.01s \times 84MHz - 1$$

$$= 840{,}000 - 1$$

$$= 839{,}999$$

$$\boldsymbol{Reload} = \boldsymbol{Tick\ Period}[\mathrm{s}] * Clock\ Freq.[\mathrm{Hz}] - 1$$

```
//   HSI 16 MHz :  15999      PLL 84 MHz : 83999
SysTick->LOAD = (uint32_t)EC_SYSCLK *1UL/ 1000UL - 1UL;   // 1[ms] = 1/1000[s]
```



한동대학교 HANDONG GLOBAL UNIVERSITY

System Tick (SysTick) Interrupt Register Description


Embedded Controller

Prof. Young-Keun Kim

SysTick Register

- **SysTick (STK or SysTick)**
  - **Clock Control and Status**
    SysTick_CTRL
  - **SysTick Reload Value**
    SysTick_LOAD
  - **SysTick Current Value**
    SysTick_VAL
  - **SysTick Calibration**
    SysTick_CALIB

For SysTick, refer to Programming Manual
(p.g. 246)
NOT Reference manual



<YIU, Ch.9, pg. 314>

SysTick Register

(RCC system clock)

Processor CLK = EC_SYSCLK (16MHz, 84MHz)

(System Tick Configuration)

1. Disable SysTick Timer — **SysTick->CTRL: ENABLE**=0
2. Choose clock signal: Processor clock — **SysTick->CTRL: CLKSOURCE** = 1
3. Choose to use Tick Interrupt (timer goes 1->0) — **SysTick->CTRL: TICKINT** = 1
4. Calculate Reload Value (24-bit) — **SysTick->LOAD: RELOAD** = ReloadValue
5. Enable SysTick Timer — **SysTick->CTRL: ENABLE**=1
6. (option) Read or Clear current counting value — **int val= (SysTick->VAL)**
   - Writing clears value of (SysTick->VAL)

(NVIC Configuration)

NVIC SysTick Interrupt priority and Enable

SysTick (System Tick Timer) Register

- **System Tick Configuration**

1. Disable/Enable SysTick Timer: **SysTick->CTRL: ENABLE**
2. Choose clock signal: System clock or ref. clock(STCLK)**:** **SysTick->CTRL : CLKSOURCE**
3. Choose to use Tick Interrupt (timer goes 1->0): **SysTick->CTRL: TICKINT**

4.5.1 SysTick control and status register (STK_CTRL)




Table 9.7 SYSTICK Control and Status Register (0xE000E010)

Bits	Name	Type	Reset Value	Description
16	COUNTFLAG	R	0	Read as 1 if counter reaches 0 since last time this register is read; clear to 0 automatically when read or when current counter value is cleared
2	CLKSOURCE	R/W	0	0 = External reference clock (STCLK) 1 = Use core clock
1	TICKINT	R/W	0	1 = Enable SYSTICK interrupt generation when SYSTICK timer reaches 0 0 = Do not generate interrupt
0	ENABLE	R/W	0	SYSTICK timer enable

```
// Disable SysTick
SysTick->CTRL &=~1UL<<0;


// Select processor clock
// 1 = processor clock;  0 = external clock
SysTick->CTRL |= 1UL << 2U;


// Enables SysTick exception request
// 1 = counting down to zero --> SysTick exception request
SysTick->CTRL |= (1UL << 1U);
```

SysTick (System Tick Timer) Register

- **System Tick Configuration**

  4. Configure Reload Counting value (24-bit):

SysTick->LOAD: RELOAD = Reload

$$Reload = \text{Interval[s]} * CLK\ \text{Freq[Hz]} - 1$$

4.5.2 SysTick reload value register (STK_LOAD)

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16
Reserved								RELOAD[23:16]							
								rw	rw	rw	rw	rw	rw	rw	rw

15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
RELOAD[15:0]															
rw	rw	rw	rw	rw	rw	rw	rw	rw	rw	rw	rw	rw	rw	rw	rw

```
//   HSI 16 MHz :  15999      PLL 84 MHz : 83999
SysTick->LOAD = (uint32_t)EC_SYSCLK *1UL/ 1000UL - 1UL;   // 1[ms] = 1/1000[s]
```

SysTick (System Tick Timer) Register

- **System Tick Configuration**

  6. Read or Clear current counting value: **uint32_t val= (SysTick->VAL)**

4.5.3 SysTick current value register (STK_VAL)

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16
Reserved								CURRENT[23:16]							
								rw	rw	rw	rw	rw	rw	rw	rw
15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
CURRENT[15:0]															
rw	rw	rw	rw	rw	rw	rw	rw	rw	rw	rw	rw	rw	rw	rw	rw

Bits 23:0 **CURRENT:** Current counter value

The VAL register contains the current value of the SysTick counter.

Reads return the current value of the SysTick counter.

A write of any value clears the field to 0, and also clears the COUNTFLAG bit in the STK_CTRL register to 0.