



## **Lexmark - 80 Scheduled Maintenance Reset**

Lexmark uses the 80 code when the printer maintenance page count has been reached. For all Optra S and Optra T versions, along with those listed below, is 300,000 pages.

The reset procedure is as follows:

### **Lexmark T640, T642, and T644:**

- Power on printer while holding the (✓) and (→) buttons until the display reads "Config Menu"
- Release and scroll down until "Reset Maint Count" - press (✓), then "Reset"
- Press (✓)

### **Lexmark Optra S and Optra T:**

- Power on printer while holding the (select) and (return) buttons until printer displays "Performing Self Test"
- Release, then press (go). Printer will read "CONFIG MENU" with "Maint Count" Showing
- Press (menu→) to show "Reset Maint Count"
- Press (select) to show "= Reset"
- Press (select)