

FG Firmware Upgrade

WinBox:

Login: IP Address

IP | Firewall

NAT tab

Double-click destination port 21

Action tab

To Addresses: 192.168.1.1nn (unit)

Niagara Workbench from Program Server:

Open Device: IP address, 90nn, TWave, NOUnicOrns

Double-click Sedona Tools

Backup the unit

Reboot the app

FileZilla:

Host: IP address

Username: sdcard

Password: 123456

Port 21

Quickconnect

T:\F32PlusFirmware\FGUpdateJune2nd\V1.5_V2.0b45d SD Card\V2.0b45d\Flashing

Drag all four files to fg320

(T:\F32PlusFirmware\FGUpdateJune2nd\V1.5_V2.0b45d SD Card\V1.5b45d\MaintainIP)

Restore WinBox settings to what they were originally!

Niagara Workbench:

Reboot the App

WAIT FIVE MINUTES

Sedona Tools

Restore backup

Verify software version

If there are items below EasyIO in the tree, then the app is present.

eIQ Manager:

Update controller version information (Equip Summary tab)

Save the backup.