
QConnect

Pi batch tracker

Wireless, cable and AT&T cellular — one row per card

Version 1.0 · 09/16/2026

Print and keep on the bench

Print this page and keep it on the bench. One row per card. Work through the three ways of getting online in the order below, because each one rules out a different fault. The same results appear by themselves on the Bench page of the fleet dashboard as each card checks in, so you never have to type them twice — this sheet is for the bench, the dashboard is the record.

How to run one card

1. Write the card, put it in the Pi, note the card name from the sticker.
2. **Cable first.** Plug in an Ethernet cable, then power. Within two minutes the card should appear online on the dashboard. This proves the card itself is good.
3. **Then Wi-Fi.** Unplug the cable, power-cycle, join the **QConnect-Setup** network, enter the office Wi-Fi details. Expect online again within two minutes.
4. **Then cellular.** Unplug the cable, fit the AT&T SIM, power-cycle, leave it ten minutes. Expect online with a mobile connection.
5. Tick or cross each of the three boxes, and write the reason shown on the dashboard next to any cross.

A card is ready to ship when cable and at least one of Wi-Fi or cellular pass. A card that fails **cable** does not go out at all — that is the card, not the site.

Tracker

#	Card name	Date	Run by	Cable	Wi-Fi	AT&T SIM	Reason if failed	Ship ?
1	QCN-0001	09/16/2026		☐	☐	☐		☐
2	QCN-0002	09/16/2026		☐	☐	☐		☐
3				☐	☐	☐		☐
4				☐	☐	☐		☐
5				☐	☐	☐		☐
6				☐	☐	☐		☐
7				☐	☐	☐		☐
8				☐	☐	☐		☐
9				☐	☐	☐		☐
10				☐	☐	☐		☐
11				☐	☐	☐		☐
12				☐	☐	☐		☐
13				☐	☐	☐		☐
14				☐	☐	☐		☐
15				☐	☐	☐		☐

#	Card name	Date	Run by	Cable	Wi-Fi	AT&T SIM	Reason if failed	Ship ?
16				☐	☐	☐		☐
17				☐	☐	☐		☐
18				☐	☐	☐		☐
19				☐	☐	☐		☐
20				☐	☐	☐		☐

Copy the block for a bigger batch.

What a failure means, in plain words

These are the exact words the dashboard uses, so you can match them without guessing.

The dashboard says	What it means	Do this
Connected	Nothing wrong	Tick and move on.
Wi-Fi password was not accepted	The password typed on the setup page is wrong	Rejoin QConnect-Setup and type it again, watching for capitals.
Wi-Fi network not found	The card cannot see that network name	Check the name for typos; move the card nearer the access point.
Wi-Fi network not found (this box is 2.4 GHz only)	The office network is 5 GHz and this card's radio cannot reach it	Put the card on the 2.4 GHz network, or use cable or the SIM.
Joined the network but there is no internet behind it	It is on the network; the network has no way out	Site firewall or guest network. Try another socket or ask the site.
Network shows a sign-in page	A guest network wants someone to click "accept"	Use a normal network, cable or the SIM.
SIM is PIN-locked	The SIM asks for a PIN	Remove the PIN in a phone first, then refit it.
SIM or modem radio is switched off	The modem is disabled	Power-cycle; if it repeats, the modem needs looking at.
Modem cannot see a mobile tower	No AT&T signal where the card is	Move near a window and retry.
Modem fitted but no mobile APN set	Card written before the AT&T settings were built in	Rewrite the card with the current writer.
Mobile data did not connect	SIM is seen but data will not come up	Check the SIM is activated on the AT&T account.
The box network service is not running	Something on the card is broken	Rewrite the card. Do not ship it.
No cable, no known Wi-Fi, no modem	Nothing was connected	Expected between steps; not a fault.

The dashboard says	What it means	Do this
No Wi-Fi radio found on this box	Hardware without Wi-Fi	Skip the Wi-Fi step; use cable or SIM.
(never checked in)	The card never reported at all	Almost always the card was written wrong. Rewrite it and start again.

When you are finished

Give the completed sheet, or the Bench page export, to whoever is shipping the batch. Anything with a cross against **cable** or **never checked in** stays on the bench.